

F71889E

Super Hardware Monitor + LPC I/O

Fintek Confidential
Do Not Copy!

Release Date: April, 2010

Version: V0.19P

F71889E Datasheet Revision History

| Version | Date | Page | Revision History |
|---------|------------|------|--|
| V0.10P | 2009/8/24 | - | Preliminary Version. |
| V0.11P | 2009/8/25 | - | Modify Pin 45~48 and Pin Configuration Made Clarification and Correction |
| V0.12P | 2009/8/31 | - | Switch BSGPIO_STRP from pin 5 to pin 2 Made Clarification and Correction |
| V0.13P | 2009/9/17 | - | Made Clarification and Correction Add VSB_CTRL2# to pin 46 Modify Section 6 Pin Description Power Type BSGPIO_TRAP: Default is GPIO (Pin 2 and Section 7.1) Support LED blinking function at deep S3 & S5 Support PECl 3.0 Add Registers & Application Circuit |
| V0.14P | 2009/9/21 | - | Update Package from 128-PQFP to 128-LQFP Made Clarification and Correction |
| V0.15P | 2009/9/28 | - | Update Application Circuit & Pin Configuration Made Clarification and Correction |
| V0.16P | 2009/10/12 | - | Update Application Circuit & Pin Configuration (Update pin 41,42, 46, 60, 65, & 99) Update Pin Description Power Type Update Fan Fault Time Register — Index 9Fh, bit 5 Made Clarification and Correction |
| V0.17P | 2009/11/11 | - | Made Clarification and Correction Update Application Circuit & Pin Configuration |

| | | | |
|--------|------------|---|---|
| V0.18P | 2009/12/22 | - | <p>Made Clarification and Correction</p> <p>Modify DIODE OPEN Status Register -- Index 6Fh (bit 3 & 2)</p> <p>Modify LED_VSB Control Register -- Index FEh (bit 6)</p> <p>Modify LED_VCC Control Register -- Index FFh (bit 6 &7)</p> <p>Modify PME Event Enable 2 Register -- Index F2h (bit 2 & 1)</p> <p>Modify PME Event Status Register -- Index F1h</p> <p>Modify ACPI Control Register 4 -- Index F7h</p> <p>Modify RI De-bounce Select Register -- Index FEh</p> <p>Modify EUP control register -- Index E1h (bit 7-6 default value)</p> <p>Modify EUP control register -- Index E2h (bit 7-6)</p> <p>Modify EUP S5 deb-register -- Index E7h</p> <p>Add EuP Wakeup Event Enable Register -- Index E8h</p> <p>Add EuP Watchdog Control Register -- Index EDh</p> <p>Add EuP Watchdog Time Register -- Index EEh</p> <p>Update Chip ID – Index 20 & 21h</p> <p>Modify PECI/SST/TSI Configuration Register 1 — Index 01h bit 5</p> <p>Modify PECI/SST/TSI Configuration Register 2 — Index 07h</p> <p>Add Over-Voltage Protection Enable Register — Index 14h</p> <p>Add Over-Voltage Protection Event Status Register — Index 15h</p> <p>Modify Voltage reading and limit— Index 2Ch- 4Fh</p> <p>Add Fan1 Base Temperature Register – Index 94h (FAN_PROG_SEL = 1)</p> <p>Add Fan1 Temperature Adjustment Rate Register – Index 95h (FAN_PROG_SEL = 1)</p> <p>Add FAN PROGRAMMABLE DUTY-CYCLE/VOLTAGE LOADED AFTER POWER-ON — Index 9Eh</p> <p>Modify FAN1 Temperature Mapping Select – Index AFh bit 1,0</p> <p>Modify FAN2 Temperature Mapping Select – Index BFh bit 1,0</p> <p>Modify FAN3 Temperature Mapping Select – Index BFh bit 1,0</p> <p>Enhance Fan Speed Count Description</p> |
| V0.19P | 2010/1/19 | | <p>Made Clarification & Correction</p> <p>Update Voltage1 PME# Enable Register Index 10h</p> <p>Voltage1 Interrupt Status Register Index 11h bit 0</p> |

| | | | |
|--|--|--|--|
| | | | Over-Voltage Protection Enable Register Index 14h Over-Voltage Protection Event Status Register Index 15h Multi Function Select 1 Register Index 2Ah bit 7-6 Wakeup Control Register Index 2Dh bit 6 GPIO0 Drive Enable Register Index F3h bit 3 EUP control register Index E2 Pin 58 & 59 pin type Add Multi Temperature Explanation |
|--|--|--|--|

Please note that all data and specifications are subject to change without notice. All the trade marks of products and companies mentioned in this data sheet belong to their respective owners.

LIFE SUPPORT APPLICATIONS

These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Fintek for any damages resulting from such improper use or sales.

Fintek Do Not Copy! Confidential

Table of Content

| | | |
|-------|--|----|
| 1. | General Description | 1 |
| 2. | Feature List..... | 1 |
| 3. | Key Specification | 4 |
| 4. | Block Diagram | 4 |
| 5. | Pin Configuration | 5 |
| 6. | Pin Description | 6 |
| 6.1 | Power Pin..... | 6 |
| 6.2 | LPC Interface | 7 |
| 6.3 | UART, SIR, GPIO and 80-Port | 7 |
| 6.4 | Parallel Port | 9 |
| 6.5 | Hardware Monitor, EUP | 11 |
| 6.6 | ACPI Function Pins | 13 |
| 6.7 | Bus Interface..... | 14 |
| 6.8 | KBC Function | 14 |
| 7. | Function Description | 15 |
| 7.1. | Power on Strapping Option | 15 |
| 7.2. | Hardware Monitor..... | 15 |
| 7.3. | Keyboard Controller | 54 |
| 7.4. | 80 Port | 56 |
| 7.5. | ACPI Function | 56 |
| 7.6. | PECI Function | 60 |
| 7.7. | SST Function | 61 |
| 7.8. | TSI Function..... | 61 |
| 7.9. | FSB Bus Interface | 61 |
| 7.10. | VID Controller | 61 |
| 8. | Register Description | 62 |
| 8.1 | Global Control Registers | 65 |
| 8.2 | UART1 Registers (CR01)..... | 69 |
| 8.3 | UART 2 Registers (CR02)..... | 70 |
| 8.4 | Parallel Port Registers (CR03)..... | 71 |
| 8.5 | Hardware Monitor Registers (CR04)..... | 72 |
| 8.6 | KBC Registers (CR05)..... | 72 |
| 8.7 | GPIO Registers (CR06) (All registers of GPIO are powered by VSB3V) | 73 |
| 8.8 | VID Registers (CR07) | 85 |

F71889E

| | | |
|------|---|-----|
| 8.9 | PME, ACPI and EUP Registers (CR0A)..... | 88 |
| 8.10 | VREF Control Registers (CR0B)..... | 95 |
| 9. | Electrical Characteristics | 96 |
| 10. | Ordering Information..... | 99 |
| 11. | Package Dimensions | 100 |
| 12. | Application Circuit..... | 101 |

Fintek Confidential
Do Not Copy!

1. General Description

The F71889E which is the featured IO chip for new generational PC system is equipped with one IEEE 1284 parallel port, two UART ports, KBC, 80-Port, SIR, and VID controller. The F71889E integrated with hardware monitor, 9 sets of voltage sensor, 3 sets of creative auto-controlling fans and 3 temperature sensor pins for the accurate dual current type temp. measurement for CPU thermal diode or external transistors 2N3906.

The F71889E provides flexible features for multi-directional application. For instance, supports Bus Interface pins, provides 54 GPIO pins (multi-pin), IRQ sharing function also designed in UART feature for particular usage and accurate current mode H/W monitor will be worth in measurement of temperature, provides 3 modes fan speed control mechanism included Manual Mode/Speed Mode/Temperature Mode for users' selection.

Additionally, integrated 80-Port, and 5VDUAL voltage switch and adjustable voltage reference outputs related functions. The 80-Port is for engineering and debugging usage. F71889E also provides 5V dual controller and some voltage reference outputs for system application. Others, the F71889E supports newest AMD new interface TSI and Intel PECL /SST interfaces for temperature reading. These features will help you more and improve product value.

In order to save the current consumption when the system is in the soft off state which is so called power saving function. The power saving function supports the system boot-on not only by pressing the power button but also by the wake-up event. When the system enters the S3/S4/S5 state, F71889E can cut off the VSB power rail which supplies power source to the devices like the LAN chip, the chipset, the SIO, the audio codec, DRAM, and etc. The PC system can be simulated to G3-like state when system enters S3/S4/S5 states. At the G3-like state, the F71889E consumes 5VSB power rail only. The integrated two control pins are utilized to turn on or off VSB power rail in the G3-like status. The turned on VSB rail is supplied to a wake up device to fulfill a low power consumption system which supports a wake up function.

Finally, the F71889E is powered by 3.3V voltage, with the LPC interface in the package of 128-LQFP green package.

2. Feature List

● General Functions

- Comply with LPC Spec. 1.1
- Support DPM (Device Power Management), ACPI
- Bus Interface for CPU use
- Provides two UARTs, KBC and Parallel Port

F71889E

- 16 pins VID controller for VRM 11.x and OTF
- Serial VID controller with CORE_TYPE input for AMD Processor
- H/W monitor functions
- Reference voltage outputs support
- 5VDUAL voltage switch
- 80-Port interface from LPT or COM2
- Support AMD TSI interface and Intel SST/PECI interface
- Comply to Peci Spec.3.0
- Support I2C protocol SMBus interface
- Support LED blinking function at deep S5
- 54 GPIO Pins for flexible application
- Provide Power Saving Function (Comply EUP lot 6.0)
- 24/48 MHz clock input
- Packaged in 128-LQFP green package and powered by 3.3VCC

UART

- Two high-speed 16C550 compatible UART with 16-byte FIFOs
- Fully programmable serial-interface characteristics
- Baud rate up to 115.2K
- Support IRQ sharing

Infrared

- Support IrDA version 1.0 SIR protocol with maximum baud rate up to 115.2K bps

Parallel Port

- One PS/2 compatible bi-directional parallel port
- Support Enhanced Parallel Port (EPP) – Compatible with IEEE 1284 specification
- Support Extended Capabilities Port (ECP) – Compatible with IEEE 1284 specification
- Enhanced printer port back-drive current protection

Keyboard Controller

- Compatibility with the 8042
- Support PS/2 mouse
- Support both interrupt and polling modes
- Hardware Gate A20 and Hardware Keyboard Reset

Hardware Monitor Functions

- 3 dual current type ($\pm 3^{\circ}\text{C}$) thermal inputs for CPU thermal diode and 2N3906 transistors
- Temperature range $-40^{\circ}\text{C} \sim 127^{\circ}\text{C}$

- 9 sets voltage monitoring (6 external and 3 internal powers)
- High limit signal (PME#) for Vcore level
- 3 fan speed monitoring inputs
- 3 fan speed PWM/DC control outputs(support 3 wire and 4 wire fans)
- Issue PME# and OVT# hardware signals output
- Case intrusion detection circuit
- WATCHDOG# comparison of all monitored values

● **80-Port Interface**

- Monitor 0x80 Port and output the value via signals defined for 7-segment display.
- High nibble and low nibble are outputted interleaved at 1KHz frequency.
- 80-Port output by LPT or COM2 interface.

● **8-IN and 8-OUT VID Controller for VRM11.x and OTF**

● **Serial VID Controller with CORE_TYPE Input for AMD CPU application**

● **Integrate AMD TSI interface**

● **Integrate Intel SST interface**

● **Comply to PECI 3.0**

● **Support I2C Protocol SMBus interface**

● **Support FSB over clocking control bus**

● **5V Dual Voltage Switch**

- Provide ACPI-compliant 5VDUAL voltage switch
- 5VDUAL for USB/Keyboard/Mouse application

● **Adjustable Voltage Reference Outputs**

- Enable pin for VREF2 and 3 Voltage Reference Output control
- 0.9V default output on VREF1~3 pins
- Adjustable voltage range from 0~2.295V

● **Power Saving Function**

- G3-like Timing Control
- Comply With EUP Lot 6.0
- Three Control Pins for VSB Power Sources Control
- Two Event Input Pins for Wakeup Devices

Package


- 128-pin LQFP green package

Noted: Patented TW207103 TW207104 TW220442 US6788131 B1 TWI235231 TW237183 TWI263778

3. Key Specification

- Supply Voltage 3.0V to 3.6V
- Operating Supply Current 10mA typ.

4. Block Diagram



5. Pin Configuration




Figure1. F71889E pin configuration

6. Pin Description

| | |
|---------------------------|--|
| I/O _{16t} | - TTL level bi-directional pin with 16 mA source-sink capability. |
| I/OOD _{12t} | - TTL level bi-directional pin, can select to OD or OUT by register, with 12 mA source-sink capability. |
| I/OOD _{18t} | TTL level bi-directional pin, can select to OD or OUT by register, with 18 mA source-sink capability. |
| I/OOD _{12st,lv} | - Low level bi-directional pin with schmitt trigger, can select to OD or OUT by register, with 12 mA source-sink capability. |
| I/OOD _{12st,5v} | - TTL bi-directional pin with schmitt trigger, can select to OD or OUT by register, with 12 mA source-sink capability, 5V tolerance. |
| I/OD _{16st,5v} | - TTL level bi-directional pin and schmitt trigger, Open-drain output with 16 mA sink capability, 5V tolerance. |
| OD _{16,u10,5v} | - Open-drain output pin with 16 mA sink capability, pull-up 10k ohms, 5V tolerance. |
| I/O _{12st,5v} | - TTL level bi-directional pin and schmitt trigger, output with 12 mA sink capability, 5V tolerance. |
| I/O _{D8,st,lv} | - Low level bi-directional pin (VIH → 0.9V, VIL → 0.6V.) with schmitt trigger. Output with 8mA drive |
| I/O _{s1,D8st,lv} | - Low level bi-directional pin (VIH → 0.9V, VIL → 0.6V.) with schmitt trigger. Output with 8mA drive and 1mA sink capability. |
| I/OD _{12st,lv} | - Low level bi-directional pin with schmitt trigger. Open-drain output with 12mA sink capability. |
| O _{8,u47,5v} | - Open-drain pin with 8 mA source-sink capability, pull-up 47k ohms, 5V tolerance. |
| O ₁₂ | - Output pin with 12 mA source-sink capability. |
| O ₁₆ | - Output pin with 16 mA source-sink capability. |
| O ₁₈ | - Output pin with 18 mA source-sink capability. |
| O ₃₀ | - Output pin with 30 mA source-sink capability. |
| AOUT | - Output pin(Analog). |
| OD ₁₂ | - Open-drain output pin with 12 mA sink capability. |
| OD _{12,5v} | - Open-drain output pin with 12 mA sink capability, 5V tolerance. |
| O ₂₄ | - Output pin with 24 mA sink capability. |
| I/OD _{14t} | - TTL level bi-directional pin, Open-drain output with 14 mA sink capability. |
| IN _{t,5v} | - TTL level input pin, 5V tolerance. |
| IN _{st} | - TTL level input pin and schmitt trigger. |
| IN _{st,5v} | - TTL level input pin and schmitt trigger, 5V tolerance. |
| IN _{st,lv} | - TTL low level input pin (VIH → 0.9V, VIL → 0.6V.) |
| AIN | - Input pin(Analog). |
| P | - Power. |

6.1 Power Pin

| Pin No. | Pin Name | Type | Description |
|-----------------|----------|------|---|
| 1,35 | VCC | P | 3.3V power supply input |
| 49 | VSB_5V | P | 5V standby power supply input. |
| 65 | I_VSB3V | P | 3.3V internal standby power regulates from VSB_5V |
| 82 | VBAT | P | 3.3V battery input |
| 88 | AGND(D-) | P | Analog GND |
| 20, 50, 70, 117 | GND | P | Digital GND |
| 99 | VSB3V_IN | P | Voltage Input for 3.3V VSB. |

6.2 LPC Interface

| Pin No. | Pin Name | Type | PWR | Description |
|---------|----------|---------------------|-----|---|
| 27 | LRESET# | IN _{st,5v} | VCC | Reset signal. It can connect to PCIRST# signal on the host. |
| 28 | LDRQ# | O ₁₆ | VCC | Encoded DMA Request signal. |
| 29 | SERIRQ | I/O _{16t} | VCC | Serial IRQ input/Output. |
| 30 | LFRAME# | IN _{st} | VCC | Indicates start of a new cycle or termination of a broken cycle. |
| 31-34 | LAD[0:3] | I/O _{16t} | VCC | These signal lines communicate address, control, and data information over the LPC bus between a host and a peripheral. |
| 36 | PCICLK | IN _{st} | VCC | 33MHz PCI clock input. |
| 37 | CLKIN | IN _{st} | VCC | System clock input. According to the input frequency 24/48MHz. |

6.3 UART, SIR, GPIO and 80-Port

| Pin No. | Pin Name | Type | PWR | Description |
|---------|-----------|-----------------------|-----|---|
| 7 | GPIO40 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 8 | GPIO41 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 9 | GPIO42 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 10 | GPIO43 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 11 | GPIO44 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 12 | GPIO45 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 13 | GPIO46 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 14 | GPIO47 | I/OD _{14t} | VCC | General purpose IO. (Select by Register) |
| 15 | GPIO50 | I/OOD _{12t} | VCC | General purpose IO. (Select by Register) |
| 16 | GPIO51 | I/OOD _{12t} | VCC | General purpose IO. (Select by Register) |
| 17 | GPIO52 | I/OOD _{12t} | VCC | General purpose IO. (Select by Register) |
| 18 | GPIO53 | I/OOD _{12t} | VCC | General purpose IO. (Select by Register) |
| 19 | GPIO54 | I/OOD _{12t} | VCC | General purpose IO. (Select by Register) |
| 118 | DCD1# | IN _{t,5v} | VCC | Data Carrier Detect. An active low signal indicates the modem or data set has detected a data carrier. |
| 119 | RI1# | IN _{t,5v} | VCC | Ring Indicator. An active low signal indicates that a ring signal is being received from the modem or data set. |
| 120 | CTS1# | IN _{t,5v} | VCC | Clear To Send is the modem control input. |
| 121 | DTR1# | O _{8,u47,5v} | VCC | UART 1 Data Terminal Ready. An active low signal informs the modem or data set that controller is ready to communicate. Internal 47k ohms pulled high and disable after power on strapping. |
| | FAN60_100 | IN _{t,5v} | | Power on strapping pin: 1(Default): (Internal pull high) Power on fan speed default duty is 60%.(PWM) 0: (External pull down) Power on fan speed default duty is 100%.(PWM) |
| 122 | RTS1# | O _{8,u47,5v} | VCC | UART 1 Request To Send. An active low signal informs the modem or data set that the controller is ready to send |

F71889E

| | | | | |
|-----|-------------|-----------------------|-----|---|
| | | | | data. Internal 47k ohms pulled high and disable after power on strapping. |
| | 80PORT_TRAP | IN _{t,5v} | | Power on strapping pin: 1(Default) : Default 80-port enable (Internal pull high) 80 port decode output from COM2 interface 0 : Disable 80-port function |
| 123 | DSR1# | IN _{t,5v} | VCC | Data Set Ready. An active low signal indicates the modem or data set is ready to establish a communication link and transfer data to the UART. |
| 124 | SOUT1 | O _{8,u47,5v} | VCC | UART 1 Serial Output. Used to transmit serial data out to the communication link. Internal 47k ohms pulled high and disable after power on strapping. |
| | Config4E_2E | IN _{t,5v} | | Power on strapping: (Internal pull high) 1(Default): Configuration register →4E 0 : Configuration register →2E |
| 125 | SIN1 | IN _{t,5v} | VCC | Serial Input. Used to receive serial data through the communication link. |
| 126 | DCD2# | IN _{t,5v} | VCC | Data Carrier Detect. An active low signal indicates the modem or data set has detected a data carrier. |
| | SEGG | O ₁₈ | | SEGG for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO30 | I/OOD _{18t} | | General purpose IO. (Select by register) |
| 127 | RI2# | IN _{t,5v} | VCC | Ring Indicator. An active low signal indicates that a ring signal is being received from the modem or data set. |
| | SEGF | O ₁₈ | | SEGF for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO31 | I/OOD _{18t} | | General purpose IO. (Select by register) |
| 128 | CTS2# | IN _{t,5v} | VCC | Clear To Send is the modem control input. |
| | SEGA | O ₁₈ | | SEGA for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO32 | I/OOD _{18t} | | General purpose IO. (Select by register) |
| 2 | DTR2# | O _{8,u47,5v} | VCC | UART 2 Data Terminal Ready. An active low signal informs the modem or data set that controller is ready to communicate. Internal 47k ohms pulled high and disable after power on strapping. |
| | SEGD | O ₁₈ | | SEGD for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO33 | I/OOD _{18t} | | General purpose IO. (Select by register) |
| | BSGPIO_TRAP | IN _{t,5v} | | Power on strapping : (Default internal pull high) 0: Pin 51-56 are Bus Interface functions 1 (Default) : Pin 51-56 are GPIO pins |
| 3 | RTS2# | O _{8,u47,5v} | VCC | UART 2 Request To Send. An active low signal informs the modem or data set that the controller is ready to send data. Internal 47k ohms pulled high and disable after power on strapping. |
| | SEGC | O ₁₈ | | SEGC for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO34 | I/OOD _{18t} | | General purpose IO. (Select by register) |
| | PWM_DC | IN _{t,5v} | | Power on strapping : 1 (Default): Fan control method will be in PWM Mode 0 Drive :Fan control method will be in Linear Mode |
| 4 | DSR2# | IN _{t,5v} | VCC | Data Set Ready. An active low signal indicates the modem or data set is ready to establish a communication |

F71889E

| | | | | |
|---|--------|-----------------------|-----|---|
| | | | | link and transfer data to the UART. |
| | L# | O ₃₀ | | L# for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO35 | I/OOD _{12t} | | General purpose IO. (Select by register) |
| 5 | SOUT2 | O _{8,u47,5v} | VCC | UART 2 Serial Output. Used to transmit serial data out to the communication link. Internal 47k ohms pulled high and disable after power on strapping. |
| | SEGB | O ₁₈ | | SEGB for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO36 | I/OOD _{18t} | | General purpose IO. (Select by register) |
| 6 | SIN2 | IN _{t,5v} | VCC | Serial Input. Used to receive serial data through the communication link. |
| | SEGE | O ₁₈ | | SEGE for 7-segment display. (Select by pin 122 power on strapping) |
| | GPIO37 | I/OOD _{18t} | | General purpose IO. (Select by register) |

6.4 Parallel Port

| Pin No. | Pin Name | Type | PWR | Description |
|---------|-----------------|----------------------|-----|--|
| 100 | SLCT | IN _{st,5v} | VCC | An active high input on this pin indicates that the printer is selected. Refer to the description of the parallel port for definition of this pin in ECP and EPP mode. |
| | VIDIN0 | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH 0.9V, VIL 0.6V |
| | GPIO60 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 101 | PE | IN _{st,5v} | VCC | An active high input on this pin indicates that the printer has detected the end of the paper. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | VIDIN1 | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH → 0.9V, VIL → 0.6V |
| | GPIO61 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 102 | BUSY | IN _{st,5v} | VCC | An active high input indicates that the printer is not ready to receive data. Refer to the description of the parallel port for definition of this pin in ECP and EPP mode. |
| | VIDIN2 (SVD_IN) | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH → 0.9V, VIL → 0.6V |
| | GPIO62 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 103 | ACK# | IN _{st,5v} | VCC | An active low input on this pin indicates that the printer has received data and is ready to accept more data. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | VIDIN3 (SVC_IN) | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH → 0.9V, VIL → 0.6V |
| | GPIO63 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |

F71889E

| | | | | |
|-----|------------|------------------------|-----|--|
| 104 | SLIN# | I/OOD _{12,5v} | VCC | Output line for detection of printer selection. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | CoreTP | IN _{st,lv} | | Processor Core_Type pin for AMD CPU identification. |
| | VIDIO_TRAP | IN _{t,5v} | | Power on strapping : Pull high 1K : Pin 100-116 as LPT interfaces Pull high 20K : Pin 100-116 as PVID Controller Pull down 1K: Pin 102/103/111/112 as SVID Controller Pull down 47K:Pin 100-103 and pin 105-116 as GPIO pins |
| 105 | INIT# | I/OOD _{12,5v} | VCC | Output line for the printer initialization. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | VIDIN4 | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH → 0.9V, VIL → 0.6V |
| | GPIO64 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 106 | ERR# | IN _{st,5v} | VCC | An active low input on this pin indicates that the printer has encountered an error condition. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | VIDIN5 | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH → 0.9V, VIL → 0.6V |
| | GPIO65 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 107 | AFD# | I/OOD _{12,5v} | VCC | An active low output from this pin causes the printer to auto feed a line after a line is printed. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | H# | O ₃₀ | | H# signal of 80-port for 7-segment display. |
| | VIDIN6 | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH → 0.9V, VIL 0.6V |
| | GPIO66 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 108 | STB# | I/OOD _{12,5v} | VCC | An active low output is used to latch the parallel data into the printer. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | L# | O ₃₀ | | L# signal of 80-port for 7-segment display. |
| | VIDIN7 | IN _{st,lv} | | CPU VID input pin. (Select by pin 104 power on strapping) Special Level input VIH (0.9V, VIL 0.6V |
| | GPIO67 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 109 | PD0 | I/O _{12st,5v} | VCC | Parallel port data bus bit 0. Refer to the description of the parallel port for the definition of this pin in ECP and EPP mode. |
| | SEGA | O ₁₂ | | SEGA signal of 80-port for 7-segment display. |
| | VIDOUT0 | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |
| | GPIO70 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 110 | PD1 | I/O _{12st,5v} | VCC | Parallel port data bus bit 1. |
| | SEGB | O ₁₂ | | SEGB signal of 80-port for 7-segment display. |
| | VIDOUT1 | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |

F71889E

| | | | | |
|-----|-------------------|------------------------|-----|--|
| | GPIO71 | I/OOD _{12t} | | strapping) General purpose IO. (Select by pin 104 power on strapping) |
| 111 | PD2 | I/O _{12st,5v} | VCC | Parallel port data bus bit 2. |
| | SEGC | O ₁₂ | | SEGC signal of 80-port for 7-segment display. |
| | VIDOUT2 (SVD_OUT) | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |
| | GPIO72 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 112 | PD3 | I/O _{12st,5v} | VCC | Parallel port data bus bit 3. |
| | SEGD | O ₁₂ | | SEGD signal of 80-port for 7-segment display. |
| | VIDOUT3 (SVC_OUT) | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |
| | GPIO73 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 113 | PD4 | I/O _{12st,5v} | VCC | Parallel port data bus bit 4. |
| | SEGE | O ₁₂ | | SEGE signal of 80-port for 7-segment display. |
| | VIDOUT4 | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |
| | GPIO74 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 114 | PD5 | I/O _{12st,5v} | VCC | Parallel port data bus bit 5. |
| | SEGF | O ₁₂ | | SEGF signal of 80-port for 7-segment display. |
| | VIDOUT5 | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |
| | GPIO75 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 115 | PD6 | I/O _{12st,5v} | VCC | Parallel port data bus bit 6. |
| | SEGG | O ₁₂ | | SEGG signal of 80-port for 7-segment display. |
| | VIDOUT6 | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |
| | GPIO76 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |
| 116 | PD7 | I/O _{12st,5v} | VCC | Parallel port data bus bit 7. |
| | VIDOUT7 | OD ₁₂ | | CPU VID output pin. (Select by pin 104 power on strapping) |
| | GPIO77 | I/OOD _{12t} | | General purpose IO. (Select by pin 104 power on strapping) |

6.5 Hardware Monitor, EUP

| Pin No. | Pin Name | Type | PWR | Description |
|---------|-------------|-----------------------------|---------|--|
| 93-97 | VIN6~VIN2 | AIN | I_VSB3V | Voltage Input 2 ~ 6. |
| 98 | Vcore(VIN1) | AIN | I_VSB3V | Voltage Input for Vcore. |
| 21 | FANIN1 | IN _{st,5v} | VCC | Fan 1 tachometer input. |
| 22 | FANCTL1 | OD _{12,5v} AOUT | VCC | Fan 1 control output. This pin provides PWM duty-cycle output or a voltage output. |
| 23 | FANIN2 | IN _{st,5,4v} | VCC | Fan 2 tachometer input. |
| 24 | FANCTL2 | OD _{12,5v} AOUT | VCC | Fan 2 control output. This pin provides PWM duty-cycle output or a voltage output. |
| 25 | FANIN3 | IN _{st,5v} | VCC | Fan 3 speed input. |
| | GPIO10 | I/OOD _{12t} | | General purpose IO. (Select by Register) |

F71889E

| | | | | |
|----|-------------|-----------------------------|---------|---|
| | IRRX1 | IN _{st} | | Infrared Receiver input. (Select by Register) |
| 26 | FANCTL3 | OD _{12,5v} AOUT | VCC | Fan 3 control output. |
| | GPIO11 | I/OOD _{12t} | | General purpose IO. (Select by Register) |
| | IRTX1 | O ₁₂ | | Infrared Transmitter Output. (Select by Register) |
| 89 | D3+(System) | AIN | I_VSB3V | Thermal diode/transistor temperature sensor input for system use. |
| 90 | D2+ | AIN | I_VSB3V | Thermal diode/transistor temperature sensor input. |
| 91 | D1+(CPU) | AIN | I_VSB3V | CPU thermal diode/transistor temperature sensor input. This pin is for CPU use. |
| 92 | VREF | AOUT | I_VSB3V | Voltage sensor output. |
| 75 | PME# | OD _{12,5v} | I_VSB3V | Generated PME event. It supports the PCI PME# interface. This signal allows the peripheral to request the system to wake up from the S3 state. |
| 45 | EVENT_IN0# | IN _{st,5v} | I_VSB3V | Wake-up event input. The signal input wakes the system up from the sleep state. |
| 46 | USBEN | O ₁₂ | I_VSB3V | USB Power Control Signal |
| | EVENT_IN1# | IN _{st,5v} | | Wake-up event input. The signal input wakes the system up from the sleep state. |
| 47 | VSB_CTRL0# | OD ₁₂ | I_VSB3V | Standby power rail control pin 0. This pin controls an external PMOS to turn on or off the standby power rail. In the S5 state, the default is set to 1 to cut off the standby power rail. |
| 48 | VSB_CTRL1# | OD ₁₂ | I_VSB3V | Standby power rail control pin 1. This pin controls an external PMOS to turn on or off the standby power rail. In the S5 state, the default is set to 1 to cut off the standby power rail. |
| 61 | OVT# | OD _{12,5v} | I_VSB3V | Over temperature signal output. |
| 40 | GPIO12 | I/OOD _{12t} | VCC | General purpose IO. |
| | WDTRST# | OD _{12,5v} | | Watch dog timer signal output. (Select by register) |
| 41 | IRTX | O ₁₂ | VCC | Infrared Transmitter Output. (Select by register) |
| | TSI_CLK | I/OD _{12st,lv} | | Clock output for AMD TSI interface. (Select by register) |
| | IBX_CLK | I/OD _{12st,lv} | | Clock output for INTEL PCH (IBex Peak) interface. (Select by register) |
| | GPIO13 | I/OOD _{12t} | | General purpose IO. (Select by register) |
| 42 | IRRX | IN _{st} | VCC | Infrared Receiver input. (Select by register) |
| | TSI_DAT | I/OD _{12st,lv} | | AMD TSI data interface. (Select by register) |
| | IBX_SDA | I/OD _{12st,lv} | | INTEL PCH (IBex Peak) data interface pin. (Select by register) |
| | GPIO14 | I/OOD _{12t} | | General purpose IO. (Select by register) |
| 43 | SST | I/O _{D8,st,lv} | VCC | Intel SST hardware monitor interface. (Default) |
| | TSI_CLK | I/OD _{12st,lv} | | Clock output for AMD TSI interface. (Select by register) |
| | IBX_CLK | I/OD _{12st,lv} | | Clock output for INTEL PCH (IBex Peak) interface. (Select by register) |

F71889E

| | | | | |
|----|---------|---------------------------|-----|--|
| | GPIO15 | I/OD _{12st,lv} | | General purpose IO. (Selecty by register) |
| 44 | PECI | I/O _{s1,D8st,lv} | VCC | Intel Peci hardware monitor interface. (Default) |
| | TSI_DAT | I/OD _{12st,lv} | | AMD TSI data interface. (Select by register) |
| | IBX_SDA | I/OD _{12st,lv} | | INTEL PCH (IBex Peak) data interface pin. (Select by register) |
| | GPIO16 | I/OD _{12st,lv} | | General purpose IO. (Selecty by register) |

6.6 ACPI Function Pins

| Pin No. | Pin Name | Type | PWR | Description |
|---------|----------|---------------------|---------|---|
| 62 | PCIRST1# | OD _{12,5v} | I_VSB3V | It is an output buffer of LRESET#. |
| 63 | PCIRST2# | O ₂₄ | I_VSB3V | It is an output buffer of LRESET#. |
| 64 | PCIRST3# | O ₂₄ | I_VSB3V | It is an output buffer of LRESET#. |
| 71 | VCCGATE | O ₁₂ | I_VSB3V | Driver output for 5VCC. Connect this pin to the gate of a suitable NMOS. |
| 72 | DUALGATE | OD ₁₂ | I_VSB3V | Driver output for 5VSB. Connect this pin to the gate of a suitable PMOS. |
| 73 | S5# | IN _{st,5v} | I_VSB3V | S5# input. This pin companies with S3# to indicate operating state from S0 to S3 and S4/S5 sleep states. |
| 74 | ATXPG_IN | IN _{st,5v} | I_VSB3V | ATX Power Good input. |
| 76 | PWSIN# | IN _{st,5v} | I_VSB3V | Main power switch button input. |
| 77 | PWSOUT# | OD _{12,5v} | I_VSB3V | Panel Switch Output. This pin is low active and pulse output. It is power on request output#. |
| 78 | S3# | IN _{st,5v} | I_VSB3V | S3# Input: Main power on-off switch input. |
| 79 | PSON# | OD _{12,5v} | I_VSB3V | Power supply on-off control output. Connect to ATX power supply PS_ON# signal. |
| 80 | PWROK | OD _{12,5v} | VBAT | PWROK function, It is power good signal of VCC, which is delayed 100ms (default) as VCC arrives at 2.8V. It falls when S3# gets low. |
| 81 | RSMRST# | OD _{12,5v} | VBAT | Resume Reset# function, It is power good signal of VSB3V_IN, which is delayed 66ms as VSB arrives at 2.95V. There is an option to set RSMRST# falls when VSB drops to 2.3V. |
| 83 | COPEN# | IN _{st,5v} | VBAT | Case Open Detection #. This pin is connected to a specially designed low power CMOS flip-flop back by the battery for case open state preservation during power loss. |
| 84 | VREF_EN | IN _{st,5v} | I_VSB3V | Reference Voltage DAC output enable pin. Input high to this pin to enable VREF2 and VREF3. On the contrary, VREF2 and VREF3 will be disabled when input low to this pin. The specific timing can be referred in Figure 16~19. |
| 85 | VREF3 | AOUT | I_VSB3V | Deafault 0.9V reference voltage output. The on/off sequence of this pin can be controlled by S3#, S5#, and VREF_EN. The specific timing can be referred in Figure 16~19. |
| 86 | VREF2 | AOUT | I_VSB3V | Deafault 0.9V reference voltage output. The on/off sequence of this pin can be controlled by S3#, S5#, and VREF_EN. The specific timing can be referred in |

F71889E

| | | | | |
|----|-------|------|---------|--|
| | | | | Figure 16~19. |
| 87 | VREF1 | AOUT | I_VSB3V | Deafault 0.9V reference voltage output. Deafault 0.9V reference voltage output. The on/off sequence of this pin can be controlled by S3# and S5#. The specific timing can be referred in Figure 16~19. |

6.7 Bus Interface

| Pin No. | Pin Name | Type | PWR | Description |
|---------|-------------|--------------------------|---------|---|
| 51-53 | GPIO2[5:7] | I/OOD _{12st,lv} | I_VSB3V | General purpose pin. (Select by pin 2 power on strapping) |
| | BUSIN[0:2] | IN _{st,lv} | | BUSIN input pins. Special level input VIH → 0.9, VIL → 0.6 |
| 54-56 | GPIO0[0:2] | I/OOD _{12t} | I_VSB3V | General purpose pin. (Select by pin 2 power on strapping) |
| | BUSOUT[0:2] | OD ₁₂ | | BUS OUT output pins. |
| 57 | SLOTOCC# | IN _{st,5v} | I_VSB3V | CPU SLOTOCC# input. |
| | GPIO03 | I/OOD _{12t} | | General purpose pin. |
| 58 | GPIO04 | I/OOD _{12t} | I_VSB3V | General purpose pin. |
| | LED_VSB | OOD ₁₂ | | Power LED for VSB |
| 59 | GPIO05 | I/OOD _{12t} | I_VSB3V | General purpose pin. |
| | LED_VCC | OOD ₁₂ | | Power LED for VCC |
| 60 | SUSC# | O ₁₂ | I_VSB3V | S5 latch signal. |
| | GPIO06 | I/OOD _{12t} | | General purpose pin. |
| | BEEP | OD ₁₂ | | Beep pin. |
| | ALERT# | OD ₁₂ | | Alert a signal when something issues. |

6.8 KBC Function

| Pin No. | Pin Name | Type | PWR | Description |
|---------|----------|-------------------------|---------|--|
| 38 | KBRST# | OD _{16,u10,5v} | VCC | Keyboard reset. This pin is high after system reset. Internal pull high 3.3V with 10k ohms. (KBC P20) |
| 39 | GA20 | OD _{16,u10,5v} | VCC | Gate A20 output. This pin is high after system reset. Internal pull high 3.3V with 10k ohms. (KBC P21) |
| 66 | KDATA | I/OD _{16st,5v} | I_VSB3V | Keyboard Data. |
| 67 | KCLK | I/OD _{16st,5v} | I_VSB3V | Keyboard Clock. |
| 68 | MDAT | I/OD _{16st,5v} | I_VSB3V | PS2 Mouse Data. |
| 69 | MCLK | I/OD _{16st,5v} | I_VSB3V | PS2 Mouse Clock. |

7. Function Description

7.1. Power on Strapping Option

The F71889 provides six pins for power on hardware strapping to select functions. Power on strapping value follows TTL voltage level. Below table describes how to set the functions you want.

Table1. Power on trap configuration

| Pin No. | Symbol | Value | Description |
|---------|-------------|---------------|---|
| 2 | BSGPIO_TRAP | 1 | Pin 51-56 are GPIO pins (Default) |
| | | 0 | Pin 51-56 are Bus Interface functions |
| 3 | PWM_DC | 1 | Fan control mode: PWM mode. (Default) |
| | | 0 | Fan control mode: DAC mode. |
| 104 | VIDIO_TRAP | Pull high 1K | Pin 100-116 as LPT interfaces |
| | | Pull high 20K | Pin 100-116 as PVID Controller |
| | | Pull down 1K | Pin 102/103/111/112 as SVID Controller |
| | | Pull down 47K | Pin 100-103 and pin 105-116 as GPIO pins |
| 121 | FAN60_100 | 1 | Fan full duty is 60%. (Default) |
| | | 0 | Fan full duty is 100%. |
| 122 | 80PORT_TRAP | 1 | Enable the 80 port function. (Default) |
| | | 0 | Disable the 80 port function. |
| 124 | Config4E_2E | 1 | Configuration Register I/O port is 4E/4F. (Default) |
| | | 0 | Configuration Register I/O port is 2E/2F. |

7.2. Hardware Monitor

For the 8-bit ADC has the 8mv LSB, the maximum input voltage of the analog pin is 2.04V. Therefore the voltage under 2.04V (ex:1.5V) can be directly connected to these analog inputs. The voltage higher than 2.04V should be reduced by a factor with external resistors so as to obtain the input range. Only 3Vcc is an exception for it is main power of the F71889E. Therefore 3Vcc can directly connect to this chip's power pin and need no external resistors. There are two functions in this pin with 3.3V. The first function is to supply internal analog power of the F71889 and the second function is that voltage with 3.3V is connected to internal serial resistors to monitor the +3.3V voltage. The internal serial resistors are two 150K ohm, so that the internal reduced voltage is half of +3.3V.

There are four voltage inputs in the F71889E and the voltage divided formula is shown as follows:

$$V_{IN} = V_{+12V} \times \frac{R_2}{R_1 + R_2} \quad \text{where } V_{+12V} \text{ is the analog input voltage, for example (Figure 1).}$$

If we choose R1=27K, R2=5.1K, the exact input voltage for V+12v will be 1.907V, which is within

the tolerance. As for application circuit, it can be refer to the figure shown as follows.




Figure 2. Hardware monitor configuration

SMI# interrupt for voltage is shown as figure 3. Voltage exceeding or going below high limit will cause an interrupt if the previous interrupt has been reset by writing "1" all the interrupt Status Register. Voltage exceeding or going below low limit will result the same condition as voltage exceeding or going below high limit.




Figure 3

The F71889E monitors three remote temperature sensors. These sensors can be measured from -40°C to 127°C . More detail please refer to the register description.

Table 2. Remote-sensor transistor manufacturers

| Manufacturer | Model Number |
|--------------|----------------|
| Panasonic | 2SB0709 2N3906 |
| Philips | PMBT3906 |

Monitor Temperature from “thermistor”

The F71889E can connect three thermistors to measure environment temperature or remote temperature. The specification of thermistor should be considered to (1) value is 3435K (2) resistor value is 10K ohm at 25°C. In the Figure 7-2, the thermistor is connected by a serial resistor with 10K ohm, then and then connected to VREF.

Monitor Temperature from “thermal diode”

Also, if the CPU, GPU or external circuits provide thermal diode for temperature measurement, the F71889E is capable to these situations. The build-in reference table is for PNP 2N3906 transistor, and each different kind of thermal diode should be matched with specific offset and BJT gain. In the Figure 7-2, the transistor is directly connected into temperature pins.

ADC Noise Filtering

The ADC is integrating type with inherently good noise rejection. Micro-power operation places constraints on high-frequency noise rejection; therefore, careful PCB board layout and suitable external filtering are required for high-accuracy remote measurement in electronically noisy environment. High frequency EMI is best filtered at D+ and D- with an external 2200pF or 3300pF capacitor. Too high capacitance may introduce errors due to the rise time of the switched current source. Nearly all noise sources tested cause the ADC measurement to be higher than the actual temperature, depending on the frequency and amplitude.

Over Temperature Signal (OVT#)

OVT# alert for temperature is shown as figure 7-4. When monitored temperature exceeds the over-temperature threshold value, OVT# will be asserted until the temperature goes below the hysteresis temperature.




Figure 4

Temperature PME#

PME# interrupt for temperature is shown as figure 7-5. Temperature exceeding high limit or going below hysteresis will cause an interrupt if the previous interrupt has been reset by writing "1" all the interrupt Status Register.




Figure 5

Fan speed count

Inputs are provided by the signals from fans equipped with tachometer outputs. The level of these signals should be set to TTL level, and maximum input voltage cannot be over 5V. If the input signals from the tachometer outputs are over the 5V, the external trimming circuit should be added to reduce the voltage to obtain the input specification. The normal circuit and trimming circuits are shown as follows:

Determine the fan counter according to:

$$\text{Count} = \frac{1.5 \times 10^6}{\text{RPM}}$$

F71889E

In other words, the fan speed counter (12 bit resolution) has been read from register, the fan speed can be evaluated by the following equation.

$$\text{RPM} = \frac{1.5 \times 10^6}{\text{Count}}$$

As for fan, it would be best to use 2 pulses (4 phases fan) tachometer output per round. So the parameter "Count" under 5 bit filter is 4096~64 and RPM is 366~23438 based on above equation. If using 8 phases fan, RPM would be from 183~11719.

Fan speed control

The F71889E provides 2 fan speed control methods:

1. DAC FAN CONTROL
2. PWM DUTY CYCLE

DAC Fan Control

The range of DC output is 0~VCC, controlled by 8-bit register. 1 LSB is about 0.013V (VCC=3.3V). The output DC voltage is amplified by external OP circuit, thus to reach maximum FAN OPERATION VOLTAGE, 12V. The output voltage will be given as followed:

$$\text{Output_voltage (V)} = V_{cc} \times \frac{\text{Programmed 8bit Register Value}}{256}$$

And the suggested application circuit for linear fan control would be:




Figure 6 DAC fan control application circuit

PWM duty Fan Control

The duty cycle of PWM can be programmed by an 8-bit register. The default duty cycle is set to 100%, that is, the default 8-bit registers is set to FFh. The expression of duty can be represented as follows.

$$\text{Duty_cycle(\%)} = \frac{\text{Programmed 8bit Register Value}}{255} \times 100\%$$




Figure 7 +12/5V PWM fan control application circuit

Fan speed control mechanism

There are some modes to control fan speed and they are 1. Manual mode, 2. Auto mode (Stage & Linear). More detail, please refer to the description of registers. The Manual Mode and Auto Mode could be selected by register 0x96h.

Manual mode

For manual mode, it generally acts as software fan speed control.

Auto mode

In auto mode, the F71889A provides automatic fan speed control related to temperature variation of CPU/GPU or the system. The F71889E can provide four temperature boundaries and five intervals, and each interval has its related fan speed count. All these values should be set by BIOS first. Take FAN1 for example, the 4 temperature boundaries could be set from register 0xA6 to 0xA9 and the five intervals for fan speed control could be set from register 0xAA to 0xAE. And the hysteresis setting (0 ~ 15°C) could also be found in register 0x98.

There are two kinds of auto mode: stage auto mode and linear auto mode.

The "FAN1_INTERPOLATION_EN" in register 0xAFh is used for linear auto mode enable. The following

examples explain the differences for stage auto mode and linear auto mode.

➤ **Stage auto mode**

In this mode, the fan keeps in a same speed for each temperature interval. And there are two types of fan speed setting: PWM Duty and RPM %.

A. Stage auto mode (PWM Duty)

Set temperature as 70°C, 60°C, 50°C, 40°C and the duty as 100%, 90%, 80%, 70%, 60%




Figure 8 Stage mode fan control illustration-2

- Once the temperature is under 40°C, the lowest fan speed keeps in the 60% PWM duty.
- Once the temperature is over 40°C, 50°C and 60°C, the fan speed will vary from 70%, 80% to 90% PWM duty and increasing with the temperature level.
- For the temperature higher than 70°C, the fan speed keeps in 100% PWM duty.
- If set the hysteresis is 3°C (default 4°C), once the temperature becomes lower than 67°C, the fan speed would reduce to 90% PWM duty.

B. Stage auto mode (RPM%)

Set the temperature as 70°C, 60°C, 50°C, 40°C and the corresponding fan speed is 6,000 RPM, 5,400 RPM, 4,800 RPM, 4,200 RPM, and 3,600 RPM (assume the Max Fan Speed is 6,000 RPM).




Figure 9 Stage mode fan control illustration-3

- Once the temperature is lower than 40°C, the lowest fan speed keeps in 3,600 RPM (60% of full speed).
- Once the temperature is higher than 40°C, 50°C and 60°C, the fan speed will vary from 4,200 RPM to 5,400 RPM and increasing with the temperature level.
- For the temperature higher than 70°C, the fan speed keeps in the full speed 6,000 RPM.
- If the hysteresis is set as 3°C (default 4°C), once temperature gets lower than 67°C, the fan speed would reduce to 5,400 RPM.

➤ **Linear auto mode**

F71889A also supports linear auto mode. The fan speed would increase or decrease linearly with the temperature. There are also PWM Duty and RPM% modes for it.

A. Linear auto mode (PWM Duty)

Set the temperature as 70°C, 60°C, 50°C and 40°C and the duty is 100%, 80%, 70%, 60% and 50%.




Figure 10 Linear mode fan control illustration-1

- Once the temperature is lower than 40°C, the lowest fan speed keeps in the 50% PWM duty
- Once the temperature becomes higher than 40°C, 50°C and 60°C, the fan speed will vary from 50% to 80% PWM duty linearly with the temperature variation. The temp.-fan speed monitoring flash interval is 1sec.
- Once the temperature goes over 70°C, the fan speed will directly increase to 100% PWM duty (full speed).
- If set the hysteresis is 5°C (default is 4°C), once the temperature becomes lower than 65°C (instead of 70°C), the fan speed will reduce from 100% PWM duty and decrease linearly with the temperature.

B. Linear auto mode (RPM%)

Set the temperature as 70°C, 60°C, 50°C, 40°C and the corresponding fan speed is 6,000 RPM, 4,800 RPM, 4,200 RPM, 3,600 RPM and 3,000 RPM (assume the Max Fan Speed is 6,000 RPM).




Figure 11 Linear mode fan control illustration-2

- Once the temperature is lower than 40°C, the lowest fan speed keeps in 3,000 RPM (50% of full speed).
- Once the temperature is over 40°C, 50°C and 60°C, the fan speed will vary from 3,000 to 4,800 RPM almost linearly with the temperature variation because the temp.-fan speed monitoring flash interval is 1sec.
- Once the temperature goes over 70°C, the fan speed will directly increase to full speed 6,000 RPM.
- If the hysteresis is 5°C (default is 4°C), once the temperature becomes lower than 65°C (instead of 70°C), the fan speed will reduce from full speed and decrease linearly with the temperature.

PWMOUT Duty-cycle operating process

In both "Manual RPM" and "Temperature RPM" modes, the F71889E adjust PWMOUT duty-cycle according to current fan count and expected fan count. It will operate as follows:

- (1). When expected count is 0xFFFF, PWMOUT duty-cycle will be set to 0x00 to turn off

fan.

- (2). When expected count is 0x000, PWMOUT duty-cycle will be set to 0xFF to turn on fan with full speed.
- (3). If both (1) and (2) are not true,
- (4). When PWMOUT duty-cycle decrease to MIN_DUTY(≠ 00h), obviously the duty-cycle will decrease to 00h next, the F71889E will keep duty-cycle at 00h for 1.6 seconds. After that, the F71889E starts to compare current fan count and expected count in order to increase or decrease its duty-cycle. This ensures that if there is any glitch during the period, the F71889E will ignore it.



Figure 12

FAN_FAULT#

Fan_Fault# will be asserted when the fan speed doesn't meet the expected fan speed within a programmable period (default is 11 seconds) or when fan stops with respect to PWM duty-cycle which should be able to turn on the fan. There are two conditions may cause the FAN_FAULT# event.

- (1). When PWM_Duty reaches 0xFF, the fan speed count can't reach the fan expected count in time. (Figure 7-13)




Figure 13 FAN_FAULT# event

- (2). After the period of detecting fan full speed, when PWM_Duty > Min. Duty, and fan count still in 0xFFFF.

T1 Architecture

The F71889E implement the Intel PECI/SST interface and AMD TSI interface to collect the CPU temperature for fan control. The CPU temperature source could be programmed to be from external

diode, Intel PECI interface or AMD TSI interface.

Device registers, the following is a register map order which shows a summary of all registers. Please refer each one register if you want more detail information.

Register CR01 ~ CR03 → Configuration Registers

Register CR0A ~ CR0F → PECI/SST/TSI Control Register

Register CR10 ~ CR4F → Voltage Setting Register

Register CR60 ~ CR8E → Temperature Setting Register

Register CR90 ~ CRDF → Fan Control Setting Register

→Fan1 Detail Setting CRA0 ~ CRAF

→Fan2 Detail Setting CRB0 ~ CRBF

→Fan3 Detail Setting CRC0 ~ CRCF

Register CR5A ~ CR5D → HW Chip ID and Vender ID Register

7.5.1 Configuration Register — Index 01h

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|--|
| 7 | BETA_EN | R/W | 1 | 0: disable the T1 beta compensation. 1: enable the T1 beta compensation. |
| 6 | INTEL_MODEL | R/W | 1 | 0: AMD model. 1: Intel model. |
| 5 | TSI_EN | R/W | 0 | 0: Disable the TSI function via PECI/SST pins. 1: Enable the TSI function via PECI/SST pins. This bit accompanying with INTEL_MODEL and SST_EN will determine the availability of AMD TSI, Intel PCH SMBus, PECI and SST (This bit is cleared by LRESET#). See below table: |

| Setting (CR07[1]- NEW_MODE_EN = 0) | | | | | | Results | | | |
|------------------------------------|------------------------|------------------------|----------------------------|-------------------------|----------------------------|---------|-----|------------|--------------------|
| INTEL_MODEL (CR01, bit6) | TSI_EN (CR01, bit5) | SST_EN (CR0A, bit4) | TSI_ALT_EN (CR07, bit3) | PECI_EN (CR07, bit2) | NEW_TSI_EN (CR07, bit0) | PECI | SST | AMD TSI | Intel PCH SMBus |
| 0 | 0 | X | X | X | X | N | N | N | N |
| 0 | 1 | X | X | X | X | N | N | Y | N |
| 1 | 0 | 0 | X | X | X | Y | N | N | N |
| 1 | 0 | 1 | X | X | X | Y | Y | N | N |
| 1 | 1 | X | X | X | X | N | N | N | Y |

| Setting (CR07[1]- NEW_MODE_EN = 1) | | | | | | Results | | | |
|------------------------------------|------------------------|------------------------|----------------------------|-------------------------|----------------------------|---------|-----|------------|--------------------|
| INTEL_MODEL (CR01, bit6) | TSI_EN (CR01, bit5) | SST_EN (CR0A, bit4) | TSI_ALT_EN (CR07, bit3) | PECI_EN (CR07, bit2) | NEW_TSI_EN (CR07, bit0) | PECI | SST | AMD TSI | Intel PCH SMBus |
| 0 | 0 | X | X | X | X | N | N | N | N |
| 0 | 1 | X | X | X | 0 | N | N | Y | N |
| 1 | 1 | 0 | X | 0 | 1 | N | N | Y | N |
| 1 | 1 | 1 | 1 | 1 | 1 | Y | Y | Y | N |
| 1 | 1 | 1 | 1 | 1 | 0 | Y | Y | N | Y |
| 0 | 1 | X | 0 | X | 1 | N | N | N | Y |
| 1 | X | 1 | X | 1 | X | Y | Y | N | N |

| | | | | |
|-----|------------|-----|---|---|
| 4-3 | Reserved | - | - | Reserved |
| 2 | POWER_DOWN | R/W | 0 | Hardware monitor function power down. |
| 1 | FAN_START | R/W | 1 | Set one to enable startup of fan monitoring operations; a zero puts the part in standby mode. |
| 0 | V_T_START | R/W | 1 | Set one to enable startup of temperature and voltage monitoring operations; a zero puts the part in standby mode. |

7.5.2 Protection Mode Configuration Register — Index 02h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7 | Reserved | R/W | 0 | Dummy register. |
| 6 | CASE_BEEP_EN | R/W | 0 | 0: Disable case open event output via BEEP. 1: Enable case open event output via BEEP. |
| 5-4 | OVT_MODE | R/W | 0 | 00: The OVT# will be low active level mode. 01: The OVT# will be high active level mode. 10: The OVT# will indicate by 1Hz LED function. 11: The OVT# will indicate by (400/800HZ) BEEP output. |
| 3 | Reserved | R/W | 0 | Dummy register. |
| 2 | CASE_SMI_EN | R/W | 0 | 0: Disable case open event output via PME. 1: Enable case open event output via PME. |
| 1-0 | ALERT_MODE | R/W | 0 | 00: The ALERT# will be low active level mode. 01: The ALERT# will be high active level mode. 10: The ALERT# will indicate by 1Hz LED function. 11: The ALERT# will indicate by (400/800HZ) BEEP output. |

7.5.3 Case Status Register — Index 03h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-1 | Reserved | R/W | 0 | Return 0 when read. |
| 0 | CASE_STS | R/W | 0 | Case open event status, write 1 to clear if case open event cleared. |

7.5.4 Debut Port Temp Register — Index 04h

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|---|
| 7-2 | Reserved | R/W | 0 | Return 0 when read. |
| 1-0 | DPORT_TEMP_SEL | R/W | 01 | Debug port temperature source select: 00: 0xff. 01: T1 reading. 10: T2 reading. 11: T3 reading. |

7.5.5 PECI/SST/TSI Configuration Register 2 — Index 07h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7-5 | Reserved | R/W | 0 | Return 0 when read. |
| 4 | DIG_T1_SEL | R/W | 0 | This bit is used to select AMD TSI/Intel IBX or PECI to be the T1 temperature when NEW_MODE_EN is set to 1. |
| 3 | IBX_ALT_EN | R/W | 0 | This bit is used to control the AMD TSI/Intel IBX/PECI function. (see configuration register 0x00) |
| 2 | PECI_EN | R/W | 0 | This bit is used to control the AMD TSI/Intel IBX/PECI function. (see configuration register 0x00) |

F71889E

| | | | | |
|---|-------------|-----|---|--|
| 1 | NEW_MODE_EN | R/W | 0 | This bit is used to control the AMD TSI/Intel IBX/PECI function. (see configuration register 0x00) |
| 0 | NEW_TSI_EN | R/W | 0 | This bit is used to control the AMD TSI/Intel IBX/PECI function. (see configuration register 0x00) |

7.5.6 SST and VTT_SEL Register — Index 0Ah

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|--|
| 7-5 | Reserved | - | 0 | Reserved. |
| 4 | SST_EN_REG | R/W | 0 | Set this bit "1" and select Intel model will enable SST interface. Otherwise will disable SST interface This bit is cleared by LRESET#. |
| 3-2 | VTT_SEL | R/W | 0 | PECI (Vtt) voltage select. 00: Vtt is 1.23V 01: Vtt is 1.13V 10: Vtt is 1.00V 11: Vtt is 1.00V |
| 1 | DIG_T1_EN | R/W | 0 | 0: Disable the digital interface of T1 (PECI/TSI). 1: Enable the digital interface of T1. |
| 0 | DIODE_T1_EN | R/W | 1 | 0: Disable the D1+ measurement. 1: Enable the D1+ measurement. |

7.5.7 PECI Address Register — Index 0Bh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7-4 | CPU_SEL | R/W | 0 | Select the Intel CPU socket number. 0000: no CPU presented. PECI host will use Ping() command to find CPU address. 0001: CPU is in socket 0, i.e. PECI address is 0x30. 0010: CPU is in socket 1, i.e. PECI address is 0x31. 0100: CPU is in socket 2, i.e. PECI address is 0x32. 1000: CPU is in socket 3, i.e. PECI address is 0x33. Otherwise are reserved. |
| 3-1 | Reserved | - | 0 | Reserved. |
| 0 | DOMAIN1_EN | R/W | 0 | If the CPU selected is dual core. Set this register 1 to read the temperature of domain1. |

7.5.8 TCC TEMP Register — Index 0Ch

| Bit | Name | R/W | Default | Description |
|-----|-------------------------|-----|---------|---|
| 7-0 | TCC_TEMP/TSI_OFFSET SET | R/W | 8'h55 | TCC Activation Temperature/TSI Offset. When PECI is enabled, the absolute value of CPU temperature is calculated by the equation: $CPU_TEMP = TCC_TEMP + PECI\ Reading$. The range of this register is -128 ~ 127. When AMD TSI or Intel PCH SMBus is enabled, this byte is used as the offset to be added to the reading. |

7.5.9 SST ADDR Register — Index 0Dh

| Bit | Name | R/W | Default | Description |
|-----|---------------------|-----|---------|---|
| 7-0 | SST_ADDR/SMBUS_ADDR | R/W | 8'h4C | When AMD TSI or Intel PCH SMBus is enabled, this byte is used as SMBUS_ADDR. SMBUS_ADDR [7:1] is the slave address sent by the embedded master to fetch the temperature. Otherwise, this byte is used as SST_ADDR if SST is enabled. |

7.5.10 Voltage DIV Register — Index 0Eh

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-6 | VIN4_DIV | R/W | 0 | The value indicates the divisor of the voltage source. 00: voltage source is directly connected to VIN4. 01: voltage source is divided by 2 and connect to VIN4. 10: voltage source is divided by 4 and connect to VIN4. 11: voltage source is divided by 16 and connect to VIN4. |
| 5-4 | VIN3_DIV | R/W | 0 | The value indicates the divisor of the voltage source. 00: voltage source is directly connected to VIN3. 01: voltage source is divided by 2 and connect to VIN3. 10: voltage source is divided by 4 and connect to VIN3. 11: voltage source is divided by 16 and connect to VIN3. |
| 3-2 | VIN2_DIV | R/W | 0 | The value indicates the divisor of the voltage source. 00: voltage source is directly connected to VIN2. 01: voltage source is divided by 2 and connect to VIN2. 10: voltage source is divided by 4 and connect to VIN2. 11: voltage source is divided by 16 and connect to VIN2. |
| 1-0 | VIN1_DIV | R/W | 0 | The value indicates the divisor of the voltage source. 00: voltage source is directly connected to VIN1. 01: voltage source is divided by 2 and connect to VIN1. 10: voltage source is divided by 4 and connect to VIN1. 11: voltage source is divided by 16 and connect to VIN1. Above is available only if SST is enabled. Otherwise, bit 7-1 will be used as I2C_ADDR if Intel PCH SMBus is enabled. |

7.5.11 PECI Config. and Voltage Register — Index 0Fh

| Bit | Name | R/W | Default | Description | | | | | | | | | | | | | | | | | | |
|--------------|-----------------------|-----|---------|---|--------------|--------------------|-----|-----------------------|-----|-----|-----|-----|-----|-----|-----|-------|-----|-------|-----|-------|-----|-------|
| 7-4 | Reserved | | | Reserved. | | | | | | | | | | | | | | | | | | |
| 3-2 | VIN6_DIV | R/W | 0 | The value indicates the divisor of the voltage source. 00: voltage source is directly connected to VIN6. 01: voltage source is divided by 2 and connect to VIN6. 10: voltage source is divided by 4 and connect to VIN6. 11: voltage source is divided by 16 and connect to VIN6. | | | | | | | | | | | | | | | | | | |
| 1-0 | VIN5_DIV | R/W | 0 | The value indicates the divisor of the voltage source. 00: voltage source is directly connected to VIN5. 01: voltage source is divided by 2 and connect to VIN5. 10: voltage source is divided by 4 and connect to VIN5. 11: voltage source is divided by 16 and connect to VIN5. VIN6_DIV[0] and VIN5_DIV are used as TSI_TEMP_SEL[2:0] if Intel PCH SMBus is enabled. TSI_TEMP_SEL is used to select the temperature source for fan control. <table border="1" data-bbox="746 1563 1369 1859"> <thead> <tr> <th>TSI_TEMP_SEL</th> <th>Temperature Source</th> </tr> </thead> <tbody> <tr> <td>000</td> <td>Maximum of MCH or CPU</td> </tr> <tr> <td>001</td> <td>PCH</td> </tr> <tr> <td>010</td> <td>CPU</td> </tr> <tr> <td>011</td> <td>MCH</td> </tr> <tr> <td>100</td> <td>DIMM0</td> </tr> <tr> <td>101</td> <td>DIMM1</td> </tr> <tr> <td>110</td> <td>DIMM2</td> </tr> <tr> <td>111</td> <td>DIMM3</td> </tr> </tbody> </table> | TSI_TEMP_SEL | Temperature Source | 000 | Maximum of MCH or CPU | 001 | PCH | 010 | CPU | 011 | MCH | 100 | DIMM0 | 101 | DIMM1 | 110 | DIMM2 | 111 | DIMM3 |
| TSI_TEMP_SEL | Temperature Source | | | | | | | | | | | | | | | | | | | | | |
| 000 | Maximum of MCH or CPU | | | | | | | | | | | | | | | | | | | | | |
| 001 | PCH | | | | | | | | | | | | | | | | | | | | | |
| 010 | CPU | | | | | | | | | | | | | | | | | | | | | |
| 011 | MCH | | | | | | | | | | | | | | | | | | | | | |
| 100 | DIMM0 | | | | | | | | | | | | | | | | | | | | | |
| 101 | DIMM1 | | | | | | | | | | | | | | | | | | | | | |
| 110 | DIMM2 | | | | | | | | | | | | | | | | | | | | | |
| 111 | DIMM3 | | | | | | | | | | | | | | | | | | | | | |

Voltage Setting
7.5.12 Voltage1 PME# Enable Register — Index 10h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7-2 | Reserved | -- | 0 | Reserved |
| 6 | V6_OVP_EN | W | 0 | Set this bit 1 to enable V6 over-voltage protection event. |
| 5 | V5_OVP_EN | W | 0 | Set this bit 1 to enable V5 over-voltage protection event. |
| 4-2 | Reserved | -- | 0 | Reserved |
| 1 | EN_V1_PME | R/W | 0 | A one enables the corresponding interrupt status bit for PME# interrupt. Set this bit 1 to enable PME# function for VIN1. |
| 0 | VCC_OVP_EN | W | 0 | Set this bit 1 to enable VCC over-voltage protection event. |

7.5.13 Voltage1 Interrupt Status Register — Index 11h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7-2 | Reserved | -- | 0 | Reserved |
| 1 | V1_EXC_STS | R/W | 0 | This bit is set when the VIN1 is over the high limit. Write 1 to clear this bit, write 0 will be ignored. |
| 0 | OVP_STS | WC | 0 | This bit indicates that the over-voltage event had ever occurred. Write 1 to clear this bit. |

7.5.14 Voltage1 Exceeds Real Time Status Register 1 — Index 12h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-2 | Reserved | -- | 0 | Reserved |
| 1 | V1_EXC | RO | 0 | A one indicates VIN1 exceeds the high or low limit. A zero indicates VIN1 is in the safe region. |
| 0 | Reserved | -- | 0 | Reserved |

7.5.15 Voltage1 BEEP Enable Register — Index 13h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7-2 | Reserved | -- | 0 | Reserved |
| 1 | EN_V1_BEEP | R/W | 0 | A one enables the corresponding interrupt status bit for BEEP output of VIN1. |
| 0 | Reserved | -- | 0 | Reserved |

7.5.16 Over-Voltage Protection Enable Register — Index 14h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7 | Reserved | -- | 0 | Reserved |
| 6 | V6_OVP_EN | R | 0 | Set this bit 1 to enable V6 over-voltage protection event. |
| 5 | V5_OVP_EN | R | 0 | Set this bit 1 to enable V5 over-voltage protection event. |
| 4-1 | Reserved | -- | 0 | Reserved |
| 0 | VCC_OVP_EN | R | 0 | Set this bit 1 to enable VCC over-voltage protection event. |

7.5.17 Over-Voltage Protection Event Status Register — Index 15h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-1 | Reserved | -- | 0 | Reserved |
| 0 | OVP_STS | R | 0 | This bit indicates that the over-voltage event had ever occurred. Write 1 to clear this bit. |

7.5.18 Voltage reading and limit—Index 20h- 4Fh

| Address | Attribute | Default Value | Description |
|---------|-----------|---------------|---|
| 20h | RO | -- | VCC3V reading. The unit of reading is 8mV. |
| 21h | RO | -- | VIN1 (Vcore) reading. The unit of reading is 8mV. |
| 22h | RO | -- | VIN2 reading. The unit of reading is 8mV. |
| 23h | RO | -- | VIN3 reading. The unit of reading is 8mV. |
| 24h | RO | -- | VIN4 reading. The unit of reading is 8mV. |
| 25h | RO | -- | VIN5 reading. The unit of reading is 8mV. |
| 26h | RO | -- | VIN6 reading. The unit of reading is 8mV. |
| 27h | RO | -- | VSB3V reading. The unit of reading is 8mV. |
| 28h | RO | -- | VBAT reading. The unit of reading is 8mV. |
| 29~2Ch | RO | FF | Reserved |
| 2Dh | RO | -- | This byte indicates current fan1 duty. |
| 2Eh | RO | -- | This byte indicates current fan2 duty. |
| 2Fh | RO | -- | This byte indicates current fan3 duty. |
| 30h | RO | FF | Reserved. |
| 31h | R/W | FF | VCC over-voltage protection limit. The unit is 9 mV |
| 32h | R/W | FF | V1 High Limit setting register. The unit is 8mV. |
| 33~35h | RO | FF | Reserved. |
| 36h | R/W | FF | V5 over-voltage protection limit. The unit is 9 mV |
| 37h | R/W | FF | V6 over-voltage protection limit. The unit is 9 mV |
| 38-4Fh | RO | FF | Reserved. |

Temperature Setting
7.5.19 Temperature PME# Enable Register — Index 60h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7 | EN_T3_OVT_PME | R/W | 0 | If set this bit to 1, PME# signal will be issued when TEMP3 exceeds OVT limit setting. |
| 6 | EN_T2_OVT_PME | R/W | 0 | If set this bit to 1, PME# signal will be issued when TEMP2 exceeds OVT setting. |
| 5 | EN_T1_OVT_PME | R/W | 0 | If set this bit to 1, PME# signal will be issued when TEMP1 exceeds OVT setting. |
| 4 | Reserved | R/W | 0 | Reserved |
| 3 | EN_T3_EXC_PME | R/W | 0 | If set this bit to 1, PME# signal will be issued when TEMP3 exceeds high limit setting. |
| 2 | EN_T2_EXC_PME | R/W | 0 | If set this bit to 1, PME# signal will be issued when TEMP2 exceeds high limit setting. |
| 1 | EN_T1_EXC_PME | R/W | 0 | If set this bit to 1, PME# signal will be issued when TEMP1 exceeds high limit setting. |
| 0 | Reserved | R/W | 0 | Reserved |

7.5.20 Temperature Interrupt Status Register — Index 61h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7 | T3_OVT_STS | R/W | 0 | A one indicates TEMP3 temperature sensor has exceeded OVT limit or below the "OVT limit –hysteresis". Write 1 to clear this bit, write 0 will be ignored. |

F71889E

| | | | | |
|---|------------|-----|---|---|
| 6 | T2_OVT_STS | R/W | 0 | A one indicates TEMP2 temperature sensor has exceeded OVT limit or below the "OVT limit –hysteresis". Write 1 to clear this bit, write 0 will be ignored. |
| 5 | T1_OVT_STS | R/W | 0 | A one indicates TEMP1 temperature sensor has exceeded OVT limit or below the "OVT limit –hysteresis". Write 1 to clear this bit, write 0 will be ignored. |
| 4 | Reserved | R/W | 0 | Reserved |
| 3 | T3_EXC_STS | R/W | 0 | A one indicates TEMP3 temperature sensor has exceeded high limit or below the "high limit –hysteresis". Write 1 to clear this bit, write 0 will be ignored. |
| 2 | T2_EXC_STS | R/W | 0 | A one indicates TEMP2 temperature sensor has exceeded high limit or below the "high limit –hysteresis" limit. Write 1 to clear this bit, write 0 will be ignored. |
| 1 | T1_EXC_STS | R/W | 0 | A one indicates TEMP1 temperature sensor has exceeded high limit or below the "high limit –hysteresis" limit. Write 1 to clear this bit, write 0 will be ignored. |
| 0 | Reserved | R/W | 0 | Reserved |

7.5.21 Temperature Real Time Status Register — Index 62h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7 | T3_OVT | R/W | 0 | Set when the TEMP3 exceeds the OVT limit. Clear when the TEMP3 is below the "OVT limit –hysteresis" temperature. |
| 6 | T2_OVT | R/W | 0 | Set when the TEMP2 exceeds the OVT limit. Clear when the TEMP2 is below the "OVT limit –hysteresis" temperature. |
| 5 | T1_OVT | R/W | 0 | Set when the TEMP1 exceeds the OVT limit. Clear when the TEMP1 is below the "OVT limit –hysteresis" temperature. |
| 4 | Reserved | R/W | 0 | Reserved |
| 3 | T3_EXC | R/W | 0 | Set when the TEMP3 exceeds the high limit. Clear when the TEMP3 is below the "high limit –hysteresis" temperature. |
| 2 | T2_EXC | R/W | 0 | Set when the TEMP2 exceeds the high limit. Clear when the TEMP2 is below the "high limit –hysteresis" temperature. |
| 1 | T1_EXC | R/W | 0 | Set when the TEMP1 exceeds the high limit. Clear when the TEMP1 is below the "high limit –hysteresis" temperature. |
| 0 | Reserved | R/W | 0 | Reserved |

7.5.22 Temperature BEEP Enable Register — Index 63h

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|---|
| 7 | EN_T3_OVT_BEEP | R/W | 0 | If set this bit to 1, BEEP signal will be issued when TEMP3 exceeds OVT limit setting. |
| 6 | EN_T2_OVT_BEEP | R/W | 0 | If set this bit to 1, BEEP signal will be issued when TEMP2 exceeds OVT limit setting. |
| 5 | EN_T1_OVT_BEEP | R/W | 0 | If set this bit to 1, BEEP signal will be issued when TEMP1 exceeds OVT limit setting. |
| 4 | Reserved | R/W | 0 | Reserved |
| 3 | EN_T3_EXC_BEEP | R/W | 0 | If set this bit to 1, BEEP signal will be issued when TEMP3 exceeds high limit setting. |
| 2 | EN_T2_EXC_BEEP | R/W | 0 | If set this bit to 1, BEEP signal will be issued when TEMP2 exceeds high limit setting. |
| 1 | EN_T1_EXC_BEEP | R/W | 0 | If set this bit to 1, BEEP signal will be issued when TEMP1 exceeds high limit setting. |
| 0 | Reserved | R/W | 0 | Reserved |

7.5.23 OVT Output Enable Register 1 — Index 66h

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|--|
| 7 | EN_T3_ALERT | R | 0 | Enable temperature 3 alert event (asserted when temperature over high limit) |
| 6 | EN_T2_ALERT | R | 0 | Enable temperature 2 alert event (asserted when temperature over high limit) |
| 5 | EN_T1_ALERT | R | 0 | Enable temperature 1 alert event (asserted when temperature over high limit) |
| 4 | Reserved | R | 0 | Reserved. |
| 3 | EN_T3_OVT | R/W | 0 | Enable over temperature (OVT) mechanism of temperature3. |
| 2 | EN_T2_OVT | R/W | 0 | Enable over temperature (OVT) mechanism of temperature2. |
| 1 | EN_T1_OVT | R/W | 1 | Enable over temperature (OVT) mechanism of temperature1. |
| 0 | Reserved | R | 0h | Reserved. |

7.5.24 Temperature Sensor Type Register — Index 6Bh

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-4 | Reserved | RO | 0 | Reserved |
| 3 | T3_MODE | R/W | 1 | 0: TEMP3 is connected to a thermistor 1: TEMP3 is connected to a BJT (default). |
| 2 | T2_MODE | R/W | 1 | 0: TEMP2 is connected to a thermistor. 1: TEMP2 is connected to a BJT (default). |
| 1 | T1_MODE | R/W | 1 | 0: TEMP1 is connected to a thermistor 1: TEMP1 is connected to a BJT (default). |
| 0 | Reserved | R | 0h | -- |

7.5.25 TEMP1 Limit Hystersis Select Register -- Index 6Ch

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-4 | TEMP1_HYS | R/W | 4h | Limit hysteresis. (0~15°C) Temperature and below the (boundary – hysteresis). |
| 3-0 | Reserved | R | 0h | -- |

7.5.26 TEMP2 and TEMP3 Limit Hystersis Select Register -- Index 6Dh

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-4 | TEMP3_HYS | R/W | 2h | Limit hysteresis. (0~15°C) Temperature and below the (boundary – hysteresis). |
| 3-0 | TEMP2_HYS | R/W | 4h | Limit hysteresis. (0~15°C) Temperature and below the (boundary – hysteresis). |

7.5.27 DIODE OPEN Status Register -- Index 6Fh

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|--|
| 7-4 | Reserved | RO | 0h | Reserved |
| 3 | T3_DIODE_OPEN | RO | 0h | External diode 3 is open or short |
| 2 | T2_DIODE_OPEN | RO | 0h | External diode 2 is open or short |
| 1 | T1_DIODE_OPEN | RO | 0h | This register indicates the abnormality of temperature 1 measurement. When TSI interface is enabled, it indicates the error of not receiving NACK bit or a timeout occurred. When PECL interface is enabled, it indicates an error code (0x0080 or 0x0081) is received from PECL slave. When external diode is used, it indicates the BJT is open or short. |
| 0 | Reserved | R | 0h | -- |

Temperature — Index 70h- 8Fh

| Address | Attribute | Default Value | Description |
|---------|-----------|---------------|--|
| 70h | Reserved | FFh | Reserved |
| 71h | Reserved | FFh | Reserved |
| 72h | RO | -- | Temperature 1 reading. The unit of reading is 1°C. At the moment of reading this register. |
| 73h | RO | -- | Reserved |
| 74h | RO | -- | Temperature 2 reading. The unit of reading is 1°C. At the moment of reading this register. |
| 75h | RO | -- | Reserved |
| 76h | RO | -- | Temperature 3 reading. The unit of reading is 1°C. At the moment of reading this register. |
| 77h | RO | -- | Reserved |
| 78h | RO | -- | PECI temperature reading |
| 79h | RO | -- | AMD TSI or Intel IBX temperature reading |
| 7Ah | RO | -- | The raw data of T3 read from digital interface. (Only available if Intel IBX interface is enabled) |
| 7Bh | RO | -- | The raw data of T2 read from digital interface. (Only available if Intel IBX interface is enabled) |
| 7Ch | RO | -- | The raw data of T1 read from digital interface. |
| 7Dh | RO | -- | The raw data of T1 read from D1+. |
| 7Eh | R/W | 00h- | T1 Slope Adjust. |
| 7Fh | R/W | 00h | T1 Source Select. |
| 80h | Reserved | FFh | Reserved |
| 81h | Reserved | FFh | Reserved |
| 82h | R/W | 64h | Temperature sensor 1 OVT limit. The unit is 1°C. |
| 83h | R/W | 55h | Temperature sensor 1 high limit. The unit is 1°C. |
| 84h | R/W | 64h | Temperature sensor 2 OVT limit. The unit is 1°C. |
| 85h | R/W | 55h | Temperature sensor 2 high limit. The unit is 1°C. |
| 86h | R/W | 55h | Temperature sensor 3 OVT limit. The unit is 1°C. |
| 87h | R/W | 46h | Temperature sensor 3 high limit. The unit is 1°C. |
| 88-8Bh | RO | -- | Reserved |
| 8C~8Dh | RO | FFh | Reserved |

7.5.28 T1 Slope Adjust Register -- Index 7Eh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | DIG_T1_ADD | R/W | 0h | This bit is the sign bit for digital T1 reading slope adjustment. See DIG_T1_SCALE below for detail. |

F71889E

| | | | | | | |
|-----|----------------|---------|----|---|--------------|---------------|
| 6-4 | DIG_T1_SCALE | R/W | 0h | Accompanying with DIG_T1_ADD, the slope adjustment of digital T1 is listed. | | |
| | | | | DIG_T1_ADD | DIG_T1_SCALE | Slope |
| | | | | 0 | 000 | No adjustment |
| | | | | 0 | 001 | 1/2 |
| | | | | 0 | 010 | 3/4 |
| | | | | 0 | 011 | 7/8 |
| | | | | 0 | 100 | 15/16 |
| | | | | 0 | 101 | 31/32 |
| | | | | 0 | 110 | 63/64 |
| | | | | 0 | 111 | 127/128 |
| | | | | 1 | 000 | No adjustment |
| | | | | 1 | 001 | 3/2 |
| | | | | 1 | 010 | 5/4 |
| | | | | 1 | 011 | 9/8 |
| | | | | 1 | 100 | 17/16 |
| | | | | 1 | 101 | 33/32 |
| | | | | 1 | 110 | 65/64 |
| 1 | 111 | 129/128 | | | | |
| 3 | DIODE_T1_ADD | R/W | 0h | The function of this bit is the same as DIG_T1_ADD expect that it is for D1+ reading. | | |
| 2-0 | DIODE_T1_SCALE | R/W | 0h | The function of this bit is the same as DIG_T1_SCALE expect that it is for D1+ reading. | | |

7.5.29 Temperature Filter Select Register -- Index 7Fh

| Bit | Name | R/W | Default | Description | |
|-----|----------------|---------|---------|---|---------------------------------|
| 7-2 | Reserved | - | - | Reserved. | |
| 1-0 | T1_SRC_SEL_REG | R/W | 00 | The bits are used when DIODE_T1_EN and DIG_T1_EN are both enabled. The real select bits T1_SCR_SEL are fixed to 2'b01 if DIODE_T1_EN is "0" and 2'b00 if DIG_T1_EN is "0". The T1 source is listed. | |
| | | | | T1_SRC_SEL | T1 source |
| | | | | 00 | From D1+ only |
| | | | | 01 | From Digital reading (PECI/TSI) |
| | | | | 10 | Average |
| | 11 | Maximum | | | |

7.5.30 Temperature Filter Select Register -- Index 8Eh

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-6 | IIR-QEUR3 | R/W | 2'b10 | The queue time for second filter to quickly update values. 00: 8 times. 01: 12 times. 10: 16 times. (default) 11: 24 times. |
| 5-4 | IIR-QEUR2 | R/W | 2'b10 | The queue time for second filter to quickly update values. 00: 8 times. 01: 12 times. 10: 16 times. (default) 11: 24 times. |
| 3-2 | IIR-QEUR1 | R/W | 2'b10 | The queue time for second filter to quickly update values. 00: 8 timers. 01: 12 times. 10: 16 times. (default) 11: 24 times. |
| 0 | Reserved | R | - | -- |

Fan Control Setting

7.5.31 FAN PME# Enable Register — Index 90h

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|---|
| 7-3 | Reserved | RO | 0h | Reserved |
| 2 | EN_FAN3_PME | R/W | 0h | A one enables the corresponding interrupt status bit for PME# interrupt. Set this bit 1 to enable PME# function for Fan3. |
| 1 | EN_FAN2_PME | R/W | 0h | A one enables the corresponding interrupt status bit for PME# interrupt. Set this bit 1 to enable PME# function for Fan2. |
| 0 | EN_FAN1_PME | R/W | 0h | A one enables the corresponding interrupt status bit for PME# interrupt. Set this bit 1 to enable PME# function for Fan1. |

7.5.32 FAN Interrupt Status Register — Index 91h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-3 | Reserved | RO | 0 | Reserved |
| 2 | FAN3_STS | R/W | -- | This bit is set when the fan3 count exceeds the count limit. Write 1 to clear this bit, write 0 will be ignored. |
| 1 | FAN2_STS | R/W | -- | This bit is set when the fan2 count exceeds the count limit. Write 1 to clear this bit, write 0 will be ignored. |
| 0 | FAN1_STS | R/W | -- | This bit is set when the fan1 count exceeds the count limit. Write 1 to clear this bit, write 0 will be ignored. |

7.5.33 FAN Real Time Status Register — Index 92h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-3 | Reserved | -- | 0 | Reserved |
| 2 | FAN3_EXC | RO | -- | This bit set to high mean that fan3 count can't meet expect count over than SMI time (CR9F) or when duty not zero but fan stop over then 3 sec. |
| 1 | FAN2_EXC | RO | -- | This bit set to high mean that fan2 count can't meet expect count over than SMI time (CR9F) or when duty not zero but fan stop over then 3 sec. |
| 0 | FAN1_EXC | RO | -- | This bit set to high mean that fan1 count can't meet expect count over than SMI time (CR9F) or when duty not zero but fan stop over then 3 sec. |

7.5.34 FAN BEEP# Enable Register — Index 93h

| Bit | Name | R/W | Default | Description |
|-----|-----------------|-----|---------|--|
| 7 | FULL_WITH_T3_EN | R/W | 0 | Set one will enable FAN to force full speed when T3 over high limit. |
| 6 | FULL_WITH_T2_EN | R/W | 0 | Set one will enable FAN to force full speed when T2 over high limit. |
| 5 | FULL_WITH_T1_EN | R/W | 0 | Set one will enable FAN to force full speed when T1 over high limit. |
| 4 | Reserved | R/W | 0 | Reserved for local temperature. |
| 3 | Reserved | - | - | Reserved. |
| 2 | EN_FAN3_BEEP | R/W | 0 | A one enables the corresponding interrupt status bit for BEEP. |
| 1 | EN_FAN2_BEEP | R/W | 0 | A one enables the corresponding interrupt status bit for BEEP. |
| 0 | EN_FAN1_BEEP | R/W | 0 | A one enables the corresponding interrupt status bit for BEEP. |

7.5.35 Fan Type Select Register -- Index 94h (FAN_PROG_SEL = 0)

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-------------|
| 7-6 | Reserved | - | - | Reserved. |

F71889E

| | | | | |
|-----|-----------|-----|--------|--|
| 5-4 | FAN3_TYPE | R/W | 2'b 0S | 00: Output PWM mode (pushpull) to control fans. 01: Use linear fan application circuit to control fan speed by fan's power terminal. 10: Output PWM mode (open drain) to control Intel 4-wire fans. 11: Reserved. Bit 0 is power on trap by RTS2# 0: RTS2# is pull up by internal 47K resistor. 1: RTS2# is pull down by external resistor. |
| 3-2 | FAN2_TYPE | R/W | 2'b 0S | 00: Output PWM mode (pushpull) to control fans. 01: Use linear fan application circuit to control fan speed by fan's power terminal. 10: Output PWM mode (open drain) to control Intel 4-wire fans. 11: Reserved. Bit 0 is power on trap by RTS2# 0: RTS2# is pull up by internal 47K resistor. 1: RTS2# is pull down by external resistor. |
| 1-0 | FAN1_TYPE | R/W | 2'b 0S | 00: Output PWM mode (push pull) to control fans. 01: Use linear fan application circuit to control fan speed by fan's power terminal. 10: Output PWM mode (open drain) to control Intel 4-wire fans. 11: Reserved. Bit 0 is power on trap by RTS2# 0: RTS2# is pull up by internal 47K resistor. 1: RTS2# is pull down by external resistor. |

S: Register default values are decided by trapping.

7.5.36 Fan1 Base Temperature Register – Index 94h (FAN_PROG_SEL = 1)

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|--|
| 7-0 | FAN1_BASE_TEMP | R/W | 8'h0 | This register is used to set the base temperature for FAN1 temperature adjustment. The FAN1 temperature is calculated according to the equation: $T_{fan1} = T_{now} + (T_a - T_b) * C_t$ Where T_{now} is selected by FAN1_TEMP_SEL_DIG and FAN1_TEMP_SEL. T_b is this register, T_a is selected by TFAN1_ADJ_SEL and C_t is selected by TFAN1_ADJ_UP_RATE/TFAN1_ADJ_DN_RATE. To access this register, FAN_PROG_SEL (CR9F[7]) must set to "1". |

7.5.37 Fan1 Temperature Adjustment Rate Register – Index 95h (FAN_PROG_SEL = 1)

| Bit | Name | R/W | Default | Description |
|-----|-------------------|-----|---------|--|
| 7 | Reserved | - | - | Reserved. |
| 6-4 | TFAN1_ADJ_UP_RATE | R/W | 3'h0 | This selects the weighting of the difference between T_a and T_b if T_a is higher than T_b . 3'h1: 1 ($C_t = 1$) 3'h2: 1/2 ($C_t = 1/2$) 3'h3: 1/4 ($C_t = 1/4$) 3'h4: 1/8 ($C_t = 1/8$) otherwise: 0 |
| 2 | Reserved | - | - | Reserved. |

F71889E

| | | | | |
|-----|-------------------|-----|------|---|
| 2-0 | TFAN1_ADJ_DN_RATE | R/W | 3'h0 | <p>This selects the weighting of the difference between Ta and Tb if Ta is lower than Tb.</p> <p>3'h1: 1 (Ct = 1)</p> <p>3'h2: 1/2 (Ct = 1/2)</p> <p>3'h3: 1/4 (Ct = 1/4)</p> <p>3'h4: 1/8 (Ct = 1/8)</p> <p>otherwise: 0</p> <p>To access this byte, FAN_PROG_SEL must set to "1".</p> |
|-----|-------------------|-----|------|---|

7.5.38 Fan mode Select Register -- Index 96h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-6 | Reserved | - | - | Reserved. |
| 5-4 | FAN3_MODE | R/W | 1h | <p>00: Auto fan speed control, fan speed will follow different temperature by different RPM that defines in 0xC6-0xCE.</p> <p>01: Auto fan speed control, fan speed will follow different temperature by different duty cycle that defines in 0xC6-0xCE.</p> <p>10: Manual mode fan control, user can write expected RPM count to 0xC2-0xC3, and F71889E will auto control duty cycle (PWM fan type) or voltage (linear fan type) to control fan speed.</p> <p>11: Manual mode fan control, user can write expected duty cycle (PWM fan type) or voltage (linear fan type) to 0xC3, and F71889E will output this value duty or voltage to control fan speed.</p> |
| 3-2 | FAN2_MODE | R/W | 1h | <p>00: Auto fan speed control, fan speed will follow different temperature by different RPM that defines in 0xB6-0xBE.</p> <p>01: Auto fan speed control, fan speed will follow different temperature by different duty cycle (voltage) that defines in 0xB6-0xBE.</p> <p>10: Manual mode fan control, user can write expected RPM count to 0xB2-0xB3, and F71889E will auto control duty cycle (PWM fan type) or voltage (linear fan type) to control fan speed.</p> <p>11: Manual mode fan control, user can write expected duty cycle (PWM fan type) or voltage (linear fan type) to 0xB3, and F71889E will output this value duty or voltage to control fan speed.</p> |
| 1-0 | FAN1_MODE | R/W | 1h | <p>00: Auto fan speed control, fan speed will follow different temperature by different RPM that defines in 0xA6-0xAE.</p> <p>01: Auto fan speed control, fan speed will follow different temperature by different duty cycle that defines in 0xA6-0xAE.</p> <p>10: Manual mode fan control, user can write expected RPM count to 0xA2-0xA3, and F71889E will auto control duty cycle (PWM fan type) or voltage (linear fan type) to control fan speed.</p> <p>11: Manual mode fan control, user can write expected duty cycle (PWM fan type) or voltage (linear fan type) to 0xA3, and F71889E will output this value duty or voltage to control fan speed.</p> |

7.5.39 Auto Fan1 and Fan2 Boundary Hysteresis Select Register -- Index 98h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-4 | FAN2_HYS | R/W | 4h | <p>0000: Boundary hysteresis. (0~15°C)</p> <p>Segment will change when the temperature over the boundary temperature and below the (boundary – hysteresis).</p> |
| 3-0 | FAN1_HYS | R/W | 4h | <p>0000: Boundary hysteresis. (0~15°C)</p> <p>Segment will change when the temperature over the boundary temperature and below the (boundary – hysteresis).</p> |

F71889E

7.5.40 Auto Fan3 Boundary Hysteresis Select Register -- Index 99h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-4 | Reserved | - | - | Reserved. |
| 3-0 | FAN3_HYS | R/W | 2h | 0000: Boundary hysteresis. (0~15°C) Segment will change when the temperature over the boundary temperature and below the (boundary – hysteresis). |

7.5.41 Auto Fan Up Speed update Rate Select Register -- Index 9Bh (FAN_RATE_PROG_SEL = 0)

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7-6 | Reserved | - | - | Reserved. |
| 5-4 | FAN3_UP_RATE | R/W | 1h | Fan3 duty update rate: 00: 2Hz 01: 5Hz (default) 10: 10Hz 11: 20Hz |
| 3-2 | FAN2_UP_RATE | R/W | 1h | Fan2 duty update rate: 00: 2Hz 01: 5Hz (default) 10: 10Hz 11: 20Hz |
| 1-0 | FAN1_UP_RATE | R/W | 1h | Fan1 duty update rate: 00: 2Hz 01: 5Hz (default) 10: 10Hz 11: 20Hz |

7.5.42 Auto Fan Down Speed update Rate Select Register -- Index 9Bh (FAN_RATE_PROG_SEL = 1)

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|--|
| 7-6 | Reserved | - | - | Reserved. |
| 5-4 | FAN3_DOWN_RATE | R/W | 1h | Fan3 duty update rate: 00: 2Hz 01: 5Hz (default) 10: 10Hz 11: 20Hz |
| 3-2 | FAN2_DOWN_RATE | R/W | 1h | Fan2 duty update rate: 00: 2Hz 01: 5Hz (default) 10: 10Hz 11: 20Hz |
| 1-0 | FAN1_DOWN_RATE | R/W | 1h | Fan1 duty update rate: 00: 2Hz 01: 5Hz (default) 10: 10Hz 11: 20Hz |

7.5.43 FAN1 and FAN2 START UP DUTY-CYCLE/VOLTAGE — Index 9Ch

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|---|
| 7-4 | FAN2_STOP_DUTY | R/W | 5h | When fan start, the FAN_CTRL2 will increase duty-cycle from 0 to this (value x 8) directly. And if fan speed is down, the FAN_CTRL 2 will decrease duty-cycle to 0 when the PWM duty cycle is less than this (value x 4). |
| 3-0 | FAN1_STOP_DUTY | R/W | 5h | When fan start, the FAN_CTRL1 will increase duty-cycle from 0 to this (value x 8) directly. And if fan speed is down, the FAN_CTRL1 will decrease duty-cycle to 0 when the PWM duty cycle is less than this (value x 4). |

F71889E

7.5.44 FAN3 START UP DUTY-CYCLE/VOLTAGE — Index 9Dh

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|---|
| 7-4 | Reserved | - | - | Reserved. |
| 3-0 | FAN3_STOP_DUTY | R/W | 5h | When fan start, the FAN_CTRL 3 will increase duty-cycle from 0 to this (value x 8 directly. And if fan speed is down, the FAN_CTRL 3 will decrease duty-cycle to 0 when the PWM duty cycle is less than this (value x 4). |

7.5.45 FAN PROGRAMMABLE DUTY-CYCLE/VOLTAGE LOADED AFTER POWER-ON — Index 9Eh

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|--|
| 7-0 | PROG_DUTY_VAL | R/W | 99h | This byte will be immediately loaded as Fan duty value after VDD is powered on if it has been programmed before shut down. |

7.5.46 Fan Fault Time Register -- Index 9Fh

| Bit | Name | R/W | Default | Description |
|-----|----------------------|-----|---------|--|
| 7 | FAN_RATE_PROG_SELECT | R/W | 0 | 0: Index 9Bh is the fan up speed update rate select register. 1: Index 9Bh is the fan down speed update rate select register. |
| 6 | Reserved | -- | -- | Reservd |
| 5 | FAN_NEG_TEMP_ENABLE | R/W | 0 | 0: Disable the negative temperature compare of fan expected value. 1: Enable the negative temperature compare of fan expected value. |
| 4 | FULL_DUTY_SEL | R/W | -- | 0: the full duty is 100%. (pull down by external resistor) 1: the full duty is 60% (default, pull up by internal 47K resistor). This register is power on trap by DTR1#. |
| 3-0 | F_FAULT_TIME | R/W | Ah | This register determines the time of fan fault. The condition to cause fan fault event is: When PWM_Duty reaches FFh, if the fan speed count can't reach the fan expected count in time. The unit of this register is 1 second. The default value is 11 seconds. (Set to 0, means 1 second; Set to 1, means 2 second; Set to 2, means 3 second...) Another condition to cause fan fault event is fan stop and the PWM duty is greater than the minimum duty programmed by the register index 9C-9Dh. |

Fan1 Index A0h- AFh

| Address | Attribute | Default Value | Description |
|---------|-----------|---------------|--|
| A0h | RO | 8'h0f | FAN1 count reading (MSB). At the moment of reading this register, the LSB will be latched. This will prevent from data updating when reading. To read the fan count correctly, read MSB first and followed read the LSB. |
| A1h | RO | 8'hff | FAN1 count reading (LSB). |
| A2h | R/W | 8'h00 | RPM mode (CR96 bit0=0): FAN1 expected speed count value (MSB), in auto fan mode (CR96 bit1→0) this register is auto updated by hardware. Duty mode (CR96 bit0=1): This byte is reserved byte. |
| A3h | R/W | 8'h01 | RPM mode (CR96 bit0=0): FAN1 expected speed count value (LSB) or expected PWM duty, in auto fan mode this register is auto updated by hardware and read only. Duty mode (CR96 bit0=1): The Value programming in this byte is duty value. In auto fan mode (CR96 bit1→0) this register is updated by hardware. Ex: 5→ 5*100/255 % 255 → 100% |
| A4h | R/W | 8'h03 | FAN1 full speed count reading (MSB). At the moment of reading this register, the LSB will be latched. This will prevent from data updating when reading. To read |

| | | | |
|-----|-----|-------|--|
| | | | the fan count correctly, read MSB first and followed read the LSB. |
| A5h | R/W | 8'hff | FAN1 full speed count reading (LSB). |

7.5.47 VT1 BOUNDARY 1 TEMPERATURE – Index A6h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND1TMP1 | R/W | 3Ch (60°C) | The 1st BOUNDARY temperature for VT1 in temperature mode. When VT1 temperature is exceed this boundary, FAN1 expect value will load from segment 1 register (index AAh). When VT1 temperature is below this boundary – hysteresis, FAN1 expected value will load from segment 2 register (index ABh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.48 VT1 BOUNDARY 2 TEMPERATURE – Index A7

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | BOUND2TMP1 | R/W | 32 (50°C) | The 2nd BOUNDARY temperature for VT1 in temperature mode. When VT1 temperature is exceed this boundary, FAN1 expected value will load from segment 2 register (index ABh). When VT1 temperature is below this boundary – hysteresis, FAN1 expected value will load from segment 3 register (index ACh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.49 VT1 BOUNDARY 3 TEMPERATURE – Index A8h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND3TMP1 | R/W | 28h (40°C) | The 3rd BOUNDARY temperature for VT1 in temperature mode. When VT1 temperature is exceed this boundary, FAN1 expected value will load from segment 3 register (index ACh). When VT1 temperature is below this boundary – hysteresis, FAN1 expected value will load from segment 4 register (index ADh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.50 VT1 BOUNDARY 4 TEMPERATURE – Index A9

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND4TMP1 | R/W | 1Eh (30°C) | The 4th BOUNDARY temperature for VT1 in temperature mode. When VT1 temperature is exceed this boundary, FAN1 expected value will load from segment 4 register (index ADh). When VT1 temperature is below this boundary – hysteresis, FAN1 expected value will load from segment 5 register (index AEh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.51 FAN1 SEGMENT 1 SPEED COUNT – Index AAh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|--|
| 7-0 | SEC1SPEED1 | R/W | FFh (100%) | The meaning of this register is depending on the FAN1_MODE (CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. Ex: 100%:full speed: User must set this register to 0. 60% full speed: (100-60)*32/60, so user must program 21 to this reg. X% full speed: The value programming in this byte is → (100-X)*32/X 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

F71889E

7.5.52 FAN1 SEGMENT 2 SPEED COUNT – Index ABh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC2SPEED1 | R/W | D9h (85%) | The meaning of this register is depending on the FAN1_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.53 FAN1 SEGMENT 3 SPEED COUNT – Index ACh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC3SPEED1 | R/W | B2h (70%) | The meaning of this register is depending on the FAN1_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.54 FAN1 SEGMENT 4 SPEED COUNT – Index ADh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC4SPEED1 | R/W | 99h (60%) | The meaning of this register is depending on the FAN1_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.55 FAN1 SEGMENT 5 SPEED COUNT – Index AEh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC5SPEED1 | R/W | 80h (50%) | The meaning of this register is depending on the FAN1_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.56 FAN1 Temperature Mapping Select – Index AFh

| Bit | Name | R/W | Default | Description |
|-----|-----------------------|-----|---------|--|
| 7 | FAN1_TEMP_SEL_DIG | R/W | 0 | This bit companying with FAN1_TEMP_SEL select the temperature source for controlling FAN1. |
| 6 | Reserved | -- | 0 | Reserved |
| 5 | FAN1_UP_T_EN | R/W | 0 | Set 1 to force FAN1 to full speed if any temperature over its high limit. |
| 4 | FAN1_INTERPOLATION_EN | R/W | 0 | Set 1 will enable the interpolation of the fan expect table. |
| 3 | FAN1_JUMP_HIGH_EN | R/W | 0 | This register controls the FAN1 duty movement when temperature over highest boundary. 0: The FAN1 duty will increases with the slope selected by FAN1_RATE_SEL register. 1: The FAN1 duty will directly jumps to the value of SEC1SPEED1 register. This bit only activates in duty mode. |
| 2 | FAN1_JUMP_LOW_EN | R/W | 0 | This register controls the FAN1 duty movement when temperature under (highest boundary – hysteresis). 0: The FAN1 duty will decreases with the slope selected by FAN1_RATE_SEL register. 1: The FAN1 duty will directly jumps to the value of SEC2SPEED1 register. This bit only activates in duty mode. |

F71889E

| | | | | |
|-----|---------------|-----|---|---|
| 1-0 | FAN1_TEMP_SEL | R/W | 1 | This registers companying with FAN1_TEMP_SEL_DIG select the temperature source for controlling FAN1. The following value is comprised by {FAN1_TEMP_SEL_DIG, FAN1_TEMP_SEL} 000: fan1 follows PECL temperature (CR78h) 001: fan1 follows temperature 1 (CR72h). 010: fan1 follows temperature 2 (CR74h). 011: fan1 follows temperature 3 (CR76h). 100: fan1 follows AMD TSI or Intel IBX temperature (CR79h) 101: fan1 follows digital temperature 1 (CR7Ch). 110: fan1 follows digital temperature 2 (CR7Bh). 111: fan1 follows digital temperature 3 (CR7Ah). Otherwise: reserved. |
|-----|---------------|-----|---|---|

Fan2 Index B0h- BFh

| Address | Attribute | Default Value | Description |
|---------|-----------|---------------|---|
| B0h | RO | 8'h0f | FAN2 count reading (MSB). At the moment of reading this register, the LSB will be latched. This will prevent from data updating when reading. To read the fan count correctly, read MSB first and followed read the LSB. |
| B1h | RO | 8'hff | FAN2 count reading (LSB). |
| B2h | R/W | 8'h00 | RPM mode (CR96 bit2=0): FAN2 expect speed count value (MSB), in auto fan mode (CR96 bit3→0) this register is auto updated by hardware. Duty mode (CR96 bit2=1): This byte is reserved byte. |
| B3h | R/W | 8'h01 | RPM mode (CR96 bit2=0): FAN2 expect speed count value (LSB) or expect PWM duty, in auto fan mode this register is auto updated by hardware and read only. Duty mode (CR96 bit2=1): The Value programming in this byte is duty value. In auto fan mode (CR96 bit3→0) this register is updated by hardware. Ex: 5→ 5*100/255 % 255→ 100% |
| B4h | R/W | 8'h03 | FAN2 full speed count reading (MSB). At the moment of reading this register, the LSB will be latched. This will prevent from data updating when reading. To read the fan count correctly, read MSB first and followed read the LSB. |
| B5h | R/W | 8'hff | FAN2 full speed count reading (LSB). |

7.5.57 VT2 BOUNDARY 1 TEMPERATURE – Index B6h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND1TMP2 | R/W | 3Ch (60°C) | The 1st BOUNDARY temperature for VT2 in temperature mode. When VT2 temperature is exceed this boundary, FAN2 expected value will load from segment 1 register (index BAh). When VT2 temperature is below this boundary – hysteresis, FAN2 expected value will load from segment 2 register (index BBh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.58 VT2 BOUNDARY 2 TEMPERATURE – Index B7

| Bit | Name | R/W | Default | Description |
|-----|------|-----|---------|-------------|
|-----|------|-----|---------|-------------|

F71889E

| | | | | |
|-----|------------|-----|--------------|---|
| 7-0 | BOUND2TMP2 | R/W | 32 (50°C) | The 2nd BOUNDARY temperature for VT2 in temperature mode. When VT2 temperature is exceed this boundary, FAN2 expected value will load from segment 2 register (index BBh). When VT2 temperature is below this boundary – hysteresis, FAN2 expected value will load from segment 3 register (index BCh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |
|-----|------------|-----|--------------|---|

7.5.59 VT2 BOUNDARY 3 TEMPERATURE – Index B8h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND3TMP2 | R/W | 28h (40°C) | The 3rd BOUNDARY temperature for VT2 in temperature mode. When VT2 temperature is exceed this boundary, FAN2 expected value will load from segment 3 register (index BCh). When VT2 temperature is below this boundary – hysteresis, FAN2 expected value will load from segment 4 register (index BDh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.60 VT2 BOUNDARY 4 TEMPERATURE – Index B9

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND4TMP2 | R/W | 1Eh (30°C) | The 4th BOUNDARY temperature for VT2 in temperature mode. When VT2 temperature is exceed this boundary, FAN2 expected value will load from segment 4 register (index BDh). When VT2 temperature is below this boundary – hysteresis, FAN2 expected value will load from segment 5 register (index BEh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.61 FAN2 SEGMENT 1 SPEED COUNT – Index BAh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|--|
| 7-0 | SEC1SPEED2 | R/W | FFh (100%) | The meaning of this register is depending on the FAN2_MODE(CR96) 2'b00: The value that set in this byte is the relative expected fan speed % of the full speed in this temperature section. Ex: 100%: full speed: User must set this register to 0. 60% full speed: (100-60)*32/60, so user must program 21 to this reg. X% full speed: The value programming in this byte is → (100-X)*32/X 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.62 FAN2 SEGMENT 2 SPEED COUNT – Index BBh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC2SPEED2 | R/W | D9h (85%) | The meaning of this register is depending on the FAN2_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.63 FAN2 SEGMENT 3 SPEED COUNT – Index BCh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC3SPEED2 | R/W | B2h (70%) | The meaning of this register is depending on the FAN2_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.64 FAN2 SEGMENT 4 SPEED COUNT – Index BDh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC4SPEED2 | R/W | 99h (60%) | The meaning of this register is depending on the FAN2_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.65 FAN2 SEGMENT 5 SPEED COUNT – Index BEh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC5SPEED2 | R/W | 80h (50%) | The meaning of this register is depending on the FAN2_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.66 FAN2 Temperature Mapping Select – Index BFh

| Bit | Name | R/W | Default | Description |
|-----|-----------------------|-----|---------|--|
| 7 | FAN2_TEMP_SEL_DIG | R/W | 0 | This bit companying with FAN2_TEMP_SEL select the temperature source for controlling FAN2. |
| 6 | Reserved | - | 0 | Reserved |
| 5 | FAN2_UP_T_EN | R/W | 0 | Set 1 to force FAN2 to full speed if any temperature over its high limit. |
| 4 | FAN2_INTERPOLATION_EN | R/W | 0 | Set 1 will enable the interpolation of the fan expect table. |
| 3 | FAN2_JUMP_HIGH_EN | R/W | 0 | This register controls the FAN2 duty movement when temperature over highest boundary. 0: The FAN2 duty will increases with the slope selected by FAN2_RATE_SEL register. 1: The FAN2 duty will directly jumps to the value of SEC1SPEED2 register. This bit only activates in duty mode. |
| 2 | FAN2_JUMP_LOW_EN | R/W | 0 | This register controls the FAN2 duty movement when temperature under (highest boundary – hysteresis). 0: The FAN2 duty will decreases with the slope selected by FAN2_RATE_SEL register. 1: The FAN2 duty will directly jumps to the value of SEC2SPEED2 register. This bit only activates in duty mode. |

F71889E

| | | | | |
|-----|---------------|-----|---|---|
| 1-0 | FAN2_TEMP_SEL | R/W | 1 | This registers companying with FAN2_TEMP_SEL_DIG select the temperature source for controlling FAN2. The following value is comprised by {FAN2_TEMP_SEL_DIG, FAN2_TEMP_SEL} 000: fan2 follows PECL temperature (CR78h) 001: fan2 follows temperature 1 (CR72h). 010: fan2 follows temperature 2 (CR74h). 011: fan2 follows temperature 3 (CR76h). 100: fan2 follows AMD TSI or Intel IBX temperature (CR79h) 101: fan2 follows digital temperature 1 (CR7Ch). 110: fan2 follows digital temperature 2 (CR7Bh). 111: fan2 follows digital temperature 3 (CR7Ah). Otherwise: reserved. |
|-----|---------------|-----|---|---|

Fan3 Index C0h- CFh

| Address | Attribute | Default Value | Description |
|---------|-----------|---------------|--|
| C0h | RO | 8'h0F | FAN3 count reading (MSB). At the moment of reading this register, the LSB will be latched. This will prevent from data updating when reading. To read the fan count correctly, read MSB first and followed read the LSB. |
| C1h | RO | 8'hff | FAN3 count reading (LSB). |
| C2h | R/W | 8'h00 | RPM mode (CR96 bit4=0): FAN3 expect speed count value (MSB), in auto fan mode (CR96 bit5→0) this register is auto updated by hardware. Duty mode (CR96 bit4=1): This byte is reserved byte. |
| C3h | R/W | 8'h01 | RPM mode (CR96 bit4=0): FAN3 expected speed count value (LSB) or expected PWM duty, in auto fan mode this register is auto updated by hardware and read only. Duty mode (CR96 bit4=1): The Value programming in this byte is duty value. In auto fan mode (CR96 bit5→0) this register is updated by hardware. Ex: 5→ 5*100/255 % 255 → 100% |
| C4h | R/W | 8'h03 | FAN3 full speed count reading (MSB). At the moment of reading this register, the LSB will be latched. This will prevent from data updating when reading. To read the fan count correctly, read MSB first and followed read the LSB. |
| C5h | R/W | 8'hff | FAN3 full speed count reading (LSB). |

7.5.67 VT3 BOUNDARY 1 TEMPERATURE – Index C6h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND1TMP3 | R/W | 3Ch (60°C) | The 1st BOUNDARY temperature for VT3 in temperature mode. When VT3 temperature is exceed this boundary, FAN3 expected value will load from segment 1 register (index CAh). When VT3 temperature is below this boundary – hysteresis, FAN3 expected value will load from segment 2 register (index CBh). This byte is a 2's complement value ranging from -128°C ~ 127°C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

F71889E

7.5.68 VT3 BOUNDARY 2 TEMPERATURE – Index C7

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | BOUND2TMP3 | R/W | 32 (50°C) | The 2nd BOUNDARY temperature for VT3 in temperature mode. When VT3 temperature is exceed this boundary, FAN3 expected value will load from segment 2 register (index CBh). When VT3 temperature is below this boundary – hysteresis, FAN3 expected value will load from segment 3 register (index CCh). This byte is a 2's complement value ranging from -128 °C ~ 127 °C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.69 VT3 BOUNDARY 3 TEMPERATURE – Index C8h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND3TMP3 | R/W | 28h (40°C) | The 3rd BOUNDARY temperature for VT3 in temperature mode. When VT3 temperature is exceed this boundary, FAN3 expected value will load from segment 3 register (index CCh). When VT3 temperature is below this boundary – hysteresis, FAN3 expected value will load from segment 4 register (index CDh). This byte is a 2's complement value ranging from -128 °C ~ 127 °C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.70 VT3 BOUNDARY 4 TEMPERATURE – Index C9

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | BOUND4TMP3 | R/W | 1Eh (30°C) | The 4th BOUNDARY temperature for VT3 in temperature mode. When VT3 temperature is exceed this boundary, FAN3 expected value will load from segment 4 register (index CDh). When VT3 temperature is below this boundary – hysteresis, FAN3 expected value will load from segment 5 register (index CEh). This byte is a 2's complement value ranging from -128 °C ~ 127 °C. Bit 7 will always be "0" (always positive) if FAN_NEG_TEMP_EN is "0". |

7.5.71 FAN3 SEGMENT 1 SPEED COUNT – Index CAh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------------|---|
| 7-0 | SEC1SPEED3 | R/W | FFh (100%) | The meaning of this register is depending on the FAN3_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. Ex: 100%: full speed: User must set this register to 0. 60% full speed: $(100-60)*32/60$, so user must program 21 to this reg. X% full speed: The value programming in this byte is $\rightarrow (100-X)*32/X$ 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.72 FAN3 SEGMENT 2 SPEED COUNT – Index CBh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC2SPEED3 | R/W | D9h (85%) | The meaning of this register is depending on the FAN3_MODE(CR96) 2'b00: The value that set in this byte is the relative expected fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte means the expected PWM duty-cycle in this temperature section. |

7.5.73 FAN3 SEGMENT 3 SPEED COUNT – Index CCh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC3SPEED3 | R/W | B2h (70%) | The meaning of this register is depending on the FAN3_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.74 FAN3 SEGMENT 4 SPEED COUNT – Index CDh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC4SPEED3 | R/W | 99h (60%) | The meaning of this register is depending on the FAN3_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.75 FAN3 SEGMENT 5 SPEED COUNT – Index CEh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|--------------|---|
| 7-0 | SEC5SPEED3 | R/W | 80h (50%) | The meaning of this register is depending on the FAN3_MODE(CR96) 2'b00: The value that set in this byte is the relative expect fan speed % of the full speed in this temperature section. 2'b01: The value that set in this byte is mean the expect PWM duty-cycle in this temperature section. |

7.5.76 FAN3 Temperature Mapping Select – Index CFh

| Bit | Name | R/W | Default | Description |
|-----|-----------------------|-----|---------|--|
| 7 | FAN3_TEMP_SEL_DIG | R/W | 0 | This bit companying with FAN3_TEMP_SEL select the temperature source for controlling FAN3. |
| 6 | Reserved | -- | 0 | Reserved |
| 5 | FAN3_UP_T_EN | R/W | 0 | Set 1 to force FAN3 to full speed if any temperature over its high limit. |
| 4 | FAN3_INTERPOLATION_EN | R/W | 0 | Set 1 will enable the interpolation of the fan expect table. |
| 3 | FAN3_JUMP_HIGH_EN | R/W | 0 | This register controls the FAN3 duty movement when temperature over highest boundary. 0: The FAN3 duty will increases with the slope selected by FAN3_RATE_SEL register. 1: The FAN3 duty will directly jumps to the value of SEC1SPEED3 register. This bit only activates in duty mode. |
| 2 | FAN3_JUMP_LOW_EN | R/W | 0 | This register controls the FAN3 duty movement when temperature under (highest boundary – hysteresis). 0: The FAN3 duty will decreases with the slope selected by FAN3_RATE_SEL register. 1: The FAN3 duty will directly jumps to the value of SEC2SPEED3 register. This bit only activates in duty mode. |

F71889E

| | | | | |
|-----|---------------|-----|---|---|
| 1-0 | FAN3_TEMP_SEL | R/W | 1 | This registers companying with FAN3_TEMP_SEL_DIG select the temperature source for controlling FAN3. The following value is comprised by {FAN3_TEMP_SEL_DIG, FAN3_TEMP_SEL} 000: fan3 follows PECL temperature (CR78h) 001: fan3 follows temperature 1 (CR72h). 010: fan3 follows temperature 2 (CR74h). 011: fan3 follows temperature 3 (CR76h). 100: fan3 follows AMD TSI or Intel IBX temperature (CR79h) 101: fan3 follows digital temperature 1 (CR7Ch). 110: fan3 follows digital temperature 2 (CR7Bh). 111: fan3 follows digital temperature 3 (CR7Ah). Otherwise: reserved. |
|-----|---------------|-----|---|---|

7.5.77 TSI Temperature 0 – Index E0h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-0 | TSI_TEMP0 | R/W | 8'h00 | This byte is used as multi-purpose as follows: <ol style="list-style-type: none"> 1. AMD TSI reading if AMD TSI enable (0~255 °C). 2. Highest temperature among CPU, MCH and PCH if Intel IBX enable (0~255 °C). 3. The 1st byte of read block protocol. To access this byte, MCH_BANK_SEL must set to "0". |
| | SMB_DATA0 | R/W | 8'h00 | This byte is used as multi-purpose: <ol style="list-style-type: none"> 1. The received data of receive protocol. 2. The first received byte of read word protocol. 3. The 10th received byte of read block protocol. 4. The sent data for send byte protocol and write byte protocol. 5. The first send byte for write word protocol. 6. The first send byte for write block protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.78 TSI Temperature 1 – Index E1h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-0 | TSI_TEMP1 | R | 8'h00 | This byte is used as multi-purpose as follows: <ol style="list-style-type: none"> 1. The PCH temperature reading (0~255 °C). This byte is only valid if Intel IBX is enabled. 2. The 2nd byte of read block protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA1 | R/W | 8'h00 | This byte is used as multi-purpose: <ol style="list-style-type: none"> 1. The second received byte of read word protocol. 2. The 11th received byte of read block protocol. 3. The second send byte for write word protocol. 4. The second send byte for write block protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.79 TSI Temperature 2 Low Byte – Index E2h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7-0 | TSI_TEMP2_LO | R | 8'h00 | This byte is used as multi-purpose as follows: 1. The low byte of Intel temperature interface CPU reading. The reading is the fraction part of CPU temperature. Bit 0 indicates the error status. Logic "1" indicates an error code. This byte is only valid if Intel Ibex is enabled. 2. The 3 rd byte of the block read protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA2 | R/W | 8'h00 | This is the 12th byte of the block read protocol. This byte is also used as the 3rd byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.80 TSI Temperature 2 High Byte – Index E3h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7-0 | TSI_TEMP2_HI | R | 8'h00 | This byte is used as multi-purpose as follows: 1. The high byte of Intel temperature interface CPU reading. The reading is the decimal part of CPU temperature. This byte is only valid if Intel Ibex is enabled. 2. The 4 th byte of the block read protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA3 | R/W | 8'h00 | This is the 13th byte of the block read protocol. This byte is also used as the 4th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.81 TSI Temperature 3 – Index E4h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-0 | TSI_TEMP3 | R | 8'h00 | This byte is used as multi-purpose as follows: 1. The MCH temperature reading (0~255 °C). This byte is only valid if Intel Ibex is enabled. 2. The 5 th byte of the block read protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA4 | R/W | 8'h00 | This is the 14th byte of the block read protocol. This byte is also used as the 5th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.82 TSI Temperature 4 – Index E5h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-0 | TSI_TEMP4 | R | 8'h00 | This byte is used as multi-purpose as follows: 1. The DIMM0 temperature reading (0~255 °C). This byte is only valid if Intel Ibex is enabled. 2. The 6 th byte of the block read protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA5 | R/W | 8'h00 | This is the 15th byte of the block read protocol. This byte is also used as the 6th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.83 TSI Temperature 5 – Index E6h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7-0 | TSI_TEMP5 | R | 8'h00 | This byte is used as multi-purpose: 1. The DIMM1 temperature reading (0~255 °C). This byte is only valid if Intel Ibex is enabled. 2. The 7 th byte of the block read protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA6 | R/W | 8'h00 | This is the 16th byte of the block read protocol. This byte is also used as the 7th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.84 TSI Temperature 6 – Index E7h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-0 | TSI_TEMP6 | R | 8'h00 | This byte is used as multi-purpose as follows: 1. The DIMM2 temperature reading (0~255 °C). This byte is only valid if Intel Ibex is enabled. 2. The 8 th byte of the block read protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA7 | R/W | 8'h00 | This is the 17th byte of the block read protocol. This byte is also used as the 8th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.85 TSI Temperature 7 – Index E8h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-0 | TSI_TEMP7 | R | 8'h00 | This byte is used as multi-purpose: 1. The DIMM3 temperature reading (0~255 °C). The byte is only valid if Intel Ibex is enabled. 2. The 9 th byte of block read protocol. To access this byte, MCH_BANK_SEL should be set to "0". |
| | SMB_DATA8 | R/W | 8'h00 | This is the 18th byte of the block read protocol. This byte is also used as the 9th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to "1". |

7.5.86 SMB Data Buffer 9 – Index E9h (MCH_BANK_SEL = 1)

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-0 | SMB_DATA9 | R/W | 0 | This is the 19 th byte of the block read protocol. This byte is also used as the 10th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to “1”. |

7.5.87 SMB Data Buffer 10 – Index EAh (MCH_BANK_SEL = 1)

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7-0 | SMB_DATA10 | R/W | 0 | This is the 20 th byte of the block read protocol. This byte is also used as the 11th byte of block write protocol. To access this byte, MCH_BANK_SEL should be set to “1”. |

7.5.88 Block Write Count Register – Index ECh

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7 | MCH_BANK_SEL | R/W | 0 | This bit is used to select the register in index E0h to E9h. Set “0” to read the temperature bank and “1” to access the data bank. |
| 6 | Reserved | - | 0 | Reserved |
| 5-0 | BLOCK_WR_CNT | R/W | 0 | Use the register to specify the byte count of block write protocol. Support up to 10 bytes. |

7.5.89 SMB Command Byte/TSI Comamdn Byte – Index EDh (TSI_CMD_PROG = 0)

| Bit | Name | R/W | Default | Description |
|-----|---------|-----|---------|---|
| 7-0 | SMB_CMD | R/W | 8'h0 | Command code for write byte/word, read byte/word, block write/read and process call protocol. |

7.5.90 SMB Command Byte/TSI Comamdn Byte – Index EDh (TSI_CMD_PROG = 1)

| Bit | Name | R/W | Default | Description |
|-----|---------|-----|---------|--|
| 7-0 | TSI_CMD | R/W | 8'h1 | The command code for Intel temperature interface block read protocol and the data byte for AMD TSI send byte protocol. |

7.5.91 SMB Status – Index EEh

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7 | TSI_PENDING | R/W | 0 | Set 1 to pending auto TSI accessing. (In AMD model, auto accessing will issue a send-byte followed a receive-byte; In Intel model, auto accessing will issue a block read). To use the TSI_SCL/TSI_SDA as a SMBus master, set this bit to “1” first. |
| 6 | TSI_CMD_PROG | R/W | 0 | Set 1 to program TSI_CMD. |
| 5 | PROC_KILL | R/W | 0 | Kill the current SMBus transfer and return the state machine to idle. It will set a fail status if the current transfer is not completed. |
| 4 | FAIL_STS | R | 0 | This is set when PROC_KILL kill an un-completed transfer. It will be auto cleared by next SMBus transfer. |

F71889E

| | | | | |
|---|-------------|---|---|---|
| 3 | SMB_ABT_ERR | R | 0 | This is the arbitration lost status if a SMBus command is issued. Auto cleared by next SMBus command. |
| 2 | SMB_TO_ERR | R | 0 | This is the timeout status if a SMBus command is issued. Auto cleared by next SMBus command. |
| 1 | SMB_NAC_ERR | R | 0 | This is the NACK error status if a SMBus command is issued. Auto cleared by next SMBus command. |
| 0 | SMB_READY | R | 1 | 0: SMBus transfer is in process. 1: Ready for next SMBus command. |

7.5.92 SMB Protocol Select – Index EFh

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7 | SMB_START | W | 0 | Write "1" to trigger a SMBus transfer with the protocol specified by SMB_PROTOCOL. |
| 6-4 | Reserved | - | - | Reserved. |
| 3-0 | SMB_PROTOCOL | R/W | 0 | Select what protocol if SMBus transfer is triggered. 0001b: send byte. 0010b: write byte. 0011b: write word. 0100b: process call. 0101b: block write. 0111b: quick command (write). 1001b: receive byte. 1010b: read byte. 1011b: read word. 1101b: block read. 1111b: quick command (read). Otherwise: reserved. |

HW Chip ID and Vender ID Information

7.5.93 HM Chip ID 1 Register — Index 5Ah

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|-------------------------|
| 7-0 | HM_CHIP_ID1 | R | 03h | Chip ID 1 of HM Device. |

7.5.94 HM Chip ID 2 Register — Index 5Bh

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|-------------------------|
| 7-0 | HM_CHIP_ID2 | R | 04h | Chip ID 2 of HM Device. |

7.5.95 HM Vendor ID 1 Register — Index 5Dh

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|-------------------------|
| 7-0 | HM_VENDOR_ID1 | R | 19h | Chip ID 1 of HM Device. |

7.5.96 HM Vendor ID 2 Register — Index 5Eh

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|-------------------------|
| 7-0 | HM_VENDOR_ID2 | R | 34h | Chip ID 2 of HM Device. |

7.3. Keyboard Controller

The KBC provides the functions included a keyboard and a PS/2 mouse, and can be used with IBM-compatible personal computers or PS/2-based systems. The controller receives serial data from the keyboard or PS/2 mouse, checks the parity of the data, and presents the data to the system as a byte of data in its output buffer. The controller will assert an interrupt to the system when data are placed in its output buffer.

The below content is about the KBC device register descriptions. All the registers are for software porting reference.

Status Register

The status register is an 8 bits register at I/O address 64h that provides information about the status of the KBC

| Bit | Name | R/W | Default | Description |
|-----|-------------------------|-----|---------|---|
| 7 | Parity error | R | 0 | 0:odd parity 1:even parity |
| 6 | Time out | R | 0 | 0:no time out error 1:time out error |
| 5 | Auxiliary device OBF | R | 0 | 0: Auxiliary output buffer empty 1: Auxiliary output buffer full |
| 4 | Inhibit | R | 0 | 0:keyboard is inhibited 1: keyboard is not inhibited |
| 3 | Command/data | R | 0 | 0:data byte 1:command byte |
| 2 | SYSTEM_FLAG | R | 0 | This bit is set or clear by command byte of KBC |
| 1 | IBF | R | 0 | 0:input buffer empty 1: input buffer full |
| 0 | OBF | R | 0 | 0:output buffer empty 1: output buffer full |

Command register

The internal KBC operation is controlled by the KBC command byte (KCCB). The KCCB resides in I/O address 64h that is read with a 20h command and written with a 60h command data.

| Bit | Name | R/W | Default | Description |
|-----|-----------------------------|-----|---------|--|
| 7 | Reserved | - | - | Reserved |
| 6 | Translate code | R/W | 1 | 0: Pass un-translated scan code. 1: Translate scan code to IBM PC standard. |
| 5 | Disable Auxiliary Device | R/W | 0 | 1: Disable Auxiliary inhibit function. |
| 4 | Disable Keyboard | R/W | 0 | 1: Disable keyboard inhibit function. |
| 3 | Reserved | - | - | Reserved |
| 2 | System flag | R/W | 1 | 0: The system is executing POST as a result of a cold boot. 1: The system is executing POST as a result of a shutdown or warm boot. |

F71889E

| | | | | |
|---|----------------------------|-----|---|---|
| 1 | Enable Auxiliary Interrupt | R/W | 1 | 0: Ao interrupt 1: A system interrupt is generated when a byte is placed in output buffer (IRQ12). |
| 0 | Enable keyboard Interrupt | R/W | 1 | 0:No interrupt 1: A system interrupt is generated when a byte is placed in output buffer (IRQ1). |

DATA register

The DATA register is an 8 bits register at I/O address 60h. the KBC used the output buffer to send the scan code received from keyboard and data byte replay by command to the system.
Power on default <7:0> = 00000000 binary

Commands

| COMMAND | FUNCTION | | | | | | | | | | | | | | | | | | |
|---------|--|-----|-------------|---|---------------------------|---|------------------------|---|-------------|---|---------|---|----------------------------|---|-------------------------|---|-----------------------------|---|---------|
| 20h | Read Command Byte | | | | | | | | | | | | | | | | | | |
| 60h | Write Command Byte <table border="1" style="margin-left: 20px;"> <thead> <tr> <th style="text-align: center;">BIT</th> <th style="text-align: center;">DESCRIPTION</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">0</td> <td style="text-align: center;">Enable Keyboard Interrupt</td> </tr> <tr> <td style="text-align: center;">1</td> <td style="text-align: center;">Enable Mouse Interrupt</td> </tr> <tr> <td style="text-align: center;">2</td> <td style="text-align: center;">System flag</td> </tr> <tr> <td style="text-align: center;">3</td> <td style="text-align: center;">Reserve</td> </tr> <tr> <td style="text-align: center;">4</td> <td style="text-align: center;">Disable Keyboard Interface</td> </tr> <tr> <td style="text-align: center;">5</td> <td style="text-align: center;">Disable Mouse interface</td> </tr> <tr> <td style="text-align: center;">6</td> <td style="text-align: center;">IBM keyboard Translate Mode</td> </tr> <tr> <td style="text-align: center;">7</td> <td style="text-align: center;">Reserve</td> </tr> </tbody> </table> | BIT | DESCRIPTION | 0 | Enable Keyboard Interrupt | 1 | Enable Mouse Interrupt | 2 | System flag | 3 | Reserve | 4 | Disable Keyboard Interface | 5 | Disable Mouse interface | 6 | IBM keyboard Translate Mode | 7 | Reserve |
| BIT | DESCRIPTION | | | | | | | | | | | | | | | | | | |
| 0 | Enable Keyboard Interrupt | | | | | | | | | | | | | | | | | | |
| 1 | Enable Mouse Interrupt | | | | | | | | | | | | | | | | | | |
| 2 | System flag | | | | | | | | | | | | | | | | | | |
| 3 | Reserve | | | | | | | | | | | | | | | | | | |
| 4 | Disable Keyboard Interface | | | | | | | | | | | | | | | | | | |
| 5 | Disable Mouse interface | | | | | | | | | | | | | | | | | | |
| 6 | IBM keyboard Translate Mode | | | | | | | | | | | | | | | | | | |
| 7 | Reserve | | | | | | | | | | | | | | | | | | |
| A7h | Disable Auxiliary Device Interface | | | | | | | | | | | | | | | | | | |
| A8h | Enable Auxiliary Device Interface | | | | | | | | | | | | | | | | | | |
| A9h | Auxiliary Interface Test 8'h00: indicate Auxiliary interface is ok. 8'h01: indicate Auxiliary clock is low. 8'h02: indicate Auxiliary clock is high 8'h03: indicate Auxiliary data is low 8'h04: indicate Auxiliary data is high | | | | | | | | | | | | | | | | | | |
| AAh | Self-test Returns 055h if self test succeeds | | | | | | | | | | | | | | | | | | |
| ABh | keyboard Interface Test 8'h00: indicate keyboard interface is ok. 8'h01: indicate keyboard clock is low. 8'h02: indicate keyboard clock is high. 8'h03: indicate keyboard data is low. 8'h04: indicate keyboard data is high. | | | | | | | | | | | | | | | | | | |
| ADh | Disable Keyboard Interface | | | | | | | | | | | | | | | | | | |

| | |
|------|--|
| A Eh | Enable Keyboard Interface |
| C 0h | Read Input Port (P1) and send data to the system |
| C 1h | Continuously puts the lower four bits of Port1 into STATUS register |
| C 2h | Continuously puts the upper four bits of Port1 into STATUS register |
| C Ah | Read the data written by CBh command. |
| C Bh | Written a scratch data. This byte could be read by CAh command. |
| D 0h | Send Port2 value to the system |
| D 1h | Only set/reset GateA20 line based on the system data bit 1 |
| D 2h | Send data back to the system as if it came from Keyboard |
| D 3h | Send data back to the system as if it came from Muse |
| D 4h | Output next received byte of data from system to Mouse |
| F Eh | Pulse only RC (the reset line) low for 6 μ S if Command byte is even |

KBC Command Description

PS2 wakeup function

The KBC supports keyboard and mouse wakeup function, keyboard wakeup function has 8 kinds of conditions, when key is pressed combinational key (1) CTRL +ESC (2) CTRL+F1 (3) CTRL+SPACE (4) ANY KEY (5) windows 98 wakeup up key (6) windows 98 Power key (7) CTRL + ALT + Backspace (8) CTRL + Alt + Space, KBC will assert PME signal. Mouse wakeup function has 2 kinds of conditions, when mouse (1) BUTTON CLICK or (2) BUTTON CLICK AND MOVEMENT, KBC will assert PME signal. Those wakeup conditions are controlled by configuration register.

7.4. 80 Port

Monitor the value of 0x80 port and output the value via the signals defined for 7-segment display. High nibble and low nibble are outputted interleaved at 1KHz frequency. The 80 Port could also be output to LPT pins if all the input pins of LPT is "0" during power on.

7.5. ACPI Function

The Advanced Configuration and Power Interface (ACPI) is a system for controlling the use of power in a computer. It lets computer manufacturer and user to determine the computer's power usage dynamically.

There are three ACPI states that are of primary concern to the system designer and they are designated S0, S3 and S5. S0 is a full-power state; the computer is being actively used in this state. The other two are called sleep states and reflect different power consumption when power-down. S3 is a state that the processor is powered down but the last procedural state is being stored in memory which is still active. S5 is a state that memory is off and the last procedural state of the processor has been stored to the hard disk. Take S3 and S5 as comparison, since memory is fast, the computer can quickly come back

F71889E

to full-power state, the disk is slower than the memory and the computer takes longer time to come back to full-power state. However, since the memory is off, S5 draws the minimal power comparing to S0 and S3.

It is anticipated that only the following state transitions may happen:

S0→S3, S0→S5, S5→S0, S3→S0 and S3→S5.

Among them, S3→S5 is illegal transition and won't be allowed by state machine. It is necessary to enter S0 first in order to get to S5 from S3. As for transition S5→S3 will occur only as an immediate state during state transition from S5→S0. It isn't allowed in the normal state transition.

The below diagram described the timing, the always on and always off, keep last state could be set in control register. In keep last state mode, one register will keep the status of before power loss. If it is power on before power loss, it will remain power on when power is resumed, otherwise, if it is power off before power loss, it will remain power off when power is resumed.




Figure 14 Default timing: Always off




Figure 15 Optional timing: Always on


PCI Reset and PWROK Signals

The F71889E supports 3 output buffers for 3 reset signals. The result of PCIRST# outcome will be affected by conditions as below:

PCIRST1# → Output buffer of LRESET#.

PCIRST2# → Output buffer of LRESET#.

PCIRST3# → Output buffer of LRESET#.



So far as the PWROK issue is as the figure above. PWROK is delayed 100ms (default) as VCC arrives 2.8V, and the delay timing can be programmed by register. (100ms ~ 400ms)

The F71889E also supports 3 output voltages for VREF1~3. The output is generated from DACs which is powered by trimmed 2.304V reference voltage. One LSB is 2.304V/512.

Below is the timing sequence between VREF1~3 pins:




Figure 16 VREF timing: S5→S0




Figure 17 VREF timing: S0→S3





Figure 18 VREF timing: S3→S0



*1: VREF_EN de-active before S5# active.

*2: S5# active before VREF_EN de-active.

*3: VRAM power down after 8ms of VSYS power down and S5# active.

Figure 19 VREF timing: S0→S5

7.6. PECl Function

The Platform Environment Control Interface (PECl) uses a single wire for self-clocking and data transfer. The bus requires no additional control lines. The physical layer is a self-clocked on-wire bus that begins each bit with a driven, rising edge from an idle level near zero volts. The duration of the signal driven high depends on whether the bit value is a logic '0' or logic '1'. PECl also includes variable data transfer rate established with every message. In this way, it is highly flexible even though underlying logic is simple.

The interface design was optimized for interfacing to Intel processor and chipset components in both single processor and multiple processor environments. The single wire interface provides low board routing overhead for the multiple load connections in the congested routing area near the processor and chipset components. Bus speed, error checking, and low protocol overhead provides adequate link bandwidth and reliability to transfer critical device operating conditions and configuration information.

7.7. SST Function

The Simple Serial Transfer (SST) temperature sensor provides a mean to digitize an analog signal and send that information over a digital bus enabling remote temperature sensing in areas previously not monitored in the PC. The temperature sensor supports an internal and external thermal diode.

The Simple Serial Transfer (SST) interface provides sensed temperatures and voltages. The sensed temperatures are T1, T2, and T3 whose reading values stored in CR72h, CR74h, and CR76h. The sensed voltages are V1~V6 whose reading values stored in CR21h~26h.

7.8. TSI Function

The Temperature Sensor Interface (TSI) was a simple SMBUS master to communicate with AMD CPU or Intel CPU to getting the temperature of CPU. It supports byte sending, byte receiving, read/write byte, read/write block and quick command of SMBus protocol. When power on the hardware automatically fetch the temperature use the protocol per the specification of AMD/Intel. User can use the provided registers to control the SCL/SDA as a SMBus master. For Intel platform, the SMBUS supports next generational IBX protocol for temperature reading.

7.9. FSB Bus Interface

The Bus interface is simply GPIs and GPIOs. There are two modes supported: bypass mode and manual mode. Default is the bypass mode, BUSIN will bypass to BUSOUT. In manual mode, BUSOUT is controlled by registers. Normally this function is for FSB over/under colcking application.

7.10. VID Controller

VID Controller provides two types of interface parallel to parallel and serial to serial (AMD only). There are three modes for each type: bypass, manual and on the fly. It's used to over-voltage control. In bypass mode, the hardware monitors the input and bypass to the output. In manual mode, the input is monitored but the output is controlled by registers. In on-the-fly mode, user programs the offset, the hardware monitors the input, adds the offset and then pass to the output.

8. Register Description

The configuration register is used to control the behavior of the corresponding devices. To configure the register, using the index port to select the index and then writing data port to alter the parameters. The default index port and data port are 0x4E and 0x4F respectively. Pull down the SOUT1 pin to change the default value to 0x2E/0x2F. To enable configuration, the entry key 0x87 must be written to the index port. To disable configuration, write exit key 0xAA to the index port. Following is a example to enable configuration and disable configuration by using debug.

- o 4e 87
- o 4e 87 (enable configuration)
- o 4e aa (disable configuration)

The Following is a register map (total devices) grouped in hexadecimal address order, which shows a summary of all registers and their default value. Please refer each device chapter if you want more detail information.

“-“ Reserved or Tri-State

| Global Control Registers | | | | | | | | | |
|--------------------------|------------------------------------|---------------|---|-----|-----|---|-----|-----|-----|
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | | | LSB | |
| 02 | Software Reset Register | 0 | - | - | - | - | - | - | 0 |
| 07 | Logic Device Number Register (LDN) | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| 20 | Chip ID Register | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 1 |
| 21 | Chip ID Register | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 1 |
| 23 | Vender ID Register | 0 | 0 | 0 | 1 | 1 | 0 | 0 | 1 |
| 24 | Vender ID Register | 0 | 0 | 1 | 1 | 0 | 1 | 0 | 0 |
| 25 | Software Power Down Register | - | - | 0 | 0 | 0 | 0 | 0 | 0 |
| 26 | UART IRQ Sharing Register | 0 | - | 0 | - | - | - | 0 | 0 |
| 27 | ROM Address Select Register | 0 | - | - | 1/0 | - | 1/0 | 1/0 | 1/0 |
| 28 | 80 Port Enable Register | 0/1 | - | 0/1 | 0 | - | - | - | - |
| 2A | Multi Function Select 1 Register | 1 | 1 | 1 | 1 | 0 | 0 | 0 | 0 |
| 2B | Multi Function Select 2 Register | 0 | 0 | 1 | 1 | 0 | 0 | 0 | 0 |
| 2C | Multi Function Select 3 Register | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 |
| 2D | Wakeup Control Register | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 |

“-“ Reserved or Tri-State

| UART1 Device Configuration Registers (LDN CR01) | | | | | | | | | |
|---|------------------------------|---------------|---|---|---|---|---|-----|---|
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | | | LSB | |
| 30 | UART1 Device Enable Register | - | - | - | - | - | - | - | 1 |
| 60 | Base Address High Register | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 1 |
| 61 | Base Address Low Register | 1 | 1 | 1 | 1 | 1 | 0 | 0 | 0 |
| 70 | IRQ Channel Select Register | - | - | - | - | 0 | 1 | 0 | 0 |
| F0 | RS485 Enable Register | - | - | - | 0 | - | - | - | - |

| UART2 Device Configuration Registers (LDN CR02) | | | | | | | | | |
|--|--------------------------------------|---------------|---|---|---|-----|---|---|---|
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | LSB | | | |
| 30 | UART2 Device Enable Register | - | - | - | - | - | - | - | 1 |
| 60 | Base Address High Register | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 |
| 61 | Base Address Low Register | 1 | 1 | 1 | 1 | 1 | 0 | 0 | 0 |
| 70 | IRQ Channel Select Register | - | - | - | - | 0 | 0 | 1 | 1 |
| F0 | RS485 Enable Register | - | - | - | 0 | 0 | 0 | - | - |
| F1 | SIR Mode Control Register | - | - | - | 0 | 0 | 1 | 0 | 0 |
| Parallel Port Device Configuration Registers (LDN CR03) | | | | | | | | | |
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | LSB | | | |
| 30 | Parallel Port Device Enable Register | - | - | - | - | - | - | - | 1 |
| 60 | Base Address High Register | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 1 |
| 61 | Base Address Low Register | 0 | 1 | 1 | 1 | 1 | 0 | 0 | 0 |
| 70 | IRQ Channel Select Register | - | - | - | - | 0 | 1 | 1 | 1 |
| 74 | DMA Channel Select Register | - | - | - | 0 | - | 0 | 1 | 1 |
| F0 | PRT Mode Select Register | 0 | 1 | 0 | 0 | 0 | 0 | 1 | 0 |
| Hardware Monitor Device Configuration Registers (LDN CR04) | | | | | | | | | |
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | LSB | | | |
| 30 | H/W Monitor Device Enable Register | - | - | - | - | - | - | - | 1 |
| 60 | Base Address High Register | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 |
| 61 | Base Address Low Register | 1 | 0 | 0 | 1 | 0 | 1 | 0 | 1 |
| 70 | IRQ Channel Select Register | - | - | - | - | 0 | 0 | 0 | 0 |
| KBC Device Configuration Registers (LDN CR05) | | | | | | | | | |
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | LSB | | | |
| 30 | KBC Device Enable Register | - | - | - | - | - | - | - | 1 |
| 60 | Base Address High Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| 61 | Base Address Low Register | 0 | 1 | 1 | 0 | 0 | 0 | 0 | 0 |
| 70 | KB IRQ Channel Select Register | - | - | - | - | 0 | 0 | 0 | 1 |
| 72 | Mouse IRQ Channel Select Register | - | - | - | - | 1 | 1 | 0 | 0 |
| FE | Auto Swap Register | 1 | - | - | 0 | 0 | 0 | 0 | 1 |
| GPIO Device Configuration Registers (LDN CR06) | | | | | | | | | |
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | LSB | | | |
| F0 | GPIO Output Enable Register | - | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F1 | GPIO Output Data Register | - | 1 | 1 | 1 | 1 | 1 | 1 | 1 |
| F2 | GPIO Pin Status Register | - | - | - | - | - | - | - | - |
| F3 | GPIO Drive Enable Register | - | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| FE | LED_VSB Control Register | - | - | 0 | 0 | 0 | 0 | 0 | 0 |
| FF | LED_VCC Control Register | 0 | - | 0 | 0 | 0 | 0 | 0 | 0 |
| E0 | GPIO1 Output Enable Register | - | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| E1 | GPIO1 Output Data Register | - | 1 | 1 | 1 | 1 | 1 | 1 | 1 |
| E2 | GPIO1 Pin Status Register | - | - | - | - | - | - | - | - |
| E3 | GPIO1 Drive Enable Register | - | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| D0 | GPIO2 Output Enable Register | 0 | 0 | 0 | - | - | - | - | - |
| D1 | GPIO2 Output Data Register | 1 | 1 | 1 | - | - | - | - | - |
| D2 | GPIO2 Pin Status Register | - | - | - | - | - | - | - | - |
| D3 | GPIO2 Drive Enable Register | 0 | 0 | 0 | - | - | - | - | - |
| C0 | GPIO3 Output Enable Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| C1 | GPIO3 Output Data Register | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

F71889E

| C2 | GPIO3 Pin Status Register | - | - | - | - | - | - | - | - |
|--|---|---------------|---|---|---|---|---|-----|---|
| C3 | GPIO3 Drive Enable Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| B0 | GPIO4 Output Enable Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| B1 | GPIO4 Output Data Register | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |
| B2 | GPIO4 Pin Status Register | - | - | - | - | - | - | - | - |
| A0 | GPIO5 Output Enable Register | - | - | - | 0 | 0 | 0 | 0 | 0 |
| A1 | GPIO5 Output Data Register | - | - | - | 1 | 1 | 1 | 1 | 1 |
| A2 | GPIO5 Pin Status Register | - | - | - | - | - | - | - | - |
| A3 | GPIO5 Drive Enable Register | - | - | - | 0 | 0 | 0 | 0 | 0 |
| 90 | GPIO6 Output Enable Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| 91 | GPIO6 Output Data Register | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |
| 92 | GPIO6 Pin Status Register | - | - | - | - | - | - | - | - |
| 93 | GPIO6 Drive Enable Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| 80 | GPIO7 Output Enable Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| 81 | GPIO7 Output Data Register | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |
| 82 | GPIO7 Pin Status Register | - | - | - | - | - | - | - | - |
| 83 | GPIO7 Drive Enable Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| VID Device Configuration Registers (LDN CR07) | | | | | | | | | |
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | | | LSB | |
| 30 | VID Device Enable Register | - | - | - | - | - | - | - | 0 |
| 60 | Base Address High Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| 61 | Base Address Low Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F0 | Watchdog Timer Configuration Register 1 | 0 | - | - | - | - | - | - | 0 |
| F2 | BUS Manual Register | 0 | - | 0 | 0 | 0 | 0 | 0 | 0 |
| F3 | Key Data Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F4 | BUSIN Status Register | 0 | 0 | 0 | 0 | 0 | - | - | - |
| F5 | WDT (Watchdog Timer) Configuration Register 2 | - | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F6 | WDT (Watchdog Timer) Configuration Register 3 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F7 | NB Offset Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F8 | VDD0 Offset Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F9 | VDD1 Offset Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| FA | Watchdog Timer PME Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| FB | VDD NB Manual Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| FC | VDD0 Manual Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| FD | VDD1 Manual Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| FE | PSI Control Register | 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 |
| PME, ACPI and EUP Device Configuration Registers (LDN CR0A) | | | | | | | | | |
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | | | LSB | |
| 30 | PME Device Enable Register | - | - | - | - | - | - | - | 0 |
| F0 | PME Event Enable 1 Register | - | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| F1 | PME Event Status 1 Register | - | - | - | - | - | - | - | - |
| F2 | PME Event Enable 2 Register | - | - | - | - | - | 0 | 0 | 0 |
| F3 | PME Event Status 2 Register | - | - | - | - | - | - | - | - |
| F4 | ACPI Control Register1 | 0 | 0 | 1 | 0 | 0 | 1 | 1 | 0 |
| F5 | ACPI Control Register2 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 |
| F6 | ACPI Control Register3 | 0 | - | 0 | 0 | 0 | 1 | 1 | 1 |
| F7 | ACPI Control Register 4 | 0 | 0 | - | 1 | - | - | 0 | 0 |
| FE | RI De-bounce Select Register | - | - | - | - | - | - | 0 | 0 |
| E0 | EUP Enable Register | 0 | - | - | - | 0 | 0 | 0 | 0 |
| E1 | EUP control register 1 | 1 | 1 | 0 | 0 | 1 | 1 | 0 | 0 |
| E2 | EUP control register 2 | - | - | 0 | 0 | 1 | 1 | 0 | 0 |
| E3 | EUP PSIN deb-register | 0 | 0 | 0 | 1 | 0 | 0 | 1 | 1 |

F71889E

| E4 | EUP RSMRST deb-register | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 1 |
|--|----------------------------------|---------------|---|---|---|-----|---|---|---|
| E5 | EUP PSOUT deb-register | 1 | 1 | 0 | 0 | 0 | 1 | 1 | 1 |
| E6 | EUP PSON deb-register | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 1 |
| E7 | EUP S5 deb-register | 0 | 1 | 1 | 0 | 0 | 0 | 1 | 1 |
| E8 | EuP Wakeup Event Enable Register | 0 | - | 0 | 1 | - | 0 | 0 | 0 |
| ED | EuP Watchdog Control Register | - | - | - | 0 | - | - | 0 | 0 |
| EE | EuP Watchdog Time Register | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| Vref Control Device Configuration Registers (LDN CR0B) | | | | | | | | | |
| Register 0x[HEX] | Register Name | Default Value | | | | | | | |
| | | MSB | | | | LSB | | | |
| F0 | VREF3 output value | 0 | 1 | 1 | 0 | 0 | 1 | 0 | 0 |
| F1 | VREF2 output value | 0 | 1 | 1 | 0 | 0 | 1 | 0 | 0 |
| F2 | VREF1 output value | 0 | 1 | 1 | 0 | 0 | 1 | 0 | 0 |
| F3 | Voltage LSB | - | - | - | - | - | 0 | 0 | 0 |
| FF | WDT Reset Enable | - | - | - | - | - | - | - | 0 |

8.1 Global Control Registers

8.1.1 Software Reset Register — Index 02h

| Bit | Name | R/W | Default | Description |
|-----|------------------|-----|---------|---|
| 7 | Temp_Update_Rate | R/W | 0 | 0: Digital interface (PECI/TSI/IBX) transmits when every temperature updates 1: Digital interface (PECI/TSI/IBX) transmits when every four times temperature updates |
| 6-1 | Reserved | - | - | Reserved |
| 0 | SOFT_RST | R/W | 0 | Write 1 to reset the register and device powered by VDD (VCC). |

8.1.2 Logic Device Number Register (LDN) — Index 07h

| Bit | Name | R/W | Default | Description |
|-----|------|-----|---------|--|
| 7-0 | LDN | R/W | 00h | 00h: Reserved. 01h: Select UART 1 device configuration registers. 02h: Select UART 2 device configuration registers. 03h: Select Parallel Port device configuration registers. 04h: Select Hardware Monitor device configuration registers. 05h: Select KBC device configuration registers. 06h: Select GPIO device configuration registers. 07h: Select VID device configuration registers. 0Ah: Select PME, ACPI & EUP device configuration registers. 0Bh: Select VREF Control device configuration registers. |

8.1.3 Chip ID Register — Index 20h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-------------|
| 7-0 | CHIP_ID1 | R | 09h | Chip ID1. |

8.1.4 Chip ID Register — Index 21h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-------------|
| 7-0 | CHIP_ID2 | R | 09h | Chip ID2. |

8.1.5 Vendor ID Register — Index 23h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|-------------------------------|
| 7-0 | VENDOR_ID1 | R | 19h | Vendor ID1 of Fintek devices. |

8.1.6 Vendor ID Register — Index 24h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|-------------------------------|
| 7-0 | VENDOR_ID2 | R | 34h | Vendor ID2 of Fintek devices. |

8.1.7 Software Power Down Register — Index 25h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7-6 | Reserved | - | - | Reserved |
| 5 | SOFTPD_KBC | R/W | 0 | Power down the KBC device. This will stop the KBC clock. (Reserved for future use) |
| 4 | SOFTPD_HM | R/W | 0 | Power down the Hardware Monitor device. This will stop the Hardware Monitor clock. |
| 3 | SOFTPD_PRT | R/W | 0 | Power down the Parallel Port device. This will stop the Parallel Port clock. |
| 2 | SOFTPD_UR2 | R/W | 0 | Power down the UART 2 device. This will stop the UART 2 clock. |
| 1 | SOFTPD_UR1 | R/W | 0 | Power down the UART 1 device. This will stop the UART 1 clock. |
| 0 | Reserved | R/W | 0 | Reserved. |

8.1.8 UART IRQ Sharing Register — Index 26h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|--|
| 7 | CLK24M_SEL | R/W | 0 | 0: CLKIN is 48MHz 1: CLKIN is 24MHz |
| 6 | Reserved | - | - | Reserved. |
| 5 | DPORT_DEC_SEL | R/W | 0 | 0: The 80 Port address is decoded as 0x0080. 1: The 80 port address is decoded as the SCR of UART2. This bit is powered by VBAT. |
| 4-2 | Reserved | - | - | Reserved. |
| 1 | IRQ_MODE | R/W | 0 | 0: PCI IRQ sharing mode (low level). 1: ISA IRQ sharing mode (low pulse). |
| 0 | IRQ_SHAR | R/W | 0 | 0: disable IRQ sharing of two UART devices. 1: enable IRQ sharing of two UART devices. |

8.1.9 ROM Address Select Register — Index 27h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-------------|
| 7-5 | Reserved | - | - | Reserved. |

F71889E

| | | | | |
|-----|--------------|-----|---|--|
| 4 | PORT_4E_EN | R/W | - | 0: The configuration register port is 2E/2F. 1: The configuration register port is 4E/4F. This register is power on trapped by SOUT1/ Config4E_2E. Pull down to select port 2E/2F. |
| 3 | Reserved | - | - | Reserved. |
| 2 | BSEL_EN | R/W | - | 0: The BUSIN/BUSOUT functions as GPIOs. 1: The BUSIN/BUSOUT functions as BUS interface. This register is power on trapped by BSGPIO_TRP. Pull down to select BSEL function. |
| 1-0 | LPT_FUNC_SEL | R/W | - | 00: The parallel port pins function as LPT. x1: The parallel port pins function as VID control. 10: The parallel port pins function as GPIOs. This register is power on trapped by VIDIO_TRAP. Different resistor will determine these three functions. |

8.1.10 80 Port Enable Register — Index 28h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7 | LPT_DPORT_EN | R/W | - | 0: The 80 port data could not be output to LPT pins. 1: The 80 port data could be output to LPT pins in DPORT_EN is set to "1". |
| 6 | Reserved | - | - | Reserved. |
| 5 | DPORT_EN | R/W | - | 0: The 80 port function is disabled. 1: The 80 port function is enabled. |
| 4 | TEMP_OUT_EN | R/W | 0 | Set this bit to "1" will output the CPU temperature to the 7-segment LED. |
| 3-0 | Reserved | - | - | Reserved. |

8.1.11 Multi Function Select 1 Register — Index 2Ah (Powered by VSB3V)

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7-6 | GPIO06_SEL | R/W | 2'b11 | SUSC#/GPIO06/BEEP/ALERT# function select. 00: The pin function is ALERT#. 01: The pin function is BEEP. 10: The pin function is GPIO06 . 11: The pin function is SUSC# . |
| 5 | GPIO05_SEL | R/W | 1 | GPIO05/LED_VCC function select. 0: The pin function is LED_VCC. 1: The pin function is GPIO05. |
| 4 | GPIO04_SEL | R/W | 1 | GPIO04/LED_VSB function select. 0: The pin function is LED_VSB. 1: The pin function is GPIO04. |
| 3 | GPIO03_SEL | R/W | 0 | SLOT0CC#/GPIO03 function select. 0: The pin function is SLOT0CC#. 1: The pin function is GPIO03. |
| 2-0 | Reserved | R/W | 0 | Reserved |

8.1.12 Multi Function Select 2 Register — Index 2Bh (Powered by VSB3V)

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7-6 | GPIO13_SEL | R/W | 00b | IRTX/GPIO13 function select. 00: Reserved. 01: The pin function is IRTX. 10: Reserved. 11: The pin function is GPIO13 |
| 5-4 | GPIO12_SEL | R/W | 11b | GPIO12/WDTRST# function select. 00: The pin function is WDTRST#. 01: reserved. 10: reserved. 11: The pin function is GPIO12. |
| 3-2 | GPIO11_SEL | R/W | 00b | FANCTRL3/GPIO11/IRTX1 function select. 00: The pin function is FANCTRL3. 01: The pin function is IRTX1. 10: Reserved. 11: The pin function is GPIO11. |
| 1-0 | GPIO10_SEL | R/W | 00b | FANIN3/GPIO10/IRRX1 function select. 00: The pin function is FANIN3. 01: The pin function is IRRX1. 10: Reserved. 11: The pin function is GPIO10. |

8.1.13 Multi Function Select 3 Register — Index 2Ch (Powered by VSB3V)

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|--|
| 7 | GPIO1/2_Clear | R/W | 0 | 0: Cleared by 3VSB 1: Cleared by LRESET# |
| 6 | UR2_GP_EN2 | R/W | 0 | 0: Pin2~4 and pin126~128 function as UART2 modem control. 1: Pin2~4 and pin126~128 function as GPIO3x. |
| 5 | UR2_GP_EN1 | R/W | 0 | 0: Pin5, 6 function as UART2 SOUT2/SIN2. 1: Pin5, 6 function as GPIO3x. |
| 4 | GP_EN | R/W | 0 | 0: Reserved. 1: Pin 7 ~19 function as GPIOs. |
| 3 | GPIO16_SEL | R/W | 0 | PECI/TSI_DAT/IBX_SDA/GPIO16 function select. 0: The pin function is PECI/TSI_DAT/IBX_SDA decided by INTEL_MODEL register. 1: The pin function is GPIO16. |
| 2 | GPIO15_SEL | R/W | 0 | SST/TSI_CLK/IBX_CLK/GPIO15 function select. 0: The pin function is SST/TSI_CLK/IBX_CLK decided by INTEL_MODEL register. 1: The pin function is GPIO15. |

| | | | | |
|-----|------------|-----|-----|--|
| 1-0 | GPIO14_SEL | R/W | 00b | IRRX/GPIO14 function select. 00: Reserved. 01: The pin function is IRRX. 10: Reserved. 11: The pin function is GPIO14. |
|-----|------------|-----|-----|--|

8.1.14 Wakeup Control Register — Index 2Dh (Powered by VBAT)

| Bit | Name | R/W | Default | Description | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|-----|---------------|--------------------|---------|--|-------------|----------------|------------|---|----|------------|---|----|-----------|---|----|--------------|---|----|---------|---|----|----------------|---|----|---------------|---|----|--------------------|---|----|-------|
| 7 | SLOT_PWR_SEL | R/W | 0 | 0: SLOTOCC# is pull-up to VSB3V. 1: SLOTOCC# is pull-up to VBAT. | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 6 | VSBOK_HYS_DIS | R/W | 0 | 0: RSMRST# will sink low when VSB3V is below 2.5V . 1: RSMRST# will sink low when VSB3V is below 2.8V . VSB3V power good level is 2.8V . | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 5 | VREF_S3 | R/W | 0 | 1: VREF2 and 3 keep power on in S3 state 0: VREF2 and 3 are power down in S3 state | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 4 | KEY_SEL_ADD | R/W | 0 | This bit is added to add more wakeup key function. | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 3 | WAKEUP_EN | R/W | 1 | 0: disable keyboard/mouse wake up. 1: enable keyboard/mouse wake up. | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 2-1 | KEY_SEL | R/W | 00 | This registers select the keyboard wake up key. Accompanying with KEY_SEL_ADD, there are eight wakeup keys: | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | <table border="1"> <thead> <tr> <th>KEY_SEL_ADD</th> <th>KEY_SEL</th> <th>Wakeup Key</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>00</td> <td>Ctrl + Esc</td> </tr> <tr> <td>0</td> <td>01</td> <td>Ctrl + F1</td> </tr> <tr> <td>0</td> <td>10</td> <td>Ctrl + Space</td> </tr> <tr> <td>0</td> <td>11</td> <td>Any Key</td> </tr> <tr> <td>1</td> <td>00</td> <td>Windows Wakeup</td> </tr> <tr> <td>1</td> <td>01</td> <td>Windows Power</td> </tr> <tr> <td>1</td> <td>10</td> <td>Ctrl + Alt + Space</td> </tr> <tr> <td>1</td> <td>11</td> <td>Space</td> </tr> </tbody> </table> | KEY_SEL_ADD | KEY_SEL | Wakeup Key | 0 | 00 | Ctrl + Esc | 0 | 01 | Ctrl + F1 | 0 | 10 | Ctrl + Space | 0 | 11 | Any Key | 1 | 00 | Windows Wakeup | 1 | 01 | Windows Power | 1 | 10 | Ctrl + Alt + Space | 1 | 11 | Space |
| | | | | KEY_SEL_ADD | KEY_SEL | Wakeup Key | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | 0 | 00 | Ctrl + Esc | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | 0 | 01 | Ctrl + F1 | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | 0 | 10 | Ctrl + Space | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | 0 | 11 | Any Key | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | 1 | 00 | Windows Wakeup | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1 | 01 | Windows Power | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1 | 10 | Ctrl + Alt + Space | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1 | 11 | Space | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 0 | MO_SEL | R/W | 0 | This register selects the mouse wake up key. 0: Wake up by clicking. 1: Wake up by clicking and movement. | | | | | | | | | | | | | | | | | | | | | | | | | | | |

8.2 UART1 Registers (CR01)
UART 1 Device Enable Register — Index 30h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-1 | Reserved | - | - | Reserved |
| 0 | UR1_EN | R/W | 1 | 0: disable UART 1. 1: enable UART 1. |

Base Address High Register — Index 60h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---------------------------------|
| 7-0 | BASE_ADDR_HI | R/W | 03h | The MSB of UART 1 base address. |

Base Address Low Register — Index 61h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---------------------------------|
| 7-0 | BASE_ADDR_LO | R/W | F8h | The LSB of UART 1 base address. |

IRQ Channel Select Register — Index 70h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|------------------------------------|
| 7-4 | Reserved | - | - | Reserved. |
| 3-0 | SELUR1IRQ | R/W | 4h | Select the IRQ channel for UART 1. |

RS485 Enable Register — Index F0h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-5 | Reserved | - | - | Reserved. |
| 4 | RS485_EN | R/W | 0 | 0: RS232 driver. 1: RS485 driver. Auto drive RTS# low when transmitting data. |
| 3-0 | Reserved | - | - | Reserved. |

8.3 UART 2 Registers (CR02)

UART 2 Device Enable Register — Index 30h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-1 | Reserved | - | - | Reserved |
| 0 | UR2_EN | R/W | 1 | 0: disable UART 2. 1: enable UART 2. |

Base Address High Register — Index 60h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---------------------------------|
| 7-0 | BASE_ADDR_HI | R/W | 02h | The MSB of UART 2 base address. |

Base Address Low Register — Index 61h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---------------------------------|
| 7-0 | BASE_ADDR_LO | R/W | F8h | The LSB of UART 2 base address. |

IRQ Channel Select Register — Index 70h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|------------------------------------|
| 7-4 | Reserved | - | - | Reserved. |
| 3-0 | SELUR2IRQ | R/W | 3h | Select the IRQ channel for UART 2. |

RS485 Enable Register — Index F0h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-5 | Reserved | - | - | Reserved. |
| 4 | RS485_EN | R/W | 0 | 0: RS232 driver. 1: RS485 driver. Auto drive RTS# low when transmitting data. |
| 3 | RXW4C_IR | R/W | 0 | 0: No reception delay when SIR is changed form TX to RX. 1: Reception delays 4 characters time when SIR is changed form TX to RX. |
| 2 | TXW4C_IR | R/W | 0 | 0: No transmission delay when SIR is changed form RX to TX. 1: Transmission delays 4 characters time when SIR is changed form RX to TX. |
| 1-0 | Reserved | - | - | Reserved. |

SIR Mode Control Register — Index F1h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-------------|
| 7-5 | Reserved | - | - | Reserved. |

| | | | | |
|-----|----------|-----|----|--|
| 4-3 | IRMODE | R/W | 00 | 00: disable IR function. 01: disable IR function. 10: IrDA function, active pulse is 1.6uS. 11: IrDA function, active pulse is 3/16 bit time. |
| 2 | H DUPLX | R/W | 1 | 0: SIR is in full duplex mode for loopbak test. TXW4C_IR and RXW4C_IR are of no use. 1: SIR is in half duplex mode. |
| 1 | TXINV_IR | R/W | 0 | 0: IRTX1 is in normal condition. 1: inverse the IRTX1. |
| 0 | RXINV_IR | R/W | 0 | 0: IRRX1 is in normal condition. 1: inverse the IRRX1. |

8.4 Parallel Port Registers (CR03)

Parallel Port Device Enable Register — Index 30h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-1 | Reserved | - | - | Reserved |
| 0 | PRT_EN | R/W | 1 | 0: disable Parallel Port. 1: enable Parallel Port. |

Base Address High Register — Index 60h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7-0 | BASE_ADDR_HI | R/W | 03h | The MSB of Parallel Port base address. |

Base Address Low Register — Index 61h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7-0 | BASE_ADDR_LO | R/W | 78h | The LSB of Parallel Port base address. |

IRQ Channel Select Register — Index 70h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7-5 | Reserved | - | - | Reserved. |
| 3-0 | SELPRTIRQ | R/W | 7h | Select the IRQ channel for Parallel Port. |

DMA Channel Select Register — Index 74h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7-5 | Reserved | - | - | Reserved. |
| 4 | ECP_DMA_MODE | R/W | 0 | 0: non-burst mode DMA. 1: enable burst mode DMA. |
| 3 | Reserved | - | - | Reserved. |
| 2-0 | SELPRTDMA | R/W | 011 | Select the DMA channel for Parallel Port. |

PRT Mode Select Register — Index F0h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7 | SPP_IRQ_MODE | R/W | 0 | Interrupt mode in non-ECP mode. 0: Level mode. 1: Pulse mode. |
| 6-3 | ECP_FIFO_THR | R/W | 1000 | ECP FIFO threshold. |
| 2-0 | PRT_MODE | R/W | 010 | 000: Standard and Bi-direction (SPP) mode. 001: EPP 1.9 and SPP mode. 010: ECP mode (default). 011: ECP and EPP 1.9 mode. 100: Printer mode. 101: EPP 1.7 and SPP mode. 110: Reserved. 111: ECP and EPP1.7 mode. |

8.5 Hardware Monitor Registers (CR04)

8.6.1 Hardware Monitor Configuration Registers

Hardware Monitor Device Enable Register — Index 30h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-1 | Reserved | - | - | Reserved |
| 0 | HM_EN | R/W | 1 | 0: disable Hardware Monitor. 1: enable Hardware Monitor. |

Base Address High Register — Index 60h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7-0 | BASE_ADDR_HI | R/W | 02h | The MSB of Hardware Monitor base address. |

Base Address Low Register — Index 61h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7-0 | BASE_ADDR_LO | R/W | 95h | The LSB of Hardware Monitor base address. |

IRQ Channel Select Register — Index 70h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-4 | Reserved | - | - | Reserved. |
| 3-0 | SELHMIRQ | R/W | 0000 | Select the IRQ channel for Hardware Monitor. |

8.6 KBC Registers (CR05)

KBC Device Enable Register — Index 30h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-----------------------------------|
| 7-1 | Reserved | - | - | Reserved |
| 0 | KBC_EN | R/W | 1 | 0: disable KBC. 1: enable KBC. |

Base Address High Register — Index 60h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7-0 | BASE_ADDR_HI | R/W | 00h | The MSB of KBC command port address. The address of data port is command port address + 4. |

Base Address Low Register — Index 61h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|--|
| 7-0 | BASE_ADDR_LO | R/W | 60h | The LSB of KBC command port address. The address of data port is command port address + 4. |

KB IRQ Channel Select Register — Index 70h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-4 | Reserved | - | - | Reserved. |
| 3-0 | SELKIRQ | R/W | 1h | Select the IRQ channel for keyboard interrupt. |

Mouse IRQ Channel Select Register — Index 72h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-4 | Reserved | - | - | Reserved. |
| 3-0 | SELMIRQ | R/W | Ch | Select the IRQ channel for PS/2 mouse interrupt. |

Auto Swap Register — Index FEh (Powered by VBAT)

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|---|
| 7 | AUTO_DET_EN | R/W | 1b | 0: disable auto detect keyboard/mouse swap. 1: enable auto detect keyboard/mouse swap. |
| 6-5 | Reserved | - | - | Reserved. |
| 4 | KB_MO_SWAP | R/W | 0b | 0: Keyboard/mouse does not swap. 1: Keyboard/mouse swaps. This bit is set/clear by hardware if AUTO_DET_EN is set to "1". Users could also program this bit manually. |
| 3-0 | Reserved | R/W | 1h | Reserved |

8.7 GPIO Registers (CR06) (All registers of GPIO are powered by VSB3V)
GPIO0 Output Enable Register — Index F0h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO06_OE | R/W | 0 | 0: GPIO06 is in input mode. 1: GPIO06 is in output mode. |
| 5 | GPIO05_OE | R/W | 0 | 0: GPIO05 is in input mode. 1: GPIO05 is in output mode. |
| 4 | GPIO04_OE | R/W | 0 | 0: GPIO04 is in input mode. 1: GPIO04 is in output mode. |
| 3 | GPIO03_OE | R/W | 0 | 0: GPIO03 is in input mode. 1: GPIO03 is in output mode. |
| 2 | GPIO02_OE | R/W | 0 | 0: GPIO02 is in input mode. 1: GPIO02 is in output mode. |

| | | | | |
|---|-----------|-----|---|---|
| 1 | GPIO01_OE | R/W | 0 | 0: GPIO01 is in input mode. 1: GPIO01 is in output mode. |
| 0 | GPIO00_OE | R/W | 0 | 0: GPIO00 is in input mode. 1: GPIO00 is in output mode. |

GPIO0 Output Data Register — Index F1h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO06_VAL | R/W | 1 | 0: GPIO06 outputs 0 when in output mode. 1: GPIO06 outputs 1 when in output mode. |
| 5 | GPIO05_VAL | R/W | 1 | 0: GPIO05 outputs 0 when in output mode. 1: GPIO05 outputs 1 when in output mode. |
| 4 | GPIO04_VAL | R/W | 1 | 0: GPIO04 outputs 0 when in output mode. 1: GPIO04 outputs 1 when in output mode. |
| 3 | GPIO03_VAL | R/W | 1 | 0: GPIO03 outputs 0 when in output mode. 1: GPIO03 outputs 1 when in output mode. |
| 2 | GPIO02_VAL | R/W | 1 | 0: GPIO02 outputs 0 when in output mode. 1: GPIO02 outputs 1 when in output mode. |
| 1 | GPIO01_VAL | R/W | 1 | 0: GPIO01 outputs 0 when in output mode. 1: GPIO01 outputs 1 when in output mode. |
| 0 | GPIO00_VAL | R/W | 1 | 0: GPIO00 outputs 0 when in output mode. 1: GPIO00 outputs 1 when in output mode. |

GPIO0 Pin Status Register — Index F2h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO06_IN | R | - | The pin status of SUSC#/GPIO06/Beep/Alert#. |
| 5 | GPIO05_IN | R | - | The pin status of GPIO05/LED_VCC. |
| 4 | GPIO04_IN | R | - | The pin status of GPIO04/LED_VSB. |
| 3 | GPIO03_IN | R | - | The pin status of SLOTCC#/GPIO03. |
| 2 | GPIO02_IN | R | - | The pin status of GPIO02/BUSOUT2. |
| 1 | GPIO01_IN | R | - | The pin status of GPIO01/BUSOUT1. |
| 0 | GPIO00_IN | R | - | The pin status of GPIO00/BUSOUT0. |

GPIO0 Drive Enable Register — Index F3h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO06_DRV_EN | R/W | 0 | 0: GPIO06 is open drain in output mode. 1: GPIO06 is push pull in output mode. |
| 5 | GPIO05_DRV_EN | R/W | 0 | 0: GPIO05 is open drain in output mode. 1: GPIO05 is push pull in output mode. |
| 4 | GPIO04_DRV_EN | R/W | 0 | 0: GPIO04 is open drain in output mode. 1: GPIO04 is push pull in output mode. |
| 3 | GPIO03_DRV_EN | R/W | 0 | 0: GPIO03 is open drain in output mode. 1: Reserved. |

| | | | | |
|---|---------------|-----|---|---|
| 2 | GPIO02_DRV_EN | R/W | 0 | 0: GPIO02 is open drain in output mode. 1: GPIO02 is push pull in output mode. |
| 1 | GPIO01_DRV_EN | R/W | 0 | 0: GPIO01 is open drain in output mode. 1: GPIO01 is push pull in output mode. |
| 0 | GPIO00_DRV_EN | R/W | 0 | 0: GPIO00 is open drain in output mode. 1: GPIO00 is push pull in output mode. |

LED_VSB Control Register — Index FEh (Powered by VBAT)

| Bit | Name | R/W | Default | Description |
|-----|-----------------|-----|---------|--|
| 7-6 | Reserved | - | - | Reserved. |
| 5-4 | LED_VSB_S5_MODE | R/W | 0 | These bits control the LED_VSB output mode in S5 state. 00: Sink 0 01: Tri-state. 10: 0.5Hz clock 11: 1Hz clock. |
| 3-2 | LED_VSB_S3_MODE | R/W | 0 | These bits control the LED_VSB output mode in S3 state. 00: Sink 0 01: Tri-state. 10: 0.5Hz clock 11: 1Hz clock. |
| 1-0 | LED_VSB_S0_MODE | R/W | 0 | These bits control the LED_VSB output mode in S0 state. 00: Sink 0 01: Tri-state. 10: 0.5Hz clock 11: 1Hz clock. |

LED_VCC Control Register — Index FFh (Powered by VBAT)

| Bit | Name | R/W | Default | Description |
|-----|-----------------|-----|---------|--|
| 7 | LED_VCC_INV_DIS | R/W | 0 | 0: LED_VCC output clock is inverted. 1: LED_VCC output clock is not inverted. |
| 6 | Reserved | - | - | Reserved. |
| 5-4 | LED_VCC_S5_MODE | R/W | 0 | These bits control the LED_VCC output mode in S5 state. 00: Sink 0 01: Tri-state. 10: 0.5Hz clock 11: 1Hz clock. |
| 3-2 | LED_VCC_S3_MODE | R/W | 0 | These bits control the LED_VCC output mode in S3 state. 00: Sink 0 01: Tri-state. 10: 0.5Hz clock 11: 1Hz clock. |
| 1-0 | LED_VCC_S0_MODE | R/W | 0 | These bits control the LED_VCC output mode in S0 state. 00: Sink 0 01: Tri-state. 10: 0.5Hz clock 11: 1Hz clock. |

GPIO1 Output Enable Register — Index E0h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO16_OE | R/W | 0 | 0: GPIO16 is in input mode. 1: GPIO16 is in output mode. |
| 5 | GPIO15_OE | R/W | 0 | 0: GPIO15 is in input mode. 1: GPIO15 is in output mode. |
| 4 | GPIO14_OE | R/W | 0 | 0: GPIO14 is in input mode. 1: GPIO14 is in output mode. |
| 3 | GPIO13_OE | R/W | 0 | 0: GPIO13 is in input mode. 1: GPIO13 is in output mode. |
| 2 | GPIO12_OE | R/W | 0 | 0: GPIO12 is in input mode. 1: GPIO12 is in output mode. |
| 1 | GPIO11_OE | R/W | 0 | 0: GPIO11 is in input mode. 1: GPIO11 is in output mode. |
| 0 | GPIO10_OE | R/W | 0 | 0: GPIO10 is in input mode. 1: GPIO10 is in output mode. |

GPIO1 Output Data Register — Index E1h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO16_VAL | R/W | 1 | 0: GPIO16 outputs 0 when in output mode. 1: GPIO16 outputs 1 when in output mode. |
| 5 | GPIO15_VAL | R/W | 1 | 0: GPIO15 outputs 0 when in output mode. 1: GPIO15 outputs 1 when in output mode. |
| 4 | GPIO14_VAL | R/W | 1 | 0: GPIO14 outputs 0 when in output mode. 1: GPIO14 outputs 1 when in output mode. |
| 3 | GPIO13_VAL | R/W | 1 | 0: GPIO13 outputs 0 when in output mode. 1: GPIO13 outputs 1 when in output mode. |
| 2 | GPIO12_VAL | R/W | 1 | 0: GPIO12 outputs 0 when in output mode. 1: GPIO12 outputs 1 when in output mode. |
| 1 | GPIO11_VAL | R/W | 1 | 0: GPIO11 outputs 0 when in output mode. 1: GPIO11 outputs 1 when in output mode. |
| 0 | GPIO10_VAL | R/W | 1 | 0: GPIO10 outputs 0 when in output mode. 1: GPIO10 outputs 1 when in output mode. |

GPIO1 Pin Status Register — Index E2h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO16_IN | R | - | The pin status of PECl/TSI_DAT/IBX_SDA/GPIO16 |
| 5 | GPIO15_IN | R | - | The pin status of SST/TSI_CLK/IBX_CLK/GPIO15. |
| 4 | GPIO14_IN | R | - | The pin status of IRRX/TSI_DAT/IBX_SDA/GPIO14. |
| 3 | GPIO13_IN | R | - | The pin status of IRTX/TSI_CLK/IBX_CLK/GPIO13. |
| 2 | GPIO12_IN | R | - | The pin status of GPIO12/WDTRST# |
| 1 | GPIO11_IN | R | - | The pin status of FANCTL3/GPIO11/IRTX1. |

| | | | | |
|---|-----------|---|---|--|
| 0 | GPIO10_IN | R | - | The pin status of FANIN3/GPIO10/IRRX1. |
|---|-----------|---|---|--|

GPIO1 Drive Enable Register — Index E3h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7 | Reserved | - | - | Reserved. |
| 6 | GPIO16_DRV_EN | R/W | 0 | 0: GPIO16 is open drain in output mode. 1: GPIO16 is push pull in output mode. |
| 5 | GPIO15_DRV_EN | R/W | 0 | 0: GPIO15 is open drain in output mode. 1: GPIO15 is push pull in output mode. |
| 4 | GPIO14_DRV_EN | R/W | 0 | 0: GPIO14 is open drain in output mode. 1: GPIO14 is push pull in output mode. |
| 3 | GPIO13_DRV_EN | R/W | 0 | 0: GPIO13 is open drain in output mode. 1: GPIO13 is push pull in output mode. |
| 2 | GPIO12_DRV_EN | R/W | 0 | 0: GPIO12 is open drain in output mode. 1: GPIO12 is push pull in output mode. |
| 1 | GPIO11_DRV_EN | R/W | 0 | 0: GPIO11 is open drain in output mode. 1: GPIO11 is push pull in output mode. |
| 0 | GPIO10_DRV_EN | R/W | 0 | 0: GPIO10 is open drain in output mode. 1: GPIO10 is push pull in output mode. |

GPIO2 Output Enable Register — Index D0h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | GPIO27_OE | R/W | 0 | 0: GPIO27 is in input mode. 1: GPIO27 is in output mode. |
| 6 | GPIO26_OE | R/W | 0 | 0: GPIO26 is in input mode. 1: GPIO26 is in output mode. |
| 5 | GPIO25_OE | R/W | 0 | 0: GPIO25 is in input mode. 1: GPIO25 is in output mode. |
| 4-0 | Reserved | - | - | Reserved. |

GPIO2 Output Data Register — Index D1h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | GPIO27_VAL | R/W | 1 | 0: GPIO27 outputs 0 when in output mode. 1: GPIO27 outputs 1 when in output mode. |
| 6 | GPIO26_VAL | R/W | 1 | 0: GPIO26 outputs 0 when in output mode. 1: GPIO26 outputs 1 when in output mode. |
| 5 | GPIO25_VAL | R/W | 1 | 0: GPIO25 outputs 0 when in output mode. 1: GPIO25 outputs 1 when in output mode. |
| 4-0 | Reserved | - | - | Reserved. |

GPIO2 Pin Status Register — Index D2h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|----------------------------------|
| 7 | GPIO27_IN | R | - | The pin status of GPIO27/BUSIN2. |
| 6 | GPIO26_IN | R | - | The pin status of GPIO26/BUSIN1. |
| 5 | GPIO25_IN | R | - | The pin status of GPIO25/BUSIN0. |

| | | | | |
|-----|----------|---|---|-----------|
| 4-0 | Reserved | - | - | Reserved. |
|-----|----------|---|---|-----------|

GPIO2 Drive Enable Register — Index D3h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7 | GPIO27_DRV_EN | R/W | 0 | 0: GPIO27 is open drain in output mode. 1: GPIO27 is push pull in output mode. |
| 6 | GPIO26_DRV_EN | R/W | 0 | 0: GPIO26 is open drain in output mode. 1: GPIO26 is push pull in output mode. |
| 5 | GPIO25_DRV_EN | R/W | 0 | 0: GPIO25 is open drain in output mode. 1: GPIO25 is push pull in output mode. |
| 4-0 | Reserved | - | - | Reserved. |

GPIO3 Output Enable Register — Index C0h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | GPIO37_OE | R/W | 0 | 0: GPIO37 is in input mode. 1: GPIO37 is in output mode. |
| 6 | GPIO36_OE | R/W | 0 | 0: GPIO36 is in input mode. 1: GPIO35 is in output mode. |
| 5 | GPIO35_OE | R/W | 0 | 0: GPIO35 is in input mode. 1: GPIO35 is in output mode. |
| 4 | GPIO34_OE | R/W | 0 | 0: GPIO34 is in input mode. 1: GPIO34 is in output mode. |
| 3 | GPIO33_OE | R/W | 0 | 0: GPIO33 is in input mode. 1: GPIO33 is in output mode. |
| 2 | GPIO32_OE | R/W | 0 | 0: GPIO32 is in input mode. 1: GPIO32 is in output mode. |
| 1 | GPIO31_OE | R/W | 0 | 0: GPIO31 is in input mode. 1: GPIO31 is in output mode. |
| 0 | GPIO30_OE | R/W | 0 | 0: GPIO30 is in input mode. 1: GPIO30 is in output mode. |

GPIO3 Output Data Register — Index C1h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | GPIO37_VAL | R/W | 1 | 0: GPIO37 outputs 0 when in output mode. 1: GPIO37 outputs 1 when in output mode. |
| 6 | GPIO36_VAL | R/W | 1 | 0: GPIO36 outputs 0 when in output mode. 1: GPIO36 outputs 1 when in output mode. |
| 5 | GPIO35_VAL | R/W | 1 | 0: GPIO35 outputs 0 when in output mode. 1: GPIO35 outputs 1 when in output mode. |
| 4 | GPIO34_VAL | R/W | 1 | 0: GPIO34 outputs 0 when in output mode. 1: GPIO34 outputs 1 when in output mode. |
| 3 | GPIO33_VAL | R/W | 1 | 0: GPIO33 outputs 0 when in output mode. 1: GPIO33 outputs 1 when in output mode. |
| 2 | GPIO32_VAL | R/W | 1 | 0: GPIO32 outputs 0 when in output mode. 1: GPIO32 outputs 1 when in output mode. |

| | | | | |
|---|------------|-----|---|--|
| 1 | GPIO31_VAL | R/W | 1 | 0: GPIO31 outputs 0 when in output mode. 1: GPIO31 outputs 1 when in output mode. |
| 0 | GPIO30_VAL | R/W | 1 | 0: GPIO30 outputs 0 when in output mode. 1: GPIO30 outputs 1 when in output mode. |

GPIO3 Pin Status Register — Index C2h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | GPIO37_IN | R | - | The pin status of SIN2/SEGE/GPIO37. |
| 6 | GPIO36_IN | R | - | The pin status of SOUT2/SEGB/GPIO36. |
| 5 | GPIO35_IN | R | - | The pin status of DSR2#/L#/GPIO35. |
| 4 | GPIO34_IN | R | - | The pin status of RTS2#/SEGC/GPIO34/PWM_DC. |
| 3 | GPIO33_IN | R | - | The pin status of DTR2#/SEGD/GPIO33. |
| 2 | GPIO32_IN | R | - | The pin status of CTS2#/SEGA/GPIO32. |
| 1 | GPIO31_IN | R | - | The pin status of RI2#/GPIO31. |
| 0 | GPIO30_IN | R | - | The pin status of DCD2#/GPIO30. |

GPIO3 Drive Enable Register — Index C3h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7 | GPIO37_DRV_EN | R/W | 0 | 0: GPIO37 is open drain in output mode. 1: GPIO37 is push pull in output mode. |
| 6 | GPIO36_DRV_EN | R/W | 0 | 0: GPIO36 is open drain in output mode. 1: GPIO36 is push pull in output mode. |
| 5 | GPIO35_DRV_EN | R/W | 0 | 0: GPIO35 is open drain in output mode. 1: GPIO35 is push pull in output mode. |
| 4 | GPIO34_DRV_EN | R/W | 0 | 0: GPIO34 is open drain in output mode. 1: GPIO34 is push pull in output mode. |
| 3 | GPIO33_DRV_EN | R/W | 0 | 0: GPIO33 is open drain in output mode. 1: GPIO33 is push pull in output mode. |
| 2 | GPIO32_DRV_EN | R/W | 0 | 0: GPIO32 is open drain in output mode. 1: GPIO32 is push pull in output mode. |
| 1 | GPIO31_DRV_EN | R/W | 0 | 0: GPIO31 is open drain in output mode. 1: GPIO31 is push pull in output mode. |
| 0 | GPIO30_DRV_EN | R/W | 0 | 0: GPIO30 is open drain in output mode. 1: GPIO30 is push pull in output mode. |

GPIO4 Output Enable Register — Index B0h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | GPIO47_OE | R/W | 0 | 0: GPIO47 is in input mode. 1: GPIO47 is in output mode. |
| 6 | GPIO46_OE | R/W | 0 | 0: GPIO46 is in input mode. 1: GPIO45 is in output mode. |
| 5 | GPIO45_OE | R/W | 0 | 0: GPIO45 is in input mode. 1: GPIO45 is in output mode. |

| | | | | |
|---|-----------|-----|---|---|
| 4 | GPIO44_OE | R/W | 0 | 0: GPIO44 is in input mode. 1: GPIO44 is in output mode. |
| 3 | GPIO43_OE | R/W | 0 | 0: GPIO43 is in input mode. 1: GPIO43 is in output mode. |
| 2 | GPIO42_OE | R/W | 0 | 0: GPIO42 is in input mode. 1: GPIO42 is in output mode. |
| 1 | GPIO41_OE | R/W | 0 | 0: GPIO41 is in input mode. 1: GPIO41 is in output mode. |
| 0 | GPIO40_OE | R/W | 0 | 0: GPIO40 is in input mode. 1: GPIO40 is in output mode. |

GPIO4 Output Data Register — Index B1h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | GPIO47_VAL | R/W | 1 | 0: GPIO47 outputs 0 when in output mode. 1: GPIO47 outputs 1 when in output mode. |
| 6 | GPIO46_VAL | R/W | 1 | 0: GPIO46 outputs 0 when in output mode. 1: GPIO46 outputs 1 when in output mode. |
| 5 | GPIO45_VAL | R/W | 1 | 0: GPIO45 outputs 0 when in output mode. 1: GPIO45 outputs 1 when in output mode. |
| 4 | GPIO44_VAL | R/W | 1 | 0: GPIO44 outputs 0 when in output mode. 1: GPIO44 outputs 1 when in output mode. |
| 3 | GPIO43_VAL | R/W | 1 | 0: GPIO43 outputs 0 when in output mode. 1: GPIO43 outputs 1 when in output mode. |
| 2 | GPIO42_VAL | R/W | 1 | 0: GPIO42 outputs 0 when in output mode. 1: GPIO42 outputs 1 when in output mode. |
| 1 | GPIO41_VAL | R/W | 1 | 0: GPIO41 outputs 0 when in output mode. 1: GPIO41 outputs 1 when in output mode. |
| 0 | GPIO40_VAL | R/W | 1 | 0: GPIO40 outputs 0 when in output mode. 1: GPIO40 outputs 1 when in output mode. |

GPIO4 Pin Status Register — Index B2h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---------------------------|
| 7 | GPIO47_IN | R | - | The pin status of GPIO47. |
| 6 | GPIO46_IN | R | - | The pin status of GPIO46. |
| 5 | GPIO45_IN | R | - | The pin status of GPIO45. |
| 4 | GPIO44_IN | R | - | The pin status of GPIO44. |
| 3 | GPIO43_IN | R | - | The pin status of GPIO43. |
| 2 | GPIO42_IN | R | - | The pin status of GPIO42. |
| 1 | GPIO41_IN | R | - | The pin status of GPIO41. |
| 0 | GPIO40_IN | R | - | The pin status of GPIO40. |

GPIO5 Output Enable Register — Index A0h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-------------|
| 7-5 | Reserved | - | - | Reserved. |

| | | | | |
|---|-----------|-----|---|---|
| 4 | GPIO54_OE | R/W | 0 | 0: GPIO54 is in input mode. 1: GPIO54 is in output mode. |
| 3 | GPIO53_OE | R/W | 0 | 0: GPIO53 is in input mode. 1: GPIO53 is in output mode. |
| 2 | GPIO52_OE | R/W | 0 | 0: GPIO52 is in input mode. 1: GPIO52 is in output mode. |
| 1 | GPIO51_OE | R/W | 0 | 0: GPIO51 is in input mode. 1: GPIO51 is in output mode. |
| 0 | GPIO50_OE | R/W | 0 | 0: GPIO50 is in input mode. 1: GPIO50 is in output mode. |

GPIO5 Output Data Register — Index A1h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7-5 | Reserved | - | - | Reserved. |
| 4 | GPIO54_VAL | R/W | 1 | 0: GPIO54 outputs 0 when in output mode. 1: GPIO54 outputs 1 when in output mode. |
| 3 | GPIO53_VAL | R/W | 1 | 0: GPIO53 outputs 0 when in output mode. 1: GPIO53 outputs 1 when in output mode. |
| 2 | GPIO52_VAL | R/W | 1 | 0: GPIO52 outputs 0 when in output mode. 1: GPIO52 outputs 1 when in output mode. |
| 1 | GPIO51_VAL | R/W | 1 | 0: GPIO51 outputs 0 when in output mode. 1: GPIO51 outputs 1 when in output mode. |
| 0 | GPIO50_VAL | R/W | 1 | 0: GPIO50 outputs 0 when in output mode. 1: GPIO50 outputs 1 when in output mode. |

GPIO5 Pin Status Register — Index A2h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---------------------------|
| 7-5 | Reserved | - | - | Reserved. |
| 4 | GPIO54_IN | R | - | The pin status of GPIO54. |
| 3 | GPIO53_IN | R | - | The pin status of GPIO53. |
| 2 | GPIO52_IN | R | - | The pin status of GPIO52. |
| 1 | GPIO51_IN | R | - | The pin status of GPIO51. |
| 0 | GPIO50_IN | R | - | The pin status of GPIO50. |

GPIO5 Drive Enable Register — Index A3h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7-5 | Reserved | - | - | Reserved. |
| 4 | GPIO54_DRV_EN | R/W | 0 | 0: GPIO54 is open drain in output mode. 1: GPIO54 is push pull in output mode. |
| 3 | GPIO53_DRV_EN | R/W | 0 | 0: GPIO53 is open drain in output mode. 1: GPIO53 is push pull in output mode. |
| 2 | GPIO52_DRV_EN | R/W | 0 | 0: GPIO52 is open drain in output mode. 1: GPIO52 is push pull in output mode. |
| 1 | GPIO51_DRV_EN | R/W | 0 | 0: GPIO51 is open drain in output mode. 1: GPIO51 is push pull in output mode. |

| | | | | |
|---|---------------|-----|---|---|
| 0 | GPIO50_DRV_EN | R/W | 0 | 0: GPIO50 is open drain in output mode. 1: GPIO50 is push pull in output mode. |
|---|---------------|-----|---|---|

GPIO6 Output Enable Register — Index 90h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | GPIO67_OE | R/W | 0 | 0: GPIO67 is in input mode. 1: GPIO67 is in output mode. |
| 6 | GPIO66_OE | R/W | 0 | 0: GPIO66 is in input mode. 1: GPIO65 is in output mode. |
| 5 | GPIO65_OE | R/W | 0 | 0: GPIO65 is in input mode. 1: GPIO65 is in output mode. |
| 4 | GPIO64_OE | R/W | 0 | 0: GPIO64 is in input mode. 1: GPIO64 is in output mode. |
| 3 | GPIO63_OE | R/W | 0 | 0: GPIO63 is in input mode. 1: GPIO63 is in output mode. |
| 2 | GPIO62_OE | R/W | 0 | 0: GPIO62 is in input mode. 1: GPIO62 is in output mode. |
| 1 | GPIO61_OE | R/W | 0 | 0: GPIO61 is in input mode. 1: GPIO61 is in output mode. |
| 0 | GPIO60_OE | R/W | 0 | 0: GPIO60 is in input mode. 1: GPIO60 is in output mode. |

GPIO6 Output Data Register — Index 91h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | GPIO67_VAL | R/W | 1 | 0: GPIO67 outputs 0 when in output mode. 1: GPIO67 outputs 1 when in output mode. |
| 6 | GPIO66_VAL | R/W | 1 | 0: GPIO66 outputs 0 when in output mode. 1: GPIO66 outputs 1 when in output mode. |
| 5 | GPIO65_VAL | R/W | 1 | 0: GPIO65 outputs 0 when in output mode. 1: GPIO65 outputs 1 when in output mode. |
| 4 | GPIO64_VAL | R/W | 1 | 0: GPIO64 outputs 0 when in output mode. 1: GPIO64 outputs 1 when in output mode. |
| 3 | GPIO63_VAL | R/W | 1 | 0: GPIO63 outputs 0 when in output mode. 1: GPIO63 outputs 1 when in output mode. |
| 2 | GPIO62_VAL | R/W | 1 | 0: GPIO62 outputs 0 when in output mode. 1: GPIO62 outputs 1 when in output mode. |
| 1 | GPIO61_VAL | R/W | 1 | 0: GPIO61 outputs 0 when in output mode. 1: GPIO61 outputs 1 when in output mode. |
| 0 | GPIO60_VAL | R/W | 1 | 0: GPIO60 outputs 0 when in output mode. 1: GPIO60 outputs 1 when in output mode. |

GPIO6 Pin Status Register — Index 92h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7 | GPIO67_IN | R | - | The pin status of STB#/L#/VIDIN7/GPIO67. |
| 6 | GPIO66_IN | R | - | The pin status of AFD#/H#/VIDIN6/GPIO66. |
| 5 | GPIO65_IN | R | - | The pin status of ERR#/VIDIN5/GPIO65. |

| | | | | |
|---|-----------|---|---|--|
| 4 | GPIO64_IN | R | - | The pin status of INIT#/VIDIN4/GPIO64. |
| 3 | GPIO63_IN | R | - | The pin status of ACK#/VIDIN3 (SVC_IN)/GPIO63. |
| 2 | GPIO62_IN | R | - | The pin status of BUSY/VIDIN2 (SVD_IN)/GPIO62. |
| 1 | GPIO61_IN | R | - | The pin status of PE/VIDIN1/GPIO61. |
| 0 | GPIO60_IN | R | - | The pin status of SLCT/VIDIN0/GPIO60. |

GPIO6 Drive Enable Register — Index 93h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7 | GPIO67_DRV_EN | R/W | 0 | 0: GPIO67 is open drain in output mode. 1: GPIO67 is push pull in output mode. |
| 6 | GPIO66_DRV_EN | R/W | 0 | 0: GPIO66 is open drain in output mode. 1: GPIO66 is push pull in output mode. |
| 5 | GPIO65_DRV_EN | R/W | 0 | 0: GPIO65 is open drain in output mode. 1: GPIO65 is push pull in output mode. |
| 4 | GPIO64_DRV_EN | R/W | 0 | 0: GPIO64 is open drain in output mode. 1: GPIO64 is push pull in output mode. |
| 3 | GPIO63_DRV_EN | R/W | 0 | 0: GPIO63 is open drain in output mode. 1: GPIO63 is push pull in output mode. |
| 2 | GPIO62_DRV_EN | R/W | 0 | 0: GPIO62 is open drain in output mode. 1: GPIO62 is push pull in output mode. |
| 1 | GPIO61_DRV_EN | R/W | 0 | 0: GPIO61 is open drain in output mode. 1: GPIO61 is push pull in output mode. |
| 0 | GPIO60_DRV_EN | R/W | 0 | 0: GPIO60 is open drain in output mode. 1: GPIO60 is push pull in output mode. |

GPIO7 Output Enable Register — Index 80h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | GPIO77_OE | R/W | 0 | 0: GPIO77 is in input mode. 1: GPIO77 is in output mode. |
| 6 | GPIO76_OE | R/W | 0 | 0: GPIO76 is in input mode. 1: GPIO75 is in output mode. |
| 5 | GPIO75_OE | R/W | 0 | 0: GPIO75 is in input mode. 1: GPIO75 is in output mode. |
| 4 | GPIO74_OE | R/W | 0 | 0: GPIO74 is in input mode. 1: GPIO74 is in output mode. |
| 3 | GPIO73_OE | R/W | 0 | 0: GPIO73 is in input mode. 1: GPIO73 is in output mode. |
| 2 | GPIO72_OE | R/W | 0 | 0: GPIO72 is in input mode. 1: GPIO72 is in output mode. |
| 1 | GPIO71_OE | R/W | 0 | 0: GPIO71 is in input mode. 1: GPIO71 is in output mode. |
| 0 | GPIO70_OE | R/W | 0 | 0: GPIO70 is in input mode. 1: GPIO70 is in output mode. |

GPIO7 Output Data Register — Index 81h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7 | GPIO77_VAL | R/W | 1 | 0: GPIO77 outputs 0 when in output mode. 1: GPIO77 outputs 1 when in output mode. |
| 6 | GPIO76_VAL | R/W | 1 | 0: GPIO76 outputs 0 when in output mode. 1: GPIO76 outputs 1 when in output mode. |
| 5 | GPIO75_VAL | R/W | 1 | 0: GPIO75 outputs 0 when in output mode. 1: GPIO75 outputs 1 when in output mode. |
| 4 | GPIO74_VAL | R/W | 1 | 0: GPIO74 outputs 0 when in output mode. 1: GPIO74 outputs 1 when in output mode. |
| 3 | GPIO73_VAL | R/W | 1 | 0: GPIO73 outputs 0 when in output mode. 1: GPIO73 outputs 1 when in output mode. |
| 2 | GPIO72_VAL | R/W | 1 | 0: GPIO72 outputs 0 when in output mode. 1: GPIO72 outputs 1 when in output mode. |
| 1 | GPIO71_VAL | R/W | 1 | 0: GPIO71 outputs 0 when in output mode. 1: GPIO71 outputs 1 when in output mode. |
| 0 | GPIO70_VAL | R/W | 1 | 0: GPIO70 outputs 0 when in output mode. 1: GPIO70 outputs 1 when in output mode. |

GPIO7 Pin Status Register — Index 82h

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7 | GPIO77_IN | R | - | The pin status of PD7/VIDOUT7/GPIO77. |
| 6 | GPIO76_IN | R | - | The pin status of PD6/SEGG/VIDOUT6/GPIO76. |
| 5 | GPIO75_IN | R | - | The pin status of PD5/SEGF/VIDOUT5/GPIO75. |
| 4 | GPIO74_IN | R | - | The pin status of PD4/SEGE/VIDOUT4/GPIO74. |
| 3 | GPIO73_IN | R | - | The pin status of PD3/SEGD/VIDOUT3 (SVC_OUT)/GPIO73. |
| 2 | GPIO72_IN | R | - | The pin status of PD2/SEGC/VIDOUT2 (SVD_OUT)/GPIO72. |
| 1 | GPIO71_IN | R | - | The pin status of PD1/SEGB/VIDOUT1/GPIO71. |
| 0 | GPIO70_IN | R | - | The pin status of PD0/SEGA/VIDOUT0/GPIO70. |

GPIO7 Drive Enable Register — Index 83h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7 | GPIO77_DRV_EN | R/W | 0 | 0: GPIO77 is open drain in output mode. 1: GPIO77 is push pull in output mode. |
| 6 | GPIO76_DRV_EN | R/W | 0 | 0: GPIO76 is open drain in output mode. 1: GPIO76 is push pull in output mode. |
| 5 | GPIO75_DRV_EN | R/W | 0 | 0: GPIO75 is open drain in output mode. 1: GPIO75 is push pull in output mode. |
| 4 | GPIO74_DRV_EN | R/W | 0 | 0: GPIO74 is open drain in output mode. 1: GPIO74 is push pull in output mode. |
| 3 | GPIO73_DRV_EN | R/W | 0 | 0: GPIO73 is open drain in output mode. 1: GPIO73 is push pull in output mode. |
| 2 | GPIO72_DRV_EN | R/W | 0 | 0: GPIO72 is open drain in output mode. 1: GPIO72 is push pull in output mode. |

| | | | | |
|---|---------------|-----|---|---|
| 1 | GPIO71_DRV_EN | R/W | 0 | 0: GPIO71 is open drain in output mode. 1: GPIO71 is push pull in output mode. |
| 0 | GPIO70_DRV_EN | R/W | 0 | 0: GPIO70 is open drain in output mode. 1: GPIO70 is push pull in output mode. |

8.8 VID Registers (CR07)

8.9.1 VID Configuration Registers

VID Device Enable Register — Index 30h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-----------------------------------|
| 7-1 | Reserved | - | - | Reserved |
| 0 | VID_EN | R/W | 0 | 0: disable VID. 1: enable VID. |

Base Address High Register — Index 60h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|------------------------------|
| 7-0 | BASE_ADDR_HI | R/W | 00h | The MSB of VID base address. |

Base Address Low Register — Index 61h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|------------------------------|
| 7-0 | BASE_ADDR_LO | R/W | 00h | The LSB of VID base address. |

8.9.2 Device Registers

Watchdog Timer Configuration Register — Index F0h (* cleared by SLOTOCC_N and watch dog timeout)

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7 | WDOUT_EN | R/W | 0 | If this bit is set to 1 and watchdog timeout event occurs, WDTRST# output is enabled. |
| 6-1 | Reserved | - | 0 | Reserved |
| 0 | WD_RST_EN | R/W | 0 | 0: Disable WDT to reset the VID register marked with *. 1: Enable WDT to reset the VID register marked with *. |

BUSOUT Manual Register — Index F2h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7* | MANUAL_MODE | R/W | 0 | 0: BUSIN2-0 is bypassed to BUSOUT2-0. 1: BUSOUT2-0 is controlled by BUSOUT_MANUAL. This bit is reset by SLOTOCC# falling edge or WDT (with WD_RT_EN set). |
| 6 | KEY_OK | R | - | This bit is 1 represents that the serial key is entered correctly. |
| 5-3 | Reserved | R/W | 0 | Dummy register for future use. |
| 2-0 | BUSOUT_MANUAL | R/W | 0 | The output value for BUSOUT2-0 if MANUAL_MODE is set. |

Serial Key Data Register — Index F3h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---|
| 7-0 | KEY_DATA | R/W | 0 | Write serial data to this register correctly, the KEY_OK bit will be set to 1. Hence, users are able to write key protected registers. The sequence to enable KEY_OK is 0x32, 0x5D, 0x42, 0xAC. When KEY_OK is set, write this register 0x35 will clear KEY_OK. |

BUSIN Register — Index F4h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|--|
| 7-3 | Reserved | R | 0 | Reserved |
| 2:0 | BUSIN | R | - | The value of this register depends on the BUSIN_MODE register: BUSIN_MODE is 1: the register indicates the BUS reading from CPU (the pin status of BUS_IN [2:0]). BUSIN_MODE is 0: the register latches the value of BUS_IN [2:0] when BUSIN_MODE changed from 1 to 0. |

Watchdog Timer Configuration Register 1— Index F5h

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|--|
| 7 | Reserved | R | 0 | Reserved |
| 6 | WDTMOUT_STS | R/W | 0 | If watchdog timeout event occurs, this bit will be set to 1. Write a 1 to this bit will clear it to 0. |
| 5 | WD_EN | R/W | 0 | If this bit is set to 1, the counting of watchdog time is enabled. |
| 4 | WD_PULSE | R/W | 0 | Select output mode (0: level, 1: pulse) of RSTOUT# by setting this bit. |
| 3 | WD_UNIT | R/W | 0 | Select time unit (0: 1sec, 1: 60 sec) of watchdog timer by setting this bit. |
| 2 | WD_HACTIVE | R/W | 0 | Select output polarity of RSTOUT# (1: high active, 0: low active) by setting this bit. |
| 1:0 | WD_PSWIDTH | R/W | 0 | Select output pulse width of RSTOUT# 0: 1 ms 1: 25 ms 2: 125 ms 3: 5 sec |

Watchdog Timer Configuration Register 2 — Index F6h

| Bit | Name | R/W | Default | Description |
|-----|---------|-----|---------|------------------------|
| 7:0 | WD_TIME | R/W | 0 | Time of watchdog timer |

NB Offset Register — Index F7h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7:0 | *NB_OFFSET | R/W | 0 | Program this byte to add offset to VDDNB in AMD SVID interface. The value will be "0" before PWROK. |

VDD0 Offset Register — Index F8h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7:0 | *VDD0_OFFSET | R/W | 0 | Program this byte to add offset to 1. VDD0 in AMD SVID interface. 2. VININ in AMD PVID interface (LSB is not used, VDD0_OFFSET[1] is the smallest step). 3. VIDIN in Intel VRM11. The value will be "0" before PWROK. |

VDD1 Offset Register — Index F9h

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7:0 | *VDD1_OFFSET | R/W | 0 | Program this byte to add offset to VDD1 in AMD SVID interface. The value will be "0" before PWROK. |

WDT PME Register — Index FAh

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7 | WDT_PME | R | 0 | 0: No WDT PME occurred. 1: WDT PME occurred. The WDT PME is occurred one unit before WDT timeout. |
| 6 | WDT_PME_EN | R/W | 0 | 0: Disable WDT PME. 1: Enable WDT PME. |
| 5-1 | Reserved | R | 0 | Reserved |
| 0 | CPU_CHANGE | R/W | 0 | This bit will be set at SLOTOCC# rise edge. Internal 1us de-bounce circuit is implemented. Write "1" to this bit will clear the status. |

VDDNB Manual Register — Index FBh

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7:0 | VDDNB_MANUAL | R/W | 0 | This byte is used to program the manual value for VDDNB of AMD SVID interface in manual mode. Set VID_BANK_SEL "1" to access this byte. |
| | VDDNB_IN | R | - | The value of VDDNB from CPU (AMD SVID interface only). Set VID_BANK_SEL "0" to read this byte. |

VDD0 Manual Register — Index FCh

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|---|
| 7:0 | VDD0_MANUAL | R/W | 0 | This byte is used to program the manual value for 1. VDD0 of AMD SVID interface in manual mode. 2. VIDOUT of AMD PVID interface in manual mode (The output is controlled by VDD0_MANUAL [6:1] since AMD PVID only has 6 pins). 3. VIDOUT of Intel VRM11 in manual mode. Set VID_BANK_SEL "1" to access this byte. |
| | VDD0_IN | R | - | This byte has three functions: 1. VDD0 read from CPU in AMD SVID interface. 2. {1'b0, VIDIN [5:0], 1'b0} in AMD PVID interface. 3. VIDIN in Intel VRM11. Set VID_BANK_SEL "0" to read this byte. |

VDD1 Manual Register — Index FDh

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|--|
| 7:0 | VDD1_MANUAL | R/W | 0 | This byte is used to program the manual value for VDD1 of AMD SVID interface in manual mode. Set VID_BANK_SEL "1" to access this byte. |
| | VDD1_IN | R | - | The value of VDD1 from CPU (AMD SVID interface only). Set VID_BANK_SEL "0" to read this byte. |

PSI Control Register — Index FEh

| Bit | Name | R/W | Default | Description |
|-----|--------------|-----|---------|---|
| 7 | VID_BANK_SEL | R/W | 0 | Select the different bank to access other register at the same index. |
| 6-5 | Reserved | - | 0 | Reserved |

F71889E

| | | | | |
|---|------------------|-----|---|--|
| 4 | VRM_SEL | R/W | 0 | If parallel VID interface is detected. Program this bit to determine AMD/Intel model. 0: Intel VRM11 1: AMD PVID |
| 3 | PSI_VDD1 | R/W | 1 | This bit is used for AMD SVID only. 0: force PSI of VDD1 "0". 1: PSI of VDD1 is determined by the reading from CPU. |
| 2 | PSI_VDD0 | R/W | 1 | This bit is used for AMD SVID only. 0: force PSI of VDD0 "0". 1: PSI of VDD0 is determined by the reading from CPU. |
| 1 | PSI_NB | R/W | 1 | This bit is used for AMD SVID only. 0: force PSI of VDDNB "0". 1: PSI of VDDNB is determined by the reading from CPU. |
| 0 | *VID_MANUAL_MODE | R/W | 0 | 0: VID is in bypass mode or on-the-fly mode determined by the offset value. 1: VID is in manual mode. This bit will be "0" before PWROK. |

*Those register is reset by SLOTOCC# falling edge (CPU change) or Watchdog timer timeout (if enabled).

8.9 PME, ACPI and EUP Registers (CR0A)

PME Device Enable Register — Index 30h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|-----------------------------------|
| 7-1 | Reserved | - | - | Reserved |
| 0 | PME_EN | R/W | 0 | 0: disable PME. 1: enable PME. |

PME Event Enable 1 Register — Index F0h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7 | Reserved | - | - | Reserved |
| 6 | MO_PME_EN | R/W | 0 | Mouse PME event enable. 0: disable mouse PME event. 1: enable mouse PME event. |
| 5 | KB_PME_EN | R/W | 0 | Keyboard PME event enable. 0: disable keyboard PME event. 1: enable keyboard PME event. |
| 4 | HM_PME_EN | R/W | 0 | Hardware monitor PME event enable. 0: disable hardware monitor PME event. 1: enable hardware monitor PME event. |
| 3 | PRT_PME_EN | R/W | 0 | Parallel port PME event enable. 0: disable parallel port PME event. 1: enable parallel port PME event. |
| 2 | UR2_PME_EN | R/W | 0 | UART 2 PME event enable. 0: disable UART 2 PME event. 1: enable UART 2 PME event. |
| 1 | UR1_PME_EN | R/W | 0 | UART 1 PME event enable. 0: disable UART 1 PME event. 1: enable UART 1 PME event. |
| 0 | Reserved | R/W | 0 | Reserved. |

F71889E

PME Event Status 1 Register — Index F1h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7 | Reserved | - | - | Reserved |
| 6 | MO_PME_ST | R/W | - | Mouse PME event status. 0: Mouse has no PME event. 1: Mouse has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 5 | KB_PME_ST | R/W | - | Keyboard PME event status. 0: Keyboard has no PME event. 1: Keyboard has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 4 | HM_PME_ST | R/W | - | Hardware monitors PME event status. 0: Hardware monitor has no PME event. 1: Hardware monitor has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 3 | PRT_PME_ST | R/W | - | Parallel port PME event status. 0: Parallel port has no PME event. 1: Parallel port has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 2 | UR2_PME_ST | R/W | - | UART 2 PME event status. 0: UART 2 has no PME event. 1: UART 2 has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 1 | UR1_PME_ST | R/W | - | UART 1 PME event status. 0: UART 1 has no PME event. 1: UART 1 has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 0 | Reserved | R/W | - | Reserved |

PME Event Enable 2 Register — Index F2h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|---|
| 7-3 | Reserved | - | - | Reserved |
| 2 | RI2_PME_EN | R/W | 0 | RI2# PME event enable. 0: disable RI2# PME event. 1: enable RI2# PME event. |
| 1 | RI1_PME_EN | R/W | 0 | RI1# PME event enable. 0: disable RI2# PME event. 1: enable RI2# PME event. |
| 0 | Reserved | R/W | 0 | Reserved. |

PME Event Status 2 Register — Index F3h

| Bit | Name | R/W | Default | Description |
|-----|------------|-----|---------|--|
| 7-4 | Reserved | - | - | Reserved |
| 3 | EUP_PME_ST | R/W | - | EUP PME event status. 0: EUP has no PME event. 1: EUP has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 2 | RI2_PME_ST | R/W | - | RI2# PME event status. 0: RI2# has no PME event. 1: RI2# has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 1 | RI1_PME_ST | R/W | - | RI1# PME event status. 0: RI1# has no PME event. 1: RI1# has a PME event to assert. Write 1 to clear to be ready for next PME event. |
| 0 | Reserved | R/W | - | Reserved |

ACPI Control Register 1 — Index F4h

| Bit | Name | R/W | Default | Description |
|-----|-----------------|-----|---------|--|
| 7 | Reserved | R/W | 0 | Reserved |
| 6 | Reserved | R/W | 0 | Dummy for future use. |
| 5 | DUAL_GATE_S5_ON | R/W | 1 | 0: DUAL_GATE_N tri-state in S5 state. 1: DUAL_GATE_N output low in S5 state. |
| 4 | EN_KBWAKEUP | R/W | 0 | Set one to enable keyboard wakeup event asserted via PWSOUT#. |
| 3 | EN_MOWAKEUP | R/W | 0 | Set one to enable mouse wakeup event asserted via PWSOUT#. |
| 2-1 | PWRCTRL | R/W | 11 | The ACPI Control the PSON_N to always on or always off or keep last state 00 : keep last state 10 : Always on 01 : Always on without PSOUT# 11: Always off |
| 0 | VSB_PWR_LOSS | R/W | 0 | When VSB 3V comes, it will set to 1, and write 1 to clear it |

ACPI Control Register 2 — Index F5h

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|--|
| 7 | Reserved | R/W | 0 | Dummy for future use. |
| 6-5 | PWROK_DELAY | R/W | 0 | The additional PWROK delay. 00: no delay 01: 100ms. 10: 200ms 11: 400ms. |

F71889E

| | | | | |
|-----|--------------|-----|----|---|
| 4-3 | VDD_DELAY | R/W | 00 | The PWROK delay timing from VDD3VOK by followed setting 00 : 100ms 01 : 200ms 10 : 300ms 11 : 400ms |
| 2 | VINDB_EN | R/W | 1 | Enable the PCIRSTIN_N and ATXPWGD de-bounce. |
| 1 | PCIRST_DB_EN | R/W | 0 | Enable the LRESET_N de-bounce. |
| 0 | Reserved | R/W | 0 | Dummy register. |

ACPI Control Register 3 — Index F6h

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|---|
| 7 | S3_SEL | R/W | 0 | Select the KBC S3 state. 0: Enter S3 state when internal VDD3VOK signal de-asserted. 1: Enter S3 state when S3# is low or the TS3 register is set to 1. |
| 6 | Reserved | - | - | Reserved. |
| 5 | WDT_RST_EN | R/W | 0 | 0: Disable WDT time out reset signal 1: Enable WDT time out reset signal output form PWROK. |
| 4 | PSON_DEL_EN | R/W | 0 | 0: PSON# is the inverted of S3# signal. 1: PSON# will sink low only if the time after the last turn-off elapse at least 4 seconds. |
| 3 | VREF_S3_RST_EN | R/W | 0 | 0: The VREF output value programmed by user will keep in S3/S5 state. 1: The VREF output value will be reset to default (64h) when enter S3/S5 state. |
| 2 | PCIRST3_GATE | R/W | 1 | Write "0" to this bit will force PCIRST3# to sink low. |
| 1 | PCIRST2_GATE | R/W | 1 | Write "0" to this bit will force PCIRST2# to sink low. |
| 0 | PCIRST1_GATE | R/W | 1 | Write "0" to this bit will force PCIRST1# to sink low. |

ACPI Control Register 4 — Index F7h

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|--|
| 7 | USBEN_DS5_ST | R/W | 0 | USBEN deep output value in deep s5 state. |
| 6 | USBEN_S5_ST | R/W | 0 | USBEN deep output value in s5 state. |
| 5 | Reserved | - | - | Reserved |
| 4 | USBEN_S3_ST | R/W | 1 | USBEN deep output value in s3 state. |
| 3-2 | Reserved | R/W | - | Reserved |
| 1-0 | VCC_GATE_DELAY | R/W | 00 | VCCGATE# will be low when S3# is high, VCC3V is power on and VCC5V is power on. This register define the delay time from the condition is ready: 00: 10ms 01: 50ms 10: 100ms 11: 200ms |

RI De-bounce Select Register — Index FEh

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|---|
| 7-2 | Reserved | - | - | Reserved |
| 1-0 | RI_DB_SEL | R/W | 0 | Select RI de-bounce time. 00: reserved. 01: 200us. 10: 2ms. 11: 20ms. |

EUP Enable Register — Index E0h

| Bit | Name | R/W | Default | Description |
|-----|-----------------|-----|---------|--|
| 7 | EUP_EN | R/W | 0 | 0 : disable EUP function 1: enable EUP function |
| 6-4 | Reserved | - | - | Reserved |
| 3 | EVENT1_PME_EN | R/W | 0 | EVENT1 PME event enable. 0: disable EVENT1 PME event. 1: enable EVENT1 PME event, when RING1 falling edge detect |
| 2 | EVENT1_PSOUT_EN | R/W | 0 | EVENT1 PSOUT event enable. 0: disable EVENT1 PSOUT event. 1: enable EVENT1 PSOUT event, when RING2 falling edge detect |
| 1 | EVENT0_PME_EN | R/W | 0 | EVENT0 PME event enable. 0: disable EVENT0 PME event. 1: enable EVENT0 PME event, when RING1 falling edge detect |
| 0 | EVENT0_PSOUT_EN | R/W | 0 | EVENT0 PSOUT event enable. 0: disable EVENT0 PSOUT event. 1: enable EVENT0 PSOUT event, when RING1 falling edge detect |

EUP control register — Index E1h

| Bit | Name | R/W | Default | Description |
|-----|---------------|-----|---------|---|
| 7-6 | Boot_Mode | R/W | 11 | Write these two bits to select Boot Mode for Always Off/ Always On/ Keep Last State. 00:Default Always Off 11:Support Always On and Keep Last State 10:Reserved 01:Reserved |
| 5 | S3_CTRL_1_DIS | R/W | 0 | If clear to "0" CTRL_1 will output Low when S3 state. Else If set to "1" CTRL_1 will output High when S3 state. |
| 4 | S3_CTRL_0_DIS | R/W | 0 | If clear to "0" CTRL_0 will output Low when S3 state. Else If set to "1" CTRL_0 will output High when S3 state. |
| 3 | S5_CTRL_1_DIS | R/W | 1 | If clear to "0" CTRL_1 will output Low when S5 state. Else If set to "1" CTRL_1 will output High when S5 state. |
| 2 | S5_CTRL_0_DIS | R/W | 1 | If clear to "0" CTRL_0 will output Low when S5 state. Else If set to "1" CTRL_0 will output High when S5 state. |

F71889E

| | | | | |
|---|---------------|-----|---|---|
| 1 | AC_CTRL_1_DIS | R/W | 0 | If clear to "0" CTRL_1 will output Low when after AC lost. Else If set to "1" CTRL_1 will output High when after AC lost. |
| 0 | AC_CTRL_0_DIS | R/W | 0 | If clear to "0" CTRL_0 will output Low when after AC lost. Else If set to "1" CTRL_0 will output High when after AC lost. |

EUP control register — Index E2h

| Bit | Name | R/W | Default | Description |
|-----|-----------------|------|---------|---|
| 7 | AC_LOST | R/WC | - | "1" indicates an AC lost occurs. Write "1" to clear. |
| 6 | Reserved | - | - | Reserved. |
| 5 | VSB_CTRL_EN[1] | R/W | 1'b0 | 0: disable EUP_CTRL2 assert RSMRST low 1: enable EUP_CTRL 2 assert RSMRST low |
| 4 | VSB_CTRL_EN[0] | R/W | 1'b0 | 0: disable EUP_CTRL1 assert RSMRST low 1: enable EUP_CTRL1 assert RSMRST low |
| 3 | S5_DET_S5# | R/W | 1 | Device into S5 state will check S5# signal and VCC_IN pin status, but when user clear this bit to 0. Device into S5 state will not check S5# become low. |
| 2 | S5_DET_VCC | R/W | 1 | Device into S5 state will check S5# signal and VCC_IN pin status, but when user clear this bit to 0. Device into S5 state will not check VCC_IN become low. |
| 1 | Reserved | - | - | Reserved |
| 0 | RSMRST_DET_3V_N | R/W | 0 | Device detects VSB5V power ok (4.4V) and VSB3V_IN become high, and after 60ms de-bounce time RSMRST will become high. But when user set this bit to 1. RSMRST will not check VSB3V_IN pin status. |

EUP PSIN deb-register — Index E3h

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|--|
| 7-0 | PS_DEB_TIME | R/W | 0x13 | PS_IN pin input de-bounce time: the unit of this register is 1ms, default is 20ms. |

EUP RSMRST deb-register — Index E4h

| Bit | Name | R/W | Default | Description |
|-----|-----------------|-----|---------|--|
| 7-0 | RSMRST_DEB_TIME | R/W | 0x09 | RSMRST internal de-bounce time: the unit of this register is 1ms, default is 10ms. |

EUP PSOUT deb-register — Index E5h

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|--|
| 7-0 | PS_OUT_PULSE_W | R/W | 0xC7 | PS_OUT_OUT output Pulse width: the unit of this register is 1ms , default is 200ms low pulse |

EUP PSON deb-register — Index E6h

| Bit | Name | R/W | Default | Description |
|-----|----------------|-----|---------|--|
| 7-0 | PS_ON_DEB_TIME | R/W | 0x09 | PSON_IN pin input de-bounce time: the unit of this register is 1ms, default is 10ms. |

EUP S5 deb-register — Index E7h

| Bit | Name | R/W | Default | Description |
|-----|-------------|-----|---------|---|
| 7-0 | S5_DEB_TIME | R/W | 0x63 | S5# pin input de-bounce time The unit of this register is 64ms, default is 6.4s. |

EuP Wakeup Event Enable Register — Index E8h

| Bit | Name | R/W | Default | Description |
|-----|-----------------|-----|---------|---|
| 7 | RI2_WAKEUP_EN | R/W | 0 | Enable RI2# PME event to wakeup. |
| 6 | Revered | - | - | Reserved. |
| 5 | RI1_WAKEUP_EN | R/W | 0 | Enable RI1# PME event to wakeup. |
| 4 | EVENT_WAKEUP_EN | R/W | 1 | Enable EVENT_IN# event to wakeup. |
| 3 | Revered | - | - | Reserved. |
| 2 | TMOUT_WAKEUP_EN | R/W | 0 | Enable EuP Watchdog Timer timeout event to wakeup. See index EDh and EEh. |
| 1 | MO_WAKEUP_EN | R/W | 0 | Enable Mouse PME event to wakeup. |
| 0 | KB_WAKEUP_EN | R/W | 0 | Enable Keyboard PME event to wakeup. |

EuP Watchdog Control Register — Index EDh

| Bit | Name | R/W | Default | Description |
|-----|----------|------|---------|---|
| 7-5 | Revered | - | - | Reserved. |
| 4 | WD_TMOUT | R/WC | 0 | EuP watchdog timer timeout status. Write 1 to clear. |
| 3-2 | Revered | - | - | Reserved. |
| 1 | WD_UNIT | R/W | 0 | 0: unit of WD_TIME is 1 sec. 1: unit of WD_TIME is 1 minute. |
| 0 | WD_EN | R/W | 0 | Enable EuP watchdog timer. |

EuP Watchdog Time Register — Index EEh

| Bit | Name | R/W | Default | Description |
|-----|---------|-----|---------|--|
| 7-0 | WD_TIME | R/W | 0 | EuP watchdog timer count time register. Start to count down when WD_EN is set. When reaching 0, WD_EN will auto clear and WD_TMOUT is set. A wakeup event will assert if enabled |

8.10 VREF Control Registers (CR0B)
VREF3 Output Value — Index F0h

| Bit | Name | R/W | Default | Description |
|-----|---------|-----|---------|-----------------------------------|
| 7-0 | VREF3_H | R/W | 8'h64 | The bit8-1 of VREF3 output value. |

VREF2 Output Value — Index F1h

| Bit | Name | R/W | Default | Description |
|-----|---------|-----|---------|-----------------------------------|
| 7-0 | VREF2_H | R/W | 8'h64 | The bit8-1 of VREF2 output value. |

VREF1 Output Value — Index F2h

| Bit | Name | R/W | Default | Description |
|-----|---------|-----|---------|-----------------------------------|
| 7-0 | VREF1_H | R/W | 8'h64 | The bit8-1 of VREF1 output value. |

Voltage LSB — Index F3h

| Bit | Name | R/W | Default | Description |
|-----|----------|-----|---------|---------------------------------|
| 7-3 | Reserved | R/W | - | Reserved. |
| 2 | VREF1_L | R/W | 0 | The bit0 of VREF1 output value. |
| 1 | VREF2_L | R/W | 0 | The bit0 of VREF2 output value. |
| 0 | VREF3_L | R/W | 0 | The bit0 of VREF3 output value. |

WDT Reset Enable — Index FFh

| Bit | Name | R/W | Default | Description |
|-----|-----------|-----|---------|--|
| 7-1 | Reserved. | - | - | Reserved. |
| 0 | WD_RST_EN | R/W | 0 | 0: disable the WDT reset function. 1: VREF1~3 will be reset to default if WDT timeout occurs. |

9. Electrical Characteristics

Absolute Maximum Ratings

| PARAMETER | RATING | UNIT |
|-----------------------|-----------------|------|
| Power Supply Voltage | -0.5 to 5.5 | V |
| Input Voltage | -0.5 to VDD+0.5 | V |
| Operating Temperature | 0 to 70 | °C |
| Storage Temperature | -55 to 150 | °C |

Note: Exposure to conditions beyond those listed under Absolute Maximum Ratings may adversely affect the life and reliability of the device

All ACPI timing accuracy is $\pm 20\%$.

DC Characteristics

($T_a = 0^\circ\text{C}$ to 70°C , $V_{DD} = 3.3\text{V} \pm 10\%$, $V_{SS} = 0\text{V}$) (Note)

| Parameter | Conditions | MIN | TYP | MAX | Unit |
|----------------------------------|--|-----|--------------------|--------------------|------|
| Temperature Error, Remote Diode | $60^\circ\text{C} < T_D < 100^\circ\text{C}$, $V_{CC} = 3.0\text{V}$ to 3.6V $-40^\circ\text{C} < T_D < 60^\circ\text{C}$ $100^\circ\text{C} < T_D < 127^\circ\text{C}$ | | ± 1 ± 1 | ± 3 ± 3 | °C |
| Supply Voltage range | | 3.0 | 3.3 | 3.6 | V |
| Average operating supply current | | | 10 | | mA |
| Standby supply current | | | 5 | | uA |
| VBAT Current | | | 1 | | uA |
| Resolution | | | 1 | | °C |
| Power on reset threshold | | | 2.2 | 2.4 | V |
| Diode source current | High Level | | 95 | | uA |
| | Low Level | | 10 | | uA |

| PARAMETER | SYM. | MIN. | TYP. | MAX. | UNIT | CONDITIONS |
|---|------|------|------|------|------|-------------|
| I/O_{12st,5v}-TTL level bi-directional pin with schmitt trigger, output with 12 mA sink capability, 5V tolerance. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Output Low Current | IOL | | +12 | | mA | VOL = 0.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0V |
| I/OOD_{12t}-TTL level bi-directional pin, Output pin with 12mA source-sink capability, and can programming to open-drain function. | | | | | | |
| Input Low Threshold Voltage | Vt- | | | 0.8 | V | VDD = 3.3 V |
| Input High Threshold Voltage | Vt+ | 2.0 | | | V | VDD = 3.3 V |
| Output Low Current | IOL | | -12 | -9 | mA | VOL = 0.4 V |
| Output High Current | IOH | +9 | +12 | | mA | VOH = 2.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0V |
| I/OOD_{18t}-TTL level bi-directional pin, Output pin with 18mA source-sink capability, and can programming to open-drain function. | | | | | | |
| Input Low Threshold Voltage | Vt- | | | 0.8 | V | VDD = 3.3 V |
| Input High Threshold Voltage | Vt+ | 2.0 | | | V | VDD = 3.3 V |

F71889E

| | | | | | | |
|---|------|-----|-----|-----|----|-------------|
| Output Low Current | IOL | | -18 | | mA | VOL = 0.4 V |
| Output High Current | IOH | | +18 | | mA | VOH = 2.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0V |
| I/OOD_{12,5v}-TTL level bi-directional pin, Output pin with 12mA source-sink capability, and can programming to open-drain function, 5v tolerance. | | | | | | |
| Input Low Threshold Voltage | Vt- | | | 0.8 | V | VDD = 3.3 V |
| Input High Threshold Voltage | Vt+ | 2.0 | | | V | VDD = 3.3 V |
| Output Low Current | IOL | | -12 | -9 | mA | VOL = 0.4 V |
| Output High Current | IOH | +9 | +12 | | mA | VOH = 2.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0V |
| I/O_{14t}-TTL level bi-directional pin, Open-drain output with 14 mA sink capability. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Output Low Current | IOL | | -14 | | mA | VOL = 0.4 V |
| I/O_{16t}- TTL level bi-directional pin, Output pin with 16mA source-sink capability. | | | | | | |
| Input Low Threshold Voltage | Vt- | | | 0.6 | V | VDD = 3.3 V |
| Input High Threshold Voltage | Vt+ | 0.9 | | | V | VDD = 3.3 V |
| Output High Current | IOH | | +16 | | mA | VOH = 2.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = 1.2V |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0V |
| IN_{st} - TTL level input pin with schmitt trigger | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| IN_{t,5v} - TTL level input pin with 5V tolerance. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| IN_{st,5v} - TTL level input pin with schmitt trigger, 5V tolerance. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| IN_{st,lv} - TTL level input pin with schmitt trigger, low level. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| OD₁₂-Open-drain output with 12 mA sink capability. | | | | | | |
| Output Low Current | IOL | | -12 | | mA | VOL = 0.4V |
| OD_{12,5v}-Open-drain output with 12 mA sink capability, 5V tolerance. | | | | | | |
| Output Low Current | IOL | | -12 | | mA | VOL = 0.4V |
| OD_{16,u10,5v}-Open-drain output with 16 mA sink capability, pull-up 10k ohms, 5V tolerance. | | | | | | |
| Output Low Current | IOL | | -16 | | mA | VOL = 0.4V |
| O_{8,u47,5v}- Output pin with 8 mA source-sink capability, pull-up 47k ohms, 5V tolerance. | | | | | | |
| Output High Current | IOH | +6 | +8 | | mA | VOH = 2.4V |
| O₁₂- Output pin with 12 mA source-sink capability. | | | | | | |
| Output High Current | IOH | +9 | +12 | | mA | VOH = 2.4V |
| O₁₆- Output pin with 16 mA source-sink capability. | | | | | | |

F71889E

| | | | | | | |
|---|------|-----|-----|-----|----|------------|
| Output High Current | IOH | | +16 | | mA | VOH = 2.4V |
| O₁₈- Output pin with 18 mA source-sink capability. | | | | | | |
| Output High Current | IOH | | +18 | | mA | VOH = 2.4V |
| O₂₄- Output pin with 24 mA source-sink capability. | | | | | | |
| Output High Current | IOH | | +24 | | mA | VOH = 2.4V |
| O₁₄- Output pin with 14 mA source-sink capability. | | | | | | |
| Output High Current | IOH | | +14 | | mA | VOH = 2.4V |
| O₃₀- Output pin with 30 mA source-sink capability. | | | | | | |
| Output High Current | IOH | +26 | +30 | | mA | VOH = 2.4V |
| I/O_{S1, D8, st, lv} - Low level bi-directional pin (VIH → 0.9V, VIL → 0.6V.) with schmitt trigger. Output with 8mA drive and 1mA sink capability. | | | | | | |
| Input Low Voltage | VIL | | | 0.6 | V | |
| Input High Voltage | VIH | 0.9 | | | V | |
| Output High Current | IOH | | +8 | | mA | VOH = 1.0V |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| I/O_{D8, st, lv} - Low level bi-directional pin (VIH → 0.9V, VIL → 0.6V.) with schmitt trigger. Output with 8mA drive | | | | | | |
| Input Low Voltage | VIL | | | 0.6 | V | |
| Input High Voltage | VIH | 0.9 | | | V | |
| Output High Current | IOH | | +8 | | mA | VOH = 1.0V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| I/OD_{12st,lv} - Low level bi-directional pin with schmitt trigger. Open-drain output with 12mA sink capability. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Output Low Current | IOL | | -12 | | mA | VOH = 0.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| I/OOD_{12st,lv} - Low level bi-directional pin with schmitt trigger, can select to OD or OUT by register, with 12 mA source-sink capability. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Output Low Current | IOL | | -12 | | mA | VOH = 0.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0 V |
| I/OD_{12st,5v}-TTL level bi-directional pin with schmitt trigger, Open-drain output with 12 mA sink capability, 5V tolerance. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Output Low Current | IOL | | +12 | | mA | VOL = 0.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0V |
| I/OD_{16st,5v}-TTL level bi-directional pin with schmitt trigger, Open-drain output with 16 mA sink capability, 5V tolerance. | | | | | | |
| Input Low Voltage | VIL | | | 0.8 | V | |
| Input High Voltage | VIH | 2.0 | | | V | |
| Output Low Current | IOL | | +16 | | mA | VOL = 0.4V |
| Input High Leakage | ILIH | | | +1 | μA | VIN = VDD |
| Input Low Leakage | ILIL | -1 | | | μA | VIN = 0V |

10. Ordering Information

| Part Number | Package Type | Production Flow |
|-------------|------------------------|--------------------------|
| F71889ED | 128-LQFP Green Package | Commercial, 0°C to +70°C |







Fintek
 F71889ED
 XXXXLAA
 ● XXXXXX.X

Version Identification:
 An example for LAA version:
 The version shows on **RED** area. Ex: LAA

11. Package Dimensions

128 LQFP (14*14)


 SECTION G-G
SCALE: 100/1

 DETAIL F
SCALE: 20/1

| | SYMBOL | MIN | NOM | MAX |
|------------------------|--------|-----------|---------|------|
| TOTAL THICKNESS | A | --- | --- | 1.6 |
| STAND OFF | A1 | 0.05 | --- | 0.15 |
| MOLD THICKNESS | A2 | 1.35 | 1.4 | 1.45 |
| LEAD WIDTH(PLATING) | b | 0.13 | 0.16 | 0.23 |
| LEAD WIDTH | b1 | 0.13 | --- | 0.19 |
| L/F THICKNESS(PLATING) | c | 0.09 | --- | 0.2 |
| L/F THICKNESS | c1 | 0.09 | --- | 0.16 |
| BODY SIZE | X | D 16 BSC | | |
| | Y | E 16 BSC | | |
| LEAD PITCH | X | D1 14 BSC | | |
| | Y | E1 14 BSC | | |
| FOOTPRINT | e | | 0.4 BSC | |
| | L | 0.45 | 0.6 | 0.75 |
| | L1 | 1 REF | | |
| PACKAGE EDGE TOLERANCE | θ | 0° | 3.5° | 7° |
| | θ1 | 0° | --- | --- |
| | θ2 | 11° | 12° | 13° |
| | θ3 | 11° | 12° | 13° |
| LEAD EDGE TOLERANCE | R1 | 0.08 | --- | --- |
| | R2 | 0.08 | --- | 0.2 |
| COPLANARITY | S | 0.2 | --- | --- |
| LEAD OFFSET | ddd | 0.07 | | |
| MOLD FLATNESS | eee | 0.05 | | |

Headquarters

3F-7, No 36, Tai Yuan St.,
 Chupei City, Hsinchu, Taiwan 302, R.O.C.
 TEL : 886-3-5600168
 FAX : 886-3-5600166







www: <http://www.fintek.com.tw>

Taipei Office






Bldg. K4, 7F, No.700, Chung Cheng Rd.,
 Chungho City, Taipei, Taiwan 235, R.O.C.
 TEL : 866-2-8227-8027
 FAX : 866-2-8227-8037

Please note that all datasheet and specifications are subject to change without notice. All the trade marks of products and companies mentioned in this datasheet belong to their respective owner



12.Application Circuit



| | | |
|-------------------------------------|---------------------------|--------------|
| Title | | |
| Feature Integration Technology Inc. | | |
| Size | Document Number | Rev |
| B | F71889 | <Rev Code> |
| Date: | Friday, November 06, 2009 | Sheet 1 of 6 |









| | | |
|-------------------------------------|---------------------------|--------------|
| File | | |
| Feature Intergration Technology Inc | | |
| Size | Document Number | Rev |
| Custom | UART_Ps2_IR | 0.1 |
| Date: | Tuesday, October 13, 2009 | Sheet 2 of 6 |








FAN CONTROL FOR PWM OR DC







| | | |
|-------------------------------------|----------------------------|--------------|
| Title | | |
| Feature Integration Technology Inc. | | |
| Size | Document Number | Rev |
| B | FAN Control | 0.1 |
| Date: | Wednesday, August 13, 2008 | Sheet 3 of 6 |




| | | | | | |
|-------|----------------------------|-------|-------------------------------------|----|------------|
| Title | | | Feature Integration Technology Inc. | | |
| Size | Document Number | | | | Rev |
| B | Hardware Monitor | | | | <Rev Code> |
| Date: | Thursday, October 01, 2009 | Sheet | 4 | of | 6 |




| | | | |
|------|-------------------------------------|-------------------|--------|
| Rev | Feature Integration Technology Inc. | Rev | |
| Doc | Document Number | VID/PKIN/TER PORT | |
| Date | Wednesday, August 13, 2008 | Sheet | 5 of 6 |



| | | | |
|-------|---------------------------|-------------------------------------|-----------------------|
| Title | | Feature Integration Technology Inc. | |
| Size | B | Document Number | AMDSI/SST/PECl/80PORT |
| Date: | Tuesday, October 13, 2009 | Sheet | 6 of 6 |
| Rev | <Rev Code> | | |



| | | |
|---------|------------------------------|--------------|
| Title | | |
| <Title> | | |
| Size | Document Number | Rev |
| A | <Doc> | <Rev Code> |
| Date: | Thursday, September 17, 2009 | Sheet 1 of 1 |



| | | |
|-------------------------------------|-------------------------|--------------|
| Title | | |
| Feature Integration Technology Inc. | | |
| Size | Document Number | Rev |
| B | ACPI SAMPLE | <Rev Code> |
| Date: | Friday, August 14, 2009 | Sheet 1 of 7 |