



## **IT8712F**

**Environment Control – Low Pin Count Input / Output  
(EC-LPC I/O)**

***Preliminary SCR Programming Guide V0.2***



Notice: The information provided in this publication is believed to be accurate. Integrated circuits sold by ITE are covered by the warranty and patent indemnification provisions stipulated in the terms ITE Terms and Conditions of Sale, as revised from time to time. ITE makes no warranty, expressed, statutory, implied, or by description, regarding the information in this publication or regarding the freedom of the described chip(s) from patent infringement, except as specifically provided in the ITE Terms and Conditions of Sale. Furthermore, ITE makes no warranty of merchantability or fitness for any purpose. ITE reserves the right to halt production or modify specifications and prices at any time without notice. Accordingly, the reader is cautioned to verify that the specification and other information included in this publication is current before placing product orders.

Products described herein are intended for use in normal commercial applications. Applications involving unusual environment or reliability requirements (e.g., military equipment or medical life-support equipment) are specifically not recommended without additional processing by ITE for such applications. All trademarks are the sole property of their respective owners.

To find out more about ITE, visit our World Wide Web site at:

<http://www.ite.com.tw>

<http://www.iteusa.com>

Copyright © ITE, Inc. 2001

THE TERMS AND CONDITIONS IN THE BACK OF THIS DOCUMENTATION GOVERN ALL SALES BY ITE. ITE WILL NOT BE BOUND BY ANY TERMS INCONSISTENT WITH THESE UNLESS ITE AGREES OTHERWISE IN WRITING. ACCEPTANCE OF BUYERS ORDER SHALL BE BASED ON THESE TERMS.



**Revision History**

Section	Revision	Page No.
2	<ul style="list-style-type: none"><li>• Figure 2-1. IT8712F Smart Card Reader Flow Chart was revised.</li></ul>	7

**Contents**

- 1. Smart Card Reader ..... 1
  - 1.1 Features ..... 1
  - 1.2 Operation ..... 1
  - 1.3 Connection of IFD to ICC Socket ..... 1
  - 1.4 Baud Rate Relationship Between UART and Smart Card Interface ..... 2
  - 1.5 Waveform Relationship ..... 2
  - 1.6 Clock Divider ..... 3
  - 1.7 Waveform Example of Activation/Deactivation Sequence ..... 3
  - 1.8 ATR and PTS Structure ..... 4
  - 1.9 Smart Card Operating Sequence Example ..... 5
- 2. Flow Chart for IT8712 Smart Card Reader ..... 7
- 3. Serial Port Configuration Registers ..... 9
  - 3.1 Serial Port Activate (Index=30h, Default=00h) ..... 9
  - 3.2 Serial Port Base Address MSB Register (Index=60h) ..... 9
  - 3.3 Serial Port Base Address LSB Register (Index=61h) ..... 9
  - 3.4 Serial Port Interrupt Level Select (Index=70h, Default=04h) ..... 9
  - 3.5 Serial Port Special Configuration Register 1 (Index=F0h, Default=00h) ..... 10
  - 3.6 Serial Port Special Configuration Register 2 (Index=F1h, Default=50h) ..... 10
  - 3.7 Serial Port Special Configuration Register 3 (Index=F2h, Default=00h) ..... 10
  - 3.8 Serial Port Special Configuration Register 4 (Index=F3h, Default=7Fh) ..... 11
  - 3.9 Serial Port Register Description ..... 11

**Figures**

- Figure 1-1. Smart Card Reader Application ..... 1
- Figure 1-2. 9600 Baud Rate Example ..... 2
- Figure 1-3. Waveform Example of IFD ..... 3
- Figure 2-1. IT8712F Smart Card Reader Flow Chart ..... 7

**Tables**

- Table 1-1. SCRCLK Selections ..... 3

## 1. Smart Card Reader

### 1.1 Features

As an IFD (InterFace Device) built in IT8712, the Smart Card Reader (SCR) includes a standard UART (Either Serial Port 1 or Serial Port 2 is set in SCR mode) to control Smart Card interface handshaking and then performs data transfers, and can be connected to smart card socket directly. The Smart Card is capable of providing secured storage facilities for sensitive personal information (such as Private keys, Account numbers, Passwords, Medical information, ... etc.). Then the SCR can be used for a broad range of applications in GSM, ID, pay TV, banking (refer to EMV96 Spec.), ... and so forth. It also provides a Smart Card clock divider for those ICC (Integrated Circuit Card) without internal clocks.

### 1.2 Operation

The SCR is a low-power consumption design. Whenever the IFD is inactive, the clock divider will turn off internal clocks even when the clock of IFD controlling / monitoring state machine is turned off to save power consumption. Also it could be waked up immediately when IC card is removed in case of emergency or when the FET control function is turned on/off.

The VCC power of IC card interface is powered from an external FET to protect the smart card interface. Also, the charge/discharge time for FET to reach 5V/0V is programmable, and FET performs automatically to meet ISO 7816 activation and deactivation sequences. The UART's modem control lines: DTR#, RTS# and DCD# are used for controlling FET on/off, Smart Card Reset signal and IC card insertion detection respectively. When an IC card is being inserted, it will switch the SCRPRE# (Smart Card Present Detect#) and then cause the DCD# signal to trigger an interrupt to the system. Then in the Smart Card interrupt service routine, the driver can assert the DTR# signal to power on the external FET (SCRPFET#) and the RTS# signal to control the Smart Card Reset signal (SCRRST). In the mean time, IT8712 will generate a proper clock frequency to allow the IC card using default serial transfer baud rate to send back an ATR (Answer-To-Reset) sequence. The interface signals are enabled after VCC reaches enough voltage level. Then transfer protocol may be negotiated to promote more efficient transfers. In the same way, when the IC card is removed in case of emergency or when the ICC processing is finished, the driver can de-assert the DTR# to turn off the FET power. But before the FET power-off and the reset, clock and data signals will be de-active, followed by a sufficient FET discharge time guaranteed to protect IC card and IFD.

### 1.3 Connection of IFD to ICC Socket




Figure 1-1. Smart Card Reader Application

## 1.4 Baud Rate Relationship Between UART and Smart Card Interface

To perform serial transfers correctly, the baud rate of UART must be set in ways similar to the ICC card.

- **Formula (Variation < 2%)**

$$\text{Baud Rate} = \frac{\text{UART } 24 \text{ MHz}}{13 \cdot 16 \cdot N} \gg \frac{\text{Smart Card } \text{SCRCLK} \cdot D}{F}$$

N = Divisor of UART, assigned by programming the DLM (Divisor Latch MSB) and DLL (Divisor Latch LSB).

F = Clock Rate Conversion Factor, default = 372.

D = Bit Rate Adjustment Factor, Default is 1.

SCRCLK duty cycle is 45%-55%.

- **ICC With Internal Clock**

ICC may use built-in internal clock, then the Baud rate is 9600 baud, just programming the Divisor Latch Registers of UART in the IT8712 for SCR IFD.

- **ICC Without Internal Clock**

Baud rate is SCRCLK/372 before negotiating, and SCRCLK is limited within 1 MHz - 5MHz. During the ATR sequence, the default F value (Clock Rate Conversion Factor) is 372, and the default D value (Bit Rate Adjustment Factor) is 1.

## 1.5 Waveform Relationship




Figure 1-2. 9600 Baud Rate Example

## 1.6 Clock Divider


The SCRCLK is generated as the selection of SCR\_CLKSEL1-0, which are determined in the S1 Special Configuration register 3 (LDN1\_F2h) or S2 Special Configuration register 3 (LDN2\_F2h).

**Table 1-1. SCRCLK Selections**

SCR_CLKSEL1-0	Selections
00	Stop
01	3.5 MHz
10	7.1 MHz
11	96 MHz / SCR DIV96M <sup>Note</sup>

Note: SCR DIV96M is determined by S1 Special Configuration Register 4 (LDN1\_F3h) or S2 Special Configuration Register 4 (LDN2\_F3h).

## 1.7 Waveform Example of Activation/Deactivation Sequence



**Figure 1-3. Waveform Example of IFD**

### • Activation Sequence

Refer to the waveform above. The SCR IFD in the IT8712 will make sure the IFD is in data receive mode (i.e. the SOUT from UART is high), and the RTS# should be programmed to high. The SCRCLK is then enabled to output to the IC card (which means that the IC card can count SCRCLK clock numbers to start ATR responses), the data transfer is then enabled, and the SCRRST is the inverse logic state of RTS#. Also, the operation procedure guarantees the correct activation sequence even if the driver cannot program the SCRCLK and SCRRST in the precise time points. In this way, the hardware meets the ICC specification.

- **ATR**

For the IC card with its own internal reset, its ATR begins within 400-40000 SCRCLK cycles. If no ATR is detected, the Smart Card IFD driver can then program the RTS# to low, and cause the SCRRST to high.

For some types of IC cards without internal reset signals, it will check out the SCRRST as active low reset, and begins its ATR within 400-40000 SCRCLK cycles from the time point of SCRRST rising edge.

The IT8712 does not support the type of IC Card that may send synchronous ATRs.

- **Deactivation and PTS Structure**

Whenever the IC card is removed or when the IFD driver intends to power off the SCR interface, the IFD will enter the deactivation sequence.


## 1.8 ATR and PTS Structure

The contents of the ATR (Answer-To-Reset) and PTS (Protocol-Type-Select) are defined in ISO/IEC 7816-X standards, which must be fully communicated by the ICC Resource manager, the ICC Service provider or the ICC application software.

After finalizing the coherent protocol, the SCR IFD enters the normal transfer mode. Since the SCRIO is the only data channel for both data transmit and receive as defined in the ICC Specification, the IT8712 can only support the half-duplex function. The SCRRST can be resent when a data transfer error occurs, and then the IFD driver will select a safer, lower-speed protocol to perform the data transfers again.

NOTE: ATR (Answer-To-Reset) is a string of characters returned from the card to the reader following the successful completion of the power-up sequence. The first byte of ATR should be "3Bh" or "3Fh".

## 1.9 Smart Card Operating Sequence Example





2. Flow Chart for IT8712 Smart Card Reader




Figure 2-1. IT8712F Smart Card Reader Flow Chart





## Serial Port Configuration Registers

### 3. Serial Port Configuration Registers

The IT8712F smart card reader can be set on serial port 1 and serial port 2. If users choose the serial port1, then LDN=01h, or serial port 2, LDN=02h.

#### 3.1 Serial Port Activate (Index=30h, Default=00h)

Bit	Description
7-1	Reserved
0	Serial Port Enable. 1: Enabled.      0: Disabled.

#### 3.2 Serial Port Base Address MSB Register (Index=60h)

Bit	Description
7-4	<b>Read only</b> as '0h" for Base Address[15:12].
3-0	<b>Read/write</b> , mapped as Base Address[11:8].

#### 3.3 Serial Port Base Address LSB Register (Index=61h)

Bit	Description
7-3	<b>Read/write</b> , mapped as Base Address[7:3].
2-0	<b>Read only</b> as '000b."

#### 3.4 Serial Port Interrupt Level Select (Index=70h)

Bit	Description
7-4	Reserved with default '0h."
3-0	Select the interrupt level <sup>Note</sup> for Serial Port 1.

**Note:** Interrupt level mapping

Fh-Dh: not valid

Ch: IRQ12

.

.

3h: IRQ3

2h: not valid

1h: IRQ1

0h: no interrupt selected

### 3.5 Serial Port Special Configuration Register 1 (Index=F0h, Default=00h)

Bit	Description
7	Reserved
6-4	Serial Port Mode <sup>Note</sup> 000: Standard (default) 001: IrDA 1.0 (HP SIR) 010: ASKIR 100: Smart Card Reader (SCR) else: Reserved
3	Reserved with default '0.'
2-1	Clock Source. 00: 24 MHz/13 (Standard) 01: 24 MHz/12 (MIDI) 10: Reserved 11: Reserved
0	1: IRQ sharing. 0: Normal.

**Note:** Except the standard mode, COM1 and COM2 cannot be selected in the same time mode.

### 3.6 Serial Port Special Configuration Register 2 (Index=F1h, Default=50h)

Bit	Description
7	1: No transmission delay (40 bits) when the SIR or ASKIR is switched from RX mode to TX mode. 0: Transmission delay (40 bits) when the SIR or ASKIR is switched from RX mode to TX mode.
6	1: No reception delay (40 bits) when the SIR or ASKIR is switched from TX mode to RX mode. 0: Reception delay (40 bits) when the SIR or ASKIR is switched from TX mode to RX mode.
5	Single Mask Mode: When set, the RX of UART is masked under TX transmission.
4	1: Half Duplex (default). 0: Full Duplex.
3-0	Reserved

### 3.7 Serial Port Special Configuration Register 3 (Index=F2h, Default=00h)

This register is valid only when Serial Port's Mode is Smart Card Reader.

Bit	Description
7-3	Reserved
2	SCRPFET# polarity.
1-0	SCR_CLKSEL1-0. 00: Stop 01: 3.5 MHz 10: 7.1 MHz <sub>j</sub> I 11: Special Divisor (96 MHz/DIV96M)



## Serial Port Configuration Registers

### 3.8 Serial Port Special Configuration Register 4 (Index=F3h, Default=7Fh)

This register is valid only when Serial Port's Mode is Smart Card Reader.

Bit	Description
7	Reserved
6-0	SCR DIV96M6-0.

### 3.9 Serial Port Register Description

Register	DLAB*	Address	READ	WRITE
Data	0	Base + 0h	RBR (Receiver Buffer Register)	TBR (Transmitter Buffer Register)
Control	0	Base + 1h	IER (Interrupt Enable Register)	IER
	x	Base + 2h	IIR (Interrupt Identification Register)	FCR (FIFO Control Register)
	x	Base + 3h	LCR (Line Control Register)	LCR
	x	Base + 4h	MCR (Modem Control Register)	MCR
	1	Base + 0h	DLL (Divisor Latch LSB)	DLL
	1	Base + 1h	DLM (Divisor Latch MSB)	DLM
Status	x	Base + 5h	LSR (Line Status Register)	LSR
	x	Base + 6h	MSR (Modem Status Register)	MSR
	x	Base + 7h	SCR (Scratch Pad Register)	SCR

\* DLAB is bit 7 of the Line Control Register.

## INTEGRATED TECHNOLOGY EXPRESS, INC. TERMS AND CONDITIONS OF SALE(Rev: May98)

These Terms and Conditions of Sale apply to all items designed, sold and/or made by Integrated Technology Express, Inc. ('ITE Taiwan') and/or Integrated Technology Express, Inc. ('ITE California'), and Buyer agrees they apply to all such items.

### 0. PARTIES

ITE Taiwan is a company headquartered in the Republic of China, Taiwan, and incorporated under Taiwan law, and ITE California is a separate company incorporated under California law and headquartered in California. These two companies are independent, and, except as to the entity which invoices for goods delivered to it, Buyer holds no rights against and has no commitments from ITE California and/or ITE Taiwan. Subject to the foregoing, "Seller" refers to the entity which invoices Buyer for product, provided however that both ITE Taiwan and ITE California shall each be entitled to claim protection under paragraphs 4(b)-4(f), 5, 8, 9, 10, 11, 12 and 13 below.

### 1. ACCEPTANCE OF TERMS

BUYER ACCEPTS THESE TERMS (i) BY WRITTEN ACCEPTANCE (BY PURCHASE ORDER OR OTHERWISE), OR (ii) BY FAILURE TO RETURN GOODS DESCRIBED ON THE FACE OF THE PACKING LIST WITHIN FIVE DAYS OF THEIR DELIVERY.

### 2. DELIVERY

(a) Delivery will be made Free Carrier (Incoterms), Seller's warehouse, Science-Based Industrial Park, Taiwan (if Seller is ITE Taiwan or ITE California) or Santa Clara, California (if Seller is ITE California).

(b) Title to the goods and the entire risk will pass to Buyer upon delivery to carrier.

(c) Shipments are subject to availability. Seller shall make every reasonable effort to meet the date(s) quoted or acknowledged; and if Seller makes such effort, Seller will not be liable for any delays.

### 3. TERMS OF PAYMENT

(a) Terms are as stated on Seller's quotation, or if none are stated, net thirty (30) days. Accounts past due will incur a monthly charge at the rate of one percent (1%) per month (or, if less, the maximum allowed by applicable law) to cover servicing costs.

(b) Seller reserves the right to change credit terms at any time in its sole discretion.

### 4. LIMITED WARRANTY

(a) Seller warrants that the goods sold will be free from defects in material and workmanship and comply with Seller's applicable published specifications for a period of ninety (90) days from the date of Seller's delivery.

(b) Goods or parts which have been subject to abuse (including without limitation repeated or extended exposure to conditions at or near the limits of applicable absolute ratings) misuse, accident, alteration, neglect, or unauthorized repair or improper application are not covered by any warranty. No warranty is made with respect to custom products or goods produced to Buyer's specifications (unless specifically stated in a writing signed by Seller).

(c) No warranty is made with respect to goods used in devices intended for use in applications where failure to perform when properly used can reasonably be expected to result in significant injury (including, without limitation, navigation, aviation or nuclear equipment, or for surgical implant or to support or sustain life) and Buyer agrees to indemnify, defend, and hold harmless Seller from all claims, damages and liabilities arising out of any such uses.

(d) This Paragraph 4 is the only warranty by Seller with respect to goods and may not be modified or amended except in writing signed by an authorized officer of Seller.

(e) Buyer acknowledges and agrees that it is not relying on any applications, diagrams or circuits contained in any literature, and Buyer will test all parts and applications under extended field and laboratory conditions. Notwithstanding any cross-reference or any statements of compatibility, functionality, interchangeability, and the like, the goods may differ from similar goods from other vendors in performance, function or operation, and in areas not contained in the written specifications, or as to ranges and conditions outside such specifications; and Buyer agrees that there are no warranties and that Seller is not responsible for such things.

(f) EXCEPT AS PROVIDED ABOVE, SELLER MAKES NO WARRANTIES OR CONDITIONS, EXPRESS, IMPLIED, OR STATUTORY; AND SELLER EXPRESSLY EXCLUDES AND DISCLAIMS ANY WARRANTY OR CONDITION OF MERCHANTABILITY OR FITNESS FOR PARTICULAR PURPOSE OR APPLICATION.

### 5. LIMITATION OF LIABILITY

(a) Seller will not be liable for any loss, damage or penalty resulting from causes beyond its reasonable control, including but not limited to delay by others, force majeure, acts of God, or labor conditions. In any such event, the date(s) for Seller's performance will be deemed extended for a period equal to any delay resulting.

(b) THE LIABILITY OF SELLER ARISING OUT OF THE CONTRACT OR ANY GOODS SOLD WILL BE LIMITED TO REFUND OF THE PURCHASE PRICE OR REPLACEMENT OF PURCHASED GOODS (RETURNED TO SELLER FREIGHT PRE-PAID) OR, WITH SELLER'S PRIOR WRITTEN CONSENT, REPAIR.

(c) Buyer will not return any goods without first obtaining a customer return order number.

(d) AS A SEPARATE LIMITATION, IN NO EVENT WILL SELLER BE LIABLE FOR COSTS OF SUBSTITUTE GOODS; FOR ANY SPECIAL, CONSEQUENTIAL, INCIDENTAL OR INDIRECT DAMAGES; OR LOSS OF USE, OPPORTUNITY, MARKET POTENTIAL, AND/OR PROFIT ON ANY THEORY (CONTRACT, TORT, FROM THIRD PARTY CLAIMS OR OTHERWISE). THESE LIMITATIONS SHALL APPLY NOTWITHSTANDING

### ANY FAILURE OF ESSENTIAL PURPOSE OF ANY REMEDY.

(e) No action against Seller, whether for breach, indemnification, contribution or otherwise, shall be commenced more than one year after the cause of action has accrued, or more than one year after either the Buyer, user or other person knew or with reasonable diligence should have known of the matter or of any claim of dissatisfaction or defect involved; and no such claim may be brought unless Seller has first been given commercially reasonable notice, a full written explanation of all pertinent details, and a good faith opportunity to resolve the matter.

(f) BUYER EXPRESSLY AGREES TO THE LIMITATIONS OF THIS PARAGRAPH 5 AND TO THEIR REASONABLENESS.

### 6. SUBSTITUTIONS AND MODIFICATIONS

Seller may at any time make substitutions for product ordered which do not materially and adversely affect overall performance with the then current specifications in the typical and intended use. Seller reserves the right to halt deliveries and shipments and alter specifications and prices without notice. Buyer shall verify that the literature and information is current before purchasing.

### 7. CANCELLATION

(a) The contract may not be canceled by Buyer except with written consent by Seller and Buyer's payment of reasonable cancellation charges (including but not be limited to expenses already incurred for labor and material, overhead, commitments made by Seller, and a reasonable profit).

(b) In no event will Buyer have rights in partially completed goods.

### 8. INDEMNIFICATION

Seller will, at its own expense, assist Buyer with technical support and information in connection with any claim that any parts as shipped by Seller under this purchase order infringe any valid and enforceable copyright, or trademark, provided however, that Buyer (i) gives immediate written notice to Seller, (ii) permits Seller to participate and to defend if Seller requests to do so, and (iii) gives Seller all needed information, assistance and authority. However, Seller will not be responsible for infringements resulting from anything not entirely manufactured by Seller, or from any combination with products, equipment, or materials not furnished by Seller. Seller will have no liability with respect to intellectual property matters arising out of products made to Buyer's specifications, code, or designs.

Except as expressly stated in this Paragraph 8 or in another writing signed by an authorized officer, Seller makes no representations and/or warranties with respect to intellectual and/or industrial property and/or with respect to claims of infringement. Except as to claims Seller agrees in writing to defend, BUYER WILL INDEMNIFY, DEFEND AND HOLD HARMLESS SELLER FROM ALL CLAIMS, COSTS, LOSSES, AND DAMAGES (INCLUDING ATTORNEYS FEES) AGAINST AND/OR ARISING OUT OF GOODS SOLD AND/OR SHIPPED HEREUNDER.

### 9. NO CONFIDENTIAL INFORMATION

Seller shall have no obligation to hold any information in confidence except as provided in a separate non-disclosure agreement signed by both parties.

### 10. ENTIRE AGREEMENT

(a) These terms and conditions are the entire agreement and the only representations and understandings between Seller and Buyer, and no addition, deletion or modification shall be binding on Seller unless expressly agreed to in a writing signed by an officer of Seller.

(b) Buyer is not relying upon any warranty or representation except for those specifically stated here.

### 11. APPLICABLE LAW

The contract and all performance and disputes arising out of or relating to goods involved will be governed where Seller is ITE Taiwan by the laws of Taiwan, Republic of China or, where Seller is ITE California, by the laws of California and the United States of America, in either event without reference to the U.N. Convention on Contracts for the International Sale of Goods or to conflict of laws principles. Buyer agrees at its sole expense to comply with all applicable laws in connection with the purchase, use or sale of the goods provided hereunder and to indemnify Seller from any failure by Buyer to so comply. Without limiting the foregoing, Buyer certifies that no technical data or direct products thereof will be made available or re-exported, directly or indirectly, to any country to which such export or access is prohibited or restricted under U.S. law or regulations, unless prior authorization is obtained from the appropriate officials and agencies of the government as required under U.S. laws and regulations.

### 12. JURISDICTION AND VENUE

Where Seller is ITE Taiwan, the courts located in Hsinchu, Taiwan, Republic of China, will have the sole and exclusive jurisdiction and venue over any dispute arising out of or relating to the contract or any sale of goods hereunder. Where Seller is ITE California, the courts located in Santa Clara County, California, USA, will have the sole and exclusive jurisdiction and venue over any dispute arising out of or relating to the contract or any sale of goods hereunder. Buyer hereby consents to the jurisdiction of such courts.

### 13. ATTORNEYS' FEES

Reasonable attorneys' fees and costs will be awarded to the prevailing party in the event of litigation involving and/or relating to the enforcement or interpretation of the contract and/or any goods sold under it.



**INTEGRATED TECHNOLOGY EXPRESS, INC.**

[www.ite.com.tw](http://www.ite.com.tw)

[www.iteusa.com](http://www.iteusa.com)

**HEADQUARTERS:** 3F, No. 13, Innovation Rd.1, Science-Based Industrial Park,  
Hsin-Chu, Taiwan 300, R.O.C.  
Tel: 886-3-5798658 Fax: 886-3-5794803

**ASIA SALES OFFICE:** 7F, No. 435, Nei Hu District, Jui Kuang Road, Taipei 114, Taiwan, R.O.C.  
Tel: 886-2-26579896 Fax: 886-2-26578561, 26578576  
**Contact Person:** P.Y. Chang  
**E-mail:** py.chang@ite.com.tw

**ITE (U.S.A. West) Inc.:** 1235 Midas Way, Sunnyvale, CA 94086, U.S.A.  
**Tel:** (408) 5308860 **Fax:** (408) 5308861  
**Contact Person:** David Lin  
**E-mail:** david.lin@iteusa.com

**ITE (U.S.A. Eastern) Inc.:** 896 Summit St., #105, Round Rock, TX 78664, U.S.A.  
**Tel:** (512) 3887880 **Fax:** (512) 3883108  
**Contact Person:** Don Gardenhire  
**E-mail:** don.gardenhire@iteusa.com