

STC TIME SPECTRUM - ASSY # 12-10057-XX

Switch Settings: SW-1

```
| | | | | | | | | | on |
| 1|2|3|4|5|6|7|8| | |
|_|_|_|_|_|_|_|_|_| off|          1=ON, 0=OFF
| | | | | | | | | |
| | | | | | | | | | _____ Parallel_Port
| | | | | | | | | | 1 = LPT1:, Primary Stand-alone Address (378h)
| | | | | | | | | | 0 = LPT2:, Secondary Stand-alone Address (278h)
| | | | | | | | | | Jumper E8-E9, IRQ7, for both addresses.
| | | | | | | | | |
| | | | | | | | | | _____ Clock/Calendar
| | | | | | | | | | 1 = Primary Address, 350h
| | | | | | | | | | 0 = Secondary Address, 250h
| | | | | | | | | |
| | | | | | | | | | _____ Serial_Port
| | | | | | | | | | 1 1 = Serial Port Not Installed, or Disabled
| | | | | | | | | | 1 0 = COM1:, Address 3F8h & Jumper E12-E13, IRQ4
| | | | | | | | | | 0 1 = COM2:, Address 2F8h & Jumper E11-E12, IRQ3
| | | | | | | | | | 1 1 = USE ONLY WITH OPTIONAL SECOND SERIAL ON
| | | | | | | | | | RAMPAK or COMPAK
| | | | | | | | | | Serial Port on STC is COM1:
| | | | | | | | | | Serial Port on Piggyback is COM2:
| | | | | | | | | | Install Jumpers E12-E13 & E14-E15
| | | | | | | | | |
| | | | | Memory_Starting_Address
0 0 0 0 64K
1 0 0 0 128K          (No Switches for Amount of Memory on STC.)
0 1 0 0 192K
1 1 0 0 256K          (Max memory on STC alone is 256KB, if optional
0 0 1 0 320K          RAMPAK added, max memory is 512KB.)
1 0 1 0 384K
0 1 1 0 448K
1 1 1 0 512K
0 0 0 1 576K
1 0 0 1 640K
```

The serial port is factory configured for DTE. To configure the port for DCE it may be best to leave the jumper block as is and configure the cable to specific needs.

DTE Jumpers: E29-E38
E30-E39
E31-E40
E32-E41
E33-E42
E34-E43

SCENARIO: You have upgraded your IBM PC1 with a new ROM BIOS or you have moved the STC Time Spectrum into an upgraded PC and now your system will not boot at all.

SOLUTION: You need a PLA upgrade for your Persyst Time Spectrum. Please contact Emulex Customer Service Department at (714) 662-5600 for the upgrade.

□