


# COMPU-SHACK PRODUCTION, GMBH CS-ETHERNET-KARTE COMBO PREMIUM

NIC Type: Ethernet  
 Transfer Rate: 10Mbps  
 Data Bus: 16-bit ISA  
 Topology: Linear Bus  
 Star  
 Wiring Type: RG58A/U 50ohm coaxial  
 Shielded/unshielded twisted pair  
 Boot ROM: Available



HARDWARE/SOFTWARE CONFIGURABLE SELECT	
Setting	J1
Card is software-configured	Open
Card is hardware (jumper) configured	Closed

BOOT ROM ADDRESS - J2						
Address	Jumper A	Jumper B	Jumper C	Jumper D	Jumper F	
Disabled	Open	Open	Open	Open	Closed	
C0000h	Open	Closed	Open	Open	Open	
C4000h	Closed	Closed	Open	Open	Open	
C8000h	Open	Open	Closed	Open	Open	
CC000h	Closed	Open	Closed	Open	Open	
D0000h	Open	Closed	Closed	Open	Open	
D4000h	Closed	Closed	Closed	Open	Open	
D8000h	Open	Open	Open	Closed	Open	
DC000h	Closed	Open	Open	Closed	Open	

Continued on next page. . .

COMPU-SHACK PRODUCTION, GMBH  
CS-ETHERNET-KARTE COMBO PREMIUM

... continued from previous page

I/O ADDRESS - J3			
Address	Jumper A	Jumper B	Jumper C
í 300h	Open	Open	Open
240h	Open	Closed	Open
280h	Closed	Closed	Open
2C0h	Open	Open	Closed
320h	Closed	Open	Closed
340h	Open	Closed	Closed
360h	Closed	Closed	Closed

INTERRUPT SELECT - J3			
IRQ	Jumper D	Jumper E	Jumper F
í IRQ3	Open	Open	Open
IRQ4	Closed	Open	Open
IRQ5	Open	Closed	Open
IRQ7	Closed	Closed	Open
IRQ9	Open	Open	Closed
IRQ11	Open	Closed	Closed
IRQ12	Closed	Closed	Closed

FAST-READ MODE	
Setting	J3/jumper G
í Disablec	Open
Enablec	Closed

NE2000/WD MODE SELECT	
Setting	J3/jumper H
í NE2000 mode	Open
WD mod	Closed

WIRING TYPE SELECT	
Setting	J4/jumper A
í BNC (coax il)	Closed
Shielded/unshielded twisted-pair	Open

TWISTED PAIR STATUS LED (D4)	
Setting	J4/jumper C
í Disablec	Open
Enablec	Closed

Continued on next page...

COMPU-SHACK PRODUCTION, GMBH  
CS-ETHERNET-KARTE COMBO PREMIUM

... continued from previous page

IOCS16 SIGNAL	
Setting	J4/jumper D
í Disablec	Open
Enablec	Closed

IOCHRDY SIGNAL	
Setting	J4/jumper E
í Disablec	Open
Enablec	Closed

BNC-TYPE - J8			
Setting	Jumper A	Jumper B	Jumper C
í RG58A U 50ohm coaxial	All pins open	'ins 2 & 3 closed	'ins 2 & 3 closed
RG62A U 93ohm coaxial	All pins open	'ins 1 & 2 closed	'ins 1 & 2 closed

BOOT ROM TYPE	
Setting	J10
í 2764 chi	Pins 2 & 3 clo ed
27256 ch )	Pins 1 & 2 clo ed


16/64KB RAM VERSION	
Setting	J11
16KB	Pins 1 & 2 clo ed
64KB	Pins 2 & 3 clo ed

Continued on next page...

# COMPU-SHACK PRODUCTION, GMBH CS-ETHERNET-KARTE COMBO PREMIUM

... continued from previous page

FACTORY CONFIGURED SETTINGS	
Jumper	Setting
J2/jumper I	Open
J2/jumper C	Open
J2/jumper I	Open
J4/jumper I	Open
J4/jumper C	Open
J4/jumper I	Open



BRACKET-MOUNTED  
LEDs

DIAGNOSTIC LEDS			
LED	Color	Status	Condition
D1	Red	On	Data is being transmitted
D2	Green	On	Data is being received
D3	Red	On	Collision detected on network
D4	Green	On	Twisted pair network connection is good
D5	Red	On	Twisted pair network connection is broken