

AT I/O CARD

ASKA-2831-06

ASKA[®]
TECHNOLOGIES

Jumper Settings:

A)

	JP1	JP2	JP3	JP4	JP8	JP9	JP11	JP12
3	COM 3 3E8	DIS- ABLE	COM 4 2E8	DIS- ABLE	IRQ 3	IRQ 4		
2	ASYN1 SEL	ASYN1	ASYN2 SEL	ASYN2	ASYN1 IRQ	ASYN2 IRQ	□	□
1	COM 1 3F8	EN- ABLE	COM 2 2F8	EN- ABLE	IRQ 4	IRQ 3		

JP11 & JP12 set to 1-2 allows you to set **ASYN1** port to COM1/COM3.

B)

	JP1	JP2	JP3	JP4	JP8	JP9	JP11	JP12
3	COM 3 3E8	DIS- ABLE	COM 4 2E8	DIS- ABLE	IRQ 3	IRQ 4	□	□
2	ASYN2 SEL	ASYN2	ASYN1 SEL	ASYN1	ASYN2 IRQ	ASYN1 IRQ		
1	COM 1 3F8	EN- ABLE	COM 2 2F8	EN- ABLE	IRQ 4	IRQ 3		

JP11 & JP12 set to 1-2 allows you to set **ASYN2** port to COM1/COM3.

C)

	JP5	JP10	JP6	JP7
3	LPT 2 278	IRQ 5	DIS- ABLE	DIS- ABLE
2	LPT SEL	LPT IRQ	LPT	GAME
1	LPT 1 378	IRQ 7	EN- 2 ABLE	EN- ABLE

Location of Ports:

PRINTER PORT: LPT1: = &H378, INT = IRQ7
LPT2: = &H278, INT = IRQ5

ASYN. PORT : COM1: = &H3F8, INT = IRQ4
COM2: = &H2F8, INT = IRQ3
COM3: = &H3E8, INT = IRQ4
COM4: = &H2E8, INT = IRQ3

GAME PORT : &H201

FACTORY DEFAULT: All jumpers are set to 1-2.