

Operating Instructions

CA9342K

FEATURES:

- * Two serial ports
- * One parallel port
- * One Game port
- * One FDD port
- * One IDE HDD port
- * AT sixteen bit slot

MAIN COMPONENT:

- UMC
- * UMC82C863
- * UMC82C865

CONENECTOR:

- * CN1 :IDE HDD connector
- * CN2 :FDD connector
- * CN3 :Joystick connector
- * CN4 :COM1/COM3 connector
- * CN5 :COM2/COM4 connector
- * CN6 : Printer connector
- * J1 : IOCHRDY connector
- * J2 : HDD LED connector

CONFIGURATION SWITCH DEFINITION:

| CONFIG# | DESCRIPTION | ACTIVATION | |
|---------|----------------------|--------------|----------------|
| | | 1-2(Default) | 2-3 |
| JP1 | COM2/COM4 select | COM2 (2F8) | COM4(2E8) |
| JP2 | ENB/DIS COM2 or COM4 | Enable | Disable |
| JP3 | ENB/DIS Game port | Enable | Disable |
| JP4 | COM1/COM3 select | COM1 (3F8) | COM3 (3E8) |
| JP5 | LPT2/LPT3 select | LPT2 (378) | LPT3 (278) |
| JP6 | ENB/DIS COM1 or COM3 | Enable | Disable |
| JP7 | ENB/DIS Floppy | Enable | Disable |
| JP8 | HDC | Not Exist | Exist(default) |
| JP9 | ENB/DIS IDE | Enable | Disable |
| JP10 | ENB/DIS Printer | Enable | Disable |

