

STRETCH MEMORY MODULE

ASSY # PA1010406

SWITCH SETTING

```
+-----+
|1|2|3|4|   SW1: 1=ON, 0=OFF
+-----+
```

```
| | | |
| | | |
| | +---- Page Frame Address
| | 0 0   C000H
| | 0 1   D000H
| | 1 0   E000H
| | 1 1   Reserved
| | | |
```

```
+---- I/O Page Register Address
1 0   0208H 4208H 8208H C208H
1 1   0218H 4218H 8218H C218H
0 0   0258H 4258H 8258H C258H
0 1   0268H 4268H 8268H C268H
```

JUMPER SETTING

E1-E2 Memory Parity disabled  
E2-E3 Memory Parity enabled

The Expanded Memory Manager driver is PEMMF.SYS and can be downloaded from Emulex BBS at (714) 556-8019 - 1200/2400 baud, 8, N, 1.

□