

DELL COMPUTER CORPORATION SYSTEM XPS 50/66 FS/MDT

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper/Switch	Position
í Factory configured - do not alter	W1	Open
í Parallel port bidirectional	W5	pins 2 & 3 closed
Parallel port unidirectional (printer)	W5	pins 1 & 2 closed
í Monitor type select color	W6	Closed
Monitor type select monochrome	W6	Open
í Factory configured - do not alter	W7	Closed
í Factory configured - do not alter	W8	pins 2 & 3 closed
í Factory configured - do not alter	W20	pins 2 & 3 closed
í Factory configured - do not alter	W31	Open
í Factory configured - do not alter	W40	pins 2 & 3 closed
í Factory configured - do not alter	W70	pins 2 & 3 closed
í Factory configured - do not alter	W71	Open
í Factory configured - do not alter	SW1/2	Closed
í Factory configured - do not alter	SW1/3	Open
í Factory configured - do not alter	SW1/4	Open

Note: The locations of the factory configured jumpers is unidentified.

DRAM CONFIGURATION				
Size	Bank 0	Bank 1	Bank 2	Bank 3
4MB	(1) 1M x 36	NONE	NONE	NONE
8MB	(1) 1M x 36	(1) 1M x 36	NONE	NONE
12MB	(1) 1M x 36	(1) 1M x 36	(1) 1M x 36	NONE
16MB	(1) 1M x 36			
16MB	(1) 4M x 36	NONE	NONE	NONE
20MB	(1) 1M x 36	(1) 4M x 36	NONE	NONE
24MB	(1) 1M x 36	(1) 1M x 36	(1) 4M x 36	NONE
32MB	(1) 4M x 36	(1) 4M x 36	NONE	NONE
36MB	(1) 1M x 36	(1) 4M x 36	(1) 4M x 36	(1) 4M x 36
40MB	(1) 1M x 36	(1) 1M x 36	(1) 4M x 36	(1) 4M x 36
48MB	(1) 4M x 36	(1) 4M x 36	(1) 4M x 36	NONE
64MB	(1) 4M x 36			

Continued on next page ...

DELL COMPUTER CORPORATION

SYSTEM XPS 50/66 FS/MDT

... continued from previous page

CACHE CONFIGURATION			
Size	Bank 0	Bank 1	TAG
128KB	(4) 32K x 8	NONE	(2) 16K x 8
256KB	(4) 32K x 8	(4) 32K x 8	(2) 16K x 8

CACHE JUMPER CONFIGURATION					
Size	W64	W65	W66	W67	W68
128KB	2 & 3	1 & 2	1 & 2	1 & 2	2 & 3
256KB	2 & 3	2 & 3	2 & 3	2 & 3	2 & 3

Note: pins designated should be in the closed position.

CPU SPEED CONFIGURATION				
Speed	SW1/1	SW1/2	SW1/3	SW1/4
50iMHz	Closed	Factory configured	Factory configured	Factory configured
66iMHz	Open	Factory configured	Factory configured	Factory configured