

WIN LAN ENTERPRISE CO., LTD.
EL - EP06

... continued from previous page

CONNECTIONS			
Purpose	Location	Purpose	Location
USB connector	CN1	IR connector	IR1
Serial port 1	CN2	Power LED & keylock	JP1
Serial port 2	CN3	Reset switch	JP2
PS/2 mouse interface	CN4	Speaker	JP3
IDE interface 2	CN5	IDE interface LED	JP4
IDE interface 1	CN6	Green PC connector	JP5
Parallel port	CN7	32-bit PCI slots	PC1 - PC3
Floppy drive interface	CN8	Cache slot	SL1

USER CONFIGURABLE SETTINGS		
Function	Label	Position
Flash BIOS voltage select 12v	J1	Pins 1 & 2 closed
Flash BIOS voltage select 5v	J1	Pins 2 & 3 closed
í CMOS memory normal operation	J2	Open
CMOS memory clear	J2	Closed

DRAM CONFIGURATION			
Size	Bank 0	Bank 1	Bank 2
8MB	None	None	(1) 1M x 64
8MB	(2) 1M x 36	None	None
16MB	None	None	(1) 2M x 64
16MB	None	(2) 1M x 36	(1) 1M x 64
16MB	(2) 2M x 36	None	None
16MB	(2) 1M x 36	(2) 1M x 36	None
24MB	None	(2) 2M x 36	(1) 1M x 64
24MB	None	(2) 1M x 36	(1) 2M x 64
24MB	(2) 2M x 36	(2) 1M x 36	None
32MB	None	None	(1) 4M x 64
32MB	None	(2) 2M x 36	(1) 2M x 64
32MB	(2) 4M x 36	None	None
32MB	(2) 2M x 36	(2) 2M x 36	None
40MB	None	(2) 4M x 36	(1) 1M x 64
40MB	None	(2) 1M x 36	(1) 4M x 64
40MB	(2) 4M x 36	(2) 1M x 36	None
48MB	None	(2) 2M x 36	(1) 4M x 64
48MB	None	(2) 4M x 36	(1) 2M x 64
48MB	(2) 2M x 36	(2) 4M x 36	None
64MB	None	None	(1) 8M x 64
64MB	None	(2) 4M x 36	(1) 4M x 64
64MB	(2) 8M x 36	None	None
64MB	(2) 4M x 36	(2) 4M x 36	None

Continued on next page. . .

WIN LAN ENTERPRISE CO., LTD.

EL - E P 0 6

... continued from previous page

DRAM CONFIGURATION (CON'T)			
Size	Bank 0	Bank 1	Bank 2
72MB	None	(2) 8M x 36	(1) 1M x 64
72MB	None	(2) 1M x 36	(1) 8M x 64
72MB	(2) 8M x 36	(2) 1M x 36	None
80MB	None	(2) 2M x 36	(1) 8M x 64
80MB	None	(2) 8M x 36	(1) 2M x 64
80MB	(2) 2M x 36	(2) 8M x 36	None
96MB	None	(2) 8M x 36	(1) 4M x 64
96MB	None	(2) 4M x 36	(1) 8M x 64
96MB	(2) 8M x 36	(2) 4M x 36	None
128MB	None	(2) 8M x 36	(1) 8M x 64
128MB	(2) 8M x 36	(2) 8M x 36	None

Note: Board accepts EDO memory..

CACHE CONFIGURATION			
Size	Bank 0	SL1	TAG
256KB	(2) 32K x 32	Not installed	Unidentified
256KB	None	256KB module installed	Unidentified
512KB	(2) 32K x 32	256KB module installed	Unidentified
512KB	(2) 64K x 32	None	Unidentified
512KB	None	512KB module installed	Unidentified

CPU SPEED SELECTION (CYRIX)						
CPU speed	Clock speed	Multiplier	JF1	JF2	JX1	JX2
120MHz	50MHz	2x	Closed	Closed	Open	Closed
133MHz	55MHz	2x	Open	Open	Open	Closed
150MHz	60MHz	2x	Open	Closed	Open	Closed
166MHz	66MHz	2x	Closed	Open	Open	Closed

CPU SPEED SELECTION (AMD)						
CPU speed	Clock speed	Multiplier	JF1	JF2	JX1	JX2
75MHz	50MHz	1.5x	Closed	Closed	Open	Open
90MHz	55MHz	1.5x	Open	Closed	Open	Open
100MHz	60MHz	1.5x	Closed	Open	Open	Open

Continued on next page. . .

WIN LAN ENTERPRISE CO., LTD.
EL - EP 06

... continued from previous page

CPU SPEED SELECTION (INTEL)						
CPU speed	Clock speed	Multiplier	JF1	JF2	JX1	JX2
75MHz	50MHz	1.5x	Closed	Closed	Open	Open
90MHz	60MHz	1.5x	Open	Closed	Open	Open
100MHz	66MHz	1.5x	Closed	Open	Open	Open
110MHz	66MHz	1.5x	Open	Open	Open	Closed
120MHz	60MHz	2x	Open	Closed	Open	Closed
133MHz	66MHz	2x	Closed	Open	Open	Closed
150MHz	60MHz	2.5x	Closed	Closed	Closed	Open
166MHz	66MHz	2.5x	Closed	Open	Closed	Closed
180MHz	60MHz	3x	Open	Closed	Closed	Open
200MHz	66MHz	3x	Closed	Open	Closed	Open

CPU TYPE SELECTION			
Type	JV1	JV2	JV3
P54C	Pins 2 & 3 closed	Pins 2 & 3 closed	Pins 2 & 3 closed
P55C	Pins 1 & 2 closed	Pins 1 & 2 closed	Pins 1 & 2 closed

CPU VOLTAGE SELECTION		
Voltage	JV4	JV5
2.6v	N/A	Closed
2.8v	N/A	Open
3.3v	Closed	N/A
3.6v	Open	N/A

Note: If an AMD CPU is installed, JV5 must be left open.