

# COMPAQ COMPUTER CORPORATION

## PROLIANT 4500

<b>Processor</b>	Pentium
<b>Processor Speed</b>	100/133/166MHz
<b>Chip Set</b>	Unidentified
<b>Video Chip Set</b>	None
<b>Maximum Onboard Memory</b>	1GB
<b>Maximum Video Memory</b>	None
<b>Cache</b>	512/2048KB
<b>BIOS</b>	Unidentified
<b>Dimensions</b>	Unidentified
<b>I/O Options</b>	32-bit VESA local bus slots (2), 32-bit PCI slots (2), bus mouse port, CD-ROM interface, floppy drive interface, game port, green PC connector, IDE interface, Fast SCSI-2 connector, Fast-Wide SCSI-2 connector, parallel port, PS/2 mouse port, serial ports (2), serial port, tape drive interface, VGA feature connector, VGA port, PC/104 Interface (2)
<b>NPU Options</b>	None

34408

### CONNECTIONS

Note: The location of the connectors is unidentified.

### USER CONFIGURABLE SETTINGS

Function	Label	Position
í On board video enabled	S1/1	Off
On board video disabled	S1/1	On
í Chassis configuration lock enabled	S1/2	Off
Chassis configuration lock disabled	S1/2	On
í System installed in a tower chassis	S1/3	Off
System installed in a rack chassis	S1/3	On
í System boot from floppy controlled through configuration settings	S1/4	Off
System boot from floppy drive regardless of configuration settings	S1/4	On
í Password enabled	S1/5	Off
Password disabled	S1/5	On
í CMOS memory normal operation	S1/6	Off
CMOS memory clear	S1/6	On

### DRAM CONFIGURATION

Size	Bank 1	Bank 2	Bank 3	Bank 4
16MB	(4) 1MB x 32			
32MB	(4) 2MB x 32			
64MB	(4) 2MB x 32	(4) 2MB x 32		
64MB	(4) 4MB x 32			
128MB	(4) 4MB x 32	(4) 4MB x 32		
128 MB	(4) 8MB x 32			
128MB	(4) 2MB x 32	(4) 2MB x 32	(4) 2MB x 32	(4) 2MB x 32
192MB	(4) 8MB x 32	(4) 4MB x 32		
192MB	(4) 4MB x 32	(4) 4MB x 32	(4) 4MB x 32	
256MB	(4) 16MB x 32			

Continued on next page . . .

COMPAQ COMPUTER CORPORATION  
 PROLIANT 4500

... continued from previous page

DRAM CONFIGURATION (CONT.)				
Size	Bank 1	Bank 2	Bank 3	Bank 4
512MB	(4) 16MB x 32	(4) 16MB x 32		
512MB	(4) 8MB x 32			
1024MB	(4) 16MB x 32			

CACHE CONFIGURATION
Note: Board accepts 512KB/2048KB cache memory.

DRIVE SELECTION			
SCSI ID	ID0	ID1	ID2
5	On	Off	On
6	Off	On	On

MISCELLANEOUS TECHNICAL NOTE
Note: Diagram not available.