


DTK COMPUTER, INC.  
PAM-0030P (VER. 1.00)

<b>Processor</b>	Pentium
<b>Processor Speed</b>	60/66MHz
<b>Chip Set</b>	OPTI
<b>Video Chip Set</b>	None
<b>Maximum Onboard Memory</b>	128MB
<b>Maximum Video Memory</b>	None
<b>Cache</b>	64/128/256/512KB
<b>BIOS</b>	AMI/Award
<b>Dimensions</b>	330mm x 220mm
<b>I/O Options</b>	32-bit VESA local bus slots (2)
<b>NPU Options</b>	None



Continued on next page . . .

DTK COMPUTER, INC.  
PAM-0030P (VER. 1.00)

... continued from previous page

CONNECTIONS			
Purpose	Location	Purpose	Location
Reset switch	J1	External battery	J20
Speaker	J2	Turbo switch	JP9
Power LED & keylock	J3	Turbo LED	JP10
Chassis fan power	J4	32-bit VESA local bus slots	SL1 & SL2

USER CONFIGURABLE SETTINGS		
Function	Label	Position
í MDHDOE# inactive select end of last T2	JP25	Closed
MDHDOE# inactive select beginning of last T2	JP25	Open
í Back to back I/O delay disabled	JP29	Open
Back to back I/O delay enabled	JP29	Closed
í LDEV# inactive select end of first T2	JP30	Open
LDEV# inactive select end of second T2	JP30	Closed
í VL-BUS enabled	JP31	Open
VL-BUS disabled	JP31	Closed
í Monitor type select color	JP32	Closed
Monitor type select monochrome	JP32	Open
í Power management IRQ select IRQ15	JP34	Pins 2 & 3 closed
Power management IRQ select IRQ12	JP34	Pins 1 & 2 closed
í Normal operation	JP35	Open
Quick testing only	JP35	Closed

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
2MB	(2) 256K x 36	None
4MB	(2) 512K x 36	None
4MB	(2) 256K x 36	(2) 256K x 36
6MB	(2) 512K x 36	(2) 256K x 36
6MB	(2) 256K x 36	(2) 512K x 36
8MB	(2) 1M x 36	None
8MB	(2) 512K x 36	(2) 512K x 36
10MB	(2) 256K x 36	(2) 1M x 36
12MB	(2) 1M x 36	(2) 512K x 36
16MB	(2) 2M x 36	None
16MB	(2) 1M x 36	(2) 1M x 36
18MB	(2) 256K x 36	(2) 2M x 36
20MB	(2) 512K x 36	(2) 2M x 36
24MB	(2) 1M x 36	(2) 2M x 36

Continued on next page...

... continued from previous page

DRAM CONFIGURATION (CON'T)		
Size	Bank 0	Bank 1
32MB	(2) 4M x 36	None
32MB	(2) 2M x 36	(2) 2M x 36
34MB	(2) 256K x 36	(2) 4M x 36
36MB	(2) 512K x 36	(2) 4M x 36
40MB	(2) 1M x 36	(2) 4M x 36
48MB	(2) 2M x 36	(2) 4M x 36
64MB	(2) 8M x 36	None
64MB	(2) 4M x 36	(2) 4M x 36
66MB	(2) 256K x 36	(2) 8M x 36
68MB	(2) 512K x 36	(2) 8M x 36
72MB	(2) 1M x 36	(2) 8M x 36
80MB	(2) 2M x 36	(2) 8M x 36
96MB	(2) 4M x 36	(2) 8M x 36
128MB	(2) 8M x 36	(2) 8M x 36

CACHE CONFIGURATION				
Size	Bank 0	Bank 1	TAG 0	TAG 1
64KB	(8) 8K x 8	None	None	(1) 8K x 8
128KB	(8) 8K x 8	(8) 8K x 8	None	(1) 8K x 8
256KB	(8) 32K x 8	None	None	(1) 8K x 8
512KB	(8) 32K x 8	(8) 32K x 8	(1) 8K x 8	(1) 8K x 8

CACHE JUMPER CONFIGURATION						
Size	JP17	JP18	JP19	JP20	JP21	JP24
64KB	Open	Open	Open	1 & 2	1 & 2	1 & 2
128KB	Closed	Open	Open	2 & 3	2 & 3	2 & 3
256KB	Closed	Closed	Open	1 & 2	1 & 2	1 & 2
512KB	Closed	Closed	Closed	2 & 3	2 & 3	2 & 3

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION			
Speed	JP6	JP7	JP8
50MHz	Closed	Open	Open
60MHz	Open	Closed	Open
66MHz	Closed	Open	Closed

CPU TYPE SELECTION		
Type	JP1	JP2
80386	Open	Closed
80486	Closed	Open
í Pentium	Closed	Closed

Continued on next page. . .

... continued from previous page

VL BUS WAIT STATE SELECTION	
Setting	JP3
0	Open
í 1	Closed

VL BUS SPEED SELECTION	
Speed	JP4
<= 33MHz	Open
í >33 MHz	Closed

VL BUS LCLK SELECTION			
Setting	JP22	JP23	JP26
í Synch = ½ CPUCLK	Pins 2 & 3 closed	Pins 2 & 3 closed	Open
Asynch U28 OSC	Pins 1 & 2 closed	Pins 1 & 2 closed	Closed

AT CLK SELECTION		
Setting	JP27	JP28
LCLK/2	Open	Open
LCLK/3	Closed	Open
í LCLK/4	Open	Closed
LCLK/5	Closed	Closed

MONITOR STANDBY SELECTION			
Timer	JP11	JP12	JP13
3 minutes	Open	Open	Closed
6 minutes	Open	Closed	Open
12 minutes	Closed	Open	Open

SYSTEM POWER MANAGEMENT SELECTION			
Timer	JP14	JP15	JP16
6 minutes	Open	Open	Closed
12 minutes	Open	Closed	Open
24 minutes	Closed	Open	Open

CMOS/BATTERY SELECTION	
Setting	JP33
í CMOS memory normal operation	Open
Battery type select internal	Pins 2 & 3 closed
CMOS memory clear	Pins 1 & 2 closed