


ZENITH DATA SYSTEMS

EXPRESS 5800 MT2000

Device Type	Mainboard
Processor	Pentium Pro
Processor Speed	180/200MHz
Chip Set	Unidentified
Video Chip Set	Unidentified
Maximum Onboard Memory	1GB
Maximum Video Memory	2MB
Cache	256/512KB (located on Pentium Pro CPU)
BIOS	Unidentified
Dimensions	355mm x 304mm
I/O Options	32-bit PCI slots (5), floppy drive interface, Narrow SCSI interface, Wide SCSI interface, RAID slot



CONNECTIONS

Purpose	Location	Purpose	Location
Chassis fan power	C1	Power connector	P1

Speaker	C2	Power connector	P2
Floppy drive interface	CN1	32-bit PCI slots	PC1 - PC5
Front panel connector	CN2	RAID slot	SL1
Narrow SCSI interface	CN3	Riser board connector	SL2
Wide SCSI interface	CN4	CPU/memory slot	SL3

USER CONFIGURABLE SETTINGS

Function		Label	Position
»	Factory configured - do not alter	J1	Unidentified
»	CMOS memory normal operation	J1B	Pins 1 & 2 closed
	CMOS memory clear	J1B	Pins 2 & 3 closed
»	Password enabled	J2B	Pins 1 & 2 closed
	Password disabled	J2B	Pins 2 & 3 closed
»	Factory configured - do not alter	J3B	Unidentified
»	Factory configured - do not alter	J4	Unidentified
»	Factory configured - do not alter	J4B	Pins 1 & 2 closed
»	Factory configured - do not alter	J5A	Pins 1 & 2 closed
»	Flash BIOS write protect disabled	J6A	Pins 1 & 2 closed
	Flash BIOS write protect enabled	J6A	Pins 2 & 3 closed
»	Factory configured - do not alter	J7A	Pins 2 & 3 closed
»	Factory configured - do not alter	J27	Unidentified
»	Factory configured - do not alter	J28	Unidentified
»	Factory configured - do not alter	J29	Unidentified
»	Factory configured - do not alter	J601	All jumpers closed
»	Factory configured - do not alter	J612	Pins 2 & 3 closed
»	Factory configured - do not alter	J613	Pins 1 & 2 closed

»	Factory configured - do not alter	J614	Pins 1 & 2 closed
»	Factory configured - do not alter	J615	Pins 2 & 3 closed
»	Factory configured - do not alter	J616	Pins 2 & 3 closed
»	Factory configured - do not alter	J624	Pins 2 & 3 closed
»	Factory configured - do not alter	J625	Pins 2 & 3 closed
»	Factory configured - do not alter	J626	Pins 2 & 3 closed
»	Factory configured - do not alter	J628	Pins 1 & 2 closed
»	Factory configured - do not alter	J629	Pins 2 & 3 closed


VIDEO MEMORY CONFIGURATION

Size	Bank 0	Bank 1
1MB	(2) 256K x 16	None
2MB	(2) 256K x 16	(2) 256K x 16

CPU SPEED SELECTION

CPU speed	Clock speed	Multiplier	J1A	J2A	J3A	J4A	J5B	J6B
180MHz	60MHz	3x	2 & 3	2 & 3	1 & 2	2 & 3	2 & 3	1 & 2
200MHz	66MHz	3x	2 & 3	2 & 3	1 & 2	2 & 3	1 & 2	2 & 3

Note: Pins designated should be in the closed position.



CONNECTIONS

Purpose	Location	Purpose	Location
DC to DC converter 1	C1	DC to DC converter 2	C2

USER CONFIGURABLE SETTINGS

Function	Label	Position
» Factory configured - do not alter	JP1	Unidentified

DIMM CONFIGURATION

Size	Bank 0	Bank 1	Bank 2	Bank 3
32MB	(1) 4M x 64	None	None	None
32MB	(1) 2M x 64	(1) 2M x 64	None	None
32MB	(1) 1M x 64			
40MB	(1) 4M x 64	(1) 1M x 64	None	None
48MB	(1) 4M x 64	(1) 2M x 64	None	None
48MB	(1) 2M x 64	(1) 2M x 64	(1) 2M x 64	None
64MB	(1) 2M x 64			
64MB	(1) 8M x 64	None	None	None

64MB	(1) 4M x 64	(1) 4M x 64	None	None
72MB	(1) 8M x 64	(1) 1M x 64	None	None

DIMM CONFIGURATION				
Size	Bank 0	Bank 1	Bank 2	Bank 3
80MB	(1) 8M x 64	(1) 2M x 64	None	None
96MB	(1) 8M x 64	(1) 4M x 64	None	None
96MB	(1) 4M x 64	(1) 4M x 64	(1) 4M x 64	None
128MB	(1) 16M x 64	None	None	None
128MB	(1) 8M x 64	(1) 8M x 64	None	None
128MB	(1) 4M x 64			
136MB	(1) 16M x 64	(1) 1M x 64	None	None
144MB	(1) 16M x 64	(1) 2M x 64	None	None
176MB	(1) 16M x 64	(1) 2M x 64	(1) 2M x 64	(1) 2M x 64
192MB	(1) 16M x 64	(1) 8M x 64	None	None
192MB	(1) 8M x 64	(1) 8M x 64	(1) 8M x 64	None
256MB	(1) 16M x 64	(1) 16M x 64	None	None
256MB	(1) 8M x 64			
272MB	(1) 16M x 64	(1) 16M x 64	(1) 1M x 64	(1) 1M x 64
288MB	(1) 16M x 64	(1) 16M x 64	(1) 2M x 64	(1) 2M x 64
320MB	(1) 16M x 64	(1) 16M x 64	(1) 4M x 64	(1) 4M x 64
384MB	(1) 16M x 64	(1) 16M x 64	(1) 16M x 64	None
512MB	(1) 16M x 64			

DIMM CONFIGURATION (CON'T)				
Size	Bank 4	Bank 5	Bank 6	Bank 7
64MB	(1) 4M x 64	None	None	None
64MB	(1) 2M x 64	(1) 2M x 64	None	None

64MB	(1) 1M x 64	(1) 1M x 64	(1) 1M x 64	(1) 1M x 64
80MB	(1) 4M x 64	(1) 1M x 64	None	None
96MB	(1) 4M x 64	(1) 2M x 64	None	None
96MB	(1) 2M x 64	(1) 2M x 64	(1) 2M x 64	None
128MB	(1) 2M x 64	(1) 2M x 64	(1) 2M x 64	(1) 2M x 64
128MB	(1) 8M x 64	None	None	None
128MB	(1) 4M x 64	(1) 4M x 64	None	None
144MB	(1) 8M x 64	(1) 1M x 64	None	None
160MB	(1) 8M x 64	(1) 2M x 64	None	None
192MB	(1) 8M x 64	(1) 4M x 64	None	None
192MB	(1) 4M x 64	(1) 4M x 64	(1) 4M x 64	None
256MB	(1) 16M x 64	None	None	None
256MB	(1) 8M x 64	(1) 8M x 64	None	None
256MB	(1) 4M x 64	(1) 4M x 64	(1) 4M x 64	(1) 4M x 64
272MB	(1) 16M x 64	(1) 1M x 64	None	None
288MB	(1) 16M x 64	(1) 2M x 64	None	None
352MB	(1) 16M x 64	(1) 2M x 64	(1) 2M x 64	(1) 2M x 64
384MB	(1) 16M x 64	(1) 8M x 64	None	None
384MB	(1) 8M x 64	(1) 8M x 64	(1) 8M x 64	None

DIMM CONFIGURATION (CON'T)

Size	Bank 4	Bank 5	Bank 6	Bank 7
512MB	(1) 16M x 64	(1) 16M x 64	None	None
512MB	(1) 8M x 64	(1) 8M x 64	(1) 8M x 64	(1) 8M x 64
544MB	(1) 16M x 64	(1) 16M x 64	(1) 1M x 64	(1) 1M x 64
576MB	(1) 16M x 64	(1) 16M x 64	(1) 2M x 64	(1) 2M x 64
640MB	(1) 16M x 64	(1) 16M x 64	(1) 4M x 64	(1) 4M x 64
768MB	(1) 16M x 64	(1) 16M x 64	(1) 16M x 64	None

1024MB	(1) 16M x 64			
--------	--------------	--------------	--------------	--------------

CACHE CONFIGURATION
Note: 256KB/512KB cache is located on the Pentium II CPU.