

GemStation 2525

[Drivers & Utilities](#) [Jumper Settings](#)

Drivers & Utilities

Various modems were used for these systems. Please look for your specific hardware in the table below. For drivers not listed, please contact the manufacturer of the hardware. For assistance determining which hardware was included in your machine, please contact our Technical Support Department at (800) 766-4377 or via email at techsupport@trigem-usa.com.

Video

SiS5597/5598

Manufacturer: Silicom Integrated Systems (www.sis.com.tw)

SIS55971.ZIP Windows 95 Drivers & Utilities Disk 1 of 3

SIS55972.ZIP Windows 95 Drivers & Utilities Disk 2 of 3

SIS55973.ZIP Windows 95 Drivers & Utilities Disk 3 of 3

Sound

Crystal

Manufacturer: Crystal

Driver not yet available.

Modem

Modem Master 6000

Manufacturer: Silicom Multimedia (www.silicom-multimedia.com)

MM6000P.ZIP Windows 95 Driver Disk (Pentium Only)

Modem Master 8000

Manufacturer: Silicom Multimedia (www.silicom-multimedia.com)

MM8000.ZIP Windows 95 Driver Disk

MS5000-U

Manufacturer: Aztech Labs (www.aztech.com.sg)

MS5000.ZIP Windows 95 Driver Disk

Jumper Settings

CPU Frequency Ratio Jumpers

Jumper Number	Jumper Setting	Freq. Ratio	Processor Type
---------------	----------------	-------------	----------------

J8 J5 J9*

2-3	1-2	---	2.5	P54C, P55C, AMD K6
1-2	1-2	---	3	P54C, P55C, AMD K6
2-3	2-3	---	2	P54C, P55C, AMD K6
1-2	2-3	---	3.5	P54C, P55C, AMD K6

* For AMD K6, set J9 to 1-2.

CPU Core Voltage Jumpers

Jumper Number	Jumper	Setting	Core Voltage	Processor Type
J10 J11 J12 J13				
	2-3	---	3.3V	P54C
	2-3	---	3.2V	AMD K6 233MHz
	2-3	---	2.9V	AMD K6 166 or
200MHz				
	---	---	2.8V	P55C

CPU I/O Voltage Jumpers

Jumper Number	Jumper	Setting	Processor Type
J14 J15			
	2-3	2-3	P54C, AMD K5
	1-2	1-2	P55C, AMD K6

CPU External Clock Speed Jumpers

Jumper Number	Jumper	Setting	CPU External Clock Speed
J18 J19			
	2-3	2-3	50MHz
	2-3	1-2	60MHz
	1-2	2-3	66.6MHz

Other Jumpers

Jumper Number	Jumper	Setting	Function
J4			
	1-2		CMOS Keep (Normal)
	2-3		CMOS Clear
J20*			
	1-2		Selects Serial Port 2 (COM2)
	2-3		Selects MIDI/Game Port