

## Table Contents

<b>Chapter 1: Introduction .....</b>	<b>1</b>
Specification .....	2
Main BOARD physical layout .....	3
<b>Chapter 2: Installation .....</b>	<b>4</b>
On board RAM installation .....	4
RAM module on board position .....	5
CPU installation .....	5
<b>Chapter 3: Connector description .....</b>	<b>7</b>
Power supply connectors .....	7
Keyboard connector .....	8
External Battery connector .....	8
Keylock connector .....	9
Speaker connector .....	9
Turbo switch & turbo led .....	10
Reset connector .....	10
CMOS RAM discharge jumper .....	10
Monitor Display setting .....	10
<b>Chapter 4: AMI BIOS SETUP .....</b>	<b>11</b>
<b>Chapter 5: AWARD BIOS SETUP .....</b>	<b>18</b>

## Chapter 1: Introduction

Congratulation on purchase of you New 386DX/486DLC CACHE M/B

The 386DX/486DLC cache M/B is a two chip solution offer optimal performance for 386DX or 486DLC system running ON 33 and 40 MHz. It support 386DX & 486DLC processor.

### Specification

Processor: 80386DX, 486DLC

CPU clock: 33/40 MHz

CPU clock source: Clock generator

Memory : Up to 64MB

Memory configuration: 1MB/2MB/4MB/5MB/8MB/16MB/20MB/32MB/64MB

Memory using: 256KB/1MB/4MB/16MB RAM Module

Cache ram configuration: 128KB


BIOS type: AMI ROM BIOS/AWARD ROM BIOS

I/O slot: Five 16-bit & ONE 8-bit ISA Slot

Dimension: 22 x 17 cm


## Main Board Physical Layout (A)

J-302A 386DX-33/40 CACHE MAIN BOARD (PQFP)



**Main Board Physical Layout (B)**

J-302B 386DX/486DLC CACHE MAIN BOARD (PGA)



HP 0607A-1(0528A)

**Chapter 2: Installation**

BEFORE TURNING ON THE SYSTEM POWER, PLEASE FOLLOW THE FOLLOWING INSTRUCTIONS CAREFULLY OR YOUR SYSTEM MAY NOT OPERATE CORRECTLY. THANK YOU!!

**On board RAM installation**

The 386DX/486DLC cache M/B can be expanded memory from 1MB to 64MB. Either 256KB, 1MB or 4MB or 16MB RAM module can be used on the 386DX/486DLC cache M/B.

RAM module DRAM on the motherboard consists of BANK 0 & 1. When you install the DRAM on the main board, first completely fill BANK 0, then fill BANK 1. The spaces of Bank 0 should be fully occupied, otherwise the main board will not work.

- **RAM module BANK installed:**

BANK 0	BANK 1	TOTAL MEMORY
256KB × 4PCS		1MB
256KB × 4PCS	256KB × 4PCS	2MB
1MB × 4PCS		4MB
256KB × 4PCS	1MB × 4PCS	5MB
1MB × 4PCS	1MB × 4PCS	8MB
4MB × 4PCS		16MB
1MB × 4PCS	4MB × 4PCS	20MB
4MB × 4PCS	4MB × 4PCS	32MB
16MB × 4PCS		64MB

### RAM module on board position

Please refer to the table for the BANK 0 and BANK 1 position

BANK 0 INSTALL	U6, U7, U8, U9
BANK 1 INSTALL	U10, U11, U12, U13

### CPU Installation

The 386DX/486DLC CACHE M/B it can use 80386DX-33 OR 40 MHz & 486DLC-33 OR 40 MHz, the table below show the jumper setting for CPU clock.

	JP7	JP8
33 MHz	OP	CL
40 MHz	OP	OP

## Chapter 3: Connector Description

### Power Supply Connectors

If you are installing the 386DX/486DLC CACHE M/B yourself, the final step is attaching the power supply cable to the motherboard POWER CON. which are located in the upper right quadrant of the board. There are some cables on the power supply.

The table below lists the voltages provided to the motherboard by the power supply output connectors.

Pin No.	Output Voltages
1	Power Good
2	+5V
3	+12V
4	-12V
5	GND
6	GND
1	GND
2	GND
3	-5V
4	+5V
5	+5V
6	+5V

### Keyboard Connector

The 386DX/486DLC CACHE M/B has a standard keyboard connection port at the rear of the board.

Pin configurations and signal assignments are shown in the figures below:

Pin No.	Signal Name
1	Clock
2	Data
3	NC
4	GND
5	VCC (+5V)

### External Battery Connector: J1

J1 on the motherboard is the connector used for the external battery pack. The battery pack connected should range from +4.5V to +6V DC and should never be less than +3.5V DC for proper operation.

The pinouts for the connector are listed below:

Pin No.	Assignment
1	DC Input
2	NC
3	GND
4	GND

### Keylock Connector (J16)

J16 is used to connector the keylock connector on the front panel of the case.

Pin assignments are as follows:

Pin No.	Assignment
1	Power Led Anode
2	NC
3	GND
4	Keylock
5	GND

### Speaker Connector: (JP6)

Speaker connector JP6 is used to connect the speaker to the system board.

Pin assignments are as follows:

Pin No.	Assignment
1	Speaker Out
2	NC
3	NC
4	+5V

## Turbo Switch (JP4) & Turbo Led (JP3)

This feature enables and disables a toggle switch within the system which is able to change the system speed. When the switch is ON, the system speed is in the fast Turbo Mode. When the switch is OFF it is in the Normal Mode.

Turbo Switch	Turbo LED	Speed
Short	Light On	Turbo
Open	Ligh Off	Normal

## Reset Connector (S1)

Reset Switch S1 is used to connect the reset switch to restart the system.

Pin assignments are as follows:

Pin No.	Assignment
1	Reset strobe
2	GND

## CMOS RAM Discharge Jumper (JP2)

The factory setting shorts Pin 2 and Pin 3 of jumper JP2 for Battery Charge Mode.

JP2	Battery
1-2	Discharge
2-3	Charge

## Monitor Display Setting (JP1)

JP1	Monitor
CL	Color
OP	Monochrome

## Chapter4: AMI BIOS Setup

### AMI BIOS System configuration Setup

This section will tell you how to set up the system configurations (CMOS) under the AMI BIOS. After booting the system and testing the memory.

The SETUP program is contained in the system's Read-Only-Memory Rather than on a diskette.

To enter SETUP, press the "DEL" key. The following menu appears:

<p>AMIBIOS SETUP PROGRAM-AM AMI BIOS SETUP UTILITIES (C) 1992 American Megatrends Inc., All Rights Reserved</p>
<p><b>STANDARD CMOS SETUP</b></p> <p>ADBANCED CMOS SETUP ADVANCED CHIPSET SETUP AUTO CONFIGURATION WITH BIOS DEFAULTS AUTO CONFIGURATION WITH POWER-ON DEFAULTS CHANGE PASSWORD HARD DISK UTILITY WRITE TO CMOS AND EXIT DO NOT WRITE TO CMOS AND EXIT</p>
<p>Standard CMOS Setup for changing Time, Date, Hard Disk Type, etc.</p>
<p>ESC: EXIT ↓ → ↑ : Sel F2/F3: Color F10: Save &amp; Exit</p>

Please enter "STANDARD CMOS SETUP" to enter the next screen. The following pages show simple charts and instructions for the CMOS setup.

**AMIBIOS SETUP PROGRAM-WARNING INFORMATION**  
(C) 1992 American Megatrends Inc., All Rights Reserved

Improper Use of Setup may Cause Problems!!

If System Hangs, Reboot System and Enter Setup by Pressing the <DEL> key

Do any of the following After Entering Setup

- (i) Alter Options to make System Work
- (ii) Load BIOS Setup Defaults
- (iii) Load Power-on Defaults

Hit "ESC" to Stop now, Any other Key to Continue  
Hit "ESC" to Stop now, Any other Key to Continue

**AMIBIOS SETUP PROGRAM - STANDARD COMOS SETUP**  
(C) 1992 American Megatrends Inc., All Rights Reserved

Date (mm/date/year) : Wed, Jul 01 1992  
Time (hour/min/sec) : 19:35:25

Base memory size : 640 KB  
Ext. memory size : 3072 KB

Hard disk C:type : 37  
Hard disk D:type : Not Installed  
Floppy drive A: : 1.2 MB, 5 1/4"  
Floppy drive B: : Not Installed  
Primary display : Monochrome  
Keyboard : Installed

Cyln	Head	WPcom	LZone	Sect	Size				
615	8	128	615	17	41MB				
			Sat	Mon	Tue	Wed	Thu	Fri	Sat
			28	29	30	1	2	3	4
			5	6	7	8	9	10	11
			12	13	14	15	16	17	18
			19	20	21	22	23	24	25
			26	27	28	29	30	31	1
			2	3	4	5	6	7	8

Month : Jan, Feb.....Dec  
Date : 01 02 03.....31  
Year : 1901, 1902.....2099

ESC: Exit ↓→↑ : Select F2/F3: Color PU/PD: Modify

**AMIBIOS SETUP PROGRAM-AM AMI BIOS SETUP UTILITIES**  
(C) 1992 American Megatrends Inc., All Rights Reserved

STANDARD CMOS SETUP

**ADVANCED CMOS SETUP**

ADVANCED CHIPSET SETUP

AUTO CONFIGURATION WITH BIOS DEFAULTS  
AUTO CONFIGURATION WITH POWER-ON DEFAULTS

CHANGE PASSWORD

HARD DISK UTILITY

WRITE TO CMOS AND EXIT

DO NOT WRITE TO CMOS AND EXIT

Advanced CMOS Setup for configuring System Options

ESC: EXIT ↓ → ↑ : Sel F2/F3: Color F10: Save & Exit

**AMIBIOS SETUP PROGRAM-WARNING INFORMATION**  
(C) 1992 American Megatrends Inc., All Rights Reserved

Improper Use of Setup may Cause Problems!!

If System Hangs, Reboot System and Enter Setup by Pressing the (DEL) key

Do any of the following After Entering Setup

- (i) Alter Options to make System Work
- (ii) Load BIOS Setup Defaults
- (iii) Load Power-on Defaults

Hit "ESC" to Stop now, Any other Key to Continue

**AMIBIOS SETUP PROGRAM – ADVANCED CMOS SETUP**  
(C) 1992 American Megatrends Inc., All Rights Reserved

Typematic Rate Programming	: Disabled	Video ROM Shadow C000,16K	Enabled
Typematic Rate Delay (msec)	: 500	Video ROM Shadow C400,16K	Enabled
Typematic Rate (Chars/Sec)	: 15	Adaptor ROM Shadow C800,16K	Disabled
Above 1 MB Memory Test	: Enabled	Adaptor ROM Shadow CC00,16K	Disabled
Moemory Test Tick Sound	: Enabled	Adaptor ROM Shadow D000,16K	Disabled
Memory Parity Error Check	: Enabled	Adaptor ROM Shadow D400,16K	Disabled
Hit (DEL) Message Display	: Eanbled	Adaptor ROM Shadow D800,16K	Disabled
Hard Disk Type 47 RAM Area	: 0:300	Adaptor ROM Shadow DC00,16K	Disabled
Wait For (F1) If Any Error	: Enabled	Adaptor ROM Shadow E000,16K	Disabled
System Boot Up Num Lock	: On	Adaptor ROM Shadow E400,16K	Disabled
Numeric Processor Test	: Enabled	Adaptor ROM Shadow E800,16K	Disabled
Floppy Drive Seek At Boot	: Enabled	Adaptor ROM Shadow EC00,16K	Disabled
System Boot Up Sequence	: A., C:	System ROM Shadow F000,64K	Enabled
System Boot Up CPU Speed	: High	BootSector Virus Protection	Disabled
External Cache Memory	: Enabled		
Internal Cache Memory	: Enabled for 80386DX should be disable		
Turbo Switch Function	: Enabled for 486DLC should be enable		
Password Checking Option	: Setup		

(Ctrl) Pu/Pd: Modify F1: Help F2/F3: Color

F5: Old Values F6: BIOS Setup Defaults F7: Power-On Defaults

**AMIBIOS SETUP PROGRAM – AMI BIOS SETUP UTILITIES**  
(C) 1992 American Megatrends Inc., All Rights Reserved

STANDARD CMOS SETUP  
ADVANCED CMOS SETUP

ADVANCED CHIPSET SETUP

AUTO CONFIGURATION WITH BIOS DEFAULTS  
AUTO CONFIGURATION WITH POWER-ON DEFAULTS  
CHANGE PASSWORD  
HARD DISK UTILITY  
WRITE TO CMOS AND EXIT  
DO NOT WRITE TO CMOS AND EXIT

Advanced Chipset Setup for Contiquare and Chipset Registering

ESC: EXIT ↓ → ↑ : Sel F2/F3: Color F10: Save & Exit

**AMIBIOS SETUP PROGRAM-WARNING INFORMATION**  
(C) 1992 American Megatrends Inc., All Rights Reserved

Improper Use of Setup may Casuse Problems!!

If System Hangs, Reboot System and Enter Setup by Pressing the (DEL) key

Do any of the following After Entering Setup

- (i) Alter Options to make System Work
- (ii) Load BIOS Setup Defaults
- (iii) Load Power-on Defaults

Hit "ESC" to Stop now, Any other Key to Continue

**AMIBIOS SETUP PROGRAM – ADVANCED CHIPSET SETUP**  
(C) 1992 American Megatrends Inc., All Rights Reserved

Hidden Refresh	: Enabled
AT BUS Clock Selection	: CLKI/5 33 MHz Should be 4 40 MHz Should be 5
Memory Read Wait State	: 1 W/S
Memory Write Wait State	: 1 W/S
Cache Read Cycle	: 2 -1-1-1
Cache Write Wait State	: 1 W/S
Non-Cacheable Block-1 Size	: Disabled
Non-Cacheable Block-1 Base	: 0 KB
Non-Cacheable Block-2 Size	: Disabled
Non-Cacheable Block-2 Base	: 0 KB
Cacheable RAM Address Range	: 16 MB
Video BIOS Area Cacheable	: Yes

(Ctrl) Pu/Pd: Modify F1: Help F2/F3: Color

F5: Old Values F6: BIOS Setup Defaults F7: Power-On Defaults

## Alternative System speed

### SOFTWARE SWITCH:

#### FOR AMI BIOS:

After booting the system. Press "CTRL" + "ALT" + "+" at the same time to select low-speed, Press "CTRL" + "ALT" + "-" at the same time to select high-speed.

Please review the following configuration:

CPU SPEED NORMAL	KEYBOARD "CTRL" + "ALT" + "+"	CPU SPEED TURBO
CPU SPEED TURBO	"CTRL" + "ALT" + "-"	CPU SPEED NORMAL

## Chapter 5: Award BIOS Setup

### Award BIOS Feature

- IDE HDD AUTO Detection
- 2.88 floppy Disk Drive Support
- Quick Post
- IDE HDD Block Mode
- 2 User Type HDD
- Gate A20 Option
- Addition Information for quick reference Jumper setting
- HDD Low-level Format
- Virus Warning Feature

### Entering Setup

Power on the computer and press (Del) immediately will allow you to enter Setup. The other way to enter Setup is to power on the computer, when the below message appears briefly at the bottom of the screen during the POST (Power On Self Test), Press (Del) key or simultaneously press (Ctrl), (Alt), and (Esc) keys.

TO ENTER SETUP BEFORE BOOT PRESS CTRL-ALT-ESC OR DEL  
KEY

If the message disappears before you respond and you still wish to enter Setup, restart the system to try again by turning it OFF then ON or pressing the "RESET" button on the system case. You may also restart by simultaneously press (Ctrl), (Alt), and (Delete) keys. If you do not press the keys at the correct time and the system does not boot, an error message will be displayed and you will again be asked to,

PRESS F1 TO CONTINUE, CTRL-ALT-ESC  
OR DEL TO ENTER SETUP



ROM ISA BIOS (2136000)  
 BIOS FEATURES SETUP  
 Award Software, Inc.

Virus Warning	: Enabled	C8000-CBFFF Shadow	: Disabled
External Cache	: Enabled	CC000-CFFFF Shadow	: Disabled
Quick Power on Self Test	: Disabled	D0000-D3FFF Shadow	: Disabled
Boot Sequence	: A, C	D4000-D7FFF Shadow	: Disabled
Boot up Floppy Seek	: Enabled	D8000-DBFFF Shadow	: Disabled
Boot up Num Lock Status	: On	DC000-DFFFF Shadow	: Disabled
Boot up System Speed	: High	E0000-E3FFF Shadow	: Disabled
IDE HDD Block Mode	: Disabled	E4000-E7FFF Shadow	: Disabled
Gate A20 Option	: Normal	E8000-EBFFF Shadow	: Disabled
Memory Parity Check	: Enabled	FC000-EFFFF Shadow	: Disabled
Typematic Rate Setting	: Disabled	Esc : Quit    ↓↑→← : Select Item	
Typematic Rate (chars/sec)	: 6	F1 : Help    Pu/PD/+/- : Modify	
Typematic Delay (Msec)	: 250	F5 : Old Values (Shift) F2: Color	
Security Option	: Setup	F6 : Load BIOS Defaults	
		F7 : Load SETUP Defaults	

ROM ISA BIOS (2136000)  
 CHIPSET FEATURES SETUP  
 Award Software, Inc.

AUTO Configuration	: Enabled	
AT Clock Selection	: CLK I/5	
DRAM Read Wait State	: 1 WS	
DRAM Write Wait State	: 1 WS	
Speed Up DRAM Access	: Enabled	
CAS Delay By 1T State	: Enabled	
Hidden Refresh Option	: Enabled	
Fast AT Cycle	: Enabled	
Single ALE Control	: Disabled	
Back To Back I/O Delay	: Enabled	
Burst Wait State	: 2 WS	
CACHE Read Burst Cycle	: 2-1-1-1	Esc : Quit    ↓↑→← : Select Item
CACHE Write State	: 1 WS	F1 : Help    Pu/PD/+/- : Modify
CA32S Inactive Delay at	: Middle of T2	F5 : Old Values (Shift) F2: Color
Video BIOS Cachable	: Enabled	F6 : Load BIOS Defaults
		F7 : Load SETUP Defaults

## Hard Disk Low Level Format Utility

This Award Low-Level-Format Utility is designed as a tool to save your time formatting your hard disk. The Utility automatically looks for the necessary information of the drive you selected. The Utility also searches for bad track and list them for your reference.

Shown below is the Main Menu after you enter into Award Low-Level-Format Utility.

<p>Hard disk Low-level-format</p> <p>SELECT DRIVE</p> <p>BAD TRACK LIST</p> <p>PREFORMAT</p>
<p>Current select drive is: C</p> <p>DRIVE: C CYLINDER: 0 HEAD: 0</p>

BAD TRACKS TABLE	
NO. CYLS HEAD	

	CYLINDERS	HEADS	SECTORS	PRECOMP	LANDZONE
Drive C: 40Mb	977	5	17	300	977
Drive D: None	0	0	0	0	0

Up/Down-Select item	Enter-Accept	ESC-Exit/Abort
Copyright (c) Award Software, Inc. 1992 All Rights Reserved		