

*12 MHz Zero-wait  
80286  
Turbo Mini Mainboard*

*< Hardware Reference >*

TABLE OF CONTENTS

**12 MHz Zero-wait  
80286  
Turbo Mini Mainboard**

< Hardware Reference >

IBM PC/XT and PC/AT are registered trademarks of International Business Machines Corporation.

INTEL is registered trademark of Intel Corporation.

AND is registered trademark of Advanced Micro Devices Inc.

and is registered trademark of American Megatrends Ltd.

PHOENIX is registered trademark of Phoenix Technologies Ltd.

WARD is registered trademark of Ward Software Inc.

TABLE OF CONTENTS

I	. GENERAL SPECIFICATION .....	2
II	. MAIN BOARD JUMPER SELECTION .....	3 --- 7
III	. CONFIGURATION .....	8 --- 9
IV	. SYSTEM MEMORY MAP .....	10
V	. I/O CHANNEL .....	11
VI	. REAL TIME CLOCK .....	12
VII	. FEATURES OF VLSI CHIP SET .....	13

*IBM PC/XT and PC/AT are registered trademarks of International Business Machines corporation.*

*INTEL is registered trademark of Intel Corporation.  
AMD is registered trademark of Advanced Micro Devices Inc.  
AMI is registered trademark of American Megatrends Inc.  
PHOENIX is registered trademark of Phoenix Technologies Ltd.  
AWARD is registered trademark of Award Software Inc.*

WHAT WE POSSESSIVE THAT OTHERS WITHOUT !

- . 5 CHIPS SET FULL CMOS PROCESS LOW POWER CONSUMPTION
- . ONLY 18 NON-MEMORY COMPONENTS, 38 TOTAL COMPONENTS
- . LANDMARK PERFORMS RATE AT 15.4 (12 MHZ 0 WAIT-STATE)
- . ZERO WAIT STATE READ OPERATIONS
- . ONE WAIT STATE WRITE OPERATIONS
- . 20 mA, 150pF DRAM DRIVE CAPABILITY
- . FOUR LAYER IMPLEMENTATION FOR LOW NOISE OPERATION

## I. GENERAL SPECIFICATION


- . AMD 80286 10MHz or 12 MHz CPU
- . 6/8/12/16 MHz speed hardware selectable
- . RAM access time 0-wait and 1-wait selectable
- . Up to 4 mega byte memory on board
- . 16 mega byte expandable memory in the protect virtual address mode
- . 2 sockets for AMI, PHOENIX or AWARD BIOS, fully compatible with IBM BIOS
- . 8 I/O expansion slots
- . Socket for 80287 math processor
- . CMOS clock and calendar circuit with rechargeable battery support
- . 24-bit addressing and 16-bit data path capabilities
- . 16-level interrupts
- . 7-channel DMA (Direct Memory Access)
- . 3-programmable timers

## II. MAIN BOARD JUMPER SELECTION

### CONNECTORS AND JUMPERS

The system board has the following connectors and jumpers

JUMPER NUMBER	FUNCTION
P1	Power supply connector
J1	Keyboard connector
J2	Speaker connector
J3	Keylock / power LED
JP1	Monitor selection
JP2	One / zero-wait selection
JP3	RAM size selection
JP4	RAM size selection
JP5	RAM size selection
JP7	Hardware reset
JP8	External battery connector
JP9	Eprom size selection
TURBO CONTROL	Select CPU clock speed between 6MHz and 12 Mhz



### P1 : POWER SUPPLY CONNECTOR

Jumper P1 is used to connect to the power supply cable. The pin assignments are as follows :

PIN	ASSIGNMENT	WIRE COLOR
1	Power good	Orange
2	+ 5V	Red
3	+ 12V	Yellow
4	- 12V	Blue
5	GND	Black
6	GND	Black
7	GND	Black
8	GND	Black
9	- 5V	White
10	+ 5V	Red
11	+ 5V	Red
12	+ 5V	Red

### J1 : KEYBOARD CONNECTOR

The keyboard connector is a 5-pin, 90-degree printed circuit board (PCB) mounting, DIN connector. The assignments are as follows :

PIN	ASSIGNMENT
1	Keyboard clock
2	Keyboard data
3	Not used
4	GND
5	+5Vdc

## J2 : SPEAKER CONNECTOR

Its pin assignment as follows :

PIN	ASSIGNMENT
1	Data out
2	Not used
3	GND
4	+5Vdc

## J3 : KEYLOCK / POWER LED

The power LED and Keylock connector is a 5 pin berg strip. Its assignments are as follows :

PIN	ASSIGNMENT
1	Power LED
2	Not used
3	GND
4	Keyboard inhibit
5	GND

## JP1 : MONITOR SELECTION

Jumper JP1 is used to select a monochrome or a color graphic primary display adapter.

Jumper setting : To select the color primary adapter, place a jumper cap over JP1. To select the monochrome primary adapter, remove the jumper cap from JP1.

## JP2 : ONE / ZERO-WAIT SELECTION

Jumper JP2 is used to select 0-wait state in read operation, place a jumper cap over JP2. To select 1-wait state, remove the jumper cap from JP2.

## JP3, JP4, JP5 : RAM SIZE SELECTION

Jumpers are used together to allow you to select the amount of RAM on board. See the table below for the connecting position. Jumpers settings:

JP3	JP4	JP5	BASE MEMORY	EXPANSION	MEMORY TYPE
ON	ON	OFF	640K	3456K	BANK 0, 18 X 1M BANK 1, 18 X 1M
OFF	OFF	ON	640K	1408K	BANK 0, 18 X 1M
ON	OFF	ON	640K	384K	BANK 0, 18 X 256K BANK 1, 18 X 256K
OFF	ON	ON	640K	OK	BANK 0, 18 X 256K BANK 1, 18 X 64K
ON	ON	ON	512K	OK	BANK 0, 18 X 256K

#### JP7 : HARDWARE RESET

#### JP8 : EXTERNAL BATTERY CONNECTOR

The connector is for connecting four size "AA" batteries instead of the blue rechargeable battery. Its pin assignments are as follows :

PIN	ASSIGNMENT
1	6 Vdc
2	Not used
3	GND
4	GND

#### JP9 : EPROM SIZE SELECTION

Jumper JP9 is used to select ROM size of either 27256 or 27128 chip. To select the 27256 chip, place a jumper cap over JP9. To select the 27128 chip, remove the jumper cap from JP9.

#### TURBO CONTROL

To select turbo mode (6MHz clock speed), place a jumper cap over turbo control jumper pin 2 and pin 3. To select normal mode (12MHz clock speed), leave all the pins open.

### III. CONFIGURATION

#### 1. SYSTEM SETUP PROGRAM

A system setup program is included in the ROM BIOS of your mainboard. The setup program is used to record the configuration of your system. Use DEL key to enter this setup program while the BIOS self-test has just finished the memory test. When you have get inside the setup program, just answer each question to tell the machine what kind of devices you have got in your system. To config a harddisk system, you have to enter a right harddisk type to the setup program, find a right one from the following table.

TYPE	CYLN	HEADS	W-PCOMP	L-ZON	CAPACITY
1	306	4	120	305	10 MB
2	615	4	300	615	20 MB
3	615	6	300	615	30 MB
4	940	8	512	940	64 MB
5	940	6	512	940	48 MB
6	615	4	FFFF	615	20 MB
7	462	8	256	511	31 MB
8	733	5	FFFF	733	31 MB
9	900	15	FFFF	901	115 MB
10	820	3	FFFF	820	21 MB
11	855	5	FFFF	855	36 MB
12	855	7	FFFF	855	51 MB
13	306	8	128	319	21 MB
14	733	7	FFFF	733	44 MB
15	---	-	----	---	-----
16	612	4	0000	663	21 MB
17	977	5	300	977	42 MB
18	977	7	FFFF	977	58 MB
19	1024	7	512	1023	61 MB
20	733	5	300	732	31 MB
21	733	7	300	732	42 MB
22	733	5	300	733	31 MB
23	306	4	0000	336	10 MB
24	925	7	0000	925	56 MB
25	925	9	FFFF	925	72 MB
26	754	7	754	754	46 MB
27	754	11	FFFF	754	72 MB
28	699	7	256	699	42 MB
29	823	10	FFFF	823	71 MB
30	918	7	918	918	55 MB

TYPE	CYLN	HEADS	W-PCOMP	L-ZONE	CAPACITY
31	1024	11	FFFF	1024	98 MB
32	1024	15	FFFF	1024	133 MB
33	1024	5	1024	1024	44 MB
34	612	2	128	612	10 MB
35	1024	9	FFFF	1024	80 MB
36	1024	8	512	1024	71 MB
37	615	8	128	615	42 MB
38	987	3	987	987	25 MB
39	987	7	987	987	60 MB
40	820	6	820	820	42 MB
41	977	5	977	977	42 MB
42	981	5	981	981	42 MB
43	830	7	512	830	50 MB
44	830	10	FFFF	830	72 MB
45	917	15	FFFF	918	115 MB

IV. SYSTEM MEMORY MAP

ADDRESS RANGE	START-END	NAME	FUNCTION
000000-03FFFF	000K-256K	BANK0	SYSTEM MEMORY(256K)
040000-07FFFF	256K-512K	BANK1	SYSTEM MEMORY(256K)
080000-09FFFF	512K-640K	BANK2	SYSTEM MEMORY(128K)
0AFFFF-0BFFFF	640K-768K	VIDEO	DISPLAY CARD BUFFER (128K)
0C0000-0DFFFF	768K-896K	I/O ROM	EXPANSION ROM(128K)
0E0000-0EFFFF	896K-960K	ROM	SYSTEM USAGE(64K)
0F0000-0FFFFF	960K-1024K	ROM	BIOS(64K)
100000-11FFFF	1024K-1152K	BANK2	SYSTEM MEMORY(128K)
120000-15FFFF	1152K-1408K	BANK3	SYSTEM MEMORY(128K)
160000-FDFFFF	1408K-16146K	RAM	EXPANSION RAM (14870K)
FE0000-FEFFFF	16146K-16210K	ROM	SYSTEM USAGE(64K)
FF0000-FFFFFF	16210K-16274K	ROM	BIOS(64K)

## V. I/O CHANNELS

The I/O channel supports

- . I/O address space hex 100 to 3FF
- . 24-bit memory addresses (16MB)
- . Refresh of system memory from channel microprocessors
- . Selection of data accesses (either 8 bit or 16 bit)
- . Interrupt
- . DMA channels
- . I/O wait-state generation
- . Open-bus structure (allowing multiple microprocessors to share the system's resources, including memory)

### I/O ADDRESS MAP

HEX RANGE	DEVICES	USAGE
000-01F	DMA CONTROLLER 1	SYSTEM
020-03F	INTERRUPT CONTROLLER 1	SYSTEM
040-05F	TIMER	SYSTEM
060-06F	8042 (KEYBOARD)	SYSTEM
070-07F	REAL TIME CLOCK, NMI MASK	SYSTEM
080-09F	DMA PAGE REGISTER	SYSTEM
0A0-0BF	INTERRUPT CONTROLLER 2	SYSTEM
0C0-0DF	DMA CONTROLLER 2	SYSTEM
0F0	CLEAR MATH COPROCESSOR BUSY	SYSTEM
0F1	RESET MATH COPROCESSOR	SYSTEM
0F8-0FF	MATH COPROCESSOR	SYSTEM
1F0-1F8	FIXED DISK	I/O
200-207	GAME I/O	I/O
278-27F	PARALLELED PRINTER PORT 2	I/O
2F8-2FF	SERIAL PORT 2	I/O
300-31F	PROTOTYPE CARD	I/O
360-36F	RESERVED	I/O
378-37F	PARALLELED PRINTER PORT 1	I/O
380-38F	SDLC, BISYNCHRONOUS 2	I/O
3A0-3AF	BISYNCHRONOUS 1	I/O
3B0-3BF	MONOCHROME DISPLAY AND PRINTER CARD	I/O
3C0-3CF	RESERVED	I/O
3D0-3DF	COLOR / GRAPHICS MONITOR CARD	I/O
3F0-3F7	FLOPPY DISKETTE CONTROLLER	I/O
3F8-3FF	SERIAL PORT 1	I/O

## VI. REAL TIME CLOCK AND NONVOLATILE RAM

The real time clock MC146818 and its 64 bytes of RAM information are backed up by a battery, the internal clock circuitry uses 14 bytes while the rest is allocated to system configuration.

ADDRESS	DESCRIPTION
00	Seconds
01	Second alarm
02	Minutes
03	Minute alarm
04	Hours
05	Hour alarm
06	Day of week
07	Date of month
08	Month
09	Year
0A	Status register A
0B	Status register B
0C	Status register C
0D	Status register D
0E	Diagnostic status byte
0F	Shutdown
10	Diskette drive type byte - driver A and B
11	Reserved
12	Fixed disk type byte - driver C and D
13	Reserved
14	Equipment byte
15	Low base memory
16	High base memory
17	Low expansion memory
18	High expansion memory
19-2D	Reserved
2E-2F	2 byte CMOS checksum
30	Low expansion memory byte
31	High expansion memory byte
32	Data century byte
33	Information flags (set during power on)
34-3F	Reserved

## VII. FEATURES OF THE VLSI CHIP SET

### VL82C100

- . Fully compatible with IBM PC/AT-type designs.
- . Replaces 19 logic devices.
- . Supports 12 MHz processor clock.
- . Seven DMA channels.
- . 14 external interrupt request.
- . Three timer/counter channels.
- . Designed in CMOS for low power consumption.

### VL82C101

- . Fully compatible with IBM PC/AT-type designs.
- . Replaces 36 integrated circuits on the PC/AT-type board.
- . Supports 12 MHz processor clock.
- . Sink 20 mA on slot driver outputs.
- . Designed in CMOS for low power consumption.

### VL82C102

- . Fully compatible with IBM PC/AT-type designs.
- . Completely performs memory control function in IBM PC/AT-compatible systems.
- . Replaces 20 integrated circuits on PC/AT-type motherboard.
- . Support 12 MHz processor clock.
- . Designed in CMOS for low power consumption.

### VL82C103

- . Fully compatible with IBM PC/AT-type designs.
- . Completely performs address buffer function in IBM PC/AT-compatible systems.
- . Replaces several buffers, latches and other logic devices.
- . Supports 12 MHz processor clock.
- . Designed in CMOS for low power consumption.

### VL82C104

- . Fully compatible with IBM PC/AT-type designs.
- . Completely performs data buffer function in IBM PC/AT-compatible systems.
- . Replaces several buffers, latches and other logic devices.
- . Supports 12 MHz processor clock.
- . Designed in CMOS for low power consumption.

