



# ASM1085 Data Sheet

---

PCIE to PCI Bridge

**Copyright Notice:**

Copyright © 2008, ASMedia TECHNOLOGY INC. All Rights Reserved.

INFORMATION IN THIS DOCUMENT IS PROVIDED IN CONNECTION WITH PRODUCTS OF ASMEDIA TECHNOLOGY INC. NO LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT. EXCEPT AS PROVIDED IN ASMEDIA'S TERMS AND CONDITIONS OF SALE FOR SUCH PRODUCTS, ASMEDIA ASSUMES NO LIABILITY WHATSOEVER, AND ASMEDIA DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY, RELATING TO SALE AND/OR USE OF ASMEDIA PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

Products of ASMEDIA TECHNOLOGY INC. are not intended for use in medical, life saving, life sustaining, critical control or safety systems, or in nuclear facility applications.

ASMedia may make changes to specifications and product descriptions at any time, without notice.

ASMedia TECHNOLOGY INC. may have patents or pending patent applications, trademarks, copyrights, or other intellectual property rights that relate to the presented subject matter. The furnishing of documents and other materials and information does not provide any license, express or implied, by estoppel or otherwise, to any such patents, trademarks, copyrights, or other intellectual property rights.

Contact your local ASMedia sales office or your agent to obtain the latest specifications and before placing your product order.

Copies of documents which have an order number and are referenced in this document, or other ASMedia literature may be obtained by calling +886-2-22196088 or by visiting ASMedia's website at [www.asmedia.com.tw](http://www.asmedia.com.tw).

ASMedia and ASMedia logo are trademarks or registered trademarks of ASMedia TECHNOLOGY INC. in Taiwan and other countries.

© 2008 祥碩科技股份有限公司，著作權所有，並保留一切權利

本文資料為與祥碩科技股份有限公司之產品相關。本文並未明示或默示授權任何智慧財產權予第三人。除在祥碩科技股份有限公司對該產品提供的買賣條款及條件以外，祥碩科技股份有限公司免於擔負任何責任，且不對產品的買賣及使用做任何明示或默示的保證，包含產品適於特殊使用目的、以及產品不侵害任何專利權、著作權或其他智慧財產權。祥碩科技股份有限公司之產品不用於醫療的、救助生命的、生命維持的、安全控管系統或核子設施等用途之上。

祥碩科技股份有限公司可隨時不經通知，逕行增訂或修改產品規格及描述。

本文之相關專利權、申請中之專利權、商標權、著作權及其餘智慧財產權均屬祥碩科技股份有限公司所有。本文及其他資訊並未明示或默示的提供任何專利、商標、著作權及其餘智慧財產權之授權。

請於下產品訂單前聯絡當地的祥碩科技銷售處或代理商以取得最新的產品規格書。

本文提及之有訂單號碼之文件或其他詳細資料可參閱祥碩科技網站 [www.asmedia.com.tw](http://www.asmedia.com.tw) 或撥打 +886-2-22196088

ASMEDIA 和 ASMEDIA 商標均為祥碩科技股份有限公司在台灣和其他國家的註冊商標或商標。

**Office:**

ASMedia Technology, Inc.

6F, No.115, Minquan Rd., Xindian City, Taipei County 231, Taiwan, R.O.C.

<http://www.asmedia.com.tw>

Tel: 886-2-2219-6088

Fax: 886-2-2219-6080



**Environmentally hazardous materials are not used in this product.**

## Revision History

Rev.	Date	Description
0.1	March. 24, 2010	Initial Release
0.2	March. 31, 2010	Sync Pin diagram and Pin description
0.3	April. 16, 2010	Add Power/Reset/Clock sequence
0.4	May. 28, 2010	Change product name to ASM1083 Add legacy mode support Add PCI clock control signal Change register set
0.5	June. 14, 2010	Add register for fixed design Change GPIO11,12 to NC pin Add power consumption table
0.6	June. 23, 2010	Sync Pin list table with real chip
1.0	July.1, 2010	Formal release
1.1	July. 23, 2010	Fix Pin PE_EC_SEL and M66EN direction Remove clock sync mode
1.2	Aug. 25, 2010	Fix REXT value to 12.1K
1.3	Sep. 16, 2010	Fix GPIO2 description Package type is LQFP128
1.4	Sep. 21, 2010	Remove 66MHz feature
1.5	April. 19, 2011	Change M66EN pin description
1.6	April. 21, 2011	Add Top Marking Information
1.7	Aug. 30, 2011	Pin 47 is not VCC33, remove it
1.8	Nov. 30, 2011	Modify for B2
1.9	Feb. 6, 2012	Add Pin80 as GND; Remove "preliminary" title
2.0	May. 11, 2012	No ASPM support
2.1	Oct. 22, 2012	Modify register
2.2	June. 7,2013	Remove core power typical value
2.3	June. 18, 2013	Modify register set offset44, 45
MOD	Feb. 18, 2025	Change product name to ASM1085 and added missing pins for PCI master 4 and 5

## Table of Contents

1. General Description .....	1
2. Features .....	1
3. Package Type .....	1
4. Functional Diagram.....	2
5. Pinout Diagram.....	3
6. Pin Description.....	4
7. Function Description .....	7
8. Register Description .....	8
8.1 Register Mapping .....	8
8.2 Register Content .....	10
9. Electrical Characteristic .....	32
9.1 Recommend Operation Condition .....	32
9.2 PCI Express Differential Transmitter Output Ranges .....	32
9.3 PCI Express Differential Receiver Input Ranges .....	33
9.4 PCI Express Differential Reference Clock Input Ranges .....	33
9.5 PCI Bus Electrical Characteristics.....	34
10. Power Consumption .....	35
11. Package Information .....	36

## List of Figures

Figure1. Function Diagram.....	2
Figure2. ASM1085 .....	3
Figure3. Mechanical Specification – LQFP128L .....	36

*This page is intentionally left blank.*

## 1. General Description

Engaged in High Speed I/O solution development, Asmedia Technology is committed to enlarging product portfolio with introducing PCI Express Bridge Products. The ASM1085, x1 PCI Express to 32-bit PCI Bridge, enable users to connect legacy parallel bus devices to the advanced serial PCI Express interface. The ASM1085 is a PCI Express-to-PCI forward bridge, fully compliant with PCI-SIG PCI Express-to-PCI Bridge Specification 1.0.

## 2. Features

### General Features

- I2C Serial EEPROM support
- Extensive PME support
- 3.3/1.2V power supply
- Legacy mode support
- Industry Specifications Compliance:
  - PCI Express Base Specification Rev. 1.0a/ 1.1*
  - PCI Bus Power Management Interface Rev.2.0*
  - PCI Express Card Electromechanical Rev.2.0*
  - PCI Specification Rev.3.0*
  - PCIe to PCI/PCIX Bridge Specification Rev.1.0*
- 14mmx14mm 128-pin LQFP package
- Green package with RoHs compliance

### PCI Express Features

- x1 PCI Express lane, at 2.5GHz signaling
- Single virtual channel
- SSC support
- ECRC and Advanced Error Reporting capability
- 100-MHz differential PCI Express reference clock in
- Maximum Payload Size up to 128 bytes
- No PCIe ASPM support

### PCI Features

- Support PCI bus 33 MHz
- Support 5 PCI masters
- CLKRUN support
- PME support

## 3. Package Type

- ◇ LQFP 128L

## 4. Functional Diagram





Figure 1: Functional Diagram

## 5. Pinout Diagrams



## 6. Pin Descriptions

This section provides a detailed description of each signal. The following notations are used to describe the signal type.

I/O Type	Definition
I	Input pin
O	Output pin
B	Bi-directional pin
TS	Tri-State bidirection
STS	Sustain Tri-State, Active Low
P	Power pin
G	Ground pin
OD	Open Drain

Pin Name	Pin Number	I/O	Descriptions
<b>PCIE Signals</b>			
PREXT	91	I	External Resistor for PCIE PHY. A 12.1K ohm+/-1% external resistor should be connected this pin to ground.
PRXP	83	I	PCIE Receiver Rx+ Signal
PRXN	84	I	PCIE Receiver Rx- Signal
PTXN	87	O	PCIE Transmitter Tx- Signal
PTXP	86	O	PCIE Transmitter Tx+ Signal
PECLKP	78	I	PCIE Diffrential Clock Input+
PECLKN	79	I	PCIE Diffrential Clock Input-
PE_WAKE#	94	O	PCIE wake up signal
PE_RST#	96	I	PCIE reset, also the global reset of whole chip
PE_PWRDET#	95	I	Power detector
PE_CLKREQ#	76	O	PCIE clock request
PE_EC_SEL	75	I	PCIExpress card select
<b>PCI Signals</b>			
AD0	105	TS	PCI Data Bus
AD1	106	TS	PCI Data Bus
AD2	107	TS	PCI Data Bus
AD3	108	TS	PCI Data Bus
AD4	109	TS	PCI Data Bus
AD5	112	TS	PCI Data Bus
AD6	113	TS	PCI Data Bus
AD7	114	TS	PCI Data Bus
AD8	115	TS	PCI Data Bus
AD9	118	TS	PCI Data Bus
AD10	119	TS	PCI Data Bus
AD11	120	TS	PCI Data Bus
AD12	123	TS	PCI Data Bus
AD13	124	TS	PCI Data Bus
AD14	125	TS	PCI Data Bus
AD15	126	TS	PCI Data Bus
AD16	16	TS	PCI Data Bus
AD17	17	TS	PCI Data Bus
AD18	18	TS	PCI Data Bus

subject to change without notice

Pin Name	Pin Number	I/O	Descriptions
AD19	19	TS	PCI Data Bus
AD20	20	TS	PCI Data Bus
AD21	21	TS	PCI Data Bus
AD22	24	TS	PCI Data Bus
AD23	25	TS	PCI Data Bus
AD24	27	TS	PCI Data Bus
AD25	28	TS	PCI Data Bus
AD26	29	TS	PCI Data Bus
AD27	30	TS	PCI Data Bus
AD28	33	TS	PCI Data Bus
AD29	34	TS	PCI Data Bus
AD30	35	TS	PCI Data Bus
AD31	36	TS	PCI Data Bus
CBE0#	116	TS	PCI Command/ByteEnable
CBE1#	127	TS	PCI Command/ByteEnable
CBE2#	15	TS	PCI Command/ByteEnable
CBE3#	26	TS	PCI Command/ByteEnable
PAR	128	TS	PCI Parity
PCIRST#	38	O	PCI reset, reset all PCI slots
FRAME#	12	STS	PCI Bus Control Signal, PCI Frame, A Pullup resistor is needed.
IRDY#	11	STS	PCI Bus Control Signal, PCI Initial Ready, A Pullup resistor is needed.
TRDY#	10	STS	PCI Bus Control Signal, PCI Target Ready, A Pullup resistor is needed.
STOP#	6	STS	PCI Bus Control Signal, PCI Stop, A Pullup resistor is needed.
DEVSEL#	9	STS	PCI Bus Control Signal, PCI Device Select, A Pullup resistor is needed.
LOCK#	5	STS	PCI Bus Control Signal, PCI Lock, A Pullup resistor is needed.
SERR#	1	OD	PCI Bus Control Signal, System Error, A Pullup resistor is needed.
PERR#	4	STS	PCI Bus Control Signal, Parity Error, A Pullup resistor is needed.
PME#	37	I	PCI Wakeup Signal, Power management event. , A Pullup resistor is needed.
REQ0#	51	TS	PCI Request Signal for master 0. A Pullup resistor is needed.
GNT0#	54	O	PCI Grant Signal for master 0
REQ1#	49	TS	PCI Request Signal for master 1. A Pullup resistor is needed.
GNT1#	50	O	PCI Grant Signal for master 1
REQ2#	45	TS	PCI Request Signal for master 2. A Pullup resistor is needed.
GNT2#	48	O	PCI Grant Signal for master 2
REQ3#	43	TS	PCI Request Signal for master 3. A Pullup resistor is needed.
GNT3#	44	O	PCI Grant Signal for master 3
REQ4#	39	TS	PCI Request Signal for master 4. A Pullup resistor is needed.
GNT4#	40	O	PCI Grant Signal for master 4
INTA#	58	OD	Interrupt A. A Pullup resistor is needed.
INTB#	57	OD	Interrupt B. A Pullup resistor is needed.
INTC#	56	OD	Interrupt C. A Pullup resistor is needed.
INTD#	55	OD	Interrupt D. A Pullup resistor is needed.
CLKRUN#	59	STS	PCI Clock Run Control Signal. A Pullup resistor is needed.
CLKRUN_EN#	60	I	A Strapping Pin. PCI Clock Run Control Enable
M66EN	117	I	No 66MHz support, connect to GND
PCICLK	72	I	PCI 33MHz Input Clock. PCI Clock Source.
CLK100SEL	73	I	Test pin, a pull down resistor is needed
<b>MISC Signals</b>			
TEST_EN	74	I	Test Mode Enable
SMB_CLK	93	B	I2C Clock Signal
SMB_DATA	92	B	I2C Data Signal

subject to change without notice

Pin Name	Pin Number	I/O	Descriptions
GPI00	61	O	GPI00, If TEST_EN=0, It's PCI Output Clock for Master 0 (PCLK00). If TEST_EN=1, It's test mode function select
GPI01	62	O	GPI01, If TEST_EN=0, It's PCI Output Clock for Master 1 (PCLK01). If TEST_EN=1, It's test mode function select
GPI02	65	O	GPI02, If TEST_EN=0, It's PCI Output Clock for Master 2 (PCLK02). If TEST_EN=1, It's test mode function select
GPI03	66	O	GPI03, If TEST_EN=0, It's PCI Output Clock for Master 3 (PCLK03). If TEST_EN=1, It's test mode function select
GPI04	67	O	GPI04, If TEST_EN=0, It's PCI Output Clock for Master 4 (PCLK04). If TEST_EN=1, It's test mode function select
GPI05	68	B	Reaserved For Debug
GPI06	69	B	Reaserved For Debug
GPI07	70	B	Reaserved For Debug
I2CCLKSEL	71	B	I2C clock select; 0: 67.5KHz; 1: 135KHz
PCLK1EN	99	B	1. PCLK01 Clock enable; 2.Reaserved For Debug
PCLK2EN	100	B	1. PCLK02 Clock enable; 2.Reaserved For Debug
PCLK3EN	101	B	1. PCLK03 Clock enable; 2.Reaserved For Debug
PCLK4EN	104	B	1. PCLK04 Clock enable; 2.Reaserved For Debug
VCC12	8, 47, 77, 103	<b>P</b>	1.2V Power Input, core power
VCC12P	81,89	<b>P</b>	1.2V Power Input for PCIE PHY
VCC33	3, 14, 23, 32, 42, 53, 64, 98, 111, 122	<b>P</b>	3.3V Power Input, for PCI Pad
VCC33P	90	<b>P</b>	3.3V Power Input, for PCIE PHY
GND	2, 7, 13, 22, 31, 41, 46, 52, 63, 80, 97, 110, 102, 121	<b>G</b>	Ground, for Core and PCI Pad
GND A	82, 85, 88	<b>G</b>	Ground, for PCIE PHY & PLL

## 7. Function Description

1. The content described here are only for specific functions in ASM1085. PCIE and PCI bus functions can be found in PCIE and PCI specifications.


2. “PEWAKE#” signal of chipset can be directly connected with PCI device signal “PME#”. It implies PCI devices can wake up system directly.

3. PCLK1(GPIO1), PCLK2(GPIO2), PCLK3(GPIO3), PCLK4(GPIO4) can be disabled if there is no slot or onboard device if there is no slot or onboard device connected. It can save unnecessary power.

	CLOCK ON	CLKOCK OFF
PCLKO1	PCLK1EN = VCC or NC	PCLK1EN = GND
PCLKO2	PCLK2EN = VCC or NC	PCLK2EN = GND
PCLKO3	PCLK3EN = VCC or NC	PCLK3EN = GND
PCLKO4	PCLK4EN = VCC or NC	PCLK4EN = GND

4. About I2C bus. ASM1085 is a I2C master before PCIRST is released. To read table in EEPROM (if exist) to set vendor defined value into register area. It changes to a I2C slave for debugging after PCIRST is released.

### 5. Power/Reset/Clock sequence



1. No sequence among 3.3V, 1.2V, PECLKP/N and PCICLK, but be sure these four signals are ready before PE\_RST is released.
2. PCIRST# will be released after PE\_RST is released.

## 8. Register Description

Register Attribute	Definition
RO	<b>Read-only register:</b> Register bits are read-only and cannot be altered by software.
RW	<b>Read-Write register:</b> Register bits are read-write and may be either set or cleared by software to the desired state.
HwInit	<b>Hardware Initialized:</b> Register bits are initialized by firmware or hardware mechanisms such as pin strapping or serial EEPROM. Bits are read-only after initialization and can only be reset (for write-once by firmware) with Fundamental Reset.
RW1C	<b>Read-only status, Write-1-to-clear status register:</b> Register bits indicate status when read, a set bit indicating a status event may be cleared by writing a 1. Writing a 0 to RW1C bits has no effect.
ROS	<b>Sticky – Read-only register:</b> Registers are read-only and cannot be altered by software. Registers are not initialized or modified by hot reset.
RWS	<b>Sticky – Read-Write register:</b> Registers are read-write and may be either set or cleared by software to the desired state. Bits are not initialized or modified by hot reset.
RW1CS	<b>Sticky – Read-only status, Write-1-to-clear status register:</b> Registers indicate status when read, a set bit indicating a status event may be cleared by writing a 1. Writing a 0 to RW1CS bits has no effect. Bits are not initialized or modified by hot reset.
RWO	<b>Read-Write Once:</b> Register can only be written once
Rsvd	<b>Reserved:</b> Reserved for future RW

### 8.1 Register Mapping

Type1 Configuration Header Register				
31:24	23:16	15:8	7:0	Byte Offset
Device ID		Vendor ID		000h
Status		Command		004h
Class Code			Revision ID	008h
			Cache Line	00Ch
Base Address 0				010h
Base Address 1				014h
Sec Bus Latency	Sub Bus Number	Sec Bus Number	Prim Bus Number	018h
Secondary Status		I/O Limit	I/O Base	01Ch
Memory Limit		Memory Base		020h
Prefetchable Memory Limit		Prefetchable Memory Base		024h
Prefetchable Base Upper 32-bits				028h
Prefetchable Limit Upper 32-bits				02Ch
I/O Limit Upper 16-bits		I/O Base Upper 16-bits		030h
			Capabilities PTR	034h
Expansion ROM base address				038h

subject to change without notice

Bridge Control		Interrupt Pin	Interrupt Line	03Ch
<b>MSI Capability Register</b>				
31:24	23:16	15:8	7:0	Byte Offset
Message Control		Next Pointer	Capabilities ID	050h
Message Address				054h
Message Upper Address				058h
Message Data				05Ch
<b>Power Management Capability Register</b>				
31:24	23:16	15:8	7:3	2:0
Capabilities Register		Next Pointer	Capabilities ID	078h
Data	PM Control/Status Bridge Extensions	Power Management Status & Control		07Ch
<b>PCI Express Capability Register</b>				
31:24	23:16	15:8	7:0	Byte Offset
Capabilities Register		Next Pointer	Capabilities ID	080h
Device Capabilities				084h
Device Status		Device Control		088h
Link Capabilities				08Ch
Link Status		Link Control		090h
Slot Capabilities				094h
Slot Status		Slot Control		098h
<b>SSID / SSVID Capability Register</b>				
31:24	23:16	15:8	7:0	Byte Offset
		Next Pointer	Capabilities ID	0C0h
SSID		SSVID		0C4h
<b>Virtual Channel Capability Register</b>				
31:24	23:16	15:8	7:0	Byte Offset
Next Point & Version		Extended Capabilities ID		100h
		Port VC Capabilities 1		104h
VAT offset			VC arbit. cap	108h
Port VC Status		Port VC Control		10Ch
PAT offset 0	VC Resource Capability Register 0			110h
VC Resource Control Register 0				114h
VC Resource Status Register				118h
<b>PCI Express AER Extended Capability Register</b>				
31:24	23:16	15:8	7:0	Byte Offset
PCI Express Enhanced Capability Header				200h
Uncorrectable Error Status Register				204h
Uncorrectable Error Mask Register				208h
Uncorrectable Error Severity Register				20Ch
Correctable Error Status Register				210h
Correctable Error Mask Register				214h
Advanced Error Capabilities and Control Register				218h
Header Log Register				21Ch
				220h
				224h
				228h
Secondary Uncorrectable Error Status Register				22Ch
Secondary Uncorrectable Error Mask Register				230h
Secondary Uncorrectable Error Severity Register				234h
Secondary Error Capabilities and Control Register				238h

subject to change without notice

Secondary Header Log Register				23Ch
				240h
				244h
				248h
<b>TOP Register</b>				
31:24	23:16	15:8	7:0	Byte Offset
				260h
		Clock Control	Interrupt MAP	264h

## 8.2 Register Content

### 8.2.1 Type1 Configuration Header Registers

**Register Name:** Vendor ID

**Address:** OFFSET 00h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:0	RO	Vendor ID	16'h 1B21

**Register Name:** Device ID

**Address:** OFFSET 02h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:0	RO	Device ID	16'h 1080

**Register Name:** Command

**Address:** OFFSET 04h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:11	Rsvd	Reserved	5'h00
10	RW	Interrupt Disable	0
9	RO	Fast Back-to-Back Transaction Enable	0
7	RW	SERR# Enable	0
6	RW	Parity Error Response	0
5	RO	VGA Palette Snoop	0
4	RW	Memory Write and Invalidate	0
3	RO	Special Cycle Enable	0
2	RW	Bus Master Enable	0
1	RW	Memory Space Enable	0
0	RW	I/O Space Enable	0

**Register Name:** Status

**Address:** OFFSET 06h

**Size:** 16 bits

Bit	Attrib	Description	Default
15	RW1C	Detected Parity Error	0
14	RW1C	Signaled System Error	0
13	RW1C	Received Master-Abort	0
12	RW1C	Received Target-Abort	0
11	RW1C	Signaled Target-Abort	0
10:9	RO	DEVSEL# Timing	0
8	RW1C	Master Data Parity Error	0
7	RO	Fast Back-to-Back Transaction Capable	0
6	Rsvd	Reserved	0
5	RO	66 MHz Capable	0
4	RO	Capabilities List	1
3	RO	Interrupt Status	0
2:0	Rsvd	Reserved	3'h0

**Register Name:** Class Code

**Address:** OFFSET 09h

**Size:** 24 bits

Bit	Attrib	Description	Default
23:16	RO	Class Code	8'h06
15:8	RO	Sub-Class Code	8'h04
7:0	RO	Programming Interface	8'h00

**Register Name:** Cache Line

**Address:** OFFSET 0Ch

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RW	Cache Line	8'h00

**Register Name:** Base Address 0

**Address:** OFFSET 10h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:0	RO	Base Address 0	32'h00000000

**Register Name:** Base Address 1

**Address:** OFFSET 14h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:0	RO	Base Address 1	32'h00000000

**Register Name:** Primary Bus Number

**Address:** OFFSET 18h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RW	Primary Bus Number	8'h00

**Register Name:** Secondary Bus Number

**Address:** OFFSET 19h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RW	Secondary Bus Number	8'h00

**Register Name:** Subordinate Bus Number

**Address:** OFFSET 1Ah

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RW	Subordinate Bus Number	8'h00

**Register Name:** Secondary Latency Timer

**Address:** OFFSET 1Bh

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RW	Secondary Latency Timer	8'h00

**Register Name:** I/O Base and I/O Limit

**Address:** OFFSET 1Ch

**Size:** 16 bits

Bit	Attrib	Description	Default
15:8	RW	I/O Limit	8'h00
7:0	RW	I/O Base	8'h00

**Register Name:** Secondary Status

**Address:** OFFSET 1Eh

**Size:** 16 bits

Bit	Attrib	Description	Default
15	RW1C	Detected Parity Error	0
14	RW1C	Received System Error	0
13	RW1C	Received Master-Abort	0
12	RW1C	Received Target-Abort	0
11	RW1C	Signaled Target-Abort	0
10:9	RO	DEVSEL Timing	2'b00
8	RW1C	Master Data parity Error	0
7	RO	Fast Back-to-Back Transactions Capable	0

subject to change without notice

6	Rsvd	Reserved	0
5	RO	66 MHz Capable	1
4:0	Rsvd	Reserved	5'h00

**Register Name:** Memory Base and Memory Limit  
**Address:** OFFSET 20h  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:16	RW	Memory Limit	16'h0000
15:0	RW	Memory Base	16'h0000

**Register Name:** Prefetchable Memory Base and Prefetchable Memory Limit  
**Address:** OFFSET 24h  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:16	RW	Prefetchable Memory Limit	16'h0000
15:0	RW	Prefetchable Memory Base	16'h0000

**Register Name:** Prefetchable Base Upper 32-bits  
**Address:** OFFSET 28h  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:0	RW	Prefetchable Base Upper 32-bits	32'h00000000

**Register Name:** Prefetchable Limit Upper 32-bits  
**Address:** OFFSET 2Ch  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:0	RW	Prefetchable Limit Upper 32-bits	32'h00000000

**Register Name:** I/O Base Upper 16-bits and I/O Limit Upper 16bits  
**Address:** OFFSET 30h  
**Size:** 16 bits

Bit	Attrib	Description	Default
15:8	RW	I/O Limit Upper 16-bits	8'h00
7:0	RW	I/O Base Upper 16-bits	8'h00

**Register Name:** Capabilities Pointer

subject to change without notice

**Address:** OFFSET 34h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Capabilities Pointer	8'h50

**Register Name:** Expansion ROM base address

**Address:** OFFSET 38h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:0	RW	Expansion ROM base address	32'h00000000

**Register Name:** Interrupt Line

**Address:** OFFSET 3Ch

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RW	Interrupt Line	8'h00

**Register Name:** Interrupt Pin

**Address:** OFFSET 3Dh

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Interrupt Pin	8'h01

**Register Name:** Bridge Control

**Address:** OFFSET 3Eh

**Size:** 16 bits

Bit	Attrib	Description	Default
15:12	Rsvd	Reserved	4'h0
11	RW	Discard Timer SERR# Enable	0
10	RW1C	Discard Timer Status	0
9	RW	Secondary Discard Timer	0
8	RO	Primary Discard Timer	0
7	RW	Fast Back-to-Back Enable	0
6	RW	Secondary Bus Reset	0
5	RW	Master-Abort Mode	0
4	RW	VGA 16-bit Decode	0
3	RW	VGA Enable	0
2	RW	ISA Enable	0
1	RW	SERR# Enable	0
0	RW	Parity Error Response Enable	0



## 8.2.2 Specific registers

**Register Name:** Hiding register

**Address:** OFFSET 40h

**Size:** 8 bits

Bit	Attrib	Description	Default
7	Rsvd	Reserved	
6	RW	Patch subtractive decode enable (Legacy enable)	1'b0
5	RW	Set zero on device number field with type1 configuration cycle	1'b1
4	RW	Reserved	
3	RW	Reserved	
2	RW	Hiding Device 2 : masking AD18	1'b0
1	RW	Hiding Device 1 : masking AD17	1'b0
0	RW	Hiding Device 0 : masking AD16	1'b0

**Register Name:** Legacy mode register

**Address:** OFFSET 41h

**Size:** 8 bits

Bit	Attrib	Description	Default
7	Rsvd	Reserved	
6	RW	Supported SSID/SSVID capability register set when legacy mode is enabled. 0: disable 1: enable	1'b0
5	RW	In legacy mode enable INTx message upward to TX when set 1 and offset 40[6] set 1.	1'b0
4	RW	In legacy mode enable PME message upward to TX when set 1 and offset 40[6] set 1.	1'b0
3	Rsvd	Reserved	
2	RW	PCI pad with internal pull-up resistance enable	1'b0
1	RW	Legacy policy configuration	1'b0
0	RW	Legacy policy configuration	1'b0

**Register Name:** GPIO PAD register

**Address:** OFFSET 44h

**Size:** 8 bits

Bit	Attrib	Description	Default
7	RW	GPIO7 PAD output	1'b0
6	RW	GPIO6 PAD output	1'b0
5	RW	GPIO5 PAD output	1'b0
4	RW	GPIO4 PAD output	1'b0
3	RW	GPIO7 PAD output enable	1'b0
2	RW	GPIO6 PAD output enable	1'b0
1	RW	GPIO5 PAD output enable	1'b0
0	RW	GPIO4 PAD output enable 0: input 1:output	1'b0

**Register Name:** GPIO PAD register

**Address:** OFFSET 45h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:4	Rsvd	Reserved	
3	RO	GPIO7 PAD input	1'b0
2	RO	GPIO6 PAD input	1'b0
1	RO	GPIO5 PAD input	1'b0
0	RO	GPIO4 PAD input	1'b0

### 8.2.3 MSI Capability Registers

**Register Name:** Capabilities ID

**Address:** OFFSET 50h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Capabilities ID	8'h05

**Register Name:** Next Pointer

**Address:** OFFSET 51h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Next Pointer	8'h78

**Register Name:** Message Control

**Address:** OFFSET 52h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:8	Rsvd	Reserved	16'h0000
7	RO	64-bit Address Capable	1
6:4	RW	Multiple Message Enable	3'h0
3:1	RO	Multiple Message Capable	3'h0
0	RW	MSI Enable	0

**Register Name:** Message Address

**Address:** OFFSET 54h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:0	RW	Message Address	32'h00000000

**Register Name:** Message Upper Address

**Address:** OFFSET 58h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:0	RW	Message Upper Address	32'h00000000

**Register Name:** Message Data

**Address:** OFFSET 5Ch

**Size:** 16 bits

Bit	Attrib	Description	Default
15:0	RW	Message Data	16'h0000

## 8.2.4 Power Management Capability Registers

**Register Name:** Capabilities ID

**Address:** OFFSET 78h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Capabilities ID	8'h01

**Register Name:** Next Pointer

**Address:** OFFSET 79h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Next Pointer	8'h80

**Register Name:** Power Management Capabilities

**Address:** OFFSET 7Ah

**Size:** 16 bits

Bit	Attrib	Description	Default
15:11	RO	PME Support Bit[11] D0 support PME message Bit[12] D1 support PME message Bit[13] D2 support PME message Bit[14] D3(hot) support PME message Bit[15] D3(cold) support PME message	5'h1F
10	RO	D2 Support	1
9	RO	D1 Support	1
8:6	RO	Aux Current	3'b000
5	RO	Device-Specific Initialization	1
4	Rsvd	Reserved	0
3	RO	PME Clock	0
2:0	RO	PCI PM spec. 1.2	3'b011

**Register Name:** Power Management Control and Status

**Address:** OFFSET 7Ch

**Size:** 32 bits

Bit	Attrib	Description	Default
31:24	Rsvd	Reserved	8'h00
23	RO	BPCC_EN	0
22	RO	B2_B3#	0
21:16	Rsvd	Reserved	5'h00
15	RW1C	PME Status	0
14:13	RO	Data Scale	2'b00
12:9	RW	Data Scale	4'h0
8	RW	PME Enable	0
7:4	Rsvd	Reserved	0

subject to change without notice

3	RW	No Soft Reset	1
2	Rsvd	Reserved	0
1:0	RW	Power State Bit[1:0] = 2'b00 PMState D0 Bit[1:0] = 2'b01 PMState D1 Bit[1:0] = 2'b10 PMState D2 Bit[1:0] = 2'b11 PMState D3	2'b00

### 8.2.5 PCI Express Capability Registers

**Register Name:** Capabilities ID  
**Address:** OFFSET 80h  
**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Capabilities ID	8'h10

**Register Name:** Next Pointer  
**Address:** OFFSET 81h  
**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Next Pointer	8'hC0

**Register Name:** Capabilities Registers  
**Address:** OFFSET 82h  
**Size:** 16 bits

Bit	Attrib	Description	Default
15:14	Rsvd	Reserved	2'b00
13:9	RO	Interrupt Message Number	5'h00
8	RO	Slot Implemented	0
7:4	RO	Device Port Type	4'h7
3:0	RO	Capability Version	4'h1

**Register Name:** Capabilities Registers  
**Address:** OFFSET 84h  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:28	Rsvd	Reserved	4'h0
27:26	RO	Captured Slot Power Limit Scale	2'b00
25:18	RO	Captured Slot Power Limit Value	8'h00
16:17	Rsvd	Reserved	2'b00
15	RO	Role-Base Error Reporting	1
14	RO	Power Indicator Present	0
13	RO	Attention Indicator Present	0
12	RO	Attention Button Present	0
11:9	RO	Endpoint L1 Acceptable Latency	3'b000

subject to change without notice

8:6	RO	Endpoint L0s Acceptable Latency	3'b000
5	RO	Extended Tag Field Supported	0
4:3	RO	Phantom Function Supported	2'b00
2:0	RO	Max Payload Size Supported	3'b000

**Register Name:** Device Control  
**Address:** OFFSET 88h  
**Size:** 16 bits

Bit	Attrib	Description	Default
15	RW	Bridge Configuration Retry Enable	0
14:12	RW	Max Read Request Size	3'b010
11	RW	Enable No Snoop	1
10	RW	Auxiliary (AUX) Power PM Enable	0
9	RW	Phantom Function Enable	0
8	RW	Extended Tag Field Enable	0
7:5	RW	Max Payload Size	3'b000
4	RW	Enable Relaxed Ordering	1
3	RW	Unsupported Request (UR) Reporting Enable	0
2	RW	Fatal Error Reporting Enable	0
1	RW	Non-Fatal Error Reporting Enable	0
0	RW	Correctable Error Reporting Enable	0

**Register Name:** Device Status  
**Address:** OFFSET 8Ah  
**Size:** 16 bits

Bit	Attrib	Description	Default
15:6	Rsvd	Reserved	10'h000
5	RO	Transactions Pending	0
4	RO	Aux Power Detected	0
3	RW1C	Unsupported Request (UR) Detected	0
2	RW1C	Fatal Error Detected	0
1	RW1C	Non-Fatal Error Detected	0
0	RW1C	Correctable Error Detected	0

**Register Name:** Link Capabilities  
**Address:** OFFSET 8Ch  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:24	RO	Port Number	8'h01
23:21	Rsvd	Reserved	3'b000

subject to change without notice

20	RO	Data Link Layer Link Active Reporting Capable	0
19	RO	Surprise Down Error Reporting capable	0
18	RO	Clock Power Management	0
17:15	RO	L1 Exit Latency	3'b001
14:12	RO	L0s Exit Latency	3'b101
11:10	RO	Active State Power Management (ASPM) Support	2'b11
9:4	RO	Maximum Link Width	6'h01
3:0	RO	Maximum Link Speed	4'h1

**Register Name:** Link Control  
**Address:** OFFSET 90h  
**Size:** 16 bits

Bit	Attrib	Description	Default
15:9	Rsvd	Reserved	7'h00
8	RW	Enable Clock Power Management	0
7	RW	Extended Sync.	0
6	RW	Common Clock Configuration	0
5	RO	Retrain Link	0
4	RW	Link Disable	0
3	RW	Read Completion Boundary (RCB)	0
2	Rsvd	Reserved	0
1:0	RW	Active State Power Management (ASPM) Control Bit[1:0] = 2'b00 Disable Bit[1:0] = 2'b01 L0s Entry Enable Bit[1:0] = 2'b10 L1 Entry Enable Bit[1:0] = 2'b11 L0s and L1 Entry Enable	2'b00

**Register Name:** Link Status  
**Address:** OFFSET 92h  
**Size:** 16 bits

Bit	Attrib	Description	Default
15:14	Rsvd	Reserved	2'b00
13	RO	Data Link Layer Link Active	0
12	RO	Slot Clock Configuration	0
11	RO	Link Training	0
10	RO	Training Error	0
9:4	RO	Negotiated Link Width	0
3:0	RO	Link Speed	4'h1

**Register Name:** Slot Capabilities  
**Address:** OFFSET 94h  
**Size:** 32 bits

subject to change without notice

Bit	Attrib	Description	Default
31:19	Rsvd	Reserved	13'h0000
18	RO	No Command Completed Support	0
17	RO	Electromechanical Interlock Present	0
16:15	RO	Slot Power Limit Scale	2'b00
14:7	RO	Slot Power Limit Value	8'h00
6	RO	Hot Plug Capable	0
5	RO	Hot Plug Surprise	0
4	RO	Power Indicator Present	0
3	RO	Attention Indicator Present	0
2	RO	MRL Sensor Present	0
1	RO	Power Controller Present	0
0	RO	Attention Button Present	0

**Register Name:** Slot Control

**Address:** OFFSET 98h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:13	Rsvd	Reserved	3'b000
12	RW	Data Link Layer State Changed Enable	0
11	RO	Electromechanical Interlock Control	0
10	RW	Power Controller Control	0
9:8	RW	Power indicator Control	2'b11
7:6	RW	Attention Indicator Control	2'b11
5	RW	Hot Plug Interrupt Enable	0
4	RW	Command Completed Interrupt Enable	0
3	RW	Presence Detect Changed Enable	0
2	RW	MRL Sensor Changed Enable	0
1	RW	Power Fault Detected Enable	0
0	RW	Attention Button Pressed Enable	0

**Register Name:** Slot Status

**Address:** OFFSET 9Ah

**Size:** 16 bits

Bit	Attrib	Description	Default
15:9	Rsvd	Reserved	7'h00
8	RW	Data Link Layer State Changed	0
7	RW	Electromechanical Interlock status	0
6	RW	Presence Detect State	0
5	RW	MRL Sensor State	0
4	RW1C	Command Completed	0
3	RW1C	Presence Detect Changed	0
2	RW1C	MRL Sensor Changed	0
1	RW1C	Power Controller Detected	0

subject to change without notice

0	RW1C	Attention Button Pressed	0
---	------	--------------------------	---

## 8.2.6 SSID / SSVID Capability Registers

**Register Name:** Capabilities ID  
**Address:** OFFSET C0h  
**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Capabilities ID	8'h0D

**Register Name:** Next Pointer  
**Address:** OFFSET C1h  
**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Next Pointer	8'h00

**Register Name:** SSVID  
**Address:** OFFSET C4h  
**Size:** 16 bits

Bit	Attrib	Description	Default
15:0	RO	SubSystem Vender ID	16'h0000

**Register Name:** SSID  
**Address:** OFFSET C6h  
**Size:** 8 bits

Bit	Attrib	Description	Default
15:0	RO	SubSystem ID	16'h0000

## 8.2.7 Virtual Channel Capability Registers

**Register Name:** Extended Capabilities ID

**Address:** OFFSET 100h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:0	RO	Extended Capabilities ID	16'h0002

**Register Name:** Next Pointer and Version

**Address:** OFFSET 102h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:4	RO	Next Capability offset	12'h200
3:0	RO	Capability Version	4'h1

**Register Name:** Port VC Capability Register 1

**Address:** OFFSET 104h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:12	Rsvd	Reserved	4'h0
11:10	RO	Port Arbitration Table Entry Size	2'b00
9:8	RO	Reference Clock	2'b00
7	Rsvd	Reserved	0
6:4	RO	Low Priority Extended VC Count	3'b000
3	Rsvd	Reserved	0
2:0	RO	Extended VC Count	8'h00

**Register Name:** VC Arbitration Capability

**Address:** OFFSET 108h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	VC Arbitration Capability	8'h00

**Register Name:** VC Arbitration Table Offset

**Address:** OFFSET 10Bh

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	VC Arbitration Table Offset	8'h00

**Register Name:** Port VC Control

**Address:** OFFSET 10Ch

**Size:** 16 bits

Bit	Attrib	Description	Default
-----	--------	-------------	---------

subject to change without notice

15:4	Rsvd	Reserved	12'h000
3:1	RW	VC Arbitration Select	3'b000
0	RW	Load VC Arbitration Table	0

**Register Name:** Port VC Status

**Address:** OFFSET 10Eh

**Size:** 16 bits

Bit	Attrib	Description	Default
15:1	Rsvd	Reserved	15'h0000
0	RO	VC Arbitration Table Status	0

**Register Name:** VC Resource Capability Register 0

**Address:** OFFSET 110h

**Size:** 24 bits

Bit	Attrib	Description	Default
23	Rsvd	Reserved	0
22:16	RO	Maximum Time Slots	7'h00
15	RO	Reject Snoop Transactions	0
14	RO	Advanced Packet Switching	0
13:8	Rsvd	Reserved	6'h00
7:0	RO	Port Arbitration Capability	8'h00

**Register Name:** Port Arbitration Table Offset 0

**Address:** OFFSET 113h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:0	RO	Port Arbitration Table Offset	8'h00

**Register Name:** VC Resource Control Register 0

**Address:** OFFSET 114h

**Size:** 32 bits

Bit	Attrib	Description	Default
31	RW	VC Enable	1
30:27	Rsvd	Reserved	4'h0
26:24	RW	VC ID	3'b000
23:20	Rsvd	Reserved	4'h0
19:17	RW	Port Arbitration Select	3'b000
16	RW	Load Port Arbitration Table	0
15:8	Rsvd	Reserved	12'h000
7:0	RW	TC/VC Map	8'hFF

**Register Name:** VC Resource Status Register 0

**Address:** OFFSET 11Ah

**Size:** 16 bits

subject to change without notice

Bit	Attrib	Description	Default
15:2	Rsvd	Reserved	14'h0000
1	RO	VC Negotiation Pending	1
0	RO	Port Arbitration Table Status	0

### 8.2.8 PCI Express AER Extended Capability Registers

**Register Name:** Extended Capabilities ID

**Address:** OFFSET 200h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:0	RO	Extended Capabilities ID	16'h0001

**Register Name:** Next Pointer and Version

**Address:** OFFSET 102h

**Size:** 16 bits

Bit	Attrib	Description	Default
15:4	RO	Next Capability offset	12'h000
3:0	RO	Capability Version	4'h1

**Register Name:** Uncorrectable Error Status

**Address:** OFFSET 204h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:21	Rsvd	Reserved	11'h000
20	RW1C	Unsupported Request Error Status	0
19	RW1C	ECRC Error Status	0
18	RW1C	Malformed TLP Status	0
17	RW1C	Receiver Overflow Status	0
16	RW1C	Unexpected Completion Status	0
15	RW1C	Completer Abort Status	0
14	RW1C	Completion Timeout Status	0
13	RW1C	Flow Control Protocol Error Status	0
12	RW1C	Poisoned TLP Status	0
11:5	Rsvd	Reserved	7'h00
4	RW1C	Data Link Protocol Error Status	0
3:1	Rsvd	Reserved	4'h0
0	Undef	Undefined	Undefined

**Register Name:** Uncorrectable Error Mask

**Address:** OFFSET 208h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:21	Rsvd	Reserved	11'h000
20	RW	Unsupported Request Error Mask	0
19	RW	ECRC Error Mask	0
18	RW	Malformed TLP Mask	0
17	RW	Receiver Overflow Mask	0
16	RW	Unexpected Completion Mask	0
15	RW	Completer Abort Mask	0
14	RW	Completion Timeout Mask	0
13	RW	Flow Control Protocol Error Mask	0
12	RW	Poisoned TLP Mask	0

subject to change without notice

11:5	Rsvd	Reserved	7'h00
4	RW	Data Link Protocol Error Mask	0
3:1	Rsvd	Reserved	4'h0
0	Undef	Undefined	Undefined

**Register Name:** Uncorrectable Error Severity

**Address:** OFFSET 20Ch

**Size:** 32 bits

Bit	Attrib	Description	Default
31:21	Rsvd	Reserved	11'h000
20	RW	Unsupported Request Error Severity	0
19	RW	ECRC Error Severity	0
18	RW	Malformed TLP Severity	1
17	RW	Receiver Overflow Severity	1
16	RW	Unexpected Completion Severity	0
15	RW	Completer Abort Severity	0
14	RW	Completion Timeout Severity	0
13	RW	Flow Control Protocol Error Severity	1
12	RW	Poisoned TLP Severity	0
11:5	Rsvd	Reserved	7'h00
4	RW	Data Link Protocol Error Severity	1
3:1	Rsvd	Reserved	4'h0
0	Undef	Undefined	Undefined

**Register Name:** Correctable Error Status

**Address:** OFFSET 210h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:14	Rsvd	Reserved	18'h00000
13	RW1C	Advisory Non-Fatal Error Status	0
12	RW1C	Replay Timer Timeout Status	0
11:9	Rsvd	Reserved	3'b000
8	RW1C	REPLAY_NUM Rollover Status	0
7	RW1C	Bad DLLP Status	0
6	RW1C	Bad TLP Status	0
5:1	Rsvd	Reserved	5'h00
0	RW1C	Receiver Error Status	0

**Register Name:** Correctable Error Mask

**Address:** OFFSET 214h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:14	Rsvd	Reserved	18'h00000
13	RW	Advisory Non-Fatal Error Mask	1
12	RW	Replay Timer Timeout Mask	0
11:9	Rsvd	Reserved	3'b000
8	RW	REPLAY_NUM Rollover Mask	0
7	RW	Bad DLLP Mask	0
6	RW	Bad TLP Mask	0

subject to change without notice

5:1	Rsvd	Reserved	5'h00
0	RW1C	Receiver Error Mask	0

**Register Name:** Advanced Error Capabilities and Control

**Address:** OFFSET 218h

**Size:** 32 bits

Bit	Attrib	Description	Default
31:9	Rsvd	Reserved	23'b000000
8	RW	ECRC Check Enable	0
7	RO	ECRC Check Capable	0
6	RW	ECRC Generation Enable	0
5	RO	ECRC Generation Capable	0
4:0	RO	First Error Pointer	5'h00

**Register Name:** Header Log Register

**Address:** OFFSET 21Ch

**Size:** 128 bits

Bit	Attrib	Description	Default
127:0	RO	Header of TLP Associated with Error	128'h0

**Register Name:** Secondary Uncorrectable Error Status

**Address:** OFFSET 22Ch

**Size:** 32 bits

Bit	Attrib	Description	Default
31:14	Rsvd	Reserved	18'h00000
13	RW1C	Internal Bridge Error Status	0
12	RW1C	SERR# Assertion Detected	0
11	RW1C	PERR# Assertion Detected	0
10	RW1C	Delayed Transaction Discard Timer Expired Status	0
9	RW1C	Uncorrectable Address Error Status	0
8	RW1C	Uncorrectable Attribute Error Status	0
7	RW1C	Uncorrectable Data Error Status	0
6	RW1C	Uncorrectable Split Completion Message Data Error Status	0
5	RW1C	Unexpected Split Completion Error Status	0
4	Rsvd	Reserved	0
3	RW1C	Received Master-Abort Status	0
2	RW1C	Received Target-Abort Status	0
1	RW1C	Master-Abort on Split Completion Status	0
0	RW1C	Target-Abort on Split Completion Status	0

**Register Name:** Secondary Uncorrectable Error Mask  
**Address:** OFFSET 230h  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:14	Rsvd	Reserved	18'h00000
13	RW	Internal Bridge Error Mask	0
12	RW	SERR# Assertion Detected Mask	1
11	RW	PERR# Assertion Detected Mask	0
10	RW	Delayed Transaction Discard Timer Expired Mask	1
9	RW	Uncorrectable Address Error Mask	1
8	RW	Uncorrectable Attribute Error Mask	1
7	RW	Uncorrectable Data Error Mask	1
6	RW	Uncorrectable Split Completion Message Data Error Mask	0
5	RW	Unexpected Split Completion Error Mask	1
4	Rsvd	Reserved	0
3	RW	Received Master-Abort Mask	1
2	RW	Received Target-Abort Mask	0
1	RW	Master-Abort on Split Completion Mask	0
0	RW	Target-Abort on Split Completion Mask	0

**Register Name:** Secondary Uncorrectable Error Severity  
**Address:** OFFSET 234h  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:14	Rsvd	Reserved	18'h00000
13	RW	Internal Bridge Error Severity	0
12	RW	SERR# Assertion Detected Severity	1
11	RW	PERR# Assertion Detected Severity	0
10	RW	Delayed Transaction Discard Timer Expired Severity	0
9	RW	Uncorrectable Address Error Severity	1
8	RW	Uncorrectable Attribute Error Severity	1
7	RW	Uncorrectable Data Error Severity	0
6	RW	Uncorrectable Split Completion Message Data Error Severity	1
5	RW	Unexpected Split Completion Error Severity	0
4	Rsvd	Reserved	0
3	RW	Received Master-Abort Severity	0
2	RW	Received Target-Abort Severity	0
1	RW	Master-Abort on Split Completion Severity	0

subject to change without notice

0	RW	Target-Abort on Split Completion Severity	0
---	----	---	---

**Register Name:** Secondary Advanced Error Capabilities and Control  
**Address:** OFFSET 238h  
**Size:** 32 bits

Bit	Attrib	Description	Default
31:5	Rsvd	Reserved	27'h000000
4:0	RO	Secondary Uncorrectable First Error Pointer	5'h00

**Register Name:** Secondary Header Log Register  
**Address:** OFFSET 23Ch  
**Size:** 128 bits

Bit	Attrib	Description	Default
127:64	RO	Transaction Address	64'h0
63:44	Rsvd	Reserved	20'h000000
43:40	RO	Transaction Command Upper	4'h0
39:36	RO	Transaction Command Lower	4'h0
35:0	RO	Transaction Attribute	36'h0

### 8.2.9 MISC Register

**Register Name:** PCI Interrupt Mapping

**Address:** OFFSET 264h

**Size:** 8 bits

Bit	Attrib	Description	Default
7:2	Rsvd	Reserved	6'h0
1:0	RW	Interrupt mapping to INTx Virtual Wires	2'b00

Device Number	Register Option	Interrupt Signals	Mapping to INTx Virtual Wires
i*4; i=0~12	Interrupt mapping=00	INTA#	INTxA
i*4; i=0~12	Interrupt mapping=00	INTB#	INTxB
i*4; i=0~12	Interrupt mapping=00	INTC#	INTxC
i*4; i=0~12	Interrupt mapping=00	INTD#	INTxD
i*4+1; i=0~12	Interrupt mapping=01	INTA#	INTxB
i*4+1; i=0~12	Interrupt mapping=01	INTB#	INTxC
i*4+1; i=0~12	Interrupt mapping=01	INTC#	INTxD
i*4+1; i=0~12	Interrupt mapping=01	INTD#	INTxA
i*4+2; i=0~12	Interrupt mapping=10	INTA#	INTxC
i*4+2; i=0~12	Interrupt mapping=10	INTB#	INTxD
i*4+2; i=0~12	Interrupt mapping=10	INTC#	INTxA
i*4+2; i=0~12	Interrupt mapping=10	INTD#	INTxB
i*4+3; i=0~12	Interrupt mapping=11	INTA#	INTxD
i*4+3; i=0~12	Interrupt mapping=11	INTB#	INTxA
i*4+3; i=0~12	Interrupt mapping=11	INTC#	INTxB
i*4+3; i=0~12	Interrupt mapping=11	INTD#	INTxC

**Register Name:** TOP Clock control option

**Address:** OFFSET 265h

**Size:** 8 bits

Bit	Attrib	Description	Default
7	RW	Dynamic Clock	0
6:0	Rsvd	Reserved	6'h0

## 9 Electrical Characteristics

### 9.1 Recommend Operation Condition

Terminals	Operation	Min	Typ	Max	Unit	Remark
VCC33	3.3V	3	3.3	3.6	V	
VCC33P	3.3V	3	3.3	3.6	V	
VCC12	1.2V	1.08		1.32	V	
VCCP	1.2V	1.08		1.32	V	
	Temperature	0	25	70	°C	

### 9.2 PCI Express Differential Transmitter Output Ranges

Terminals	Parameter	Min	Typ	Max	Unit	Remark
PTXP PTXN	Unit Interval (UI)	399.88	400	400.12	ps	300PPM, no SSC included
PTXP PTXN	VTX-DIFFp-p Differential peak-to-peak output voltage	0.8		1.2	V	
PTXP PTXN	VTX-DE-RATIO De-emphasized differential output voltage (ratio)	-3.0	-3.5	-4.0	dB	This is the ratio of the VTX-DIFFp-p of the second and following bits after a transition divided by the VTX-DIFFp-p of the first bit after a transition.
PTXP PTXN	TTX-RISE, TTX-FALL P/N TX output rise/fall time	0.125			UI	
PTXP PTXN	VTX-CM-ACp RMS ac peak common mode output voltage			20	mV	
PTXP PTXN	VTX-CM-DC-ACTIVE-IDLE DELTA Absolute delta of dc common mode voltage during L0 and electrical idle	0		100	mV	
PTXP PTXN	VTX-CM-DC-LINE-DELTA Absolute delta of dc common mode voltage between P and N	0		25	mV	
PTXP PTXN	VTX-IDLE-DIFFp Electrical idle differential peak output voltage	0		20	mV	
PTXP PTXN	VTX-RCV-DETECT The amount of voltage change allowed during receiver detection			600	mV	The total amount of voltage change that a transmitter can apply to sense whether a low impedance receiver is present.
PTXP PTXN	VTX-DC-CM The TX dc common mode voltage	0		3.6	V	The allowed dc common mode voltage under any condition
PTXP PTXN	TTX-IDLE-SET-to-IDLE Maximum time to transition to a valid electrical idle after sending an electrical			20	UI	After sending an electrical idle ordered set, the transmitter must meet all electrical idle specifications within this time. This is considered a debounce time for

subject to change without notice

Terminals	Parameter	Min	Typ	Max	Unit	Remark
	idle ordered set					the transmitter to meet electrical idle after transitioning from L0.
PTXP PTXN	TTX-IDLE-to-DIFF-DATA Maximum time to transition to valid TX specifications after leaving an electrical idle Condition			20	UI	Maximum time to meet all TX specifications when transitioning from electrical idle to sending differential data. This is considered a debounce time for the TX to meet all TX specifications after leaving electrical idle.
PTXP PTXN	RLTX-DIFF Differential return loss	10			dB	
PTXP PTXN	RLTX-CM Common mode return loss	6			dB	
PTXP PTXN	ZTX-DIFF-DC DC differential TX impedance	80	100	120	$\Omega$	TX dc differential mode low impedance
PTXP PTXN	ZTX-DC Transmitter dc impedance	40			$\Omega$	Required PTPX as well as PTXN dc impedance during all states
PTXP PTXN	CTX AC coupling capacitor	75		200	nF	All transmitters are ac-coupled and are required on the PWB.

### 9.3 PCI Express Differential Receiver Input Ranges

Terminals	Parameter	Min	Typ	Max	Unit	Remark
PRXP PRXN	Unit Interval (UI)	399.88	400	400.12	ps	300PPM, no SSC included
PRXP PRXN	VTX-DIFFp-p Differential peak-to-peak output voltage	0.175		1.2	V	
PRXP PRXN	VRX-CM-ACp AC peak common mode input voltage			150	mV	
PRXP PRXN	RLRX-DIFF Differential return loss	10			dB	
PRXP PRXN	RLRX-CM Common mode return Loss	6			dB	
PRXP PRXN	ZRX-DIFF-DC DC differential input impedance	80	100	120	$\Omega$	RX dc differential mode impedance
PRXP PRXN	ZRX-DC DC input impedance	40	50	60	$\Omega$	Required PRXP as well as PRXN dc impedance (50 $\wedge$ $\pm$ 20% tolerance)
PRXP PRXN	ZRX-HIGH-IMP-DC Powered down dc input Impedance	200K			$\Omega$	Required PRXP as well as PRXN dc impedance when the receiver terminations do not have power.
PRXP PRXN	VRX-IDLE-DET-DIFFp-p Electrical idle detect Threshold	65		175	mV	measured at the receiver package terminals
PRXP PRXN	TRX-IDLE-DET-DIFF-ENTER-TIME Unexpected electrical idle enter detect threshold integration time			10	ms	

### 9.4 PCI Express Differential Reference Clock Input Ranges

Terminals	Parameter	Min	Typ	Max	Unit	Remark
-----------	-----------	-----	-----	-----	------	--------

subject to change without notice

Terminals	Parameter	Min	Typ	Max	Unit	Remark
PECLKP PECLKN	fIN-DIFF Differential input frequency		100		MHz	The input frequency is 100 MHz + 300 ppm and – 2800 ppm including SSC-dictated variations.
PECLKP PECLKN	VRX-DIFFp-p Differential input peak-to-peak voltage	0.175		1.2	V	
PECLKP	VIH-SE	0.7 * VCC33P		VCC33P	V	Single-ended, reference clock mode high-level input voltage
PECLKP	VIL-SE	VCC33P		0.3 * VCC33P	V	Single-ended, reference clock mode low-level input voltage
PECLKP PECLKN	VRX-CM-ACp AC peak common mode input voltage			140	mV	
PECLKP PECLKN	Duty cycle	40		60	%	Differential and single-ended waveform input duty cycle
PECLKP PECLKN	ZRX-DIFF-DC DC differential input impedance		20		k $\Omega$	REFCLK+/- dc differential mode impedance
PECLKP PECLKN	ZRX-DC DC input impedance		20		k $\Omega$	REFCLK+ dc single-ended mode impedance


## 9.5 PCI Bus Electrical Characteristics

Parameter	Min	Max	Unit	Operation
VIH High-level input voltage	0.5 * VCC33	VCC33	V	VCC33
VIL Low-level input voltage	0	0.3 * VCC33	V	VCC33
VI Input voltage	0	VCC33	V	
VO Output voltage	0	VCC33	V	
VOH High-level output voltage	0.7 * VCC33		V	VCC33
VOL Low-level output voltage		0.18 * VCC33	V	VCC33
IOZ High-impedance, output current		10	$\mu$ A	VCC33
II Input current		10	$\mu$ A	VCC33

## 10 Power Consumption

	3.3V	1.2V
Min. Power	70mA	100mA
Max. Power	90mA	115mA

## 11 Package Information



CONTROL DIMENSIONS ARE IN MILLIMETERS.

SYMBOL	MILLIMETER			INCH		
	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.
A	—	—	1.60	—	—	0.063
A1	0.05	—	0.15	0.002	—	0.006
A2	1.35	1.40	1.45	0.053	0.055	0.057
D	16.00	BSC.	—	0.630	BSC.	—
D1	14.00	BSC.	—	0.551	BSC.	—
E	16.00	BSC.	—	0.630	BSC.	—
E1	14.00	BSC.	—	0.551	BSC.	—
R2	0.08	—	0.20	0.003	—	0.008
R1	0.08	—	—	0.003	—	—
$\theta$	0°	3.5°	7°	0°	3.5°	7°
$\theta_1$	0°	—	—	0°	—	—
$\theta_2$	11°	12°	13°	11°	12°	13°
$\theta_3$	11°	12°	13°	11°	12°	13°
c	0.09	—	0.20	0.004	—	0.008
L	0.45	0.60	0.75	0.018	0.024	0.030
L1	1.00	REF	—	0.039	REF	—
S	0.20	—	—	0.008	—	—


SYMBOL	128L					
	MILLIMETER			INCH		
	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.
b	0.13	0.16	0.23	0.005	0.006	0.009
e	—	0.40	BSC.	—	0.016	BSC.
D2	—	12.40	—	—	0.488	—
E2	—	12.40	—	—	0.488	—
aaa	—	0.20	—	—	0.008	—
bbb	—	0.20	—	—	0.008	—
ccc	—	0.08	—	—	0.003	—
ddd	—	0.07	—	—	0.003	—

NOTES :

- DIMENSIONS D1 AND E1 DO NOT INCLUDE MOLD PROTRUSION. ALLOWABLE PROTRUSION IS 0.25mm PER SIDE. D1 AND E1 ARE MAXIMUM PLASTIC BODY SIZE DIMENSIONS INCLUDING MOLD MISMATCH.
- DIMENSION b DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION SHALL NOT CAUSE THE LEAD WIDTH TO EXCEED THE MAXIMUM b DIMENSION BY MORE THAN 0.08mm. DAMBAR CAN NOT BE LOCATED ON THE LOWER RADIUS OR THE FOOT. MINIMUM SPACE BETWEEN PROTRUSION AND AN ADJACENT LEAD IS 0.07mm FOR 0.4mm and 0.5mm PITCH PACKAGES.
- ALL DIMENSION OF 128L WERE BASE ON THOSE OF 120L SINCE THEY ARE NOT MENTIONED IN JEDEC SPEC MS-026.

Figure 3: Mechanical Specification – LQFP 128L

## Marking Information



1. asmedia: ASMedia Logo
2. ASM1085: Product Name
3. B: Version of ASMedia Logo
4. XXXXXXXXXX: Serial No. Reserved for Vendor
5. YYWW: Date Code