


ZENITH DATA SYSTEMS
LAN 16 TR - XT

NIC Type Token-Ring
Transfer Rate 4/16Mbps
Data Bus 16-bit ISA
Topology Ring
Wiring Type Unshielded twisted pair
 Shielded twisted pair
Boot ROM Available



I/O BASE ADDRESS	
Address	SW1/1
A20 - A4Fh	On
A60 - A6Fh	Off

INTERRUPT REQUEST	
IRQ	SW1/2
2	Off
3	On

BOOT ROM ADDRESS	
Address	SW1/3
CC000 - CFFFFh	On
DC000 - DFFFFh	Off

BOOT ROM	
Setting	SW1/4
iDisabled	On
Enabled	Off

Continued on next page . . .

ZENITH DATA SYSTEMS
LAN 16 TR - XT

... continued from previous page

LLC EPROM ENABLED	
Setting	SW1/5
iRAM-based LLC	On
ROM-based LLC	Off
Note: The LLC EPROMs contain the Logic Link Control program. With the LLC ROMs disabled, the LLC logic can be loaded into RAM. The card will function properly with the LLC chips disabled.	

NETWORK SEGMENT SPEED	
Speed	SW1/6
16Mbps	On
4Mbps	Off
Note: All cards on the network segment must have this option set the same.	

CABLE TYPE	
Type	SW1/7
Unshielded twisted pair (RJ-45 Jack)	Off
Shielded twisted pair (DB-9 Connector)	On

FACTORY CONFIGURED SETTINGS	
Switch	Setting
SW1/8	Unused