


COMPU-SHACK PRODUCTION, GMBH CS-ETHERNET BUSMASTER-KARTE

NIC Type: Ethernet
 Transfer Rate: 10Mbps
 Data Bus: 16-bit ISA
 Topology: Linear Bus
 Wiring Type: AUI transceiver via DB-15 port
 RG58A/U 50ohm coaxial
 Boot ROM: Available



DMA SELECT - J2 & J3								
Channel	Jumper A	Jumper B	Jumper C	Jumper D	Jumper E	Jumper F	Jumper G	
i DMA5	Open	Open	Closed	Open	Open	Open	Open	Open
DMA0	Open	Closed						
DMA1	Open	Open	Open	Open	Open	Closed	Open	Open
DMA2	Open	Open	Open	Open	Closed	Open	Open	Open
DMA3	Open	Open	Open	Closed	Open	Open	Open	Open
DMA6	Open	Closed	Open	Open	Open	Open	Open	Open
DMA7	Closed	Open	Open	Open	Open	Open	Open	Open

Note: The corresponding jumpers on both J2 and J3 are closed when designated. J2 is for DRQ and J3 is for DACK.

Continued on next page. . .

COMPU-SHACK PRODUCTION, GMBH

CS-ETHERNET BUSMASTER KARTE

... continued from previous page

WIRING TYPE SELECT - J5						
Setting	Jumper A	jumper B	Jumper C	Jumper D	Jumper E	Jumper F
BNC	1 & 2 closed					
AUI	2 & 3 closed					

BNC TYPE		
Setting	J6/jumper A	J6/jumper B
í RG58A J 50ohm coaxial	Pins : & 3 closed	Pins &3 closed
RG62A J 93ohm coaxial	Pins & 2 closed	Pins & 2 closed

INTERRUPT SELECT - J8									
IRQ	A	B	C	D	E	F	G	H	I
í IRQ3	Open	Closed							
IRQ4	Open	Closed	Open						
IRQ5	Open	Open	Open	Open	Open	Open	Closed	Open	Open
IRQ7	Open	Open	Open	Open	Open	Closed	Open	Open	Open
IRQ9	Open	Open	Open	Open	Closed	Open	Open	Open	Open
IRQ10	Open	Open	Open	Closed	Open	Open	Open	Open	Open
IRQ11	Open	Open	Closed	Open	Open	Open	Open	Open	Open
IRQ12	Open	Closed	Open						
IRQ15	Closed	Open							

Continued on next page...

COMPU-SHACK PRODUCTION, GMBH
CS-ETHERNET BUSMASTER KARTE

... continued from previous page

I/O ADDRESS					
Address	SW1/1	SW1/2	SW1/3	SW1/4	SW1/5
300h	Off	On	On	On	On
200h	On	On	On	On	On
210h	On	On	On	On	Off
220h	On	On	On	Off	On
230h	On	On	On	Off	Off
240h	On	On	Off	On	On
250h	On	On	Off	On	Off
260h	On	On	Off	Off	On
270h	On	On	Off	Off	Off
280h	On	Off	On	On	On
290h	On	Off	On	On	Off
2A0h	On	Off	On	Off	On
2B0h	On	Off	On	Off	Off
2C0h	On	Off	Off	On	On
2D0h	On	Off	Off	On	Off
2E0h	On	Off	Off	Off	On
2F0h	On	Off	Off	Off	Off
310h	Off	On	On	On	Off
320h	Off	On	On	Off	On
330h	Off	On	On	Off	Off
340h	Off	On	Off	On	On
350h	Off	On	Off	On	Off
360h	Off	On	Off	Off	On

I/O ADDRESS					
Address	SW1/1	SW1/2	SW1/3	SW1/4	SW1/5
370h	Off	On	Off	Off	Off
380h	Off	Off	On	On	On
390h	Off	Off	On	On	Off
3A0h	Off	Off	On	Off	On
3B0h	Off	Off	On	Off	Off
3C0h	Off	Off	Off	On	On
3D0h	Off	Off	Off	On	Off
3E0h	Off	Off	Off	Off	On
3F0h	Off	Off	Off	Off	Off

Continued on next page...

COMPU-SHACK PRODUCTION, GMBH
CS-ETHERNET BUSMASTER KARTE

... continued from previous page

FACTORY CONFIGURED SETTINGS	
Switch	Setting
SW1/6	N/A
SW1/7	N/A
SW1/8	N/A