


ACTIX SYSTEMS, INC. GRAPHICS ENGINE ULTRA

Category Video
Video Types Supported XVGA
Video Processor S3 86C928
Highest Resolution Supported 1280 x 1024
Data Bus Type 16-bit ISA
Memory Type VRAM
Maximum Onboard Memory 2MB



| CONNECTIONS | | | |
|--------------------------|----------|------------------------|----------|
| Purpose : | Location | Purpose : | Location |
| 15-pin analog video port | J1 | VESA Feature connector | J2 |

| FACTORY CONFIGURED SETTINGS | |
|-----------------------------|-------------------|
| Jumper | Setting |
| JP3 | Pins 2 & 3 closed |
| JP4 | Pins 2 & 3 closed |

| INTERRUPT SELECTION | | | | |
|---------------------|-------------------|-------------------|-------------------|-------------------|
| IRQ | JP7 | JP8 | JP9 | JP10 |
| Disabled | Pins 2 & 3 closed |
| 2/9 | Pins 1 & 2 closed | Pins 2 & 3 closed | Pins 2 & 3 closed | Pins 2 & 3 closed |
| 3 | Pins 2 & 3 closed | Pins 2 & 3 closed | Pins 1 & 2 closed | Pins 2 & 3 closed |
| 5 | Pins 2 & 3 closed | Pins 1 & 2 closed | Pins 2 & 3 closed | Pins 2 & 3 closed |
| 15 | Pins 2 & 3 closed | Pins 2 & 3 closed | Pins 2 & 3 closed | Pins 1 & 2 closed |

Note: An IRQ channel must only be selected when using a CGA or EGA monitor.

Continued on next page . . .

ACTIX SYSTEMS, INC.
 GRAPHICS ENGINE ULTRA

... continued from previous page

| MONITOR TYPE SELECT | | | |
|-------------------------------|-----------------------------|-------|-------|
| Horizontal Retrace @ 1024x768 | Vertical Retrace @ 1024x768 | SW1/1 | SW1/2 |
| 31.5KHz - 35.5KHz | 43.5Hz (Interlaced) | Off | Off |
| 30KHz - 38KHz | 43.5Hz (Interlaced) | Off | On |
| 30KHz - 48KHz | 60Hz | On | Off |
| 30KHz - 57KHz | 72Hz | On | On |

| WAIT STATE CONFIGURATION | |
|--------------------------|-------|
| Wait States | SW1/3 |
| i > 0 wait states | Off |
| 0 wait states | On |

| BIOS WIDTH SELECTION | |
|----------------------|-------|
| BIOS | SW1/4 |
| i 8-bit | On |
| 16-bit | Off |

| VIDEO MEMORY CONFIGURATION | | | |
|----------------------------|--------------|--------------|-------------------|
| Size | Bank 0 | Bank 1 | Bank 2 |
| 1MB | (8) 256K x 4 | NONE | Pins 1 & 2 closed |
| 2MB | (8) 256K x 4 | (8) 256K x 4 | Pins 2 & 3 closed |

| ENGINE SPEED SELECTION | | |
|------------------------|-------------------|-------------------|
| Mode | JP5 | JP6 |
| Fast | Pins 1 & 2 closed | Pins 2 & 3 closed |
| Slow | Pins 2 & 3 closed | Pins 1 & 2 closed |

| CLOCK CHIP SELECTION |
|---|
| Jumpers JP1, JP2, JP11, and JP12 are factory configured for the clock chip installed. They should not be changed. |