

DIALOGIC CORPORATION
D/21D (REV. 3)

. . . continued from previous page

BASE I/O ADDRESS						
Setting	JP5	JP6	SW1/1	SW1/2	SW1/3	
A0000h	Closed	Open	Off	Off	Off	
A2000h	Closed	Open	Off	Off	On	
A4000h	Closed	Open	Off	On	Off	
A6000h	Closed	Open	Off	On	On	
A8000h	Closed	Open	On	Off	Off	
i D0000h	Open	Open	Off	Off	Off	
D6000h	Open	Open	Off	On	On	
D8000h	Open	Open	On	Off	Off	
DA000h	Open	Open	On	Off	On	
DC000h	Open	Open	On	On	Off	
DE000h	Open	Open	On	On	On	
Note:	A total of 32 base address settings are available. The switches are a binary representation of the decimal memory addresses. JP5 is the Most Significant Bit and switch SW1/3 is the Least Significant Bit. The switches have the following decimal values: JP5=131072 JP6=65536, SW1/1=32768, SW1/2=16384, SW1/3=8192. Turn off the switches and add the values of the switches to obtain the correct memory address. (Off=1, On=0)					

INTERRUPT						
Setting	JP1/A	JP1/B	JP1/C	JP1/D	JP1/E	JP1/F
i IRQ2/9	Closed	Open	Open	Open	Open	Open
IRQ3	Open	Closed	Open	Open	Open	Open
IRQ4	Open	Open	Closed	Open	Open	Open
IRQ5	Open	Open	Open	Closed	Open	Open
IRQ6	Open	Open	Open	Open	Closed	Open
IRQ7	Open	Open	Open	Open	Open	Closed
Note:	All D/21D & D/41D boards in the system should be set to the same interrupt.					