

AB-740G IDE MULTI I/O

```

1
2 +-----+
3 | PORTS | +-----+ ||||-----+SER
4 | IDE  CN1 | | 1:.....: 1:.....: 1:.....: 1:.....: +||PIN
5 | FDC  CN2 | |      CN1      CN3      CN5      CN6      +++CONN
6 | LED  J1  | | 1:  J1+ - |
7 | S1   CN5 | | ::      +-----+ |
8 | S2   CN6 | C ::      |HM83740 | J10 J11 J12      CN8||LPT
9 | LPT  CN8 | N ::      +-----+ |JJJJ|JJJ|J
10 | GAME CN3 | 2 ::      |8673|294|5
11 +-----+ | ::      |
12 |         | | ::      |
13 +-----+ | +-----+ |
14 |         | + + ...J13 |
15 J2 IDE EXIST INDICATOR 1-2 = EXIST, 2-3 = NON EXIST|
16 J3 GAME PORT ENA/DIS 1-2 = ENA, 2-3 = DIS +-----+
17 J4 FDC PORT ENA/DIS 1-2 = ENA, 2-3 = DIS |J12 LPT PORT 1-2=ENA, 2-3=DIS
18 J5 IDE IOCHRDY 1-2 = ENA, OPEN= DIS |J13 LPT IRQ 1-2=IRQ7, 2-3=IRQ5
19 J6 IDE ENA/DIS 1-2 = ENA, 2-3 = DIS |
20 J7 S1 ENA/DIS 1-2 = ENA, 2-3 = DIS |
21 J8 LPT ADDRESS 1-2 = 378, 2-3 = 278 |
22 J9 S2 ENA/DIS 1-2 = ENA, 2-3 = DIS |
23 J10 S1 SELECTION 1-2 = COM1,2-3 = COM3|
24 J11 S2 SELECTION 1-2 = COM2,2-3 = COM4|
25
26

```

NOTE: SERIAL PORT INFO
COM1=3F8-3FF (IRQ4);
COM2=2F8-2FF (IRQ3);
COM3=3E8-3EF (IRQ4);
COM4=2E8-2EF (IRQ3);