

MODEM DIP-SWITCH SETTINGS

A. DS288 Series 28.8K Modem:

IRQ Select

COM Port Select			IRQ2	IRQ3	IRQ4	IRQ5	IRQ6	IRQ7
Switch	1	2	3	4	5	6	7	8
COM1	ON	ON	Off	Off	ON	Off	Off	Off
COM2	Off	ON	Off	ON	Off	Off	Off	Off
COM3	ON	Off	Off	Off	ON	Off	Off	Off
COM4	Off	Off	Off	ON	Off	Off	Off	Off

Note: You can select other IRQ for any COM port. But only one switch from 3 to 8 can be turned on at a time.

B. DS144 Series 14.4K Modem:

IRQ Select

COM Port Select			IRQ2	IRQ3	IRQ4	IRQ5	IRQ6	IRQ7
Switch	1	2	3	4	5	6	7	8
COM1	ON	ON	Off	Off	ON	Off	Off	Off
COM2	Off	ON	Off	ON	Off	Off	Off	Off
COM3	ON	Off	Off	Off	ON	Off	Off	Off
COM4	Off	Off	Off	ON	Off	Off	Off	Off

Note: You can select other IRQ for any COM port. But only one switch from 3 to 8 can be turned on at a time.

C. DS92 Series 2.4K Modem/9.6K Fax:

IRQ Select

COM Port Select					IRQ2	IRQ3	IRQ4	IRQ5
Switch	1	2	3	4	5	6	7	8
COM1	ON	Off	ON	Off	Off	Off	ON	Off
COM2	Off	ON	ON	Off	Off	ON	Off	Off
COM3	ON	Off	Off	ON	Off	Off	ON	Off
COM4	Off	ON	Off	ON	Off	ON	Off	Off

Note: You can select other IRQ for any COM port. But only one switch from 5 to 8 can be turned on at a time.

[[HOME](#)] [[BACK](#)] [[FLYER](#)]

Digitan Systems Inc. • 2363 Bering Drive, San Jose, CA 95131

Tel: (408)-954-8270 Fax: (408)-954-9641