

RTX-138(I)
ENHANCED PARALLEL PRINTER CARD
USER'S MANUAL

(I) FEATURES:

- * ONE ENHANCED PARALLEL PRINTER PORTS (SPP, BIDI, EPP).
- * IT SUPPORT LPT1 TO LPT6 AND CONTROLLED BY HARDWARE.
- * IT CAN BE SELECTED ITS OWN INTERRUPT (IRQ3, 4, 5, 7, 9)
- * PARALLEL MODE : STANDARD PRINTER MODE, PS/2 BI-DIRECTIONAL AND ENHANCED PARALLEL MODE (EPP).
- * SOFTWARE DRIVE MODE : BI-DIRECTIONAL MODE
 ENHANCED PARALLEL MODE (386 UP).

(II) HARDWARE DESCRIPTION

- 1) 1ST PORT : CONTROL JUMPER JP4, JP5, JP6, P2 IRQ, U1 CLK
 JP4-6 : PRINTER PORT ADDRESS SELECT.
 P2 IRQ : PRINTER PORT INTERRUPT SELECT.
 U1 CLK : PRINTER PORT OPERATING CLOCK SELECT.
 PIN 1&2 SHORT -- STANDARD OPERATE MODE.
 PIN 2&3 SHORT -- HIGH SPEED OPERATE MODE.
 (STANDARD x 1.75)

2) IRQ, ADDRESS AND MODE DESCRIPTION :

LPT1 : \$3BC - \$3BE (IRQ3, 4, 5, 7, 9, SPP, BIDI)
 LPT2 : \$378 - \$37A (IRQ7, SPP, BIDI, EPP)
 LPT3 : \$278 - \$27A (IRQ5, SPP, BIDI, EPP)
 LPT4 : \$268 - \$26A (IRQ3, 4, 5, 7, 9, SPP, BIDI, EPP)
 LPT5 : \$27C - \$27E (IRQ3, 4, 5, 7, 9, SPP, BIDI)
 LPT6 : \$26C - \$26E (IRQ3, 4, 5, 7, 9, SPP, BIDI)

3) ADDRESS JUMPER (NOTE: O -- OPEN, S -- SHORT)

	378	278	268	26C	27C	3BC
JP4	O	O	S	O	S	O
JP5	O	O	O	S	S	S
JP6	S	O	O	S	O	O