


UNIDENTIFIED SCAT TURBO 286

Processor 80286
Processor Speed 12/16/20MHz
Chip Set C & T
Max. Onboard DRAM 8MB
Cache None
BIOS C & T
Dimensions 220mm x 220mm
I/O Options None
NPU Options 80287



CONNECTIONS			
Purpose	Location	Purpose	Location
External battery	JP1	Speaker	JP8
Turbo switch	JP6	Reset switch	JP9
Turbo LED	JP7	Power LED & keylock	JP10

Continued on next page . . .

UNIDENTIFIED

SCAT TURBO 286

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper	Position
í Monitor type select color	JP3	pins 1 & 2 closed
Monitor type select monochrome	JP3	pins 2 & 3 closed
í NPU speed select synchronous with CPU	JP11 & JP12	pins 1 & 2 closed
NPU speed select asynchronous with CPU	JP11 & JP12	pins 2 & 3 closed

DRAM CONFIGURATION				
Size	Bank 0	Bank 1	Bank 2	Bank 3
512KB	(2) 256K x 9	NONE	NONE	NONE
640KB	(2) 256K x 9	(2) 64K x 9	NONE	NONE
1MB	(2) 256K x 9	(2) 256K x 9	NONE	NONE
1.5MB	(2) 256K x 9	(2) 256K x 9	(2) 256K x 9	NONE
2MB	(2) 256K x 9			
2MB	(2) 1M x 9	NONE	NONE	NONE
4MB	(2) 1M x 9	(2) 1M x 9	NONE	NONE
6MB	(2) 1M x 9	(2) 1M x 9	(2) 1M x 9	NONE
8MB	(2) 1M x 9			

CMOS MEMORY CONFIGURATION		
Setting	JP13	JP14
CMOS memory normal operation	Open	Closed
CMOS memory clear	Closed	Open