


**EVEREX SYSTEMS, INC.**  
**AGI 286-12 (EV-1815)**

**Processor** 80286  
**Processor Speed** 12MHz  
**Chip Set** C & T/Suntac  
**Max. onboard DRAM** 1MB  
**Cache** None  
**BIOS** AMI  
**Dimensions** 330mm x 218mm  
**I/O Options** None  
**NPU Options** 80287



CONNECTIONS			
Purpose	Location	Purpose	Location
Front panel connector	J1	External battery connector	J4
Speaker	J2		

Continued on next page . . .

**EVEREX SYSTEMS, INC.**  
**AGI 286-12 (EV-1815)**

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Jumper/Switch	Position
í Monitor type select color	SW1	Off
Monitor type select monochrome	SW1	On
í Factory configured - do not alter	W7	pins 2 & 3 closed
í Factory configured - do not alter	W8	pins 2 & 3 closed

DRAM CONFIGURATION			
Size	Bank 0	Bank 1	W6/pins 3 & 4
512KB	(2) 256K x 9	NONE	Closed
1MB	(2) 256K x 9	(2) 256K x 9	Open

8-bit I/O BUS WAIT STATE CONFIGURATION			
Wait state	W2A	W2B	W2C
4	Closed	Open	Open
5	Open	Closed	Open
í 6	Open	Open	Closed

16-bit I/O BUS WAIT STATE CONFIGURATION				
Wait states	W3D	W3C	W3B	W3A
1	Open	Open	Open	Closed
í 2	Open	Open	Closed	Open
3	Open	Closed	Open	Open
4	Closed	Open	Open	Open