


UNIDENTIFIED 486SX/DX/DX2 - MAINBOARD

Processor	80486SX/80486DX/80486DX2
Processor Speed	20/25/33/50(internal)/50/66(internal)MHz
Chip Set	UNI
Video Chip Set	None
Maximum Onboard Memory	32MB
Maximum Video Memory	None
Cache	64/128/256KB
BIOS	AMI
Dimensions	260mm x 220mm
I/O Options	32-bit VESA local bus slots (3)
NPU Options	None



CONNECTIONS			
Purpose	Location	Purpose	Location
Turbo switch	H1	Reset switch	H5
Turbo LED	H2	External battery	J1
Power LED & keylock	H3	32-bit VESA local bus slots	SL1 - SL3
Speaker	H4		

Continued on next page. . .

UNIDENTIFIED

486SX/DX/DX2 - MAINBOARD

... continued from previous page

USER CONFIGURABLE SETTINGS		
Function	Label	Position
í Turbo enabled	H1	Closed
Turbo enabled through keyboard (CTRL, ALT, +)	H1	Open
Turbo disabled through keyboard (CTRL, ALT, -)	H1	Open
í CMOS memory normal operation	J1	Pins 2 & 3 closed
CMOS memory clear	J1	Pins 3 & 4 closed
Battery type select external	J1	Closed
í Monitor type select color	J3	Closed
Monitor type select monochrome	J3	Open
í VL-BUS clock normal operation	JP43	Pins 2 & 3 closed
VL-BUS clock adjusted	JP43	Pins 1 & 2 closed

DRAM CONFIGURATION		
Size	Bank 0	Bank 1
1MB	(4) 256K x 9	None
2MB	(4) 256K x 9	(4) 256K x 9
4MB	(4) 1M x 9	None
5MB	(4) 256K x 9	(4) 1M x 9
8MB	(4) 1M x 9	(4) 1M x 9
16MB	(4) 4M x 9	None
20MB	(4) 1M x 9	(4) 4M x 9
20MB	(4) 4M x 9	(4) 1M x 9
32MB	(4) 4M x 9	(4) 4M x 9

CACHE CONFIGURATION			
Size	Bank 0	Bank 1	TAG
64KB	(4) 8K x 8	(4) 8K x 8	(1) 8K x 8
128KB	(4) 32K x 8	None	(1) 8K x 8
256KB	(4) 32K x 8	(4) 32K x 8	(1) 32K x 8

CACHE JUMPER CONFIGURATION				
Size	JP6	JP7	JP8	JP9
64KB	Open	Closed	Open	Pins 1 & 2 closed
128KB	Open	Closed	Closed	Pins 1 & 2, 3 & 4 closed
256KB	Closed	Closed	Closed	Pins 1 & 2, 4 & 5 closed

CPU SPEED SELECTION			
Speed	JP29	JP30	JP31
20MHz	Open	Closed	Open
25MHz	Closed	Open	Closed
33MHz	Closed	Closed	Open
50iMHz	Closed	Open	Closed
50MHz	Open	Closed	Open
66iMHz	Closed	Closed	Open

Continued on next page...

UNIDENTIFIED

486SX/DX/DX2 - MAINBOARD

... continued from previous page

CPU TYPE SELECTION	
Type	JP4
80486SX	Pins 5 & 6 closed
80486DX	Pins 1 & 2, 4 & 5, 6 & 7 closed
80486DX2	Pins 1 & 2, 4 & 5, 6 & 7 closed

VL BUS WAIT STATE SELECTION	
Setting	JP20
0	Open
1	Closed

VL BUS SPEED SELECTION	
Speed	JP19
<= 33MHz	Open
>33 MHz	Closed