


SOYO COMPUTER CO., LTD.

5 V X 0 / X 2 / X 5

Processor	CX M1/AM K5/Pentium
Processor Speed	75/90/100/120/133/150/166/180/200MHz
Chip Set	Intel
Video Chip Set	None
Maximum Onboard Memory	128MB (EDO supported)
Maximum Video Memory	None
Cache	256/512KB
BIOS	Award
Dimensions	305mm x 244mm
I/O Options	32-bit PCI slots (3), CD-ROM connector, floppy drive interface, game port, green PC connector, IDE interfaces (2), parallel port, PS/2 mouse port, serial ports (2), IR connector, USB connectors (2), ATX power connector, speaker out, line in, microphone in, wavetable connector, Creative Labs wavetable connector
NPU Options	None



Continued on next page . . .

SOYO COMPUTER CO., LTD.
5 V X 0 / X 2 / X 5

... continued from previous page

CONNECTIONS			
Purpose	Location	Purpose	Location
ATX power connector	ATX	Green PC connector	J23
USB connector	J2	IDE interface LED	J24
USB connector	J3	Parallel port	J25
Creative Labs wavetable connector	J4	PS/2 mouse port	J26
CD-ROM in connector	J7	Serial port 1	J28
Game port	J11	Serial port 2	J29
Speaker out	J12	Floppy drive interface	J30
Microphone in	J13	IDE interface 1	J31
Line out	J14	IDE interface 2	J32
Power LED & keylock	J17	IR connector	JP15
Speaker	J18	Wavetable connector	JP52
Reset switch	J19	32-bit PCI slots	PC1- -PC3

USER CONFIGURABLE SETTINGS		
Function	Label	Position
í Monitor type select EGA/VGA	JP3	Closed
Monitor type select monochrome	JP3	Open
í CMOS memory normal operation	JP5	Open
CMOS memory clear	JP5	Closed
í Factory configured - do not alter	JP9	Unidentified
í Factory configured - do not alter	JP50	Unidentified
í PS/2 mouse disabled	JPS2	Open
PS/2 mouse enabled	JPS2	Closed

DIMM/DRAM CONFIGURATION				
Size	Bank 0	Bank 1	Bank 2	Bank 3
4MB	(2) 512K x 36	None	None	None
8MB	(2) 1M x 36	None	None	None
8MB	None	None	(1) 1M x 64	None
16MB	(2) 2M x 36	None	None	None
16MB	None	None	(1) 2M x 64	None
16MB	(2) 1M x 36	(2) 1M x 36	None	None
16MB	(2) 1M x 36	None	None	(1) 1M x 64
16MB	None	None	(1) 1M x 64	(1) 1M x 64
24MB	(2) 2M x 36	None	None	(1) 1M x 64
32MB	(2) 4M x 36	None	None	None
32MB	None	None	(1) 4M x 64	None
32MB	(2) 2M x 36	(2) 2M x 36	None	None
32MB	(2) 2M x 36	None	None	(1) 2M x 64
32MB	None	None	(1) 2M x 64	(1) 2M x 64
32MB	(2) 2M x 36	None	None	(1) 2M x 64
40MB	(2) 4M x 36	(2) 1M x 36	None	None

Continued on next page. . .

SOYO COMPUTER CO., LTD.
5 V X 0 / X 2 / X 5

... continued from previous page

DIMM/DRAM CONFIGURATION (CON'T)				
Size	Bank 0	Bank 1	Bank 2	Bank 3
40MB	(2) 4M x 36	None	None	(1) 1M x 64
48MB	None	(2) 2M x 36	(1) 4M x 64	None
48MB	(2) 2M x 36	None	None	(1) 4M x 64
48MB	(2) 4M x 36	(2) 2M x 36	None	None
48MB	(2) 4M x 36	None	None	(1) 2M x 64
64MB	(2) 8M x 36	None	None	None
64MB	None	None	(1) 8M x 64	None
64MB	(2) 4M x 36	None	None	(1) 4M x 64
64MB	None	None	(1) 4M x 64	(1) 4M x 64
64MB	(2) 4M x 36	(2) 4M x 36	None	None
64MB	None	(2) 4M x 36	(1) 4M x 64	None
72MB	(2) 8M x 36	(2) 1M x 36	None	None
72MB	(2) 8M x 36	None	None	(1) 1M x 64
80MB	None	(2) 2M x 36	(1) 8M x 64	None
80MB	(2) 2M x 36	None	None	(1) 8M x 64
80MB	(2) 8M x 36	(2) 2M x 36	None	None
96MB	(2) 4M x 36	None	None	(1) 8M x 64
96MB	(2) 8M x 36	(2) 4M x 36	None	None
96MB	(2) 8M x 36	None	None	(1) 4M x 64
96MB	None	(2) 8M x 36	(1) 4M x 64	None
128MB	(2) 8M x 36	(2) 8M x 36	None	None
128MB	(2) 8M x 36	None	None	(1) 8M x 64
128MB	None	None	(1) 8M x 64	(1) 8M x 64
128MB	(2) 8M x 36	None	None	(1) 8M x 64

Note: Board accepts EDO memory. Banks 0 & 1 and 2 & 3 are interchangeable. Banks 0 & 3 and banks 1 & 2 may be used together.

DIMM VOLTAGE CONFIGURATION	
Voltage	JP37
3.3v	Pins 5 & 6 closed
5v	Pins 1 & 2 closed

CACHE CONFIGURATION		
Size	Bank 0	TAG
256KB	(2) 32K x 32	(1) 16K x 8
512KB	(2) 64K x 32	(1) 16K x 8

CPU SPEED SELECTION (CYRIX)							
CPU speed	Clock speed	Multiplier	JP10	JP11	JP12	JP13	JP14
120MHz	50MHz	2x	Closed	Closed	Open	Closed	Open
133MHz	55MHz	2x	Open	Closed	Open	Closed	Open
150MHz	60MHz	2x	Closed	Open	Open	Closed	Open
166MHz	66MHz	2x	Open	Open	Open	Closed	Open

Continued on next page. ...

SOYO COMPUTER CO., LTD.

5 V X 0 / X 2 / X 5

... continued from previous page

CPU SPEED SELECTION (AMD)							
CPU speed	Clock speed	Multiplier	JP10	JP11	JP12	JP13	JP14
75MHz	50MHz	1.5x	Closed	Closed	Open	Open	Open
90MHz	60MHz	1.5x	Closed	Open	Open	Open	Open
100MHz	66MHz	1.5x	Open	Open	Open	Open	Open
120MHz	60MHz	1.5x	Closed	Open	Open	Open	Open
133MHz	66MHz	1.5x	Open	Open	Open	Open	Open
150MHz	60MHz	2x	Closed	Open	Open	Closed	Open
166MHz	66MHz	2x	Open	Open	Open	Closed	Open

CPU SPEED SELECTION (INTEL)							
CPU speed	Clock speed	Multiplier	JP10	JP11	JP12	JP13	JP14
75MHz	50MHz	1.5x	Closed	Closed	Open	Open	Open
90MHz	60MHz	1.5x	Closed	Open	Open	Open	Open
100MHz	66MHz	1.5x	Open	Open	Open	Open	Open
120MHz	60MHz	2x	Closed	Open	Open	Closed	Open
133MHz	66MHz	2x	Open	Open	Open	Closed	Open
150MHz	60MHz	2.5x	Closed	Open	Open	Closed	Closed
166MHz	66MHz	2.5x	Open	Open	Open	Closed	Closed
180MHz	60MHz	3x	Closed	Open	Open	Open	Closed
200MHz	66MHz	3x	Open	Open	Open	Open	Closed

CPU VOLTAGE SELECTION (SINGLE)				
Voltage	JP30	JP31	JP36	JP43
3.3v	Open	Open	Open	1 & 2, 3 & 4
3.52v	Open	Closed	Open	Open

Note: Pins designated should be in the closed position.

CPU VOLTAGE SELECTION (SINGLE, CON'T)					
Voltage	JP44	JP45	JP46	JP47	JP48
3.3v	Open	Open	Open	Open	Closed
3.52v	1 & 2, 3 & 4	Closed	Open	Open	Open

Note: Pins designated should be in the closed position.

CPU VOLTAGE SELECTION (DUAL)					
Voltage	V core	JP30	JP31	JP36	JP43
3.3v	2.5v	Open	Open	Open	Open
3.3v	2.7v	Open	Open	Open	Open
3.3v	2.8v	Open	Open	Open	Open
3.3v	2.9v	Open	Open	Open	Open
3.52v	2.5v	Open	Open	Open	Open
3.52v	2.7v	Open	Open	Open	Open
3.52v	2.8v	Open	Open	Open	Open
3.52v	2.9v	Open	Open	Open	Open

Continued on next page. ...

SOYO COMPUTER CO., LTD.
5 VX0/X2/X5

... continued from previous page

CPU VOLTAGE SELECTION (DUAL, CON'T)						
Voltage	V core	JP44	JP45	JP46	JP47	JP48
3.3v	2.5v	1 & 2, 3 & 4	Open	Open	Closed	Closed
3.3v	2.7v	1 & 2, 3 & 4	Open	Closed	Open	Closed
3.3v	2.8v	1 & 2, 3 & 4	Open	Closed	Open	Closed
3.3v	2.9v	1 & 2, 3 & 4	Open	Closed	Open	Closed
3.52v	2.5v	1 & 2, 3 & 4	Open	Open	Closed	Closed
3.52v	2.7v	1 & 2, 3 & 4	Open	Closed	Open	Closed
3.52v	2.8v	1 & 2, 3 & 4	Open	Closed	Open	Closed
3.52v	2.9v	1 & 2, 3 & 4	Open	Closed	Open	Closed