


MPL IPM486

| | |
|-------------------------------|--|
| Processor | AM486DX |
| Processor Speed | 50/66/75/90/100/120/133MHz |
| Chip Set | OPTI |
| Video Chip Set | OPTI |
| Maximum Onboard Memory | 64MB (EDO supported) |
| Maximum Video Memory | 1MB |
| Cache | None |
| BIOS | Unidentified |
| Dimensions | 160mm x 100mm |
| I/O Options | Floppy drive interface, IDE interface, parallel port, PS/2 mouse port, serial ports (2), VGA port, PC/104 connectors (2) |
| NPU Options | None |



| CONNECTIONS | | | |
|------------------------|----------|------------------------------|----------|
| Purpose | Location | Purpose | Location |
| VGA port | CN1 | IDE interface | CN7 |
| Front panel connector | CN2 | Parallel, serial, PS/2 mouse | J3 |
| CAN CONNECTOR | CN3 | Reset, green PC, speaker | J5 |
| External power | CN4 | G-96 bus connector | J15 |
| ISP connector | CN5 | PC/104 connector | P1 |
| Floppy drive interface | CN6 | PC/104 connector | P2 |

Continued on next page. . .

MPL
IPM486

... continued from previous page

| USER CONFIGURABLE SETTINGS | | |
|--|-------|----------|
| Function | Label | Position |
| Dual scan panel installed | S1/1 | On |
| Single scan panel installed | S1/1 | Off |
| STN panel installed | S1/4 | On |
| TFT panel installed | S1/4 | Off |
| Video resolution select 640 x 480 | S1/5 | On |
| Video resolution select 800 x 600 & 1024 x 768 | S1/5 | Off |
| í VGA address select 46C8h | S1/8 | Off |
| VGA address select 03C3h | S1/8 | On |
| í BIOS write protect enabled | S2/6 | Off |
| BIOS write protect disabled | S2/6 | On |
| í BIOS normal operation | S2/7 | Off |
| BIOS update enabled | S2/7 | On |
| í Internal battery enabled | S2/8 | On |
| Internal battery disabled | S2/8 | Off |

| DIMM CONFIGURATION | | |
|--------------------|-------------|-------------|
| Size | Bank 0 | Bank 1 |
| 8MB | (1) 1M x 64 | None |
| 16MB | (1) 2M x 64 | None |
| 16MB | (1) 1M x 64 | (1) 1M x 64 |
| 24MB | (1) 2M x 64 | (1) 1M x 64 |
| 32MB | (1) 4M x 64 | None |
| 32MB | (1) 2M x 64 | (1) 2M x 64 |
| 40MB | (1) 4M x 64 | (1) 1M x 64 |
| 48MB | (1) 4M x 64 | (1) 2M x 64 |
| 64MB | (1) 4M x 64 | (1) 4M x 64 |

| FLASH MEMORY CONFIGURATION | |
|----------------------------|-------------|
| Size | Bank 2 |
| 8MB | (1) 1M x 64 |
| 16MB | (1) 2M x 64 |

| VIDEO MEMORY CONFIGURATION |
|--|
| Note: Board is factory installed with 1MB of video memory. The location is unidentified. |

Continued on next page. . .

| CPU SPEED SELECTION | | | | |
|---------------------|--------------|------|------|------|
| CPU speed | System speed | S2/1 | S2/2 | SW/3 |
| 50MHz | 16.7MHz | Off | Off | Off |
| 66MHz | 16.7MHz | On | Off | Off |
| 75MHz | 25MHz | Off | On | Off |
| 90MHz | 30MHz | Off | On | On |
| 100MHz | 25MHz | On | On | Off |
| 100MHz | 33.3MHz | Off | Off | On |
| 120MHz | 30MHz | On | On | On |
| 133MHz | 33.3MHz | On | Off | On |

| FLASH SELECTION | | |
|----------------------------|------|------|
| Setting | S2/4 | S2/5 |
| í No flash disk installed | Off | Off |
| Flash mirror C8000 - CFFFF | On | Off |
| Flash mirror D0000 – D7FFF | Off | On |
| Flash mirror D8000 - DFFFF | On | On |

| STN SELECTION | | |
|---|------|------|
| Setting | S1/2 | S1/3 |
| STN mono 4-bit (single) mono 8-bit (dual) | On | On |
| STN mono 8-bit (single) | On | Off |
| STN color 8-bit | Off | On |
| STN color 16-bit | Off | Off |

| LINE PULSE SELECTION | | |
|------------------------------|------|------|
| Setting | S1/6 | S1/7 |
| 240 line pulses/frame | On | On |
| 242 line pulses/frame | On | Off |
| 244 line pulses/frame | Off | On |
| 800 x 600 panel (STN or TFT) | Off | Off |