


# FIRST INTERNATIONAL COMPUTER, INC.

## VT-503

<b>Device Type</b>	Mainboard
<b>Processor</b>	CX 6X86L/IBM 6X86L/CX 686MX/IBM 6X86MX/AM K5/AM K6/Pentium
<b>Processor Speed</b>	90/100/120/133/150/166/200/233/266/300MHz
<b>Chip Set</b>	Intel
<b>Video Chip Set</b>	None
<b>Maximum Onboard Memory</b>	512MB (EDO & SDRAM supported)
<b>Maximum Video Memory</b>	None
<b>Cache</b>	512KB
<b>BIOS</b>	Unidentified
<b>Dimensions</b>	254mm x 218mm
<b>I/O Options</b>	32-bit PCI slots (4), floppy drive interface, green PC connector, IDE interfaces (2), parallel port, PS/2 mouse interface, serial ports (2), IR connector, USB connectors (2)
<b>NPU Options</b>	None



Continued on next page . . .

FIRST INTERNATIONAL COMPUTER, INC.  
VT - 503

... continued from previous page

CONNECTIONS			
Purpose	Location	Purpose	Location
Power LED & keylock	C1/pins 1 - 5	Parallel port	CN3
Turbo LED	C1/pins 6 & 7	Floppy drive interface	CN4
Green PC connector	C1/pins 8 & 9	IDE interface 2	CN5
Green PC LED	C1/pins 10 & 11	IDE interface 1	CN6
Speaker	C1/pins 12 - 15	PS/2 mouse interface	CN7
IDE interface LED	C1/pins 16 & 17	CPU fan power	CPU
Soft off power supply	C1/pins 18 & 19	EISCA CPU fan connector	EIC
Reset switch	C1/pins 20 & 21	IR connector	IR1
Chassis fan power	CHA	32-bit PCI slots	PC1 – PC4
Serial port 2	CN1	USB connector 1	USB1
Serial port 1	CN2	USB connector 2	USB2

USER CONFIGURABLE SETTINGS		
Function	Label	Position
í Password disabled	CPW	Open
Password enabled	CPW	Closed

SIMM CONFIGURATION		
Size	Bank 0	Bank 1
8MB	(2) 1M x 36	None
16MB	(2) 2M x 36	None
16MB	(2) 1M x 36	(2) 1M x 36
24MB	(2) 2M x 36	(2) 1M x 36
32MB	(2) 4M x 36	None
32MB	(2) 2M x 36	(2) 2M x 36
40MB	(2) 4M x 36	(2) 1M x 36
48MB	(2) 4M x 36	(2) 2M x 36
64MB	(2) 8M x 36	None
64MB	(2) 4M x 36	(2) 4M x 36
72MB	(2) 8M x 36	(2) 1M x 36
80MB	(2) 8M x 36	(2) 2M x 36
96MB	(2) 8M x 36	(2) 4M x 36
128MB	(2) 8M x 36	(2) 8M x 36
128MB	(2) 16M x 36	None
136MB	(2) 16M x 36	(2) 1M x 36

Continued on next page. . .

FIRST INTERNATIONAL COMPUTER, INC.  
VT-503

... continued from previous page

SIMM CONFIGURATION (CON'T)		
Size	Bank 0	Bank 1
144MB	(2) 16M x 36	(2) 2M x 36
160MB	(2) 16M x 36	(2) 4M x 36
192MB	(2) 16M x 36	(2) 8M x 36
256MB	(2) 16M x 36	(2) 16M x 36
Note: Board accepts EDO memory.		

DIMM CONFIGURATION		
Size	Bank 2	Bank 3
8MB	(1) 1M x 64	None
16MB	(1) 2M x 64	None
16MB	(1) 1M x 64	(1) 1M x 64
24MB	(1) 2M x 64	(1) 1M x 64
32MB	(1) 4M x 64	None
32MB	(1) 2M x 64	(1) 2M x 64
40MB	(1) 4M x 64	(1) 1M x 64
48MB	(1) 4M x 64	(1) 2M x 64
64MB	(1) 8M x 64	None
64MB	(1) 4M x 64	(1) 4M x 64
72MB	(1) 8M x 64	(1) 1M x 64
80MB	(1) 8M x 64	(1) 2M x 64
96MB	(1) 8M x 64	(1) 4M x 64
128MB	(1) 16M x 64	None
128MB	(1) 8M x 64	(1) 8M x 64
136MB	(1) 16M x 64	(1) 1M x 64
144MB	(1) 16M x 64	(1) 2M x 64
160MB	(1) 16M x 64	(1) 4M x 64
192MB	(1) 16M x 64	(1) 8M x 64
256MB	(1) 16M x 64	(1) 16M x 64
Note: Board accepts SDRAM memory.		

CACHE CONFIGURATION		
Size	Bank 0	TAG
512KB	(1) 64K x 64	Unidentified

Continued on next page...

FIRST INTERNATIONAL COMPUTER, INC.  
VT-503

... continued from previous page

CPU SPEED SELECTION (CX 6X86)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
133MHz	55MHz	2x	2 & 3	1 & 2	1 & 2
150MHz	60MHz	2x	2 & 3	1 & 2	1 & 2
166MHz	66MHz	2x	2 & 3	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION (IBM 6X86)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
133MHz	55MHz	2x	2 & 3	1 & 2	1 & 2
150MHz	60MHz	2x	2 & 3	1 & 2	1 & 2
166MHz	66MHz	2x	2 & 3	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION (CX 6X86L)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
133MHz	55MHz	2x	2 & 3	1 & 2	1 & 2
150MHz	60MHz	2x	2 & 3	1 & 2	1 & 2
166MHz	66MHz	2x	2 & 3	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION (IBM 6X86L)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
133MHz	55MHz	2x	2 & 3	1 & 2	1 & 2
150MHz	60MHz	2x	2 & 3	1 & 2	1 & 2
166MHz	66MHz	2x	2 & 3	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION (CX 6X86MX)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
166MHz	50MHz	3x	1 & 2	2 & 3	1 & 2
166MHz	66MHz	2x	2 & 3	1 & 2	1 & 2
166MHz	55MHz	2.5x	2 & 3	2 & 3	1 & 2
166MHz	60MHz	2.5x	2 & 3	2 & 3	1 & 2
200MHz	55MHz	3x	1 & 2	2 & 3	1 & 2
200MHz	66MHz	2.5x	2 & 3	2 & 3	1 & 2
200MHz	60MHz	3x	1 & 2	2 & 3	1 & 2
200MHz	66MHz	3x	1 & 2	2 & 3	1 & 2
233MHz	66MHz	3.5x	1 & 2	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

Continued on next page...

FIRST INTERNATIONAL COMPUTER, INC.  
VT-503

... continued from previous page

CPU SPEED SELECTION (IBM 6X86MX)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
166MHz	50MHz	3x	1 & 2	2 & 3	1 & 2
166MHz	66MHz	2x	2 & 3	1 & 2	1 & 2
166MHz	55MHz	2.5x	2 & 3	2 & 3	1 & 2
166MHz	60MHz	2.5x	2 & 3	2 & 3	1 & 2
200MHz	55MHz	3x	1 & 2	2 & 3	1 & 2
200MHz	66MHz	2.5x	2 & 3	2 & 3	1 & 2
200MHz	60MHz	3x	1 & 2	2 & 3	1 & 2
200MHz	66MHz	3x	1 & 2	2 & 3	1 & 2
233MHz	66MHz	3.5x	1 & 2	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION (AM K5)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
90MHz	60MHz	1.5x	1 & 2	1 & 2	1 & 2
100MHz	66MHz	1.5x	1 & 2	1 & 2	1 & 2
120MHz	60MHz	1.5x	1 & 2	1 & 2	1 & 2
133MHz	66MHz	1.5x	1 & 2	1 & 2	1 & 2
150MHz	60MHz	1.75x	1 & 2	2 & 3	2 & 3
166MHz	66MHz	1.75x	1 & 2	2 & 3	2 & 3
200MHz	66MHz	2x	1 & 2	1 & 2	2 & 3

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION (AM K6)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
166MHz	66MHz	2.5x	1 & 2	2 & 3	2 & 3
200MHz	66MHz	3x	1 & 2	2 & 3	1 & 2
233MHz	66MHz	3.5x	1 & 2	1 & 2	1 & 2
266MHz	66MHz	4x	2 & 3	1 & 2	2 & 3
300MHz	66MHz	4.5x	2 & 3	2 & 3	2 & 3

Note: Pins designated should be in the closed position.

Continued on next page...

FIRST INTERNATIONAL COMPUTER, INC.  
VT-503

... continued from previous page

CPU SPEED SELECTION (INTEL)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
90MHz	60MHz	1.5x	1 & 2	1 & 2	1 & 2
100MHz	66MHz	1.5x	1 & 2	1 & 2	1 & 2
120MHz	60MHz	2x	2 & 3	1 & 2	1 & 2
133MHz	66MHz	2x	2 & 3	1 & 2	1 & 2
150MHz	60MHz	2.5x	2 & 3	2 & 3	1 & 2
166MHz	66MHz	2.5x	2 & 3	2 & 3	1 & 2
200MHz	66MHz	3x	1 & 2	2 & 3	1 & 2

Note: Pins designated should be in the closed position.

CPU SPEED SELECTION (INTEL MMX)					
CPU speed	Clock speed	Multiplier	FREQ1	FREQ2	FREQ3
166MHz	66MHz	2.5x	2 & 3	2 & 3	1 & 2
200MHz	66MHz	3x	1 & 2	2 & 3	1 & 2
233MHz	66MHz	3.5x	1 & 2	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

CPU VOLTAGE SELECTION (SINGLE)	
Voltage	VR
3.3v	Pins 1 & 2, 5 & 6, 7 & 8 closed
3.5v	Pins 1 & 2, 3 & 4, 5 & 6, 7 & 8 closed

CPU VOLTAGE SELECTION (DUAL)		
Voltage	V core	VR
3.3v	2.1v	Pins 1 & 2 closed
3.3v	2.8v	Pins 7 & 8 closed
3.3v	2.9v	Pins 1 & 2, 7 & 8 closed
3.3v	3.2v	Pins 5 & 6, 7 & 8 closed