

4DVS CPU Jumper Settings with AMD Enchance CPU

CPU TYPE

3 JP4 3 JP7 3 JP9 3 JP23 3 JP25 3 JP26 3 JP27 3 JP32 3 JP33

³ INTEL SL-Enh 486SX/SX2³2-3³1-2³0P ³0P ³2-3 ³ 2-3 ³0P ³2-3 ³3-4 ³2-3

$${}^3\text{INTEL SL-Enh 486DX} \quad {}^32-3^31-2^3\text{OP} \quad {}^3\text{OP} \quad {}^32-3 \quad {}^31-2,3-4^3\text{OP} \quad {}^32-3 \quad {}^33-4 \quad {}^32-3$$

3																		
3	INTEL	486DX4	32	334	330B	30B	32	3	34	3	3	430B	32	3	32	4	32	3

$$^3\text{INTEL 486DX4} \quad ^3\text{2-3}^3\text{1-2}^3\text{UP} \quad ^3\text{UP} \quad ^3\text{2-3} \quad ^3\text{1-2,3-4}^3\text{UP} \quad ^3\text{2-3} \quad ^3\text{3-4} \quad ^3\text{2-3}$$
$$^3\text{JMC JIS-SUPER } 25/33/40^3 2-3^3 1-2^3 \text{OP } 3\text{OP } 32-3 \quad 3 \quad 2-3 \quad 3\text{OP } 32-3 \quad 33-4 \quad 32-3$$

3

$${}^3\text{AMD } 486\text{DX2} \quad {}^32-3{}^31-2{}^3\text{OP} \quad {}^3\text{OP} \quad {}^3\text{OP} \quad {}^31-2,3-4{}^32-3 \quad {}^32-3 \quad {}^3\text{OP} \quad {}^3\text{OP}$$
$${}^3\text{AMD } 486\text{DX4} \quad {}^32-3{}^31-2{}^3\text{OP} \quad {}^3\text{OP} \quad {}^3\text{OP} \quad {}^31-2,3-4{}^31-2 \quad {}^32-3 \quad {}^3\text{OP} \quad {}^3\text{OP}$$

3 AMD 486DX4 Enhance 3 1-2 3 1-2 3 OP 3 1-2 3 2-3 3 1-2,3-4 3 2-3 3 1-2 3 1-2,3-4 3 2-3

³ Nor-Sl-Enhancer	486CY	32	231	23OD	3OD	3OD	3	2	2	3OD	32	2	3	OD	3OD
------------------------------	-------	----	-----	------	-----	-----	---	---	---	-----	----	---	---	----	-----

Non SL-Enhance 486SX 2-3 1-2 UP UP UP 2-3 UP 2-3 UP UP

³Non SI-Enhance 486DX ³2-3³1-2³0P ³0P ³0P ³1-2 3-4³0P ³2-3 ³ 0P ³0P

3

$$^3\text{Cyr} \times 486\text{S} \text{ M6}^{**} \quad ^31-2^32-3^3\text{OP} \quad ^3\text{OP} \quad ^31-2 \quad ^32-3 \quad ^3\text{OP} \quad ^32-3 \quad ^32-3,4-5^31-2$$
$$^3\text{Cyr} \times 486\text{S2} \quad ** \quad {}^31-2 \quad {}^32-3 \quad {}^3\text{CL} \quad {}^3\text{OP} \quad {}^31-2 \quad {}^32-3 \quad {}^3\text{OP} \quad {}^32-3 \quad {}^32-3,4-5 \quad {}^31-2$$

3
16 1 106BY (BYG (WT)) 11 31 313 3135 325 31 3 31 3 3 1335 33 3 3 3 3 31 3

³Cyr1x 486DX/DX2(M7)** ³1-2³2-3³OP ³OP ³1-2 ³1-2,3-4³OP ³2-3 ³2-3 ³1-2

Cyrix 486DX4	31	232	230R	30R	31	2	31	2	2	430R	32	2	3	2	2	31	2
--------------	----	-----	------	-----	----	---	----	---	---	------	----	---	---	---	---	----	---

3

³Cyrix 5X86 ³1-2³2-3³0P ³1-2 ³2-3 ³1-2.3-4³0P ³2-3 ³1-2.3-4³2-3

3

$${}^3\text{P}24\text{D} \quad {}^31-2 {}^31-2 {}^3\text{O}^{\text{P}} \quad {}^31-2 \quad {}^32-3 \quad {}^31-2,3-4 {}^32-3 \quad {}^31-2 \quad {}^31-2,3-4 {}^32-3$$
$$^3\text{P}24\text{T} \quad ^31-2^31-2^3\text{OP} \quad ^3\text{OP} \quad ^32-3 \quad ^31-2,3-4^3\text{OP} \quad ^31-2 \quad ^33-4 \quad ^32-3$$

3

[illegible]

CL=CLOSE OP=OPEN

```
** Only support 5V Cyrix CPU
```

CPU VOLTAGE SELECT

* 4DVS00 SUPPORTS BOTH 3.3V & 5V CPU.

[illegible][illegible]