



## AD586 AT-size Socket 7 MotherBoard

Chip Set: NEC Power TX + Sound (option)

FormFactor: Baby AT size ( 220mm x 170mm )

CPU:

Intel Pentium P54C & P55C

Cyrix 6x86/6x86L/6x86MX/MII

AMD K5/K6/K-2

IBM 6x86/6x86L/6x86MX

IDT WinChip 166/180/200/233

CPU Speed: 166 - 350MHz or above

BIOS Size: 1M OTP or Flash EEPROM

Exp. Slots: 2 ISA + 3 PCI

DRAM Slot: 1 DIMM + 2 SIMM

DRAM Size: Up to 64M

I/O:

2 x IDE

1 x Floppy

2 x COM port

1 x PS/2 Mouse Header

1 x Parallel port

### JP7 - SINGLE/DUAL CPU VOLTAGE

000 (all open) - SINGLE CPU VOLTAGE

SSS (all short) - DUAL CPU VOLTAGE

### JP6 - CPU VOLTAGE

S000000 - 2.1V

OS00000 - 2.2V

OOS0000 - 2.8V

000S000 - 2.9V

0000S00 - 3.2V

00000S0 - 3.3V

000000S - 3.5V

### JP5 - CPU MULTIPLIER

0	0	0	0	S	S	S	S
0 1,5X (3,5X)	0 2X	S 2,5X	S 3X	0 4X	S 4,5X	S 5X	0 5.5X (?)
0	S	S	0	S	S	0	0

### JP4 - CPU CLOCK

SSS - 60MHZ

OSS - 66 MHZ

S00 - 75MHZ

OS0 - 83MHZ

OOS - 90MHZ

000 - 100MHZ

### JP11 - ?

### JP13 - CLEAR CMOS

S0 - NORMAL

OS - CLEAR CMOS

### J9 - FRONT PANEL

KEYLOCK	TB-LED	HD-LED	RESET	
SPEAKER	EMPTY			

### PS/2 MOUSE HEADER

PIN1 5V

PIN2 NO CONNECTION

PIN3 MOUSE DATA

PIN4 GROUND

PIN5 MOUSE CLOCK

### INSTALL DOS POWERIDE! DRIVER

1. Locate and run the SETUP.EXE file from the root directory of driver package.
2. Follow the on-screen instructions to install the driver.

### INSTALL WINDOWS 9X POWERIDE! DRIVER

1. Right-click the relevant device in Device Manager and select Properties.
2. Click the Driver tab and select Update driver.
3. Select Specify a location: and browse to the folder containing the new driver files.
4. Click Next to install the driver and complete the process.

### Performance comparison: IDE interface with STANDART BIOS and IDE drivers vs. POWERIDE! drivers

HDDSPEED for DOS	BIOS	POWERIDE!
Average Seek Time:	9.0 ms	5.6 ms
Maximal Seek Time:	13.9 ms	8.1 ms
Track-To-Track Seek Time:	1.8 ms	1.4 ms
Average Access Time	15.9 ms	13.5 ms

Max. Linear Read Speed:	3.5 MB/sec	5.9 MB/sec
Max. Linear Write Speed:	3.1 MB/sec	7.0 MB/sec
Max. Cache Read Speed:	17.0 MB/sec	7.5 MB/sec

Disk Speed Index:	227	444
-------------------	-----	-----

ATTO Disk Benchmart Win98	BIOS	POWERIDE!
Direct I/O Write:	3014 MB/sec	5285 MB/sec
Direct I/O Read:	2559 MB/sec	4042 MB/sec
Driver I/O Write:	3015 MB/sec	6450 MB/sec
Driver IO Read:	4890 MB/sec	5479 MB/sec