



[News Room](#)

[Products](#)

[Download](#)

[Support](#)

[Awards](#)

[Where to buy](#)



[Global Website](#)

[Home](#) > [Products](#) > [Book PC](#) > [Book PC II](#)

Global Site

[BIOS](#) | [Drivers](#)

[▶ BKV8601 Specification](#)

Model Name: [BKV8601](#) [BKi815](#) [BKS630E](#) [BKi810E](#)

Processor	<ul style="list-style-type: none">■ Intel® Celeron™ PPGA / FC-PGA series■ Intel® Pentium® III (Coppermine) series■ Cyrix® III series			
System Chipsets	<ul style="list-style-type: none">■ Intel® 815 Chipset■ Video Chip: Embedded in Intel® 815■ CMI8738 PCI 3D Audio supports 5.1 channel output■ HSP 56K flex/V.90 modem chip embedded in CMI8738■ RealTek 8100 LAN Chip on board			
System Memory	<ul style="list-style-type: none">■ 2 DIMMs, up to 512MB, support PC133/PC100			
IDE Drives	<ul style="list-style-type: none">■ 2 IDE drive support ATA33/66/100			
Floppy	<ul style="list-style-type: none">■ 3.5" Floppy support 3 mode			
I/O Interface	<table><tr><td><ul style="list-style-type: none">■ 1 x Parallel Port■ 1 x Serial Port■ 2 x PS/2 Ports</td><td><ul style="list-style-type: none">■ 1 x VGA Port■ 2 x USB Ports■ 1 x LAN Port</td><td><ul style="list-style-type: none">■ 1 x S-Out / AV-Out TV-Out Ports■ 1 x MIDI Port■ 1 x Audio Out Port■ 1 x Mic. Phone Port■ 5.1 Channel Audio Out / Front / Rear / Center & Subwoofer</td></tr></table>	<ul style="list-style-type: none">■ 1 x Parallel Port■ 1 x Serial Port■ 2 x PS/2 Ports	<ul style="list-style-type: none">■ 1 x VGA Port■ 2 x USB Ports■ 1 x LAN Port	<ul style="list-style-type: none">■ 1 x S-Out / AV-Out TV-Out Ports■ 1 x MIDI Port■ 1 x Audio Out Port■ 1 x Mic. Phone Port■ 5.1 Channel Audio Out / Front / Rear / Center & Subwoofer
<ul style="list-style-type: none">■ 1 x Parallel Port■ 1 x Serial Port■ 2 x PS/2 Ports	<ul style="list-style-type: none">■ 1 x VGA Port■ 2 x USB Ports■ 1 x LAN Port	<ul style="list-style-type: none">■ 1 x S-Out / AV-Out TV-Out Ports■ 1 x MIDI Port■ 1 x Audio Out Port■ 1 x Mic. Phone Port■ 5.1 Channel Audio Out / Front / Rear / Center & Subwoofer		
Drive Bay Configuration	<ul style="list-style-type: none">■ 1 x 5.25" CD-ROM / DVD-ROM■ 1 x 3.5" HDD■ 1 x 3.5" FDD			
Power Management	<ul style="list-style-type: none">■ Power Voltage Range: 110V / 220V Auto Switch■ Power Capacity: 100W Max.■ Power EMI: FCC, CE, CCIB, BSMI■ Power Safety: UL, TUV			
Accessory	<ul style="list-style-type: none">■ 1 x Manual■ 1 x Support CD■ 1 x Getting Start Guide■ 1 x Howto use stand			
Bundled Software	<ul style="list-style-type: none">■ Fast Windows V1.2■ Gamut 2000■ Media Ring Talk 2000■ Super Voice 99■ PC-Cillin 2000 V1.0b			

Options

- CD-ROM / DVD-ROM (Bundled Win DVD)
- Wireless Keyboard and Remote Control
- 5.1 Channel Speakers
- Windows OS, Linux OS

Dimension & Weight

- Case & Power: 310 x 272 x 82 mm
- Packing Configuration: 510 x 360 x 210 mm, 9.2Kg

Certifications

- FCC, CE, C-Tick, PC99

[◀ BACK](#) [▶ TOP](#)



Best view in IE5.0 and Netscape 6.2 or above under 1024x768 resolution © 2002 Elitegroup Computer Systems. All Rights Reserved.

