

Switch Settings for MXS386-16 System Board

Switch Bank SW1

Sw 1	Sw 2	Function
OFF	OFF	100ns DRAM with fast page mode (4 page active) Default
OFF	ON	100ns DRAM with fast page mode (1 page active)
ON	OFF	Use 100ns DRAMs, non-fast page mode
ON	ON	Use 120ns DRAMs non-fast page mode

Switch Bank SW3

Switch	Meaning if OFF	Meaning if ON
J1	Disable Serial Port	Enable Serial Port
J2	Disable ParallelPort	Enable Parallel Port
J3	Serial Port is COM1	Serial Port is COM2
J4	Parallel Port is LPT1	Parallel Port is LPT2
J5	IRQ3 is Disabled	IRQ3 is Enabled
J6	IRQ4 is Disabled	IRQ4 is Enabled