

Switch 1	Function
ON	Zero wait state
OFF	One wait state

Switch Setting

3	4	Memory configuration
---	---	----------------------

Using 44256K DIPs :

ON	ON	256KB / 0KB
OFF	ON	512KB / 0KB
ON	OFF	640KB / 0KB
OFF	OFF	640KB / 384KB

Jumper

PinFunction

JP1 (default)	2,3	DRAM speed selector
JP2	1,2	256K ROM BIOS
	2,3	128K ROM BIOS
JP3	Short	CGA / EGA / VGA
	Open	Monochrome
JP4	1,2	Parity bit disable
	2,3	Parity bit enable

Connector

Function

P1	Speaker connector
P2	Hardware reset connector
P3	Turbo LED connector
P4	Turbo switch connector
P5	Power LED & Ext-Lock connector
P6, P7	Power supply connector
P8	External battery connector
KB1	Keyboard connector