



MANUAIS DE MOTHERBOARDS JBOND

PCI600E



- **Slot 1 for Intel Pentium II**
- **Intel 82440LX Chipset.**
- **Winbond W83977TF Multi I/O Chip.**
- **Dimensions: 30.5cm x 21.5cm (12 inches x 8.5 inches) ATX form.**
- Award PnP PCI flash BIOS.
- Three 168-pin DIMM sockets.
- Two Enchance IDE sockets (up to four IDE devices) support fast ATA-2, ATAPI, and Ultra DMA/33 functions.
- One Floppy socket supports two floppy drivers with 360K, 720K, 1.22M, 1.44M, and 2.88M bytes.
- One AGP slot supports x1 and x2 AGP card.
- Four PCI slots. (PCI spec. V2.1)
- Three ISA slots. (1 PCI/ISA shared slot)
- PS/2 keyboard and PS/2 mouse connectors on board.
- Two Serial Port sockets.
- One Parallel Port socket supports SPP, EPP, and ECP.
- Two USB Port connectors on board.
- One FIR (Fast IrDA) Port connector on board (transfer rate up to 4MB/s).

1. CPU jumper settings

- **CPU System Speed Settings is on BIOS setup. Please read menu.**

Intel	JW1	JW1	JW1	JW1
Pentium II (66MHz)	DIP 1	DIP 2	DIP 3	DIP 4
233MHz	ON	NC	NC	ON
266MHz	NC	ON	ON	ON
300MHz	NC	ON	NC	ON
333MHz	NC	NC	ON	ON
Intel	JW1	JW1	JW1	JW1
Celeron	DIP 1	DIP 2	DIP 3	DIP 4
233MHz	ON	NC	NC	ON
266MHz	NC	ON	ON	ON
300MHz	NC	ON	NC	ON
333MHz	NC	NC	ON	ON

Note:

- ON - DIP up
- NC- DIP down

2. Clear CMOS Data Jumper Settings

Operating Mode	J4
Normal Operation (default)	Short 1-2
Clear CMOS Data	Short 2-3 while computer powered OFF

3. Support DIMM model list

- Each DIMM socket supports 2M to 128M bytes DIMM module.
- Vcc provides 3.3v
- Support SDRAM-II, SDRAM and EDO DIMM modules.

4. Support Year 2000 Compliance

- BIOS version 1.00 supports Year 2000 compliance.

