

DTK Computers

Technical Information Sheet for PIM-640

S=shorted, O=open DIP switch 1=on 0=off

SW1:Coprocessor	SW1:Floppys Installed
2 Function	7 8 Number of Floppy drives
1 Disabled	1 1 One drive
0 Enabled	0 1 Two drives
	1 0 Three drives
SW1:Display Select	0 0 Four drives
5 6 Display type	
1 1 EGA	JP1:Reset Connector
1 0 CGA (80x25)	S Reset
0 1 CGA (40x25)	0 Normal Operation
0 0 Monochrome	

RAM Installed (-= horizontal jumper, |= vertical jumper)

JP3	JP4	Option	Bank 0	Bank 1	Bank 2	Bank 3
o-o o-o o o						
		256k	4164x9	4164x9	4164x9	4164x9
o o o o o o						

o o o o o o						
		640k	41256x9	41256x9	4164x9	4164x9
o-o o-o o o						

P4:Speaker

<1>	Data out
<2>	+5Vdc
<3>	Data out
<4>	+5Vdc

P1:Power Connector

<1>	Power Good	<7>	Ground
<2>	Not used	<8>	Ground
<3>	+12 VDC	<9>	-5 VDC
<4>	-12 VDC	<10>	+5 VDC
<5>	Ground	<11>	+5 VDC
<6>	Ground	<12>	+5 VDC