

DTK Computers

Technical Information Sheet for PTM-1230

S=shorted, 0=open

DIP switch 1=on 0=off

JP1:ROM Size

0 32k (27128x2)

S 64k (27256x2)

JP3:Turbo LED

<1> Select pin

<2> Ground

JP5:Wait State Select-Turbo

S 0 Wait State (80ns)

0 1 Wait State (100ns)

JP7:Reset Jumper

S Reset

0 Normal operation

J13:Battery Connector

<1> 6Vdc

<2> Not used

<3> Not used

<4> Ground

RAM Installation

RAM DRAM Type

SIZE	Bank 0	Bank 1
------	--------	--------

512k	41256x18	none
------	----------	------

640k	41256x18	4164x18
------	----------	---------

1MB	41256x18	41256x18
-----	----------	----------

JP2:Speaker

<1> Data out

<2> 5Vdc

<3> Ground

<4> 5Vdc

JP4:Hardware Turbo Switch

S Normal mode

0 Turbo mode

JP6:Base Memory

S 512k base

0 640k base

J12:Display Select

o-o o Monochrome

o o-o Color

J15:Keyboard lock

<1> Power LED

<2> Not used

<3> Ground

<4> Keyboard inhibit

<5> Ground

J6:Power Connector

<12> Power Good

<11> +5 VDC

<10> +12 VDC

<9> -12 VDC

<8> Ground

<7> Ground

<6> Ground

<5> Ground

<4> -5 VDC

<3> +5 VDC

<2> +5 VDC

<1> +5 VDC