

Switch Settings for XT386-16/20 System Board

- Switch 1: ON: On board EGA BIOS is Enabled.
OFF: On board EGA BIOS is Disabled (default).
- Switch 2: ON: 08000-090FFFF memory will be cached.
OFF: All the memory will be cached.
- Switch 3: ON: 387 is not present.
OFF: 387 is present.
- Switch 4: ON: 6/8 Mhz system operation-cache off
OFF: 16/20 Mhz system operation-cache on
- Switch 5: ON: Color display(VGA/EGA/CGA)
OFF: Monochrome display

Memory Board Switch settings

Switches	Function	Setting
SW1	Bank select	ON: for two banks OFF: for one banks
SW2	Memory size Below 1 MB	ON: for 640k OFF: for 512k
SW3	384k memory above 1/2MB boundary	ON: Enable OFF: Disable