



# Personal488/MM™

## IEEE 488.2 PC/104® MiniModule Board & Software for Embedded Applications

### Features

- Compact PC/104 form-factor
- Provides 330 Kbytes/s data transfer
- Offers full IEEE 488.2 support
- DOS & Windows® 3.x/95/98/2000/NT\* drivers available
- 8-bit PC/104 bus compliant

IOtech's Personal488/MM™ converts any PC/104 embedded PC into an IEEE 488.2 controller or peripheral. It includes our IEEE 488.2 module and our Windows 3.x and DOS software drivers.

### Software Driver Selection

A brief overview of IOtech's IEEE 488 drivers follows, with a more detailed description beginning on page 271.

**Driver488/W95**—High-performance Windows 95/98 drivers, with C, Delphi™, and Visual Basic® support.

**Driver488/WNT**—High-performance Microsoft Windows NT driver with C, Delphi, and Visual Basic support.

**Driver488/W31**—High-performance Microsoft Windows DLL (Dynamic Link Library) with C and Visual Basic support.

**Driver488/DRV**—Easy-to-use DOS driver, compatible with all languages and spreadsheets. Recommended for BASIC programmers.

**Driver488/SUB**—High-performance DOS driver with subroutine-style interface. Supports C, Pascal, and QuickBasic®.

**Driver488/NI\*\***—National Instruments compatible Windows drivers for IOtech IEEE 488.2 hardware.



*Personal488/MM converts any PC/104 embedded PC into an IEEE 488.2 controller*

### Specifications

- IEEE 488 Controller Device:** 7210  
**Maximum Transfer Rate:** 330 Kbytes/s  
**Connector:** 26-pin header ribbon cable to IEEE 488 standard connector  
**Environment:** 0° to 70°C; 0 to 95% RH, non-condensing  
**DMA:** Channels 0, 1, 2, or 3 (jumper selectable)  
**Interrupts:** IRQ 2, 3, 4, 5, 6, or 7  
**IEEE 488 Base I/O Addresses:** &h02E1, &h22E1, &h42E1, or &h62E1

### Ordering Information

| Description  | Part No.        |
|--|-----------------|
| GP488B/MM IEEE 488.2 board including all compatible drivers and Windows 95/NT users manual | Personal488/MM  |
| GP488B/MM PC/104 IEEE hardware only  | GP488B/MM       |
| Ribbon cable with IEEE 488 connector, 1 ft.  | CA-103          |
| DOS & Windows® 3.1 drivers user manual   | Personal488-902 |

### Related Products

|               |        |
|---------------|--------|
| DASyLab       | p. 194 |
| Driver488/W95 | p. 272 |
| Driver488/WNT | p. 274 |
| Driver488/W31 | p. 276 |
| Driver488/DRV | p. 277 |
| Driver488/SUB | p. 278 |
| Driver488/NI  | p. 279 |

### QUICK FIND

For up-to-date information on products, and to order online, visit the IOtech Web site and enter the corresponding page number in the QUICK FIND field.



\* Contact factory for Windows® 2000 driver availability  
 \*\* 16-bit only