


NORTHGATE COMPUTER SYSTEMS, INC.

NORTHGATE 386

Processor 80386DX
Processor Speed 25/33MHz
Chip Set OPTI
Max. Onboard DRAM 32MB
Cache 64KB
BIOS AMI
Dimensions 330mm x 218mm
I/O Options 32-bit external memory card slot
NPU Options 80387/3167



| CONNECTIONS | | | |
|------------------|-----------------|-----------------------------|------------------|
| Purpose | Location | Purpose | Location |
| External battery | J10 | Reset switch | J23 pins 9 & 19 |
| Speaker | J23 pins 1 - 4 | Power LED & keylock | J23 pins 11 - 15 |
| Turbo switch | J23 pins 7 & 17 | 32-bit external memory card | S1 |
| Turbo LED | J23 pins 8 & 18 | | |

Continued on next page . . .

NORTHGATE COMPUTER SYSTEMS, INC.

NORTHGATE 386

... continued from previous page

| USER CONFIGURABLE SETTINGS | | |
|-------------------------------------|--------|-------------------|
| Function | Jumper | Position |
| í Monitor type select monochrome | JP1 | Open |
| Monitor type select color | JP1 | Closed |
| í Battery type select internal | JP2 | pins 2 & 3 closed |
| Battery type select external | JP2 | pins 1 & 2 closed |
| í Factory configured - do not alter | JP3 | N/A |
| í Factory configured - do not alter | JP4 | N/A |
| í Factory configured - do not alter | JP9 | pins 2 & 3 closed |
| í Factory configured - do not alter | JP12 | N/A |

| DRAM CONFIGURATION | | |
|--------------------|--------------|--------------|
| Size | Bank 0 | Bank 1 |
| 1MB | (4) 256K x 9 | NONE |
| 2MB | (4) 256K x 9 | (4) 256K x 9 |
| 4MB | (4) 1M x 9 | NONE |
| 5MB | (4) 256K x 9 | (4) 1M x 9 |
| 8MB | (4) 1M x 9 | (4) 1M x 9 |
| 16MB | (4) 4M x 9 | NONE |
| 20MB | (4) 4M x 9 | (4) 1M x 9 |
| 32MB | (4) 4M x 9 | (4) 4M x 9 |

| CACHE CONFIGURATION |
|---|
| Note: Cache is factory installed and is not configurable. |