

## Jumper sheet for Biostar MBVLSI-166

J2	Battery
ON	Enabled
OFF	Disabled

J3	Video mode
1-2	Color
2-3	Mono

J4	KBC pin select for turbo
1-5	Pin 23
2-6	Pin 27
3-7	Pin 30 (default)
4-8	Pin 32

J7	ROM size
1-2	256Kb
2-3	128Kb

J10	Power Good source
1-2	Motherboard
2-3	Power Supply

23	Shadow RAM
ON	Disabled
OFF	Enabled

24	RAM Read Wait State
ON	0
OFF	1

25	RAM Write Wait State
ON	0
OFF	1

26	ROM Wait State
ON	2
OFF	3

JPD	Parity
ON	Enabled
OFF	Disabled

Memory Size	18	19	20
512KB (18 * 256Kb x 1)	ON	ON	OFF
1MB (8 * 256Kb x 4 and 4 * 256Kb x 1 parity)	ON	OFF	ON
1MB (36 * 256Kb x 1)			
2MB (18 * 1Mb x 1)	OFF	ON	OFF
4MB (36 x 1Mb x 1)	OFF	OFF	ON