The Wayback Machine - https://web.archive.org/web/19971221141953/http://sowah.com:80/products/board/m512.htm

M512 - VIA Apollo VP1 Chipset Pentium Motherboard

Processor

- *Full range of Intel Pentium P54C, P55C MMX CPU AMD K5, K6 Cyrix 6X86, 6X86MX*

Chipset

- *VIA Apollo VP1*

Bios

- *1Mb PnP Flash Eprom IDE Auto LBA Mode Supports HDD up to 8.4GB*
- *Anti-Virus Protection*

External Cache

- *512Kb on-board Synchronous Pipelined Burst SRAM*

Memory

- *8Mb to 256MB Two 168-pins DIMMs (64Bit) and Two 72-Pins Standard SIMMs (32Bit)*
- *Fast Page Mode, EDO And SDRAM*

On Board I/O

- *Support Two PCI Enhanced IDEs PIO Mode 3, Mode 4 and "Ultra DMA 33" Mode HDDs*
- *Support Two FDDs of 360Kb, 720Kb, 1.2Mb, 1.44Mb or 2.88Mb*
- *One ECP/EPP parallel port. Two 16550AUART serial port*
- *Two USB Ports (Optional Adapter Cable)*
- *One PS/2 Mouse Port (Optional Adapter Cable)*
- *One IrDA Port (Optional Adapter Cable)*

Expansion Slot

- *Three ISA Bus Slots (One IDA Shared Slot) Four PCI Bus Slots (One PCI Shared Slot)*

Plug and Play

- *Plug and Play Specification 1.1. Plug and Play for DOS, Windows 3.x, and Windows 95*

Power Management

- *Support SMM and APM. Comply to Energy Star "Green PC" Program*

PCI

- *PCI 2.1 Compliant*

Battery

- *On-board Lithium Battery*

Board Size

- *220mm x 225mm, Baby-AT Form Factor*

Call today and get Sowah working for you.

Sowah (H.K.) Ltd., Unit 8 & 10, 3 Floor, Block B,
Tonic Industrial Centre, 19 Lam Hing Street,
Kowloon Bay, Kowloon, Hong Kong.

Telephone No.: (852)-2757-7677
Facsimile No.: (852)-2798-0503
E-mail: enquiry@sowah.com